



## Reference Guide





## INSTRUCTIONS

Initialize or clear programming of docking station	Simultaneously hold down star (*) and number sign (#) buttons. Feature lights will start to flash slowly in about 10 seconds and then commence flashing quickly. Release buttons and the process is complete.
Sync Phone	Set phone in docking station cradle. Bluetooth light will illuminate. Press *01 and Bluetooth light and conference light will start to flash. Docking station is now ready to pair to phone. Once synced, lights will stop flashing and a solid blue light will be present.
Sync Multiple Phones	To sync multiple phones follow above instructions but press *02 for second phone and *03 for the third phone and so on.
Using Multiple Phones	Each smartphone must input their original sync code after being placed in the cradle; *01, *02, *03 etc.
Docking phone	Place handset into cradle blue light starts to slow flash, then quick flash and finally solid indicating successful connection.
Docking phone while on a call	Place handset into cradle, call will move to phone speaker and once connected will move to docking station speaker.
Handset Dial	Lift handset and dial tone will be heard, dial number. Dial telephone number.
Handsfree Dial	Simply dial appropriate telephone number.
Voice Dial	Press voice dial button. Wait for phone to respond – give instructions: name or telephone number
Last Number Redial	Press last number redial button and call will be processed.
Disconnect	Push speakerphone button.
Speakerphone call	To put a call on hold, press hold button. To rejoin call, depress hold button. Place active call on hold, press speaker button and dial second call, once answered depress conference button and callers are joined
Hold	
Conference Call	
Call Waiting	Answer call waiting by putting active call on hold and second call will be presented
Mute	Press mute button.

\*\*\* Mobile phones can be connected to only one blue tooth device at a time

Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation.

If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.