

Instruction Manual Of KUL01TX-01

1. Installation:

- 1) Open the battery cover of KUL01TX-01, and put 2x AAA batteries into;
- 2) There are 8 channels on the dial part of KUL01TX-01, which are "1" "2" "5" "15" "30" "NO CDS" "TEST1" "TEST2". "TEST1" and "TEST2" are used by factory workers on testing, do not select; If need work at night, select one of "1, 2, 5, 15, 30" according to your need of Time-delay. The time delay is a period of time from the person walk into and out the detective range of KUL01TX-01; "NO CDS" is working in whole day and turned off by Time-delay 5 minutes;
- 3) According to the detective range, install the plastic mounting of KUL01TX-01 to the right position on the wall; Adjust the angle of sensor window, which face to the needed area you want.

2. Function:

- 1) KUL01TX-01 will not work during the day when select "1, 2, 5, 15, 30". At night, when person go across the detective range of KUL01TX-01, it will send an "ON" signal to KUQ01RF-01 and off power when "Delay Time" was gone.
- 2) Select "NO CDS" which will work in whole day. When person goes across the detective range of KUL01TX-01, it will send an "ON" signal to KUQ01RF-01 and turn off after 5 minutes when it enters into "Time Delay" mode automatically.
- 3) Under selection of "1, 2, 5, 15, 30", the LED inside of KUL01TX-01 will be turned ON for 10 seconds when it's from the day enters into the night.
- 4) The LED inside of KUL01TX-01 will be flicker once time when change the channel to the next one.

3. Specification:

Voltages: 2* AAA batteries
Remote Distance: 8M
Frequency: 315MHZ
Battery Life: 1 year

REMINDING

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation

Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.