

## Anker TC930 Bluetooth Keyboard Cover for iPad Air

### Package Contents

Anker TC930 Bluetooth Keyboard Cover for iPad Air

USB charging cable

4 foot pads

Welcome guide

### Features

- Automatic pop-up stand triggered by setting down your tablet in the stand groove.
- Opening and closing the cover turns the keyboard on and off automatically.
- The keyboard automatically connects to your iPad Air.
- Rechargeable lithium battery with an industry-high capacity lasts for 6 months between charges (based on 2 hours of use per day).
- Low-profile, quiet keys enhance the typing experience.
- Stylish, super-slim body fits securely onto your iPad Air and easily into your bag.
- Great for writing messages and emails when you're on the go.

### Product Overview

加入产品图

- (1) Back to Home
- (2) Brightness Down
- (3) Brightness Up
- (4) Keyboard Display
- (5) Copy
- (6) Paste
- (7) Switch Input Language
- (8) Previous Song
- (9) Play/Pause
- (10) Next Song
- (11) Mute
- (12) Volume Down
- (13) Volume Up
- (14) Screen Lock / Unlock
- (15) Magnet
- (16) Stand Groove

(17) Pop-up Stand Trigger

(18) Caps Lock Indicator

(19) Bluetooth Indicator

(20) Power Indicator

(21) Power Switch

## Specifications

Bluetooth Specification	Bluetooth 3.0
Product Dimensions	240 × 175 × 7.4mm / 9.4 × 6.9 × 0.3in
Product Weight	328g / 11.6oz
Operating Range	Up to 10 meters / 33 feet
Modulation System	GFSK
Standby Time	300 days
Charge Time	5 hours
Uninterrupted Work Time	300 hours
Working Temperature	-10 - +55 °C
Lithium Battery Capacity	800mAh
Battery's Lifespan	400 charge cycles
Key Life	5 million clicks

## Pairing Instructions

1. Push the Power Switch to the ON position to turn on the keyboard, then place your device onto the Stand Groove.
2. Simultaneously press the Fn and C keys to enter pairing mode. The blue Bluetooth Indicator will start to flash rapidly.
3. Activate your device's Bluetooth function and search for the keyboard cover.
4. Once the Bluetooth keyboard cover has been found, click on its name to connect.
5. Enter the password code as displayed on the screen.
6. Once the Bluetooth keyboard cover has successfully connected to your device, the Bluetooth

Indicator will turn off.

After pairing for the first time, your device will connect to the keyboard automatically when opening the keyboard.

Note: In case of connect failure, delete the pairing record from your device, and repeat the procedures above.

### **Power Saving Mode**

The keyboard cover will enter sleep mode after being idle for 15 minutes. To activate it, press any key and wait for **3** seconds.

### **Charging Instructions**

When the battery power is low, the Power Indicator will turn red, indicating that it is time to recharge the keyboard cover.

1. Connect the micro end of the USB power cable to the micro USB port on the keyboard cover.
2. Connect the other end of the cable to a power adapter or computer USB port.
3. The Power Indicator will show a solid light while the keyboard cover is charging. Once it is fully charged, the Power Indicator will turn green.

### **Usage Tips**

- Do not place heavy objects on the keyboard cover.
- Do not drop the product, bump it against hard surfaces, or dismantle it.
- Keep the product away from oil, chemicals, and liquids.
- Clean the keyboard by lightly wiping it with a slightly damp cloth.
- Dispose of batteries according to local laws.

### **Federal Communication Commission Interference Statement**

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:

1. This device may not cause harmful interference.
2. This device must accept any interference received, including interference that may cause undesired operation. Caution: Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

## **FCC STATEMENT :**

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:

- (1) This device may not cause harmful interference, and
- (2) This device must accept any interference received, including interference that may cause undesired operation.

**Warning:** Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation.

This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

Reorient or relocate the receiving antenna.

Increase the separation between the equipment and receiver.

Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.

Consult the dealer or an experienced radio/TV technician for help.

## **RF warning statement:**

The device has been evaluated to meet general RF exposure requirement. The device can be used in portable exposure condition without restriction.