

















## 12.5.3. CDD Mode Test Result

Mode	Frequency (MHz)	PSD (dBm/MHz)			Directional gain (dBi)	EIRP PSD (dBm/MHz)	EIRP Limit (dBm/MHz)
		ANT1	ANT2	Total			
802.11ax HE20	5955	-13.05	-10.83	-8.79	7.00	-1.78	-1
	6175	-11.84	-11.11	-8.45	7.00	-1.44	-1
	6415	-12.31	-10.83	-8.50	7.00	-1.49	-1
	6435	-12.64	-11.40	-8.97	7.00	-1.96	-1
	6475	-11.94	-11.22	-8.55	7.00	-1.54	-1
	6515	-11.79	-11.13	-8.44	7.00	-1.43	-1
	6535	-11.60	-11.21	-8.39	7.00	-1.38	-1
	6715	-12.08	-11.59	-8.82	7.00	-1.81	-1
	6855	-12.69	-10.97	-8.74	7.00	-1.73	-1
	6875	-12.90	-11.18	-8.95	7.00	-1.94	-1
	7015	-11.92	-10.40	-8.08	7.00	-1.07	-1
	7115	-11.97	-11.94	-8.94	7.00	-1.93	-1
802.11ax HE40	5965	-12.39	-10.56	-8.37	7.00	-1.36	-1
	6165	-12.24	-10.46	-8.25	7.00	-1.24	-1
	6405	-12.28	-10.46	-8.49	7.00	-1.48	-1
	6445	-12.16	-11.08	-8.58	7.00	-1.57	-1
	6485	-12.49	-10.74	-8.52	7.00	-1.51	-1
	6525	-12.95	-10.24	-8.38	7.00	-1.37	-1
	6565	-12.44	-10.96	-8.63	7.00	-1.62	-1
	6725	-12.10	-11.70	-8.89	7.00	-1.88	-1
	6845	-13.19	-10.78	-8.81	7.00	-1.80	-1
	6885	-12.83	-10.86	-8.72	7.00	-1.71	-1
	7005	-12.48	-10.14	-8.14	7.00	-1.13	-1
	7085	-11.71	-10.58	-8.10	7.00	-1.09	-1
802.11ax HE80	5985	-13.28	-10.79	-8.85	7.00	-1.84	-1
	6145	-12.23	-11.42	-8.80	7.00	-1.79	-1
	6385	-12.60	-10.83	-8.62	7.00	-1.61	-1
	6465	-11.91	-11.90	-8.89	7.00	-1.88	-1
	6545	-11.75	-10.85	-8.27	7.00	-1.26	-1
	6625	-12.25	-11.33	-8.76	7.00	-1.75	-1
	6705	-12.48	-11.12	-8.74	7.00	-1.73	-1
	6785	-13.03	-11.16	-8.98	7.00	-1.97	-1
	6865	-12.28	-10.24	-8.17	7.00	-1.16	-1
	6945	-11.92	-10.75	-8.29	7.00	-1.28	-1
	7025	-12.16	-10.88	-8.46	7.00	-1.45	-1

Note: 1. The Result and Limit Unit is dBm/500 kHz in the band 5.725–5.85 GHz.

2. The Duty Cycle Factor and RBW Factor is compensated in the graph.

## 12.5.4. CDD Test Graphs

































