

1. Effective (Isotropic) Radiated Power Output Data

1.1 Test Result

1.1.1 PCS1900_EIRP

Band: PCS1900								
ENV	Mode		Frequency (MHz)	Conducted Power (dBm)	Gain (dBi)	EIRP (dBm)		Verdict
	Network	Subset				Result	Limit	
NTNV	GSM	GSM	1850.2	29.15	-1.51	27.64	<=33.01	Pass
			1880	29.39	-1.51	27.88	<=33.01	Pass
			1909.8	29.58	-1.51	28.07	<=33.01	Pass
	GPRS	1 TX Slot	1850.2	29.27	-1.51	27.76	<=33.01	Pass
		2 TX Slots	1850.2	26.66	-1.51	25.15	<=33.01	Pass
		3 TX Slots	1850.2	24.97	-1.51	23.46	<=33.01	Pass
		4 TX Slots	1850.2	22.82	-1.51	21.31	<=33.01	Pass
		1 TX Slot	1880	29.41	-1.51	27.90	<=33.01	Pass
		2 TX Slots	1880	26.47	-1.51	24.96	<=33.01	Pass
		3 TX Slots	1880	24.72	-1.51	23.21	<=33.01	Pass
		4 TX Slots	1880	22.51	-1.51	21.00	<=33.01	Pass
		1 TX Slot	1909.8	29.55	-1.51	28.04	<=33.01	Pass
		2 TX Slots	1909.8	26.41	-1.51	24.90	<=33.01	Pass
		3 TX Slots	1909.8	24.65	-1.51	23.14	<=33.01	Pass
		4 TX Slots	1909.8	22.52	-1.51	21.01	<=33.01	Pass
	EGPRS	1 TX Slot	1850.2	25.46	-1.51	23.95	<=33.01	Pass
		2 TX Slots	1850.2	23.64	-1.51	22.13	<=33.01	Pass
		3 TX Slots	1850.2	21.15	-1.51	19.64	<=33.01	Pass
		4 TX Slots	1850.2	18.79	-1.51	17.28	<=33.01	Pass
		1 TX Slot	1880	25.73	-1.51	24.22	<=33.01	Pass
		2 TX Slots	1880	23.81	-1.51	22.30	<=33.01	Pass
		3 TX Slots	1880	21.30	-1.51	19.79	<=33.01	Pass
		4 TX Slots	1880	18.90	-1.51	17.39	<=33.01	Pass
		1 TX Slot	1909.8	25.66	-1.51	24.15	<=33.01	Pass
		2 TX Slots	1909.8	23.58	-1.51	22.07	<=33.01	Pass
		3 TX Slots	1909.8	21.17	-1.51	19.66	<=33.01	Pass
		4 TX Slots	1909.8	18.85	-1.51	17.34	<=33.01	Pass

Note1: EIRP=Conducted Power+Antenna Gain