

bluetooth keyboard charging case

Packing contents:

1. Cordless keyboard
2. USB power charging cable
3. User manual
 - (1) Bluetooth Keyboard Specification
1. Built-in BROADCOM Bluetooth module 3.0
2. Suitable for IOS, Android, Windows
3. The combination of the design of the leather and plastic
4. MICR interface, easy to charge
5. Built-in rechargeable lithium battery, last for approximately 140 hours per charge
6. Light weight, quiet keystrokes, water-proof, dust-proof
7. Energy saving keyboard sleep mode

Bluetooth Keyboard Specification and Pairing Instruction

- (2) Bluetooth Keyboard Specification
 - 1. Bluetooth 3.0 interface standard
 - 2. Operating Distance to 10 meters
 - 3. Modulating System: GFSK
 - 4. Operation Voltage: 3.0-4.2V
 - 5. Working Current: <2.5mA
 - 6. Standby Current: <0.3mA
 - 7. Sleeping Current: <40UA
 - 8. Charging Current \geq 200mA
 - 9. Standby Time: 90days
 - 10. Charging Time: < 2hours
 - 11. Lithium Battery Capacity: 280mA
 - 12. Uninterrupted Working Time: 100hours
 - 13. Lithium Battery Life: 3year
 - 14. Lithium Battery Specification: 3.8*20*35mm
 - 15. Key Strength: 80 \pm 10g
 - 16. Key life: 5 million strokes
 - 17. Operating Temperature: -10-+55 C

(3) Bluetooth Keyboard Pairing

Step 1: Turn on the power toggle switch. The state indicator light will be on for 5 seconds, then the light will go off.

Step2: Press on the [connect] button, the [Bluetooth] indicator light will be blinking and the [Power] indicator will be off, until the [Bluetooth] indicator light be off, the keyboard is now ready to be connect to Ipad.

Step3: Turn on and unlock Ipad, Click on the Ipad [setting] icon.

Step4: On the setting menu, select item [general] to access [Bluetooth] settings. Click on [Bluetooth] to turn on the connection. Ipad will automatically search for a Bluetooth-enabled device.

Step5: Bluetooth 3.0 Keyboard is found, Click on the device to connect.

Step6: Enter the password code as displayed on screen.

Step7: Wireless Keyboard connected successfully. Wireless keyboard [Status] indicator light will

off.

Special Note:

For other Bluetooth enabled device,please verify the Bluetooth Standard&compatibility before attempting to connect to the keyboard.

(4) Keyboard indicator light

1. “CAPS” indicator light is: Capital and Lower Case Transform light, after the keyboard was ready to be connect to Ipad. Press on the [Caps lock] button, the [CAPS] indicator light will be Blue. Then the letters is Capital. Press on the [Caps lock] button again. The [CAPS] indicator light will be off. Then the letters is Lower Case.
- 2.* indicator light is Bluetooth indicator: When the keyboard was ready to be connect to Ipad, Press on the [connect],the*indicator light will be blue and blinking ,until the *indicator light be off, the keyboard is now ready to be connect to Ipad.
3. “Charge” indicator light : the [charge] red indicator light will stay on when the keyboard is charging. Once it finished charging the [charge] indicator light will turn off.
4. “Power” indicator light: Turn on the power toggle switch. The state indicator light will be on for 5 seconds, then the light will go off.

(5) Battery

The long-lasting rechargeable battery can service you for several weeks

With no memory effect,the lithium battery can be charged at any time.

In order to extend service life,we recommend you turn the keyboard off when there is long time with no interactive.

(6) Charging

When the battery power is low, the[power] indicator light will start blinking,it is time to recharge the keyboard.

Step1: Used the USB power charge cable MICR plug to the keyboard MICR interface.

Step2: Connect USB other plug to the power adapter or computer's USB interface.

Step3:the [charge] red indicator light will stay on when the keyboard is charging. Once it finished charging the [charge] indicator light will turn off.

(7) Energy Saving Sleep Mode

The keyboard will kick into sleep mode when it is inactive for 15 minutes and the keyboard [power] indicator or light will go off. To activate from sleep mode, just press any key and wait 3seconds ,the keyboard will come back on.

(8) Safety Caution

- 1.Keep the item away from sharp objects.
- 2.Do not place heavy object on top of the keyboard.
- 3.Do not Microwave the item.
- 4.Do not force or distorted the keyboard
- 5.Keep away from oil.chemical or any other organic liquid.

(9) Cleaning

Clean the silicone keyboard with water, alcohol or alcohol based disinfectant

(10) Troubleshooting

A, Unable to connect

1. Make sure the power switch is on.(the power light is on or off)
2. Make sure the keyboard is within the operating distance.(the available distance is 10 meter)
3. Make sure the battery is charged.(connect the USB power charge cable, the [charge] red indicator light is stay on. The keyboards will be used after charging)
4. Make sure Ipad Bluetooth setting is on .
5. Make sure wireless keyboard is connected to Ipad.(Press on the [connect] switch, the [Bluetooth] indicator light [Status] will be blinking.)
6. Make sure wireless keyboard has been paired with the Ipad.

B. Unable to Charge Keyboard

1. Make sure the USB power cable is connected properly to the keyboard and the power source.
2. Make sure the wall charger is plug into the power outlet.

Special Note:

The Power adapter output voltage < DC5.0V, Output Voltage <500mA. Or will damage Bluetooth keyboard internal electronics and caused can not be used.

(11) Special Keys Description

Long press Fn, Combined media keys for convenient operation, these mainly more convenient to use your Ipad.

(12) Special Features and Options

Bluetooth protective shell for the protection of Bluetooth PCBA board, compatible with the whole leather Bluetooth keyboard designed. Easy to operate, and more intuitive to use.

(13) Storing the Ipad for Travel

To store the Ipad

1. Put Ipad into a keyboard holster internal, and Merging with keyboard cover.

To separate the Ipad from the keyboard case.

1. Open Keyboard leather case , pull out the Ipad.

(14) Product End of Life:

Keyboard battery disposal

1. Removed the holster sutures, Pry up the plastic cover and remove it completely.
This action destroys keyboard.
2. Turn top over and remove tape from battery.
3. Separate battery from circuit board

4.Dispose of battery according to local laws.Recycle remaining keyboard parts.

5.Table of Toxic and Hazardous Substance / Elements and Their Content

Ingredients	(Pb)	(Hg)	(Cd)	(Cr(VI))	(PBB)	(PBDE)
Cable	X	O	O	O	O	O
PWAs	X	O	O	O	O	O
Plastic parts	O	O	O	O	O	O
Membrane	O	O	O	O	O	O
Meter parts	X	O	O	O	O	O
Rubber dome	O	O	O	O	O	O

O stands for this toxic and hazardous content in homogeneous material is under the SJ/T11363-2006 Standards limits

X stands for this toxic and hazardous content in homogeneous material is beyond the SJ/T11363-2006 Standards limits

Under the ingredients with 'X' in the form all are up to ROHS;

“on 27 January 2003 the European parliament and the council announce electronic equipment in limiting the use of certain hazardous substances directive 2002/95 / EC”

Note: the environmental protection using period reference standard depends on the product of the regular work temperature and humidity conditions.

(15) Special Note

The keyboard on the charge state Instructions for use:

If the keyboard is out of power, or there is no power when using, in this case need charging please use the power cord in the original packaging. Other MICR interface cable is also available, but it can not be used immediately, if you want to use, then you must disconnect the data cable. Please understand the inconvenience!

FCC Caution: Any changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate this equipment.

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules.

These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications.

However, there is no guarantee that interference will not occur in a particular installation.

If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.