

1. Controls

OFF/ON



Slide switch to turn keyboard off or on.

Fn+S



To Pair the keyboard with your tablet, press and hold the function (Fn) key and tap "S".

connect



Press the Bluetooth connect button to establish wireless keyboard connection with tablet PC.

2. Keyboard Indicator Lamp (TM970W510L)**Battery Status Light:** Slide the OFF/ON button to ON.

The power light will illuminate for 3 seconds. The keyboard will remain on although the light will disappear.

Bluetooth Status Light: Press the "Connect" button and the Bluetooth status light will be flash. This indicator light will stay on until the keyboard connects to your device.**Caps Lock Indicator:** Indicator lamp is lit when the keyboard is set to uppercase text mode.**Charging Light:** When the keyboard is charging, the charging indicator illuminates red. When fully charged, the red indicator will turn off.**3. Connecting the Keyboard to the Tablet (TM970W510L)**

Step 1: Turn the power toggle switch to the ON position.

The indicator light will stay on for about three seconds then will turn off.

Step 2: Press the Connect button. The Bluetooth indicator light will blink. The keyboard is now ready to connect to the tablet computer. Step 3: On the tablet, select SETTINGS > Bluetooth > ON. The tablet will automatically search for Bluetooth compatible devices. When the Bluetooth Keyboard is recognized, tap or click to connect.

Step 4: Use the keyboard to enter the password code as displayed on screen; then press enter.
 Step 5: When the keyboard has connected successfully, the Bluetooth indicator light will turn off.

4. Charging the Bluetooth Keyboard (TM970W510L)

When battery power is running low the power light will begin to blink indicating that you need to recharge the keyboard. Connect the USB AC adapter to the keyboard USB port.

Alternate Charging Method:

Step 1: Attach the long USB cable (included with this keyboard) to the short transfer cable (included with the tablet).

Step 2: Connect the long USB cable to the keyboard's USB port and the other end to the tablet.

NOTE: Tablet must be powered on to charge the keyboard. If battery level on the tablet is low, plug in AC power adapter to recharge.

**5. Battery**

The long-lasting lithium ion rechargeable battery will provide many hours of service with no "memory effect". So the battery can be recharged at any time. We recommend that you turn the keyboard off during long periods of inactivity.

6. Energy Saving Sleep Mode

The keyboard automatically enters an idle, or sleep mode, when it is inactive for 15 minutes. At that time, the keyboard power will turn off. To resume normal operation, or wake up the keyboard from sleep mode, press any key and wait about three seconds for the keyboard to reset.

7. Function Keys

Hold the [Fn] key while selecting the desired special keys.



	Home		Copy		Forward
	Search		Cut		Volume Down
	Select All		Rewind		Volume Up
	Duplicate		Play/Pause		

Fn+A To pair the keyboard with your Android system equipment, press and hold the "Fn" key and tap "A".

Fn+S To pair the keyboard with your Windows system equipment, press and hold the "Fn" key and tap "S".

Fn+D To pair the keyboard with your iOS system equipment, press and hold the "Fn" key and tap "D".

8. Product Features:

- 1) Bluetooth wireless keyboard
- 2) Protective leather case with integrated kickstand
- 3) Micro USB interface for easy recharging
- 4) Long lasting, built-in rechargeable lithium battery
- 5) Light weight, quiet keystrokes, water-proof, dust-proof design
- 6) Energy saving sleep mode

9. Keyboard Specification

- 1) Bluetooth interface standard
- 2) Operating distance up to 30 feet
- 3) Modulation system: GFSK

4) Operation voltage: 3.3V

5) Operating current: <3.5mA (Average)

6) Sleep current: <30uA

7) Charge time: <2 hours

8) Lithium battery capacity: 180mAh

9) Operating time: Up to 40 hours

10. Safety Precaution

- 1) Keep the keyboard away from sharp objects.
- 2) Do not place heavy objects on the keyboard.
- 3) Do not expose the keyboard to microwaves.
- 4) Do not apply undue force or pressure on the keyboard.
- 5) Keep keyboard away from oil, chemicals or any other organic liquids.
- 6) Warning: This product may contain a chemical known to the State of California to cause cancer, birth defects, or other reproductive harm.

11. Cleaning

Using a damp cloth, clean the keyboard with water, diluted alcohol or light cleaning solution.

12. Troubleshooting**A. Unable to Connect**

- 1) Make sure the keyboard is on (the power indicator ON).
- 2) Make sure the keyboard is in within the proper operating distance of 30 feet.
- 3) Make sure the battery is recharging properly (the power indicator is red when keyboard is connected to power).
- 4) Make sure the Bluetooth setting on the tablet PC is ON.
- 5) Press the key "Connect" to establish Bluetooth connection.

B. Unable to Charge Keyboard

- 1) Make sure the USB power cable is connected properly to the keyboard and the power source.
- 2) Make sure the wall charger is plug into the power outlet. NOTE: The output voltage and current of the power adapter cannot exceed DC5.0V, 500mA or it may damage the keyboard.

FCC Statement

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions:

- (1) This device may not cause harmful interference, and
- (2) this device must accept any interference received, including interference that may cause undesired operation.