

# Wi-Fi Smart Socket User Manual


## Technological Specifications

- 1).Rated Current:10A
- 2).Rated voltage: 90V-260V
- 3).Rated frequency:50-60HZ
- 4).Rated Power: 2200W
- 5).Wireless Frequency: 2.4Ghz
- 6).Wireless standard: IEEE802.11 b/g/n
- 7).Receive sensitive: 802.11b: <-84dBm(11Mbps);  
802.11g: <-68dBm(54Mbps)
- 8).Output power: 802.11b:16±2dBm; 802.11g:13±2dBm

- 9).Safety: WEP/WPA-PSK/WPA2-PSK
- 10).Encryption: AES/TKIP
- 11).Static power loss: <0.8W
- 12).Working temp: -20 °C ~ 75 °C
- 13).Humidity: 10%-95%
- 14).Dimensions: 10x6x4 cm
- 15).Carton package: 72x36x30.5 cm
- 16).Unit packge: color box, 16x13x5 cm
- 17).50 pcs/carton; GW: 16.5KG

## Download APP

Method 1: Open your QR code scanner in your phone or tablet pc, scan the QR code on the box, then you can download "I Smart" APP, and install the APP to your cellphone or tablet pc.



Method 2: scan the QR code on the label of the Wi-Fi socket, download "I Smart" APP, and install the APP to your cellphone or tablet pc.

## First time set up for using

- 1).Plug the Wi-Fi smart socket into a normal socket, wait for about 3 minutes for launch.



- 2).Long press 4 seconds the light button(with LED indicator) for reset, When the LED indicator blinking quickly, now the status is ready for configure.



- 3).Then start the "I Smart" APP, touch the right bottom menu button, then touch "Add new device" .

- 4).Enter your wifi password, before you do this, please ensure your cellphone has already connected to wifi.



- 5).Touch "Start configure" on the APP to configure the device(Make sure the socket LED indicator is in rapid blinking status before start the configuration).

- 6).When the LED indicator die out, it will appear a notice "successfully configured" on the APP when the configure operation been succeed.

- 7).When complete the above process, you can start to enjoy the wifi socket for its functions. The configure operation is only for the first time set up or reset the device. When you configured successfully, you can control the socket and don't need to configure it again.

## APP user interface and operation

- 1).Run "I Smart" APP on the phone, touch the "Wi-Fi smart socket" option, enter into the main page(picture 1), the left button shows "on/off" status (picture 1).



Picture 1

- 2).Touch to choose the socket, then touch the  button to enter the socket setting page (picture 2), the page displays the state of the connected sockets(on/off, date,time).



Picture 2

- 3).Touch left button  , enter the New Socket Page(picture 2), you can edit the date on the top, slip to choose the time to turn on the smart socket, touch  to choose ON/OFF. Edit the panel on the bottom to set the delaying settings, slip to set a timer to turn on the socket. Setting finished, choose  to Save/Cancel in the right top corner. (picture 3)



Picture 3

- 4).After all the procedures done, you can use your mobile phone to control your socket remotely.

**Federal Communications Commission (FCC) Interference Statement**

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules.

These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications.

However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:

(1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

FCC Caution: Any changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate this equipment.

**RF exposure warning**

This equipment complies with FCC radiation exposure limits set forth for an uncontrolled environment.

The equipment must not be co-located or operating in conjunction with any other antenna or transmitter.