## **BLUETOOTH STEREO HEADPHONE**



Bluetooth\*




#### **Get started**

To know more about your F3L Bluetooth headphone

#### **Features**

- 1.Bluetooth 4.2
- 2,3.5mm music line-in function
- 3.Smart voice alerts
- 4, Support connecting with 2 phones devices
- 5, iOS show the headphone battery power status



How to use

#### 1, General Function

Operation	LED Status
Power on	Blue LED flashes 2 times
Power off	Red LED flashes 2 times
Pairing	Red LED & Blue LED flashes alternately
Standby	Blue LED flashes 3 times in 5 seconds
Incoming call	Blue LED flashes continuous
Low battery	Red LED flashes 2 times every 2 seconds
Charging	Red LED keep lighting during charging, Blue LED keep lighting charging finished.

# 2, Basic Buttons Operation

**Power on:** Press multifunction button for 2 seconds. Blue LED flashes 2 times. Headphone turn on. **Power off:** Press multifunction button for 3 seconds. Red LED turn off after flashes 2 times. Headphone turn off.

Volume adjust: Each press on 'Volume up' or 'Volume down' buttons, one level voice volume changes. When volume reaches to Max or Minimum, "Tick" reminding voice occurs.

Play/Pause: Short press multifunction button ,music pause. Press it again, music continues.

**Previous:** Short press 'Previous' button, music turns to previous one

**Next:** Short press 'Next' button, music turns to next one. **Answer Call:** Short press multifunction button to answer the phone call.

End call: Short press multifunction button, phone call ended

**Reject call:** Press 'Volume up' button, for 2 seconds to rejected a call.

Transfer call: During the phone call conversation, press 'Volume up' button for 2 seconds, call switches to mobile phone. Press 'Volume up' button, for 2 seconds again, call switches to headphone.

Last number redial: in standby status ,continuously press headphone multifunction button twice to redial the last number.

**Call Mute function:** Press 'Volume down' button for 2 seconds, call mute. Press 'Volume down' button for 2 seconds again, call mute cancel.

Battery Capacity status: When headphone connect to iOS devices, iOS devices show the headphone battery power status on the upper right corner. **Charging:** new headphone has enough power for pairing and dialing out for several times. When in low battery, please charging via USB cable for 2 hours. Red LED keep lighting during charging, blue LED keep lighting charging finished.

Reset Mode: Connect the headphone to computer via Micro USB cable. When red LED light flashes, headphone reset finished.

4

3.5mm music line-in function: Connect Audio line in cable to 3.5 audio jack for wired music.

Phone call function cannot be used in this mode

The headphone is on status (not connect with mobile phone )

A) connect the 3.5 audio wire to the headphone and

B) you can adjust volume button of the mobile phone to reach right volume to listen music.

3, Pairing (One headphone support connecting 2 phone devices )

Pairing with one phone or other device

Make sure the headphone is power off. Press and hold the multifunctional button for 5 seconds to enter into the pairing mode. Red LED & Blue LED flashes alternately. Smart voice remind entering into pairing mode. Activate your phone or device Bluetooth function and search for headphone. from the list of found devices on your mobile phone, select the headphone "F3L" to connect it .follow the instruction to enter "0000" as PIN if the mobile phone reminder to need.

Headphone or device can be used to play your phone music or dial phone call etc.

#### Pairing with two phones or other devices at the same time

This headphone can support 2 devices multi-connection. It can pair with two mobile phones simultaneously, taking the call from any of them.

1. Pairing with the A phone successfuly, thenturn off the headphone.

2.Do the same procedure with B phone.

3. Then power off the headphone again.

4.restart the headphone, it will automatically connect to the Phone B of Last connected, and short press the two key of "volume +" and "volume -" simultaneously ,can enable the multipoint Connect function, from the list of found devices on another mobile phone A, select the headphone to connect it.

#### **Kit Contents**

- 1, 1 X Stereo Bluetooth headphone F3L
- 2, 1 X Charging Micro USB Cable
- 3, 1 X User Manual
- 4. 1 X 3.5mm audio wire

### Warning

2

- 1, You must choose a qualified charger from a r egular manufacturer to charge the headphone.
- 2. You must charge the headphone if it has not been used for more than 12 months.

# **Specification**

Weight:

Bluetooth version: 42 Talk time: Stand-by time: 130h Music play time: Wireless range: 10m

Bluetooth profiles: A2DP / AVRCP/ HSP /HFP

169.6g

Impedance: 32Ω Speaker diameter: 40mm Sound pressure level: 103±3dB Frequency Response: 20Hz---20KHz Signal-To-Noise: >85dB ≤1.0% Distortion:

Dimension: 176 x 166 x 65mm

## FCC Statement

3

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- —Reorient or relocate the receiving antenna.
- —Increase the separation between the equipment and receiver. —Connect the equipment into an outlet on a circuit different
- from that to which the receiver is connected. —Consult the dealer or an experienced radio/TV technician for

help. This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any

interference received, including interference that may cause undesired operation.

changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment. This equipment complies with FCC radiation exposure limits set forth for an uncontrolled environment. The device has been evaluated to meet general RF exposure requirement. The device can be used in portable exposure condition without restriction.

5

6