无线键盘使用说明书

(for iOS)

包装包含：说明书×1 蓝牙键盘×1 USB充电线×1

产品型号规格

1.蓝牙标准接口
2.有效操作距离：10米内
3.规格尺寸：GY5K
4.工作电流：＜0mA(键盘施工作时)
5.待机电流：＜0.3mA
6.睡眠电流＜40uA
7.充电电流：100mA/200mA(背光指)
8.待机时间＞10天
9.充电时长：2-3小时
10.锂电池容量：250mAh/500mAh(智光型)
11.工作时长：不小于50/100小时(实际视光)
12.锂电池寿命：3年
13.键键行距：约21毫
14.键键高度：3.0/3.5(点击
15.工作温度：-10℃～+55℃

入门指南

蓝牙/工作指示灯：进入蓝牙配对模式后慢闪，连接成功长亮，键盘休眠或关机后熄灭

大小写状态指示灯：当键盘处于大写输入状态时灯亮

充电指示灯：当电压低于3.3V时闪烁，提示需要充电

充电指示灯：充电时长亮，充满后熄灭

USB Type C 充电接口：即电指示灯闪烁时，请将原装配件USB充电线插入此口进行充电，建议使用5V 1A设备充电

电源开关

蓝牙键盘连接操作步骤

1.确保开关至ON处，蓝牙指示灯：大小写指示灯，键盘指示灯同时长亮3秒后指示灯开始，即为配对中，进入配对(蓝牙指示灯慢闪)

2.打开并解锁iPad，点击"设置"图标

3.在设置菜单中，点击"蓝牙"菜单

4.打开蓝牙开关，iPad会自动搜索蓝牙键盘设备

5. 发现 蓝 牙 键 盘 设 备 ：Bluetooth Keyboard，点击 它并确认连接后，蓝牙键盘会自动连接

6.蓝牙连接成功后，工作指示灯长亮，在蓝牙设备列表中会显示出设备"已连接"

蓝牙快捷功能介绍用

返回主界面	亮度减	亮度加
搜索	屏幕键盘	截屏
上一曲	播放/暂停	下一曲
静音	音量减	音量加
剪切	复制	粘贴
全选	拍门	锁屏
蓝牙配对	背光亮度调节	组合功能键
语音文字输入	向前分类	向后分类
触摸板开启/关闭	语言切换	多任务窗口

注●:底部功能分配按布长短，以适应不同机型

短型：适用于带Home键的机型

长型2款：适用于无Home键的机型

注●:首次连接键盘才有此步骤

●:调色调节：直接单击，共7种颜色循环

●:背景调节：Fn+F4 自带键，只1档亮度循环

●:语音输入：第一次使用时，需要启用听写功能

IOS 14.5以上系统触摸板手势





⑦ 注意

1.在长期不使用时，我们建议关闭键盘，以延长电池的寿命
2.为了获得更长的电池使用寿命，建议电源灯闪烁时才给键盘充电，每次充电时间最好不少于2小时

节能休眠模式

当键盘15分钟内无任何操作，将会自动进入休眠模式，所有LED都会关闭，需要使用时，只需要按任意键就将苹果3秒左右，键盘会被唤醒并自动连接蓝牙，就可以进行正常工作

故障清除

1.确定已开启电源
2.确定键盘在可操作的距离范围内
3.确定电池电量有电量
4.确定手机电脑的蓝牙设置已打开
5.确定无线键盘和蓝牙连接
6.确定无线键盘在蓝牙已配对

语言

将语言，选择或者检查酷的浏览器的语言键盘

充电

当电池电量变灯，或电量指示灯会不断闪烁，这时需给键盘充电
1.将所提供与USB转Type C 数据线的键盘上的充电接口
2.将USB线插入设备通话配置或电脑USB接口(充电适配器不包括)
3.键盘充电过程中，充电指示灯会长亮，充满后熄灭

iOS升到14.2, 蓝牙键盘上的CapsLock 键由默认为切换为切下键盘的功能 IOS 13-15 CapsLock键由默认为切换语言功能），从而导致无法进行大小写切换, 可按以下设置, 还原正常功能：

1. 显先连接上蓝牙
2. 在设置>通用里面设备看到一个名称键盘
3. 点进去后，会看到"大写锁定键切换至下键盘，IOS 13-15 CapsLock键会默认为切换语言功能"，将打开开关选，关掉即可

保 修 卡

用户填写资料

公司或个人全称 _____

通讯地址 _____

电话 _____ 邮编 _____

所购产品名称及型号 _____

购买日期 _____

本有限质保手册适用于以下供应商的无线键盘产品：
(1) 操作操作，误用，操作不当或以非授权的维修，改装或者检查
(2) 操作或维护不当，违反已提供产品产品说明或违反产品的包装
(3) 键盘损坏非本公司原因的其他品或损坏电池，但这些问题不在此质保的范围内

合格证

FCC Caution：

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

Any Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

Note: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

-Reorient or relocate the receiving antenna.

-Increase the separation between the equipment and receiver.

-Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.

-Consult the dealer or an experienced radio/TV technician for help.

The device has been evaluated to meet general RF exposure requirement. The device can be used in portable exposure condition without restriction.

Wireless Keyboard User Manual

(for iOS)

Package included:Instruction manual×1 Wireless keyboard×1 USB charging cable×1

Product Model Specification

1.Bluetooth Interface Standard: 5.0
2.Effective Operating Distance: 10 meters
3.Multi-Motion System: GY5K
4.Working Current: < 9mA
(When the touchpad is working)
5.Standby Current: < 0.2mA
6.Sleeping Current: < 40uA
7.Charging Current: 100mA/200mA
(Backlight)
8.Standby Time: > 100 days
9.Charging Time: 2-3hours
10.Lithium Battery Capacity:
250mAh/500mAh (Backlight)
11.Working Time: > 50/100 hours (turn off the backlight)
12.Lithium Battery Life: 3 years
13.Key Strength: 80 ± 10g
14.Key Life: 5 Million Stroke
15.Operating Temperature: -10°C ~ +55°C

Getting Started Guide

Bluetooth Working Indicator: Slow flash after entering the Bluetooth pairing mode.Long turn on when the connection is successful.And turn off after the keyboard sleeps or shuts down

Caps Lock Indicator: Lights up when the keyboard is in uppercase input

Low Battery Indicator Light: The light will blink when the voltage is lower than 3.3V

Charging Indicator: The light will be on when charging.When fully charged the indicator light is steady in green light.

USB Type C Charging Dock: When Weak current indicator light flashes,Use the original accessories.Plug the USB charging cable into this port for charging.Recommended to use a 5V 1A device to charge it

Power Switch

Bluetooth Keyboard Connection Steps

1.Toggle the switch to ON, the Bluetooth indicator, Caps Lock indicator, and weak power indicator will light up for 3 seconds at the same time.then the keyboard working indicator turn on, manually press Fn + fn to enter pairing (the Bluetooth indicator flashing slowly)

2.Open and unlock your tablet and click on the "Settings" icon

3.In the settings menu,click on the "Bluetooth"menu

4.Turn on the Bluetooth switch and the tablet will automatically search for Bluetooth keyboard devices

5.Discover the Bluetooth keyboard device: Bluetooth Keyboard, click it and confirm this connection, the Bluetooth keyboard will automatically connect

6.After the Bluetooth connection is successful, the working indicator will turn off, and the device will display "connected" in the Bluetooth device list

Keyboard Shortcut Function Description

Back to Home page	Brightness-	Brightness +
Search	ON /OFF Keyboard	Screen Capture
Previous track	Pause/Play	Next Track
Mute Key	Volume -	Volume +
Cut	Copy	Paste
Select all	Take a photo	Lock Screen
Bluetooth pairing	Backlight Brightness Adjustment	Combination Function Keys
Voice text input	adjust forward part	adjust backward part
Touchpad on/off	Language Switching	Multitasking window

Note●: Screen capture function is divided into short press and long press to adapt to different models

Short Press: for models with Home button

Long Press for 2 seconds: for models without Home button

Note●: This button is only available on the backlit version of the keyboard

●:Color Adjustment: direct click a total of 7 color cycles

●: Brightness Adjustment: Fn combination button a total of 3 brightness cycle

●: Voice Input: the first time to use,you need to enable dictation

Touch pad gestures for systems above IOS 14.5





⑦ Attention

1.When not use for long time,suggest to close keyboard,in order to prolong battery life
2.In order to get longer battery life,charging before keyboard power light flashes,charging time must be better more than 2 hours

Energy Saving Sleep Mode

When keyboard not use will be enter sleep mode after 15 minutes,keyboard indicator will off press any key 3s to wake it up when need use again,then keyboard indicator will turn on

Troubleshooting

1.Make sure the power is turned on
2.Ensure keyboard operable distance
3.Make sure the battery has power
4.Ensure the device's Bluetooth was turned on
5.Ensure the wireless keyboard was connected with the Bluetooth
6.Ensure the wireless keyboard paired successfully

Cleaning

Washing alcohol or a similar cleaning agent decontaminationkeyboard

Charging

When battery in low, the power indicator blinking,means need to charge the keyboard
1.Connect Genuine Parts USB cable B port to keyboard oneNo
2.Connect USB cable A port to power adapter or computer USB port
3.During charging, the charging indicator will be on, and it will turn green when fully charged

When system is upgraded to IOS10 - IOS12, the CapsLock key on the Bluetooth keyboard will default to the function of switching to the Latin keyboard (the CapsLock key will default to the function of switching language in IOS 13+15), which makes it impossible to switch between upper and lower case, You can do the following settings to restoring normal functionality:

1、First connect the bluetooth
2、Settings => General => Hardware keyboard
3、After clicking in, you will see"Caps Lock Latin Switch", (IOS 13-15 CapsLock key will default to switch language function)" is on, just turn it off

Warranty Card

User information

Company or personage full name _____

Contact address _____

TEL _____ Zip _____

The purchased product name and model NO. _____

Purchased date _____

This reason due to the product broken and damage is not include on the warranty:

(1) Accident misuse,improper operation,or any unauthorized repair, modified or removed

(2) Improper operation or noncompliance with operation instruction of the product or damage caused by abnormal battery

(3) Or see our warranty is not provided by our company (such as users batteries), unless such restrictions are prohibited by applicable law

Certification

字体：思源黑体中文 + arial字体英文