



HAC Receive Volume Control Test Report

For


Applicant Name: Sun Cupid Technology (HK) Ltd.
Address: 16/F, CEO Tower, 77 Wing Hong St, Cheung Sha Wan, Kowloon, Hong Kong.
EUT Name: LTE Smart Phone
Brand Name: NUU
Model Number: S6603L
Serial Model Number NUU N10, N10

Issued By

Company Name: BTF Testing Lab (Shenzhen) Co., Ltd.
Address: F101, 201 and 301, Building 1, Block 2, Tantou Industrial Park, Tantou Community, Songgang Street, Bao'an District, Shenzhen, China

Report Number: BTF240906R00303
Test Standards: ANSI C63.19:2019 FCC 47 CFR §20.19 TIA-5050:2018
FCC ID: 2ADINS6603L

Test Conclusion: Pass
Test Date: 2025-04-27 to 2025-04-29
Date of Issue: 2025-04-30

Tested By: 
Jim Yin / Tester
Date: 2025-04-30

Prepared By: 

Date: 2025-04-30
Prepared By: Zoey Zhang / Project Engineer

Approved By: 

Date: 2025-04-30
Approved By: Olic Huang / EMC Manager



Note: All the test results in this report only related to the testing samples. Which can be duplicated completely for the legal use with approval of applicant; it shall not be reproduced except in full without the written approval of BTF Testing Lab (Shenzhen) Co., Ltd., All the objections should be raised within thirty days from the date of issue. To validate the report, you can contact us.

Revision History		
Version	Issue Date	Revisions Content
Rev_V0	2025-04-03	Original
Note:	Once the revision has been made, then previous versions reports are replaced by the latest version.	

Table of Contents

1. Introduction	4
1.1 Identification of Testing Laboratory	4
1.2 Identification of the Responsible Testing Location	4
1.3 Laboratory Condition	4
1.4 Announcement	4
2. Product Information	5
2.1 Application Information	5
2.2 Manufacturer Information	5
2.3 General Description of Equipment under Test (EUT)	5
2.4 Equipment under Test Ancillary Equipment	5
2.5 Technical Information	5
3. Summary of Test Results	6
3.1 Test Standards	6
3.2 Air Interfaces / Bands Indicating Operating Modes	6
4. Test Uncertainty	7
5. Measurement System	8
5.1 MEASUREMENT SET-UP	8
6. Evaluation of Test	9
6.1 RECEIVE VOLUME CONTROL PERFORMANCE	9
6.2 RECEIVE DISTORTION AND NOISE PERFORMANCE	10
6.3 RECEIVE ACOUSTIC FREQUENCY RESPONSE PERFORMANCE	11
7. Test Equipment List	13
8. Air Interfaces / Bands used for testing	13
9. Test Result	14
9.1 Receive volume control, distortion and noise performance	14
9.2 Receive acoustic frequency response performance	15
10. EUT photograph	16
ANNEX A Test Data	17
1.1 Receive Distortion and Noise 8N NB	17
1.2 Receive Distortion and Noise 2N NB	19
1.3 Receive Frequency Response	22
2.1 Receive Distortion and Noise 8N WB	23
2.2 Receive Distortion and Noise 2N WB	27
2.3 Receive Frequency Response	31
3.1 Receive Distortion and Noise 8N WB	32
3.2 Receive Distortion and Noise 2N WB	36
3.3 Receive Frequency Response	40
ANNEX B Test Setup Photo	41
ANNEX C CALIBRATION REPORT	41

1. Introduction

1.1 Identification of Testing Laboratory

Company Name:	BTF Testing Lab (Shenzhen) Co., Ltd.
Address:	F101, 201 and 301, Building 1, Block 2, Tantou Industrial Park, Tantou Community, Songgang Street, Bao'an District, Shenzhen, China
Phone Number:	+86-0755-23146130
Fax Number:	+86-0755-23146130

1.2 Identification of the Responsible Testing Location

Test Location:	BTF Testing Lab (Shenzhen) Co., Ltd.
Address:	F101, 201 and 301, Building 1, Block 2, Tantou Industrial Park, Tantou Community, Songgang Street, Bao'an District, Shenzhen, China
Description:	All measurement facilities used to collect the measurement data are located at F101, 201 and 301, Building 1, Block 2, Tantou Industrial Park, Tantou Community, Songgang Street, Bao'an District, Shenzhen, China
FCC Registration Number	518915
Designation Number	CN1409

1.3 Laboratory Condition

Ambient Temperature:	18°C to 25°C
Ambient Relative Humidity:	32% to 49%
Ambient Pressure:	100 kPa to 102 kPa

1.4 Announcement

- (1) The test report reference to the report template version v0.
- (2) The test report is invalid if not marked with the signatures of the persons responsible for preparing, reviewing and approving the test report.
- (3) The test report is invalid if there is any evidence and/or falsification.
- (4) This document may not be altered or revised in any way unless done so by BTF and all revisions are duly noted in the revisions section.
- (5) Content of the test report, in part or in full, cannot be used for publicity and/or promotional purposes without prior written approval from the laboratory.
- (6) The laboratory is only responsible for the data released by the laboratory, except for the part provided by the applicant.

2. Product Information

2.1 Application Information

Company Name:	Sun Cupid Technology (HK) Ltd.
Address:	16/F, CEO Tower, 77 Wing Hong St, Cheung Sha Wan, Kowloon, Hong Kong.

2.2 Manufacturer Information

Company Name:	Sun Cupid Technology (HK) Ltd.
Address:	16/F, CEO Tower, 77 Wing Hong St, Cheung Sha Wan, Kowloon, Hong Kong.

2.3 General Description of Equipment under Test (EUT)

EUT Name	LTE Smart Phone
Under Test Model Name	S6603L
Series Model Name	NUU N10, N10
Description of Model name differentiation	NUU N10, N10 have the same technical construction including circuit diagram, PCB Layout, components and component layout, all electrical construction and mechanical construction with S6603L. The difference lies only the model number. all these changes do not degrade the unwanted emissions of the certified product.
Hardware Version	N/A
Software and Firmware Version	N/A
Dimensions (Approx.)	164*74*8mm
Weight (Approx.)	213g

2.4 Equipment under Test Ancillary Equipment

Ancillary Equipment 1	Battery	
	Brand Name	NUU
	Model No.	S6603L
	Serial No.	NUU N10, N10
	Capacity	Typical capacity: 5000mAh
	Rated Voltage	3.87V

2.5 Technical Information

Network and Wireless connectivity	2G Network GSM/GPRS/EGPRS 850/1900 3G Network WCDMA/HSDPA/HSUPA Band 2/4/5 4G Network FDD LTE Band 2/4/5/12/25/26/66/71 2.4G WIFI 802.11b, 802.11g, 802.11n(HT20/HT40) 5G WIFI 802.11a, 802.11n(HT20/HT40), 802.11ac(VHT80) BT (EDR+BLE)
-----------------------------------	---

3. Summary of Test Results

3.1 Test Standards

No.	Identity	Document Title
1	ANSI C63.19-2019	American National Standard for Methods of Measurement of Compatibility between Wireless Communication Devices and Hearing Aids
2	FCC 47 CFR §20.19	Hearing Aid Compatible Mobile Headsets
3	TIA-5050:2018	Telecommunications Communications Products Receive Volume Control Requirements for Wireless (Mobile) Devices
4	KDB285076 D05v01	HACWaiverDA23-914
5	KDB285076 D04v02	Volume Control
6	KDB285076 D01v06r04	HAC Guidance

3.2 Air Interfaces / Bands Indicating Operating Modes

Air Interface	Band	Type	Simultaneous Transmitter	Name of Service
GSM	850	VO	WLAN & BT	CMRS Voice
	1900	VO	WLAN & BT	CMRS Voice
	GPRS/EGPRS	DT	N/A	N/A
WCDMA	Band II	VO	WLAN & BT	CMRS Voice
	Band IV	VO	WLAN & BT	CMRS Voice
	Band V	VO	WLAN & BT	CMRS Voice
	HSPA	DT	N/A	N/A
LTE	Band 2	VD	WLAN & BT	VoLTE
	Band 4	VD	WLAN & BT	VoLTE
	Band 5	VD	WLAN & BT	VoLTE
	Band 12	VD	WLAN & BT	VoLTE
	Band 25	VD	WLAN & BT	VoLTE
	Band 26	VD	WLAN & BT	VoLTE
	Band 66	VD	WLAN & BT	VoLTE
	Band 71	VD	WLAN & BT	VoLTE
WLAN	2.4g&5g	DT	WWAN	N/A
BT	2450	DT	WWAN	N/A

NA: Not Applicable
VO: Voice Only
VD: CMRS and IP Voice Service over Digital Transport
DT: Digital Transport Only

Note: The hearing aid compatibility mode of the prototype was turned on during testing, and all tests were performed in HAC mode.


4. Test Uncertainty

UNCERTAINTY EVALUATION FOR AUDIO HAC MEASUREMENT					
Uncertainty Component	Tol (+- %)	Prob. Dist.	Div.	Uncertainty (dB)	Uncertainty (%)
Measurement System					
RF reflections	0.1	R	$\sqrt{3}$	0.06	
Acoustic noise	0.1	R	$\sqrt{3}$	0.06	
Probe coil sensitivity	0.49	R	$\sqrt{3}$	0.28	
Reference signal level	0.25	R	$\sqrt{3}$	0.14	
Positioning accuracy	0.4	R	$\sqrt{3}$	0.23	
Cable loss	0.1	N	2	0.05	
Frequency analyzer	0.15	R	$\sqrt{3}$	0.09	
System repeatability	0.2	N	1	0.20	
Repeatability of the WD	0.4	N	1	0.40	
Combined Standard Uncertainty		N	1	0.61	
Expanded uncertainty (confidence level of 95%, k = 2)		N	K=2	1.22	15.05
REPORTED Expanded uncertainty (confidence level of 95%, k = 2)		N	K=2	1.20	15.00

5. Measurement System

5.1 MEASUREMENT SET-UP

The general test arrangement is shown in Figure 1. The Call Box passes the voice channel stream to the DUT without modification. There is no gain or loss in the voice channel stream due to the Call Box interface.



NOTES:

1. Additional information related to the air interface for the various RF technologies is specified in several 3GPP documents. A list of these can be found in 3GPP TS 26.132 V14.0.0 clause 4
2. Additional information related to the test setup can be found in 3GPP TS 26.132, V14.0.0 clause 5.1.
3. The RETP (receive electrical test point) is the point in the device test arrangement where signals are applied to the DUT in the receive direction.

6. Evaluation of Test

6.1 RECEIVE VOLUME CONTROL PERFORMANCE

6.1.1 Requirement

1. With a mounting force of 8N, the DUT shall have at least one volume control setting that will produce a conversational gain of ≥ 18 dB with the output distortion and the frequency response meeting the requirements in clause 5.2.1 & 5.3.1 respectively.
2. With a mounting force of 2N, the DUT shall have at least one volume control setting that will produce a conversational gain of ≥ 6 dB with the output distortion and the frequency response meeting the requirements in clause 5.2.1 & 5.3.1 respectively.

NOTE: Other acoustic receive features may be available such as additional amplification, tone control, automatic gain control, etc. ANSI/TIA-4953-B contains performance requirements for output levels and tone control operation for amplified devices.

6.1.2 Method of Measurement

1. Configure the DUT with a mounting force of 8N and test equipment as shown in Figure 1 in an active call state with the applicable codec for the transmission mode under test.
2. Set the DUT volume control to the maximum setting.
3. If the DUT has an adjustable tone control feature, a tone control setting that meets the frequency response requirements in section 5.3.1 shall be used.
4. Apply the real speech test signal at a level of -20 dBm0 at the RETP and measure the acoustic output at the Drum Reference Point (DRP) over one complete sequence of the test signal.
5. Translate the measurement made at the DRP to the Free Field (FF) using the translation data in Annex B.
6. Over the applicable frequency band, determine the ASL in dBSPL for the resulting sound pressure level in accordance with Method B of ITU-T Recommendation P.56:
 - a. Narrowband 100 Hz through 4000 Hz.
 - b. Wideband 100 Hz through 7720 Hz.
7. Calculate the Conversational Gain by subtracting 70 dB from the measured dBSPL.
[Conversational Gain = (Measured dBSPL Level – 70 dBSPL) dB]
8. Measure the output distortion per clause 5.2. If a distortion failure occurs at the maximum volume control setting, reduce the volume control setting and repeat the measurement to determine if a setting can be found for which the conversational gain requirement is met without a distortion failure.
9. Repeat steps 2-8 with a mounting force of 2N.

6.1.3 Test Result

Refer to Part Nine test result.

Remark: The report only reflects the test data plots of worst mode (for GSM 850, WCDMA Band 2, LTE Band 2)

6.1.4 Test Conclusion

PASS.

6.2 RECEIVE DISTORTION AND NOISE PERFORMANCE

6.2.1 Requirement

With a mounting force of 8N and 2N, the ratio of the stimulus signal power to the 100 Hz to 8000 Hz total A-weighted distortion and noise power shall be ≥ 20 dB when tested over the range of 1/3 octave band center frequencies:

1. Narrowband transmission mode: Each 1/3 octave band center frequency from 400 Hz to 3150 Hz.
2. Wideband transmission mode: Each 1/3 octave band center frequency from 250 Hz to 5000 Hz.

6.2.2 Method of Measurement

1. Configure the DUT with a mounting force of 8N and test equipment as shown in Figure 1 in an active call state with the applicable codec for the transmission mode under test with the volume control at the setting determined in 5.1.1.
2. Receive distortion and noise is measured using the PN-SDNR procedure as described in Annex A.
3. To ensure DUT activation, apply the real speech test signal at a level of -20 dBm0 followed immediately by the initial 1/3 octave center frequency PN test signal in Table A.1 based on the narrowband or wideband operating mode. Measure the acoustic output at the DRP over the complete sequence of the PN test signal.
4. Translate the measurement made at the DRP to the FF using the translation data in Annex B.
5. Calculate the acoustic output unweighted total signal power of the stimulus measurement band as described in A.2.
6. Calculate the notched A-weighting distortion and noise components as described in A.3.
7. Calculate the ratio of the signal power to the total A-weighted distortion and noise power using Eq A-1.
8. Repeat for each of the remaining 1/3 octave center frequencies in Table A.1 based on the narrowband or wideband operating mode.
9. Repeat steps 2-8 with a mounting force of 2N.

6.2.3 Test Result

Refer to test Annex A.

Remark: The report only reflects the test data plots of worst mode (for GSM 850, WCDMA Band 2, LTE Band 2)

6.2.4 Test Conclusion

PASS.


6.3 RECEIVE ACOUSTIC FREQUENCY RESPONSE PERFORMANCE

6.3.1 Requirement

1. Narrowband: The 1/12 octave band frequency response after translation to the FF or DF shall fall between the upper and lower limits given in Table 1 and shown in Figure below.

Table 1 – Narrowband Receive Frequency Response Limits


Lower Limit Frequency (Hz)	Lower Limit (dB)	Upper Limit Frequency (Hz)	Upper Limit (dB)
300	-6	100	+6
3400	-6	4000	+6



2. Wideband: The 1/12 octave band frequency response after translation to the FF or DF shall fall between the upper and lower limits given in Table 2 and shown in Figure below.

Table 2 – Wideband Receive Frequency Response Limits

Lower Limit Frequency (Hz)	Lower Limit (dB)	Upper Limit Frequency (Hz)	Upper Limit (dB)
200	-10	100	+6
300	-6	1000	+6
5000	-6	2000	+8
6300	-12	8000	+8



6.3.2 Method of Measurement

1. Configure the DUT with a mounting force of 8N and test equipment as shown in Figure 1 in an active call state with the applicable codec for the transmission mode under test with the volume control at the setting determined in 5.1.1.
2. If the DUT has an adjustable tone control feature the initial measurement is to be performed with the default tone control setting.
3. Apply the real speech test signal with a level of -20 dBm0 at the RETP.
4. Capture the frequency spectrum at the DRP of the HATS using real-time analysis with 1/12 octave bands over the frequency range from 100 Hz to 4000 Hz for narrowband measurements, or over the frequency range from 100 Hz to 8000 Hz for wideband measurements, averaged over the entire duration of the test signal.
5. Transform the DRP frequency spectrum measurement to the FF or DF (see Annex B).
6. Divide the 1/12 octave measurement data by the 1/12 octave frequency spectrum of the test signal at the RETP and present the measurement in terms of dB(Pa/V).
7. Apply the applicable frequency response limits to determine compliance.
8. If the default tone control setting does not meet the requirement, repeat the above steps for other tone control settings to determine a tone control setting that meets the requirements.
9. Repeat with a mounting force of 2N.

6.3.3 Test Result

Refer to test Annex A.

Remark: The report only reflects the test data plots of worst mode (for GSM 850, WCDMA Band 2, LTE Band 2)

6.3.4 Test Conclusion

PASS.

7. Test Equipment List

Description	Manufacturer	Model	Internal number	Cal. Date	Cal. Due
WIDEBAND RADIO COMMUNICATION TESTER	ROHDE&SCHWARZ	CMW500	BTF-EM-023	2024/10/25	2025/10/24
Conditioning Amplifier	Brule&Kjaer	Type -2690--030	BTF-EM- 146	2025/2/11	2026/2/10
Head and Torso Simulator	Brule&Kjaer	Type 4128C	BTF-EM- 148	2025/2/11	2026/2/10
Sound Calibration	Brule&Kjaer	Type 4231	BTF-EM- 149	2025/2/08	2026/2/07
Anechoic Test Chamber	MEC	Type 115	BTF-EM- 150	N/A	N/A

8. Air Interfaces / Bands used for testing

Air-interface	Band	Tested Codec	Tested Rate(kbps)
GSM	850/1900	EFR	/
WCDMA(UMTS)	Band 2/4/5	AMR-NB	4.75/12.2
		AMR-WB	6.6/14.25
VoLTE	Band 2/4/5/12/25/26/66/71	AMR-NB	4.75/12.2
		AMR-WB	6.6/14.25

9. Test Result

9.1 Receive volume control, distortion and noise performance

Plot No.	Mode	Channel/Freq.	BW	Codec B itrate	Volume Level	Codec T ype	Codec B andwidt h	Mountin g Force (N)	Freque ncy(H Z)	Min PN-SDNR(d B)	PN-SDN R Limb (dB)	Signal Q uality (d B)	Convers ational Gain	FCC CG Limit (d B)	CG Mar gin (dB)	Verdi ct
1	GSM850	128/824.2MHz	/	/	Max	EFR	NB	8N	800	20.54	20.00	91.41	21.41	6.00	15.41	Pass
			/	/	Max	EFR	NB	2N	3150	20.31	20.00	84.24	14.24	6.00	8.24	
2	PCS1900	810/1909.8MHz	/	/	Max	EFR	NB	8N	3150	20.65	20.00	91.63	21.63	6.00	15.63	Pass
			/	/	Max	EFR	NB	2N	3150	20.51	20.00	85.08	15.08	6.00	9.08	
3	WCDMA Band II	9538/1907.6MHz	/	12.20	Max	AMR	NB	8N	500	23.56	20.00	88.69	18.69	6.00	12.69	Pass
			/	12.20	Max	AMR	NB	2N	3150	21.69	20.00	91.57	21.57	6.00	15.57	
			/	14.25	Max	AMR	WB	8N	2000	22.15	20.00	88.20	18.20	6.00	12.20	
			/	14.25	Max	AMR	WB	2N	5000	20.87	20.00	79.81	9.81	6.00	3.81	
4	WCDMA Band IV	1312/1712.4MHz	/	12.20	Max	AMR	NB	8N	500	23.29	20.00	88.82	18.82	6.00	12.82	Pass
			/	12.20	Max	AMR	NB	2N	3150	21.75	20.00	91.66	21.66	6.00	15.66	
			/	14.25	Max	AMR	WB	8N	2000	22.30	20.00	88.41	18.41	6.00	12.41	
			/	14.25	Max	AMR	WB	2N	5000	21.05	20.00	80.56	10.56	6.00	4.56	
5	WCDMA Band V	4183/836.4MHz	/	12.20	Max	AMR	NB	8N	500	23.52	20.00	88.74	18.74	6.00	12.74	Pass
			/	12.20	Max	AMR	NB	2N	3150	21.86	20.00	91.78	21.78	6.00	15.78	
			/	14.25	Max	AMR	WB	8N	2000	22.37	20.00	88.58	18.58	6.00	12.58	
			/	14.25	Max	AMR	WB	2N	5000	21.14	20.00	80.74	10.74	6.00	4.74	
6	LTE FDD Band 2	19100/1900.0MHz	20MHz_QPSK_1_99	12.20	Max	AMR	NB	8N	500	20.83	20.00	89.15	19.15	6.00	13.15	Pass
				12.20	Max	AMR	NB	2N	630	21.35	20.00	85.53	15.53	6.00	9.53	
				14.25	Max	AMR	WB	8N	2000	20.82	20.00	88.18	18.18	6.00	12.18	
				14.25	Max	AMR	WB	2N	5000	22.29	20.00	85.17	15.17	6.00	9.17	
7	LTE FDD Band 4	20050/1720.0MHz	20MHz_QPSK_1_0	12.20	Max	AMR	NB	8N	500	20.98	20.00	89.25	19.25	6.00	13.25	Pass
				12.20	Max	AMR	NB	2N	3150	21.50	20.00	85.78	15.78	6.00	9.78	
				14.25	Max	AMR	WB	8N	2000	21.08	20.00	88.32	18.32	6.00	12.32	
				14.25	Max	AMR	WB	2N	5000	22.41	20.00	85.63	15.63	6.00	9.63	
8	LTE FDD Band 5	20525/836.5MHz	10MHz_QPSK_1_0	12.20	Max	AMR	NB	8N	500	21.02	20.00	89.28	19.28	6.00	13.28	Pass
				12.20	Max	AMR	NB	2N	630	21.44	20.00	86.65	16.65	6.00	10.65	
				14.25	Max	AMR	WB	8N	2000	21.15	20.00	88.41	18.41	6.00	12.41	
				14.25	Max	AMR	WB	2N	2000	22.45	20.00	85.33	15.33	6.00	9.33	
9	LTE FDD Band 12	23095/707.5MHz	10MHz_QPSK_1_49	12.20	Max	AMR	NB	8N	500	20.89	20.00	89.40	19.40	6.00	13.40	Pass
				12.20	Max	AMR	NB	2N	3150	21.48	20.00	85.88	15.88	6.00	9.88	
				14.25	Max	AMR	WB	8N	5000	20.91	20.00	89.02	19.02	6.00	13.02	
				14.25	Max	AMR	WB	2N	5000	22.40	20.00	86.16	16.16	6.00	10.16	
10	LTE FDD Band 25	26590/1905.0MHz	20MHz_QPSK_1_99	12.20	Max	AMR	NB	8N	3150	21.04	20.00	89.85	19.85	6.00	13.85	Pass
				12.20	Max	AMR	NB	2N	3150	21.53	20.00	86.25	16.25	6.00	10.25	
				14.25	Max	AMR	WB	8N	2000	20.95	20.00	89.74	19.74	6.00	13.74	
				14.25	Max	AMR	WB	2N	5000	22.36	20.00	85.98	15.98	6.00	9.98	
11	LTE FDD Band 26	26865/831.5MHz	10MHz_QPSK_1_0	12.20	Max	AMR	NB	8N	500	21.26	20.00	90.05	20.05	6.00	14.05	Pass
				12.20	Max	AMR	NB	2N	630	21.59	20.00	86.11	16.11	6.00	10.11	
				14.25	Max	AMR	WB	8N	5000	21.09	20.00	88.95	18.95	6.00	12.95	
				14.25	Max	AMR	WB	2N	5000	22.57	20.00	85.86	15.86	6.00	9.86	
12	LTE FDD Band 66	132072/1720.0MHz	20MHz_QPSK_1_0	12.20	Max	AMR	NB	8N	500	21.51	20.00	89.57	19.57	6.00	13.57	Pass
				12.20	Max	AMR	NB	2N	3150	21.69	20.00	85.78	15.78	6.00	9.78	
				14.25	Max	AMR	WB	8N	2000	21.77	20.00	88.36	18.36	6.00	12.36	
				14.25	Max	AMR	WB	2N	5000	21.85	20.00	85.42	15.42	6.00	9.42	
13	LTE FDD Band 71	133222/673.0MHz	20MHz_QPSK_1_49	12.20	Max	AMR	NB	8N	630	21.43	20.00	90.00	20.00	6.00	14.00	Pass
				12.20	Max	AMR	NB	2N	630	21.58	20.00	85.89	15.89	6.00	9.89	
				14.25	Max	AMR	WB	8N	5000	21.62	20.00	89.03	19.03	6.00	13.03	
				14.25	Max	AMR	WB	2N	5000	21.80	20.00	86.12	16.12	6.00	10.12	

Note: 1.This device does not support VoWiFi, so VoWiFi is not tested and evaluated.

2.With a mounting force of 8N, the DUT shall have at least one volume control setting that will produce a conversational gain of ≥ 18 dB with the output distortion and the frequency response.


3.With a mounting force of 2N, the DUT shall have at least one volume control setting that will produce a conversational gain of ≥ 6 dB with the output distortion and the frequency response.

4.With a mounting force of 8N and 2N, the ratio of the stimulus signal power to the 100 Hz to 8000 Hz total A-weighted distortion and noise power shall be ≥ 20 dB.

9.2 Receive acoustic frequency response performance

Plot No.	Mode	Channel/Freq.	BW	Volume Level	Codec Type	Codec Bandwidth	Mounting Force (N)	RFR
								Test Result
1	GSM850	128/824.2MHz	/	Max	EFR	NB	2N	Pass
				Max	EFR	NB	8N	
2	PCS1900	810/1909.8MHz	/	Max	EFR	NB	2N	Pass
				Max	EFR	NB	8N	
3	WCDMA Band II	9538/1907.6MHz	/	Max	AMR	NB	2N	Pass
				Max	AMR	NB	8N	
				Max	AMR	WB	2N	
				Max	AMR	WB	8N	
4	WCDMA Band IV	1312/1712.4MHz	/	Max	AMR	NB	2N	Pass
				Max	AMR	NB	8N	
				Max	AMR	WB	2N	
				Max	AMR	WB	8N	
5	WCDMA Band V	4183/836.4MHz	/	Max	AMR	NB	2N	Pass
				Max	AMR	NB	8N	
				Max	AMR	WB	2N	
				Max	AMR	WB	8N	
6	LTE FDD Band 2	19100/1900.0MHz	20MHz_QPSK_1_99	Max	AMR	NB	2N	Pass
				Max	AMR	NB	8N	
				Max	AMR	WB	2N	
				Max	AMR	WB	8N	
7	LTE FDD Band 4	20050/1720.0MHz	20MHz_QPSK_1_0	Max	AMR	NB	2N	Pass
				Max	AMR	NB	8N	
				Max	AMR	WB	2N	
				Max	AMR	WB	8N	
8	LTE FDD Band 5	20525/836.5MHz	10MHz_QPSK_1_0	Max	AMR	NB	2N	Pass
				Max	AMR	NB	8N	
				Max	AMR	WB	2N	
				Max	AMR	WB	8N	
9	LTE FDD Band 12	23095/707.5MHz	10MHz_QPSK_1_49	Max	AMR	NB	2N	Pass
				Max	AMR	NB	8N	
				Max	AMR	WB	2N	
				Max	AMR	WB	8N	
10	LTE FDD Band 25	26590/1905.0MHz	20MHz_QPSK_1_99	Max	AMR	NB	2N	Pass
				Max	AMR	NB	8N	
				Max	AMR	WB	2N	
				Max	AMR	WB	8N	
11	LTE FDD Band 26	26865/831.5MHz	10MHz_QPSK_1_0	Max	AMR	NB	2N	Pass
				Max	AMR	NB	8N	
				Max	AMR	WB	2N	
				Max	AMR	WB	8N	
12	LTE FDD Band 66	132072/1720.0MHz	20MHz_QPSK_1_0	Max	AMR	NB	2N	Pass
				Max	AMR	NB	8N	
				Max	AMR	WB	2N	
				Max	AMR	WB	8N	
13	LTE FDD Band 71	133222/673.0MHz	20MHz_QPSK_1_49	Max	AMR	NB	2N	Pass
				Max	AMR	NB	8N	
				Max	AMR	WB	2N	
				Max	AMR	WB	8N	

10. EUT photograph







Volume Control Verification Test Results

Date of Testing	Test Location	Air Interface Equipment	Acoustical Calibrator	HATS Sens.(dB)	Ambient Noise(dBA)
27/4/2025	JB HATS R	CMW 500	B&K 4231 & UA1546	97.06	32.63
28/4/2025	JB HATS R	CMW 500	B&K 4231 & UA1546	97.16	32.41
29/4/2025	JB HATS R	CMW 500	B&K 4231 & UA1546	97.25	32.55


ANNEX A Test Data

1. GSM 850 in channel 128


1.1 Receive Distortion and Noise 8N NB

400Hz**500Hz****630Hz****800Hz**


1000Hz




1250Hz




1600Hz




2000Hz



2500Hz



3150Hz




Frequency	SDNR	Frequency	SDNR
400Hz	23.92 dB	1250Hz	29.83 dB
500Hz	21.53 dB	1600Hz	25.31 dB
630Hz	23.19 dB	2000Hz	28.61 dB
800Hz	20.54 dB	2500Hz	24.66 dB
1000Hz	24.60 dB	3150Hz	20.94 dB


All SDNRs were greater than 20.0 dB, requirement was met. Smallest SDNR was 20.54dB at 800Hz.

1.2 Receive Distortion and Noise 2N NB


400Hz




500Hz




630Hz




800Hz




1000Hz




1250Hz




1600Hz




2000Hz



2500Hz




3150Hz



Frequency	SDNR	Frequency	SDNR
400Hz	24.74 dB	1250Hz	28.55 dB
500Hz	26.68 dB	1600Hz	23.03 dB
630Hz	21.75 dB	2000Hz	27.41 dB
800Hz	22.38 dB	2500Hz	28.64 dB
1000Hz	25.35 dB	3150Hz	20.31 dB

All SDNRs were greater than 20.0 dB, requirement was met. Smallest SDNR was 20.31dB at 3150Hz.


1.3 Receive Frequency Response




2. WCDMA band 2 in channel 9538

2.1 Receive Distortion and Noise 8N WB


250Hz




315Hz




400Hz




500Hz




630Hz




800Hz




1000Hz




1250Hz




1600Hz




2000Hz




2500Hz




3150Hz



4000Hz




5000Hz




Frequency	SDNR	Frequency	SDNR
250Hz	23.43 dB	1250Hz	24.46 dB
315Hz	28.23 dB	1600Hz	27.86 dB
400Hz	29.76 dB	2000Hz	22.15 dB
500Hz	31.61 dB	2500Hz	22.34 dB
630Hz	27.17 dB	3150Hz	27.81 dB
800Hz	28.40 dB	4000Hz	27.23 dB
1000Hz	27.27 dB	5000Hz	22.19 dB

All SDNRs were greater than 20.0 dB, requirement was met. Smallest SDNR was 22.15 dB at 2000Hz.


2.2 Receive Distortion and Noise 2N WB




630Hz




800Hz




1000Hz




1250Hz




1600Hz




2000Hz




2500Hz




3150Hz



4000Hz




5000Hz



Frequency	SDNR	Frequency	SDNR
250Hz	22.84 dB	1250Hz	23.47 dB
315Hz	30.53 dB	1600Hz	29.45 dB
400Hz	32.43 dB	2000Hz	21.59 dB
500Hz	33.78 dB	2500Hz	23.44 dB
630Hz	26.03 dB	3150Hz	27.70 dB
800Hz	29.90 dB	4000Hz	27.18 dB
1000Hz	27.37 dB	5000Hz	20.87 dB


All SDNRs were greater than 20.0 dB, requirement was met. Smallest SDNR was 20.87 dB at 5000Hz.

2.3 Receive Frequency Response




3. LTE band 2 in channel 19100


3.1 Receive Distortion and Noise 8N WB




630Hz




800Hz




1000Hz




1250Hz




1600Hz




2000Hz




2500Hz




3150Hz



4000Hz




5000Hz




Frequency	SDNR	Frequency	SDNR
250Hz	23.80 dB	1250Hz	24.50
315Hz	30.61 dB	1600Hz	26.38
400Hz	31.26 dB	2000Hz	20.82
500Hz	33.42 dB	2500Hz	22.50
630Hz	27.57 dB	3150Hz	28.22
800Hz	28.00 dB	4000Hz	27.66
1000Hz	26.96 dB	5000Hz	22.01

All SDNRs were greater than 20.0 dB, requirement was met. Smallest SDNR was 20.82 dB at 2000 Hz.


3.2 Receive Distortion and Noise 2N WB




630Hz




800Hz




1000Hz




1250Hz




1600Hz




2000Hz




2500Hz




3150Hz



4000Hz




5000Hz



Frequency	SDNR	Frequency	SDNR
250Hz	23.94 dB	1250Hz	24.22 dB
315Hz	28.47 dB	1600Hz	24.38 dB
400Hz	29.28 dB	2000Hz	26.26 dB
500Hz	33.24 dB	2500Hz	22.52 dB
630Hz	29.25 dB	3150Hz	27.12 dB
800Hz	30.32 dB	4000Hz	26.47 dB
1000Hz	28.05 dB	5000Hz	22.29 dB

All SDNRs were greater than 20.0 dB, requirement was met. Smallest SDNR was 22.29 dB at 5000Hz.

3.3 Receive Frequency Response



ANNEX B Test Setup Photo



ANNEX C CALIBRATION REPORT

Please refer the document "CALIBRATION REPORT.pdf".



BTF Testing Lab (Shenzhen) Co., Ltd.

F101, 201 and 301, Building 1, Block 2, Tantou Industrial Park, Tantou Community, Songgang Street,
Bao'an District, Shenzhen, China

www.btf-lab.com

--END OF REPORT--