TranXformer™ One


Quick Guide

(SP932)




SUMMARY

TranXformer 1 is the ultimate pocket speaker. With its patented expandable design, the TranXformer 1 produces a decent sound with the best bass in its class while maintaining a height of only 1 3/4 inch when collapsed.




CONNECTIONS



AUTO ON

The TranXformer 1 will automatically turn on when expanded



AUTO OFF

When there is no Bluetooth or Aux in signals for over 5 minutes, the TranXformer 1 will automatically switch off to preserve battery power. To turn it on again, please press the X button.

POWRER BUTTON

Holding down the X button for 1 second will toggle the unit on and off.

FIRST-TIME SETUP



The TranXformer 1 needs to be paired with your mobile device first.

When first switched on, the TranXformer 1 will enter paring mode automatically. The Bluetooth LED will be flashing quickly during paring.

Please turn on Bluetooth via Settings, then select 'X-1' when it appears on the device list.

To enter paring mode for other devices, please hold down the Bluetooth button for over 3 seconds until the Bluetooth LED flashes quickly.





BLUETOOTH SPEAKER

Pressing the Bluetooth button briefly will pause/platy the music player. You can use the Vol+ and Vol- button to adjust the volume.

HANDS-FREE CALL

When the phone rings, pressing the Bluetooth button once will answer the call in hands-free speaker phone mode. When the phone is idle, pressing the Bluetooth button twice will redial the number.

BATTERY

The unit has a 1000mAh Li-Polymer rechargeable battery. When battery is low, the LED will flash in red. You can charge the unit via the micro-USB port. The charging time is about 3 hours.

The average play time is 6 hours. You can monitor the battery usage on your mobile device.

LIGHTSHOW

There are three modes for the Lightshow. Pressing the X button briefly will toggle between the 3 modes.

- On the colors and brightness of the lights are synchronized with the music. If the music is turned down, the lights will go dark.
- 2) Ambient Light Lightshow is on when the music level is above 50%. The light will breathe in different color when the music is turned down.
- 3) Off No light at all.



SPORTS JACKETS

The sports jacket can be put on to the top of the unit for carrying. This provides a different look. It can also support the TranXformer 1 to stand sideway.









Hiking

BIKE MOUNT KIT



Bike mount kit is included for easy mounting and dismounting of the TranXformer 1 to a bike.



X-BASS™

The TranXformer 1 incorporates a few technologies in order to 'break the sound barrier' in such a compact unit. With the X-Bass™ structure, the TranXformer triples the airspace to lower the resonance frequency for a full low (120-200Hz).

Secondly, a custom-made passive radiator helps to boost a deep low (80-120Hz). In addition, active equalization is used to provide a smooth mid and a clear high.

And finally, a 2-inch dual-magnet/dual-coil driver with 5 watts RMS delivers the most powerful and balanced sound in its class.



Note: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- —Reorient or relocate the receiving antenna.
- —Increase the separation between the equipment and receiver.
- —Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- —Consult the dealer or an experienced radio/TV technician for help.

This device complies with part 15 of the FCC rules. Operation is subject to the following two conditions:

- (1) this device may not cause harmful interference, and
- (2) this device must accept any interference received, including interference that may cause undesired operation.

Changes or modifications to this unit not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

In order to comply with RF exposure requirements, a minimum distance of 5mm must be maintained between the antenna and all persons