



MPE TEST REPORT

Report Reference No.....	TRE1607018202	R/C.....:90529
FCC ID.....	2AEKCPR800VHF	
Applicant's name.....	ZTE TRUNKING TECHNOLOGY CORPORATION	
Address.....	4/F, R&D Building 1, ZTE Industrial Park, LiuXian Road, Xili, Nanshan District, Shenzhen, P. R. China	
Manufacturer.....	ZTE TRUNKING TECHNOLOGY CORPORATION	
Address.....	4/F, R&D Building 1, ZTE Industrial Park, LiuXian Road, Xili, Nanshan District, Shenzhen, P. R. China	
Test item description	DIGITAL REPEATER	
Trade Mark	ZTE	
Model/Type reference.....	PR800 VHF	
Listed Model(s)	-	
Standard	FCC Per 47 CFR 2.1091(b); KDB447498 v05r02	
Date of receipt of test sample.....	July 27, 2016	
Date of testing.....	July 28, 2016 – Aug 24, 2016	
Date of issue.....	Aug 24, 2016	
Result.....	PASS	

Compiled by	
(position+printed name+signature)..:	File administrators Shayne Zhu
Supervised by	
(position+printed name+signature)..:	Project Engineer Cary Luo
Approved by	
(position+printed name+signature)..:	RF Manager Hans Hu

Testing Laboratory Name	Shenzhen Huatongwei International Inspection Co., Ltd
Address.....	1/F, Bldg 3, Hongfa Hi-tech Industrial Park, Genyu Road, Tianliao, Gongming, Shenzhen, China

Shenzhen Huatongwei International Inspection Co., Ltd. All rights reserved.

This publication may be reproduced in whole or in part for non-commercial purposes as long as the Shenzhen Huatongwei International Inspection Co., Ltd is acknowledged as copyright owner and source of the material. Shenzhen Huatongwei International Inspection Co., Ltd takes no responsibility for and will not assume liability for damages resulting from the reader's interpretation of the reproduced material due to its placement and context.

Contents

<u>1. SUMMARY</u>	3
1.1. Client Information	3
1.2. Report version	3
1.3. Product Description	4
1.4. Test frequency list	5
1.5. EUT operation mode	6
1.6. EUT configuration	6
1.7. Modifications	6
<u>2. TEST ENVIRONMENT</u>	7
2.1. Address of the test laboratory	7
2.2. Environmental conditions	7
2.3. Statement of the measurement uncertainty	7
<u>3. METHOD OF MEASUREMENT</u>	8
3.1. Applicable Standard	8
3.2. Limit	8
3.3. MPE Calculation Method	8
<u>4. CONCLUSION</u>	11

1. **SUMMARY**

1.1. Client Information

Applicant:	ZTE TRUNKING TECHNOLOGY CORPORATION
Address:	4/F, R&D Building 1, ZTE Industrial Park, LiuXian Road, Xili, Nanshan District, Shenzhen, P. R. China
Manufacturer:	ZTE TRUNKING TECHNOLOGY CORPORATION
Address:	4/F, R&D Building 1, ZTE Industrial Park, LiuXian Road, Xili, Nanshan District, Shenzhen, P. R. China

1.2. Report version

Version No.	Date of issue	Description
00	August 24, 2016	Original
01	October 12, 2016	New
02	October 13, 2016	New

1.3. Product Description

Name of EUT:	DIGITAL REPEATER	
Trade mark:	ZTE	
Model/Type reference:	PR800 VHF	
Listed mode(s):	-	
Power supply:	DC 13.6V,AC120V/60Hz	
Battery information:	-	
Charger information:	-	
Adapter information:	-	
Operation Frequency Range:	From 136MHz to 174MHz	
Rated Output Power:	High Power: 45W (46.53dBm)/Low Power: 25W(43.98dBm)	
Modulation Type:	Analog Voice:	FM
	Digital Voice /Digital Data:	4FSK
Digital Type:	DMR	
Channel Separation:	Analog Voice:	<input checked="" type="checkbox"/> 12.5kHz
	Digital Voice /Digital Data:	<input checked="" type="checkbox"/> 12.5kHz <input type="checkbox"/> 6.25kHz
Emission Designator:	Analog Voice:	<input checked="" type="checkbox"/> 12.5kHz Channel Separation: 6K88F3E <input type="checkbox"/> 25kHz Channel Separation: ---
	Digital Voice& Data:	<input checked="" type="checkbox"/> 12.5kHz Channel Separation: 7K80FXW <input type="checkbox"/> 6.25kHz Channel Separation: ---
	Digital Data:	<input checked="" type="checkbox"/> 12.5kHz Channel Separation: 7K80FXD <input type="checkbox"/> 6.25kHz Channel Separation: ---
Support data rate:	9.6kbps	
Antenna Type:	External	
Maximum Transmitter Power:	Digital	46.24W for 12.5kHz Channel Separation
	Analog	45.81W for 12.5kHz Channel Separation

Note: The product has the same digital working characters when operating in both two digitized voice/data mode. So only one set of test results for digital modulation modes are provided in this test report.

1.4. Test frequency list

Mode	Modulation	Operation Frequency Range (MHz)	Test Frequency (MHz)
Analog	FM	136-174	CH _L 150.0125
			CH _M 162.0000
			CH _H 173.9875
Digital	4FSK	136-174	CH _L 150.0125
			CH _M 162.0000
			CH _H 173.9875

Note:

In section 15.31(m), regards to the operating frequency range over 10 MHz, the Lowest frequency, the middle frequency, and the highest frequency of channel were selected to perform the test, please see the above listed frequency for testing.

1.5. EUT operation mode

Test mode	Transmitting	Power level	Digital	Analog
		High	12.5kHz	12.5kHz
TX1	✓	✓	✓	
TX2	✓	✓		✓

✓: is operation mode.

1.6. EUT configuration

The following peripheral devices and interface cables were connected during the measurement:

- - supplied by the manufacturer
- - supplied by the lab

●	Power Cable	Length (m) :	3.00
		Shield :	Unshielded
		Detachable :	Undetachable
○	Multimeter	Manufacturer :	/
		Model No. :	/

1.7. Modifications

No modifications were implemented to meet testing criteria.

2. TEST ENVIRONMENT

2.1. Address of the test laboratory

1/F, Bldg 3, Hongfa Hi-tech Industrial Park, Genyu Road, Tianliao, Gongming, Shenzhen, China
 Phone: 86-755-26748019 Fax: 86-755-26748089

The sites are constructed in conformance with the requirements of ANSI C63.7, ANSI C63.4 (2009) and CISPR Publication 22.

2.2. Environmental conditions

During the measurement the environmental conditions were within the listed ranges:

Temperature:	15-35 ° C
Humidity:	30-60 %
Atmospheric pressure:	950-1050mbar

2.3. Statement of the measurement uncertainty

The data and results referenced in this document are true and accurate. The reader is cautioned that there may be errors within the calibration limits of the equipment and facilities. The measurement uncertainty was calculated for all measurements listed in this test report acc. to TR-100028-01 "Electromagnetic compatibility and Radio spectrum Matters (ERM);Uncertainties in the measurement of mobile radio equipment characteristics; Part 1" and TR-100028-02 "Electromagnetic compatibility and Radio spectrum Matters (ERM);Uncertainties in the measurement of mobile radio equipment characteristics; Part 2" and is documented in the Shenzhen Huatongwei International Inspection Co., Ltd quality system acc. to DIN EN ISO/IEC 17025. Furthermore, component and process variability of devices similar to that tested may result in additional deviation. The manufacturer has the sole responsibility of continued compliance of the device.

Hereafter the best measurement capability for Shenzhen Huatongwei laboratory is reported:

Test Items	Measurement Uncertainty	Notes
Transmitter power conducted	0.57 dB	(1)

(1) This uncertainty represents an expanded uncertainty expressed at approximately the 95% confidence level using a coverage factor of $k=1.96$.

3. Method of measurement

3.1. Applicable Standard

According to §1.1307(b)(1), systems operating under the provisions of this section shall be operated in a manner that ensures that the public is not exposed to radio frequency energy level in excess of the Commission's guidelines.

According to §1.1310 and §2.1091 RF exposure is calculated.

KDB447498 v05r02:Mobile and Portable Devices RF Exposure Procedures and Equipment Authorization Policies

3.2. Limit

FCC Part 2.1091:

Limits for Maximum Permissible Exposure (MPE)/Controlled Exposure

Frequency Range(MHz)	Electric Field Strength(V/m)	Magnetic Field Strength(A/m)	Power Density (mW/cm ²)	Averaging Time (minute)
Limits for Occupational/Controlled Exposure				
0.3 – 3.0	614	1.63	(100) *	6
3.0 – 30	1842/f	4.89/f	(900/f ²)*	6
30 – 300	61.4	0.163	1.0	6
300 – 1500	/	/	f/300	6
1500 – 100,000	/	/	5	6

F=frequency in MHz

*=Plane-wave equivalent power density

3.3. MPE Calculation Method

Predication of MPE limit at a given distance

Equation from page 18 of OET Bulletin 65, Edition 97-01

$$S = PG/4\pi R^2$$

Where: S=power density

P=power input to antenna

G=power gain of the antenna in the direction of interest relative to an isotropic radiator

R=distance to the center of radiation of the antenna

As declared by the Applicant, the EUT transmits with the maximum source-based Duty Cycle of 100%-see the User manual, and the EUT is a wireless device used in a mobile application, at least 360cm from any body part of the user or nearby persons; from the maximum EUT RF output power, the minimum mobile separation distance, r =360cm, as well as the gain of the used antenna is 8.5dBi, the RF power density can be obtained.

TEST RESULTS

FCC Part 2.1091:
DC 13.6V

TX1										
Test Frequency (MHz)	Minimum Separation Distance (cm)	Output Power (1) (dBm)	Output Power (2) (W)	Output Power (3) (dBm)	Output Power (4) (W)	Output Power (5) (mW)	Antenna Gain (Numeric)	Power Density At 360cm (mW/cm ²)	Power Density Limit FCC (mW/cm ²)	Test Results
150.0125	360	46.44	44.02	47.44	55.42	55423	7.0795	0.2410	1.0000	PASS
162	360	46.38	43.42	47.38	54.67	54666	7.0795	0.2378	1.0000	
173.9875	360	46.28	42.44	47.28	53.43	53427	7.0795	0.2324	1.0000	

TX2										
Test Frequency (MHz)	Minimum Separation Distance (cm)	Output Power (1) (dBm)	Output Power (2) (W)	Output Power (3) (dBm)	Output Power (4) (W)	Output Power (5) (mW)	Antenna Gain (Numeric)	Power Density At 360cm (mW/cm ²)	Power Density Limit FCC (mW/cm ²)	Test Results
150.0125	360	46.40	43.62	47.40	54.92	54917	7.0795	0.2388	1.0000	PASS
162	360	46.35	43.13	47.35	54.29	54292	7.0795	0.2361	1.0000	
173.9875	360	46.28	42.44	47.28	53.43	53427	7.0795	0.2324	1.0000	

Note: Output Power(1)=Measured power,

Output Power(2)= $(10^{(Output\ Power(1))/10}) / 1000$

Output Power(3)=Output Power(1)+Tolerance, Tolerance=1dB

Output Power(4)= $(10^{(Output\ Power(3))/10}) / 1000$

Output Power(5)= Output Power(2)* (Output Power(4)/Output Power(2))

AC 120V:

TX1										
Test Frequency (MHz)	Minimum Separation Distance (cm)	Output Power (1) (dBm)	Output Power (2) (W)	Output Power (3) (dBm)	Output Power (4) (W)	Output Power (5) (mW)	Antenna Gain (Numeric)	Power Density At 360cm (mW/cm ²)	Power Density Limit FCC (mW/cm ²)	Test Results
150.0125	360	46.65	46.24	47.65	58.21	58210	7.0795	0.2532	1.0000	PASS
162	360	46.59	45.60	47.59	57.41	57412	7.0795	0.2497	1.0000	
173.9875	360	46.49	44.57	47.49	56.10	56105	7.0795	0.2440	1.0000	

TX2										
Test Frequency (MHz)	Minimum Separation Distance (cm)	Output Power (1) (dBm)	Output Power (2) (W)	Output Power (3) (dBm)	Output Power (4) (W)	Output Power (5) (mW)	Antenna Gain (Numeric)	Power Density At 360cm (mW/cm ²)	Power Density Limit FCC (mW/cm ²)	Test Results
150.0125	360	46.61	45.81	47.61	57.68	57677	7.0795	0.2508	1.0000	PASS
162	360	46.56	45.29	47.56	57.02	57016	7.0795	0.2480	1.0000	
173.9875	360	46.49	44.57	47.49	56.10	56105	7.0795	0.2440	1.0000	

Note: Output Power(1)=Measured power,

Output Power(2)= $(10^{(Output\ Power(1))/10}) / 1000$

Output Power(3)=Output Power(1)+Tolerance, Tolerance=1dB

Output Power(4)= $(10^{(Output\ Power(3))/10}) / 1000$

Output Power(5)= Output Power(2)* (Output Power(4)/Output Power(2))

4. Conclusion

The measurement results comply with the FCC Limit per 47 CFR 2.1091 for the controlled RF Exposure.

.....End of Report.....