HB6550Plus(JD) 说明书 (hellobaby)

说明书为折叠式

尺寸: 720*120MM 材质:80g双胶纸(彩色) 版本: V1.0(JDT)

类型: 环保


料号: W4-0100-6550-013-10

审批 审核 Tony-W 2024/10/14

HelloBaby[®]

User Manual

2.4GHz Digital Wireless Video Baby Monitor 2.4GHz Digital Wireless Video Baby Camera



www.hellobabv.net.cn

ee and hear your baby sleeping or playing in their room anytime

Please retain your original dated sales receipt for your records. For warranty service of product, you will need to provide a copy of your dated sales receipt to confirm warranty tatus. Registration is not required for warranty coverage.

PLEASE MAKE SURE THE FOLLOWING INCLUDED IN YOUR PACKAGE

1. SAFETY INSTRUCTIOINS

Strangulation hazard: Keep this cord out of the reach of children (more than 3ft (0.9m v). Never use extension cords with AC Adapters. Only usethe AC Adapters provide Choking hazard: This product contains small parts, please be careful when unpack and

Read and keep to instructions: All the safety and operating in structions should be real before the yideo baby monitor is operated. This product cannot replace responsible adult Water and moisture: The unit should not be exposed to rain, moisture, dripping or

plashing. No objects filled with liquid should be placed on top of, or beside the product, such as a

y block the ventilation openings, or be placed in an enclosed area such as a boo

uch as a candle, radiator, heat register, stove or other appliance that emits heat. The uni hould not be left in direct sunlight. **Power source:** This unit should only be used with the AC power adapters included in thi

package (rated 5V DC 1A). **Damage requiring service:** This unit should be serviced by qual

. The units do not appear to operate normally or exhibits a dis

The units have been dropped or the enclosure damaged. WARRANTVTERMS

3. INSTALLATION GUIDELINES

To use your parent unit and camera unit together, you have to establish a radio link between them, and the range will be affected by environmental conditions.

Any large metal object, like a refrigerator, a mirror, a filling cabinet, metallic doors or reinforced concrete between the baby and parent unit may block the radio signal.

The signal strength may also be reduced by other solid structures, like walls, or by radio or electrical equipment, such as TV, computers, cordless or mobile phones, fluorescent likebes or dispures switches.

lights or dimmer switches.
Use of other 2.4GHz product, such as wireless networks (Wi-Fi routers), Bluetooth systems, or microwave ovens, may cause interference with this product, so keep the baby monitor away at least 5ft (1.5m) from such products, or turn them off if they cause

. PLACEMENT OF THE BABY MONITOR

the camera can be placed on the desktop or mounted on the wall. Don't place baby monito
n soft quilts or blankets or in the corners of cupboards, shelves, etc; Keep the baby monit
way from heat sources such as radiators, chimneys, cookers and direct sunlight; Keep the by unit away from TV sets, microwave oven and radios. If interference occurs, move the

* Place the camera within 6 feet (2 meters) of the area being monitored for optimum

.1 TURN ON THE BABY UNIT:

GETTING STARTED

1. I LINEN ON THE BABY UNIT:

1. Insert the DC plug of the power adapter into the DC jack in the rear of the Baby Unit.

2. Insert the other end of the power adapter into a suitable electrical outlet.

[ote: To prevent any disturbance to children, we have implemented an advanced invisible

. Insert the DC plug of the power adapter into the DC jack in the side of the Parent Unit. Insert the other end of the power adapter into a suitable electrical outlet. . Press and hold the power key 3 seconds on the side of the parent unit 4. Once parent unit is on, the power LED will light up and the image will display on the

5.3 PAIRING THE CAMERA AND PARENT UNITS

5.3 PAIRING THE CAMERAAND PARENT UNITS

The baby unit is pre-registered to your parent unit, just watch your baby from the screen, enjoy it! If the two devices don't pair, follow the procedure below:

1. Make sure the parent unit has power and the baby unit is plugged in.
(Please check in a dim environment to ensure that the camera is powered.)

2. Enter "Camera" on the screen of the parent unit, and choose to add a camera.

3. When the hourglass icon is displayed on the LCD screen, press the PAIR button on the back of the baby unit.

Note: The camera icon with "


5.4 INFRARED NIGHT VISION (AUTOMATIC)


ision mode, the icon 🛂 will be displayed on the top of screen.

nfrared night vision function allows the camera to pick up images in dark or low ligh tions. In this mode, only black and white images will be displayed on the monitor, tl optimum image lie in where baby unit is 6ft (2m) away from object. The camera is in nigh

6. PRODUCT OVERVIEW








6.3 BABY UNIT OVERVIEW

720.00 mm



. KEY OPERATION 1 TURN ON/OFF

7.2 UP ▲ KEY

7.3 DOWN ▼ KEY 7.4 LEFT **⋖** KEY

7.5 RIGHT ► KEY

7.6 CAMERA VIEW/SCAN

user to see both cameras side by side on the same screen.

Press (a) key to view/scan camera:

Press 2 times: View camera 1, and icon − ② 1 displays on the top of the screen.

Press 2 times: View camera 2, and icon − ② 2 displays on the top of the screen.

Press 2 times: Enter into SPLIT-SCREEN mode, both the icon − ② 1 and − ③ 2 displays on the top of the screen. You can see both camera side by side on the same screen.

Press 4 times: Loop scan camera 1 and camera 2, and icon − ② 1 & − ② 2 displays on the top of the screen. Each camera's video will display on the screen around 10 seconds.

Nate: In the split-screen interface, the cursor defaults to Camera 1. The video sound that the Note: In the split-screen interface, the cursor defaults to Camera 1. The video sound that t display screen plays comes from Camera 1. If you want to listen to the sound from Camera please move the cursor to Camera 2. The video sound that the display screen plays will the

come from Camera 2. (I **7.7 DIGITAL ZOOM** mode, press and hold the (a) key around 2 seconds to operate zoom in/ou 7.8 TWO WAY TALK node, Press and hold 👀 key to enter two-way talk mode. A microphone

icon 🖢 will be displayed in the corner of the LCD screen. Release the key to stop Note: When you are in the two-way talk mode, the parent unit speaker is muted.

8.1 PAIRING THE CAMERA AND PARENT UNITS

he baby unit loses its link with the parent unit. To re-register your baby unit, or register

8.1.1 ADD CAMERA . Press the MENU (key then the menu will pop up

2. Press the ◀ / ▶ / ▲ / ▼ keys until the camera icon ② is selected. 3. Press OK (key to enter into sub-menu, then press ▲ / ▼ keys to sel

4. Press 🚇 key enter into sub-menu; Press 🛦 / 🔻 keys to select 💁 then press 🖫 ke

camera.

Once paired, Successful pairing icon (S) shows on the LCD screen.

8.1.2 DELETE CAMERA

1. Press the MENU (♣) key and the menu will pop up.
2. Press the ◀/▶/▲/▼ keys until the camera icon ② is selected.

3. Press OK (key to enter into sub-menu, then press ▲ / ▼ key

4. Press 🖫 key enter into sub-menu; Press 🛦 / 🔻 keys to select 🔼 then press 🧓 ke

4. Press (a) key enter into suo-menu; Press ▲ / ▼ key

5. Press key to select ▼ icon to delete the camera.

6. Press OK (a) key to confirm the option.

8.2 VOLUME

1. Press the (a) key then the menu will pop up.

2. Press the ◀/▶/▲/▼ keys until the Volume icon 🚳 is selected.

 Press the ▲ / ▼ keys to select the desired volume level from level 1 ~ 5. 3.3 DISPLAY BRIGHTNESS

2. Press the ◀/▶/▲/▼ keys until the brightness icon 👺 is selected.

3. Press (key enter into sub-menu.
4. Press (√) keys to select the desired brightness level from level 1 ~ 5.

. Press the MENU (key then the menu will pop up. 2. Press the ◀ / ▶ / ▲ / ▼ kevs until the tem

4. Press the ◀/▶ keys to select the °F or °C for setting temperature unit.

1. Press the ◀ / ▶ / ▲ / ▼ keys to select 🍿 for turning on alarm function; Press ເ key

2. Press the ◀ / ▶ / ▲ / ▼ keys to select 🕷 for turning off alarm function; Press 👼 key 8.4.2 SET TEMPERATURE HI/LO ALERT LIMITS

1. Press ◀/ ▶ keys to select ⑧ or ⑧ for Hi/Lo limits settings

2. Press ▲ / ▼ keys to adjust the Hi limit when • (red) is selected. 3. Press A / V keys to adjust the Lo limit when (green) is selected.

default setting is 8 °C. When the temperature goes above or below the settings, the e icon 📺 will display on the screen. It will alert user by beeping. Press

4. Press the ◀/►/▲/▼ keys to select one of the 8 available lullabies, and you can pic single playback, loop (all 8 lullabies) playback $\mathcal{P}_{\mathcal{C}}^{\bullet}$ or stop 2. 5. Press 3 key to confirm.

1. Press MENU (key and the menu will pop up.

2. Press the ◀/▶/▲/▼ keys until the Setting ico ♣ is selected
3. Press the MENU Key ⑤. The sub-menu Settings will pop up.

4. Press the ◀/▶ keys until the alarm icon is selected. 5. Press the (key enter into sub-menu, Press the ◀ / ▶ / ▲ / ▼ keys to selected the

he radiator & your body.

ecific Absorption Rate (SAR) information:

SAR English

Note 1: The minimum unit is 0.5 hour. The maximum setting is 5 hours (7 levels).

Note 2: Once the alarm is turned on, alarm icon of will display on the screen. Note 3: The alarm default setting is OFF.

du cnr - 102 et conformité avec rss 102 de l'exposition aux rf, les utilisateurs per

des données canadiennes sur l'exposition aux champs rf et la conformité. This equipment complies with Canada radiation exposure limits set forth for an uncontr

This equipment should be installed and operated with minimum distance 0cm between

Cet équipement doit être installé et utilisé avec une distance minimale de 0 cm entre le

Specific Absorption Rate (SAR) information.

This Tablet meets the government's requirements for exposure to radio waves. The guidelines are based on standards that were developed by independent scientific organizations through periodic and thorough evaluation of scientific studies. The standar

include a substantial safety margin designed to assure the safety of all persons regardless (age or health, ISED RF Exposure Information and Statement the SAR limit of Canada (ISED) is 1.6 W/kg averaged over one gram of tissue. Device types: Tablet has also been tested against this SAR limit. This device was tested for typical body-worn operations with

the back of the Tablet kept 0mm from the body. To maintain compliance with ISED RF

exposure requirements, use accessories that maintain an 0mm separation distance bet the user's body and the back of the Tablet . The use of belt clips, holsters and similar

nforme Canada limites d'exposition aux radiations dans un









the alarm will ring again for 1 minute. The alarm will ring for three times in total, after this 8.6.2 DATE/TIME SETTING

2. Press the ◀ / ▶ / ▲ / ▼ keys until the Setting icon ♣ is selected.
3. Press the MENU Key ᠍. The sub-menu Settings will pop up.
4. Press ◀ / ▶ keys until the time icon ⓓ is selected. 5. Press the (key enter into sub-menu, Press ◀ / ▶ keys to select Month, Day and Yea setting; Press ▲ / ▼ keys to set your desired month, date and year.

6. Press the ◀ / ▶ keys to select the timing method 12H or 24H.

6. Press the ◀ / ▶ keys to select the timing method 12H or 24H.

8.7 ENERGY SAVING

This mode allows you to control the sound activation of your baby unit. If there is no sound around the baby unit within 30 seconds, it will stop audio transmission and turn off the screen of the parent unit. When the baby unit detects any sounds louder than the sensitivity level, it will start transmitting the signal to the parent unit again and turn on the screen of the parent unit. To change the ECO level, please follow the below instructions.

1. Press the MENU ② key and the menu will pop up.

2. Press the ◀/►/▲/▼ keys until the ECO icon is so

3. Press ∰ key enter into sub-menu, then press ▲ /▼ keys to select desired level.
4. Press ∰ key to confirm. Note: Is Low sensitivity level, the baby have to make a lot of sound before the ECO function is activated

Note: is High sensitivity level, the baby don't have to make a lot of sound before the EC

8.8 LANGUAGE SETTING

2. Press the ◀/ ▶/▲/▼ keys until the language icon ② is selected.

3. Press ∰ key to enter into sub-menu, then press ◀/ ▶/▲/▼ keys to select the language you need.

4. Press (key to confirm.

5. Press (key to exit.

2412MHz~2469MHz Parent Unit: Input: 100-240VAC 50/60Hz Output: 5V DC 1A Camera Unit: Input: 100-240VAC 50/60Hz Output: 5V DC 1A Up to 1000ft (300m) outdoor (line of sight) Up to 165ft (50m) indoor Operating Range 6.0" IPS TFT LCD Li-ion 3.7V 4000mAh (14.8Wh Operation Temperature: +32°F~+104°F (0°C~40°C) Battery Charging Temperature: +50°F~+104°F (10°C~40°C)

Camera may be far away from the monitor. Camera and monitor may not be paired, please follow the PAIRING instructions:

Repower the baby unit(plug out the adapter, then plug it into the stock again)
Press the RESET key at the back of parent unit, then enter to the MENU and select Add Press the PAIR key at the back of baby unit, waiting for pairing successfully

Q: Audio Feedback(High Pitched Noise)

* The camera and monitor may be placed too close.

* The volume on the monitor may be set too high.

* Check the volume of the lullabies and the two-way calls, contact: service@hellobaby.net.cn if there is no sound.

Other electronic devices may be intrefering with the siginal.

O: Frozen Picture on Screen * Repower the baby unit(plug out the adapter, then plug it into the stock again) * Press the RESET key at the back of parent unit, then turn it on agai

Q: No Reception on the Monitor

Q: Interference or Poor Reception

* The battery power may be too low.

O: No LED Light on Baby Unit

O: Parent Unit often Goes Black

Check if there is a ECO logo on the top of the screen. in this mode, parent unit will go black every 30 seconds, which saves a lot of power. To keep the screen on all the time, to the menu and choose to turn off the "ECO" function.

10. MAINTENANCE

I. DISPOSAL GUIDE FOR BATTERY AND PRODUCT

For proper collection and processing of these products, take them to the collection points designated by local authorities. You can also contact the store where you

AUTION: Risk of Fire and Burns. Do Not Open, Crush, Heat Above 45 degree C or

battery subjected to extremely low air pressure that may result in an expl eakage of flammable liquid or gas.

with Innovation. Science and Economic Development Canada's licence-exempt RSS(s). ation is subject to the following two conditions

nformes aux CNR exempts de licence d'Innovation. Sciences et Dévelor

oquer un fonctionnement indésirable de l'appareil d compliance with RSS 102 RF exposure, users can obtain Canadian inform

et appareir est conformit à rexemption des filmites à evaluation confaine dans la secti lu cnr - 102 et conformité avec rss 102 de l'exposition aux rf, les utilisateurs peuvent les données canadiennes sur l'exposition aux champs rf et la conformité. l'his equipment complies with Canada radiation exposure limits set forth for an unco

This equipment should be installed and operated with minimum distance 20cm between the radiator & your body. Cet équipement est conforme Canada limites d'exposition aux radiations dans un

Cet équipement doit être installé et utilisé avec une distance minimale de 20 cm entre le

FCC Statement Camera. This equipment has oven tested and found to comply with the fillints for a Class B digital device, pursuant to part 15 of the FCC rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or

elevision reception, which can be determined by turning the equipment off and on, the ser is encouraged to try to correct the interference by one or more of the following Regrient or relocate the receiving antenna

the radiator and your body.

CC Warnning:

levision reception, which can be determined by turning the equipment off and on, the use encouraged to try to correct the interference by one or more of the following measures:

Connect the equipment into an outlet on a circuit different from that to which the receive • Consult the dealer or an experienced radio/TV technician for help.

Caution: Any changes or modifications to this device not explicitly approved by

Specific Absorption Rate (SAR) information: This device meets the government's equirements for exposure to radiowaves. The guidelines are based on standards that were eveloped by independentscientific organizations through periodic and thorough

The standards include a substantial safety margin designed to assure the safety of all per ardless of age or health. mation and Statement the SAR limit of USA (FCC) is 1.6 W/kg

ries that maintain an 0mm separation distance between the user's body and the ack of the phone. The use of belt clips, holsters and similar access nponents in its assembly. The use of accessories that do not satisfy these s may not comply with FCC RF exposure requirements, and should be avoic

1) This device may not cause interference.
2) This device must accept any interference, including interference that may cause indesired operation of the device.

Note 4: When the alarm is ringing, press any key on the parent unit to turn the alarm off.

Note 5: If you don't turn off the alarm, the alarm will ring for 1 minute. After three minutes are the second of the sec











Responsible Party(US): Startline LLC Add: 22 Hazelwood Drive, Jericho, NY 11753 Tel: 1-516-681-3729 Authorized UK Representative(UK): APEX CE SPECIALISTS LIMITED Add: 89 Princess Street, M14HT,UK info@apex-ee.com

Shenzhen Videotimes Technology Co., Ltd Room 2106, Building 11, Tianan Yungu Phase II , Gangtou (Longgang District, Shenzhen, Guangdong, China





AVERTISSEMENT

DANGER D'ÉTRANGLEMENT: Des enfants se sont ÉTRANGLÉS avec des cordons électriques. Garde le cordonélectrique hors de la portée des enfants(à plus de 0.9m/3 pi du lit d'enfant). Ne pas enlever cette étiquette.

WARNING IR emitted from this product. Do not stare at operating lamp

Risk Group 1

14

This device complies with part 15 of the FCC Rules. Operation is subject to the following his equipment complies with FCC radiation exposure limits set forth for an uncontrolled nvironment. This equipment should be installed and operated with minimum distance 0ci

raged over one gram of tissue. vice types: device has also been tested against this SAR limit. his device was tested for typical body-worn operations with the back of the phone kept nm from the body. To maintain compliance with FCC RF exposure requirements, use

ation is subject to the following two conditions

compliance with RSS 102 RF exposure, users can obtain Canadi

that do not satisfy these requirements may not comply with ISED RF exposure rmations sur le débit d'absorption spécifique (DAS):

Informations sur le débit d'absorption spécifique (DAS):
Cette tablette répond aux exigences du gouvernement en matière d'exposition aux ondes radio. Les lignes directrices sont basées sur des normes élaborées par des organisations scientifiques indépendantes à travers une évaluation périodique et approfondie des études scientifiques. Les nor mes comprennent une marge de sécurité substantielle conçue pour assurer la sécurité de toutes les personnes, quel que soit leur âge ou leur état de santé. Information et déclaration d'ISDE sur l'exposition aux RF la limite DAS du Canada (ISD est de 1,6 W / kg en moyenne sur un gramme de tissu. Types d'appareils: la tablette a également été testée par rapport à cette limite SAR. Cet appareil a été testé pour des opérations typiques portées sur le corps avec le dos de la tablette gardé à 0 mm du corps. Pour maintenir la conformité avec les exigences d'exposition RF d'ISDE, utilisez des accessoirs qui maintennet la conformité avec les exigences d'exposition RF d'ISDE, utilisez des

(more than 3 ft (0.9 m) away). Do not remove this tag.