



Specification		Regulated Substances in the Product	Safety Warnings	Standards	Environmental Compliance (WEEE, Batteries, and Packaging)																																																
<b>Port</b>	USB Device Port (Type-C) *1 - Connects to host computer's USB port RJ45 Ethernet Port *1 - Connects to wired network RJ22 Serial Port *1 - Connects to serial peripherals/host computer USB Host Port (Type A) *1 - Connects to USB peripherals	<table border="1"> <thead> <tr> <th>Part name</th> <th colspan="6">Hazardous substances</th> </tr> <tr> <th></th> <th>Lead (Pb)</th> <th>Mercury (Hg)</th> <th>Cadmium (Cd)</th> <th>Hexavalent chromium (Cr(VI))</th> <th>Polybrominated biphenyls (PBB)</th> <th>Polybrominated diphenyl ethers (PBDE)</th> </tr> </thead> <tbody> <tr> <td>Casing</td> <td>○</td> <td>○</td> <td>○</td> <td>○</td> <td>○</td> <td>○</td> </tr> <tr> <td>Circuit board</td> <td>○</td> <td>○</td> <td>○</td> <td>○</td> <td>○</td> <td>○</td> </tr> <tr> <td>Power Supply (optional)</td> <td>×</td> <td>○</td> <td>○</td> <td>○</td> <td>○</td> <td>○</td> </tr> <tr> <td>Wire (optional)</td> <td>○</td> <td>○</td> <td>○</td> <td>○</td> <td>○</td> <td>○</td> </tr> <tr> <td>Packaging materials</td> <td>○</td> <td>○</td> <td>○</td> <td>○</td> <td>○</td> <td>○</td> </tr> </tbody> </table>	Part name	Hazardous substances							Lead (Pb)	Mercury (Hg)	Cadmium (Cd)	Hexavalent chromium (Cr(VI))	Polybrominated biphenyls (PBB)	Polybrominated diphenyl ethers (PBDE)	Casing	○	○	○	○	○	○	Circuit board	○	○	○	○	○	○	Power Supply (optional)	×	○	○	○	○	○	Wire (optional)	○	○	○	○	○	○	Packaging materials	○	○	○	○	○	○	<ul style="list-style-type: none"> <li>Immediately turn off power if an unusual odor is detected, the unit overheats, or smoke is visible.</li> <li>Do not allow metal objects or liquid to contact the M20SE/M20/Battery DC output pins. This may cause the M20 BASE-WF1 to malfunction.</li> <li>Do not position the M20 BASE-WF1 in areas with high temperature, humidity, dust or strong electromagnetic fields.</li> <li>Avoid use in extremely hot or cold environments such as near open flames or lit cigarettes.</li> <li>Turn off power before plugging/unplugging components or external devices to prevent circuit damage.</li> <li>Always turn off power before disconnecting the power supply from the M20 BASE-WF1.</li> <li>Do not apply excessive pressure to the M20 BASE-WF1 or place objects on top of it.</li> <li>Avoid severe vibrations, shaking, or impacts to prevent damage to the M20 BASE-WF1.</li> <li>Use in a clean, dust-free area to prevent foreign objects from entering the terminal.</li> <li>Do not use near medical equipment without permission.</li> <li>Do not use flammable sprays or paints near the M20 BASE-WF1 to avoid fire hazards.</li> </ul>	<p><b>CE Marking</b> The CE marking indicates that M20 BASE-WF1 complies with the essential health, safety, and electromagnetic compatibility requirements of European Directive 2014/53/EU on Radio Equipment for:</p> <ul style="list-style-type: none"> <li>Protecting the health and safety of users and all other parties.</li> <li>Meeting electromagnetic compatibility protection standards.</li> </ul> <p><b>FCC Statement</b> Any Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.</p> <p>This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions:</p> <ol style="list-style-type: none"> <li>This device may not cause harmful interference.</li> <li>This device must accept any interference received, including interference that may cause undesired operation.</li> </ol> <p><b>ISED RSS Warning</b> This device complies with Innovation, Science and Economic Development Canada licence-exempt RSS standard(s). Operation is subject to the following two conditions: (1) this device may not cause interference, and (2) this device must accept any interference, including interference that may cause undesired operation of the device.</p> <p><b>Environmental Compliance (WEEE, Batteries, and Packaging)</b> This product is labeled in accordance with European Directives 2012/19/EU concerning Waste Electrical and Electronic Equipment (WEEE) and 2013/56/EC concerning Batteries and Accumulators. Those provisions are requiring producers and manufacturers to become liable for take-back, treatment and recycling upon end of life of equipment and batteries.</p> <p>The crossed-out wheeled bin symbol on the product or accessories indicates it is considered electronic equipment waste (WEEE) which must be properly disposed of and should not be thrown away. Spent batteries must also be collected separately for recycling.</p> <p>Please contact your retailer for more details on the take-back and recycling program in place for disposing of old equipment and batteries. Participating ensures their responsible re-use and recycling, which benefits both the environment and human health.</p> <p>The Green Dot symbol on the packaging confirms it complies with Directive 94/62/EC concerning packaging and packaging waste. Packaging bearing this symbol must be returned through collection schemes managed by accredited Green Dot organizations for recovery and recycling.</p>
Part name	Hazardous substances																																																				
	Lead (Pb)	Mercury (Hg)	Cadmium (Cd)	Hexavalent chromium (Cr(VI))	Polybrominated biphenyls (PBB)	Polybrominated diphenyl ethers (PBDE)																																															
Casing	○	○	○	○	○	○																																															
Circuit board	○	○	○	○	○	○																																															
Power Supply (optional)	×	○	○	○	○	○																																															
Wire (optional)	○	○	○	○	○	○																																															
Packaging materials	○	○	○	○	○	○																																															
<b>Power</b>	Power Supply 220V AC input M20SE/M20 Charging 19V DC output		<p><b>Safety Warnings</b></p> <ul style="list-style-type: none"> <li>Immediately turn off power if an unusual odor is detected, the unit overheats, or smoke is visible.</li> <li>Do not allow metal objects or liquid to contact the M20SE/M20/Battery DC output pins. This may cause the M20 BASE-WF1 to malfunction.</li> <li>Do not position the M20 BASE-WF1 in areas with high temperature, humidity, dust or strong electromagnetic fields.</li> <li>Avoid use in extremely hot or cold environments such as near open flames or lit cigarettes.</li> <li>Turn off power before plugging/unplugging components or external devices to prevent circuit damage.</li> <li>Always turn off power before disconnecting the power supply from the M20 BASE-WF1.</li> <li>Do not apply excessive pressure to the M20 BASE-WF1 or place objects on top of it.</li> <li>Avoid severe vibrations, shaking, or impacts to prevent damage to the M20 BASE-WF1.</li> <li>Use in a clean, dust-free area to prevent foreign objects from entering the terminal.</li> <li>Do not use near medical equipment without permission.</li> <li>Do not use flammable sprays or paints near the M20 BASE-WF1 to avoid fire hazards.</li> </ul>	<p><b>CE Marking</b> The CE marking indicates that M20 BASE-WF1 complies with the essential health, safety, and electromagnetic compatibility requirements of European Directive 2014/53/EU on Radio Equipment for:</p> <ul style="list-style-type: none"> <li>Protecting the health and safety of users and all other parties.</li> <li>Meeting electromagnetic compatibility protection standards.</li> </ul> <p><b>FCC Statement</b> Any Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.</p> <p>This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions:</p> <ol style="list-style-type: none"> <li>This device may not cause harmful interference.</li> <li>This device must accept any interference received, including interference that may cause undesired operation.</li> </ol> <p><b>ISED RSS Warning</b> This device complies with Innovation, Science and Economic Development Canada licence-exempt RSS standard(s). Operation is subject to the following two conditions: (1) this device may not cause interference, and (2) this device must accept any interference, including interference that may cause undesired operation of the device.</p> <p><b>Environmental Compliance (WEEE, Batteries, and Packaging)</b> This product is labeled in accordance with European Directives 2012/19/EU concerning Waste Electrical and Electronic Equipment (WEEE) and 2013/56/EC concerning Batteries and Accumulators. Those provisions are requiring producers and manufacturers to become liable for take-back, treatment and recycling upon end of life of equipment and batteries.</p> <p>The crossed-out wheeled bin symbol on the product or accessories indicates it is considered electronic equipment waste (WEEE) which must be properly disposed of and should not be thrown away. Spent batteries must also be collected separately for recycling.</p> <p>Please contact your retailer for more details on the take-back and recycling program in place for disposing of old equipment and batteries. Participating ensures their responsible re-use and recycling, which benefits both the environment and human health.</p> <p>The Green Dot symbol on the packaging confirms it complies with Directive 94/62/EC concerning packaging and packaging waste. Packaging bearing this symbol must be returned through collection schemes managed by accredited Green Dot organizations for recovery and recycling.</p>																																																	
<b>Operating Environment</b>	Operating Temperature 0°C~40°C / 32°F~104°F Storage Temperature -20°C~70°C / -4°F~158°F Operating Humidity 10%~90% (Non-condensing)																																																				
<b>Battery Charging Indicator</b>	Solid Red Battery not connected Solid Blue Battery charging Solid Green Battery fully charged Blinks Blue Invalid battery connected																																																				
<b>Pairing Indicator</b>	Solid Red Base to be paired Solid Blue Base paired and connected with M20 BASE-WF1 Solid Green Base upgrading Blinks Blue Base paired but disconnected with M20 BASE-WF1																																																				

#### Disclaimer

- Every effort has been made to ensure the accuracy and completeness of the information in this quick start guide. However, errors or omissions may exist.
- Fujian LANDI Commercial Equipment Co., Ltd. holds full copyright over this guide and reserves the right to modify product software, hardware or documentation without notice.
- Product details in this guide may differ from the actual product due to updates. Refer to the physical product for authoritative information.
- Interpretation of this guide belongs solely to Fujian LANDI Commercial Equipment Co., Ltd. Unauthorized copying, distribution or use of any part is strictly prohibited without written permission.
- Fujian LANDI Commercial Equipment Co., Ltd. reserves the right to take legal action for any infringement according to law.
- Fujian LANDI Commercial Equipment Co., Ltd. shall not be held liable for damages, malfunctions, data loss or accessory loss caused by operations not complying with instructions in this guide.

#### FCC Radiation Exposure Statement

This equipment complies with FCC radiation exposure limits set forth for an uncontrolled environment. This equipment should be installed and operated with minimum distance 20cm between the radiator & your body. This transmitter must not be co-located or operating in conjunction with any other antenna or transmitter.

Le rayonnement de la classe B répète ISED fixent un environnement non contrôlé. Installation et mise en œuvre de ce matériel devrait avec échangeur distance minimale entre 20cm ton corps. L'antenne ou ne peuvent pas coexister cette antenne ou capteurs avec d'autres.

#### Manufacturer

<http://www.landicorp.com/>  
Fujian LANDI Commercial Equipment Co., Ltd.  
5th & 6th Floor, Building 3A, Area A, Software Park, No. 89, Software Avenue, Gulou District, Fuzhou, Fujian, China