

1.1.1 GSM850_ERP

Band: GSM850									
ENV	Mode		Frequency (MHz)	Conducted Power (dBm)	Gain (dBi)	ERP (dBm)		Verdict	
	Network	Subset				Result	Limit		
NTNV	GSM	GSM	824.2	33.45	-1.16	30.14	<=38.45	Pass	
			836.6	33.56	-1.16	30.25	<=38.45	Pass	
			848.8	33.44	-1.16	30.13	<=38.45	Pass	
	GPRS	1 TX Slot	824.2	33.47	-1.16	30.16	<=38.45	Pass	
		2 TX Slots	824.2	32.65	-1.16	29.34	<=38.45	Pass	
		3 TX Slots	824.2	30.51	-1.16	27.2	<=38.45	Pass	
		4 TX Slots	824.2	29.35	-1.16	26.04	<=38.45	Pass	
		1 TX Slot	836.6	33.48	-1.16	30.17	<=38.45	Pass	
		2 TX Slots	836.6	32.77	-1.16	29.46	<=38.45	Pass	
		3 TX Slots	836.6	30.70	-1.16	27.39	<=38.45	Pass	
		4 TX Slots	836.6	29.48	-1.16	26.17	<=38.45	Pass	
		1 TX Slot	848.8	33.35	-1.16	30.04	<=38.45	Pass	
		2 TX Slots	848.8	32.56	-1.16	29.25	<=38.45	Pass	
		3 TX Slots	848.8	30.45	-1.16	27.14	<=38.45	Pass	
		4 TX Slots	848.8	29.23	-1.16	25.92	<=38.45	Pass	
		EGPRS	1 TX Slot	824.2	27.34	-1.16	24.03	<=38.45	Pass
			2 TX Slots	824.2	26.70	-1.16	23.39	<=38.45	Pass
			3 TX Slots	824.2	24.74	-1.16	21.43	<=38.45	Pass
	4 TX Slots		824.2	23.52	-1.16	20.21	<=38.45	Pass	
	1 TX Slot		836.6	27.53	-1.16	24.22	<=38.45	Pass	
	2 TX Slots		836.6	28.86	-1.16	25.55	<=38.45	Pass	
	3 TX Slots		836.6	26.81	-1.16	23.5	<=38.45	Pass	
	4 TX Slots		836.6	23.60	-1.16	20.29	<=38.45	Pass	
	1 TX Slot		848.8	27.12	-1.16	23.81	<=38.45	Pass	
	2 TX Slots		848.8	26.62	-1.16	23.31	<=38.45	Pass	
	3 TX Slots		848.8	24.36	-1.16	21.05	<=38.45	Pass	
	4 TX Slots		848.8	23.35	-1.16	20.04	<=38.45	Pass	

Note1: ERP=Conducted Power+Antenna Gain-2.15