



# TEST REPORT

**APPLICANT** : Nubia Technology Co., Ltd.

**PRODUCT NAME** : 5G Mobile Phone

**MODEL NAME** : NX709J

**BRAND NAME** : REDMAGIC

**FCC ID** : 2AHJO-NX709J

**STANDARD(S)** : FCC 47 CFR Part 2(2.1093)  
IEEE 1528-2013

**RECEIPT DATE** : 2022-01-25

**TEST DATE** : 2022-02-22 to 2022-03-16

**ISSUE DATE** : 2022-04-01

Edited by :

*Gan Yueming*

Gan Yueming (Rapporteur)

Approved by :

*Shen Junsheng*

Shen Junsheng (Supervisor)

**NOTE:** This document is issued by Shenzhen Morlab Communications Technology Co., the test report shall not be reproduced except in full without prior written permission of the company. The test results apply only to the particular sample(s) tested and to the specific tests carried out which is available on request for validation and information confirmed at our website.





## DIRECTORY

<b>1. SAR Results Summary</b> .....	<b>5</b>
<b>2. Technical Information</b> .....	<b>7</b>
<b>2.1. Applicant and Manufacturer Information</b> .....	<b>7</b>
<b>2.2. Equipment under Test (EUT) Description</b> .....	<b>7</b>
<b>2.3. Environment of Test Site/Conditions</b> .....	<b>9</b>
<b>3. Specific Absorption Rate (SAR)</b> .....	<b>10</b>
<b>3.1. Introduction</b> .....	<b>10</b>
<b>3.2. SAR Definition</b> .....	<b>10</b>
<b>4. RF Exposure Limits</b> .....	<b>11</b>
<b>4.1. Uncontrolled Environment</b> .....	<b>11</b>
<b>4.2. Controlled Environment</b> .....	<b>11</b>
<b>5. Applied Reference Documents</b> .....	<b>12</b>
<b>6. SAR Measurement System</b> .....	<b>13</b>
<b>6.1. E-Field Probe</b> .....	<b>14</b>
<b>6.2. Data Acquisition Electronics (DAE)</b> .....	<b>15</b>
<b>6.3. Robot</b> .....	<b>15</b>
<b>6.4. Measurement Server</b> .....	<b>16</b>
<b>6.5. Light Beam Unit</b> .....	<b>16</b>
<b>6.6. Phantom</b> .....	<b>16</b>
<b>6.7. Device Holder</b> .....	<b>17</b>
<b>6.8. Data Storage and Evaluation</b> .....	<b>18</b>
<b>6.9. Test Equipment List</b> .....	<b>20</b>
<b>7. Tissue Simulating Liquids</b> .....	<b>22</b>
<b>8. SAR System Verification</b> .....	<b>24</b>
<b>8.1. Purpose of System Performance check</b> .....	<b>24</b>
<b>8.2. System Setup</b> .....	<b>24</b>



<b>8.3. Validation Results</b>	<b>25</b>
<b>9. EUT Testing Position</b>	<b>29</b>
<b>9.1. Handset Reference Points</b>	<b>29</b>
<b>9.2. Positioning for Cheek / Touch</b>	<b>30</b>
<b>9.3. Positioning for Ear / 15° Tilt</b>	<b>31</b>
<b>9.4. SAR Evaluation near the Mouth/Jaw Regions of the Phantom</b>	<b>31</b>
<b>9.5. Body-worn Configurations</b>	<b>32</b>
<b>9.6. Hotspot Mode Exposure Position Conditions</b>	<b>32</b>
<b>10. Measurement Procedures</b>	<b>33</b>
<b>10.1. Spatial Peak SAR Evaluation</b>	<b>33</b>
<b>10.2. Power Reference Measurement</b>	<b>34</b>
<b>10.3. Area Scan Procedures</b>	<b>34</b>
<b>10.4. Zoom Scan Procedures</b>	<b>34</b>
<b>10.5. SAR Averaged Methods</b>	<b>35</b>
<b>10.6. Power Drift Monitoring</b>	<b>35</b>
<b>11. SAR Test Procedure</b>	<b>36</b>
<b>11.1. General Scan Requirements</b>	<b>36</b>
<b>11.2. Test Procedure</b>	<b>37</b>
<b>11.3. Description of Interpolation/Extrapolation Scheme</b>	<b>37</b>
<b>11.4. Wireless Router</b>	<b>37</b>
<b>12. SAR Test Configuration</b>	<b>39</b>
<b>13. Conducted Power List</b>	<b>51</b>
<b>14. LTE Carrier Aggregation</b>	<b>51</b>
<b>15. 5G NR EN-DC Consideration</b>	<b>53</b>
<b>16. Hotspot Mode Evaluation Procedure</b>	<b>54</b>
<b>17. Block Diagram of the Tests to be Performed</b>	<b>56</b>
<b>17.1. Head</b>	<b>56</b>
<b>17.2. Body</b>	<b>57</b>



<b>18. Test Results List</b>	58
<b>18.1. Test Guidance</b>	58
<b>18.2. Head SAR Data</b>	61
<b>18.3. Body SAR Data</b>	70
<b>18.4. Repeated SAR Assessment</b>	79
<b>18.5. Extremity SAR Assessment</b>	80
<b>19. Simultaneous Transmission Evaluation</b>	81
<b>19.1. Simultaneous Transmission Consideration</b>	81
<b>19.2. Simultaneous Transmission Analysis</b>	82
<b>20. Uncertainty Assessment</b>	83
<b>Annex A General Information</b>	84
<b>Annex B Test Setup Photos</b>	
<b>Annex C Plots of System Performance Check</b>	
<b>Annex D Plots of Maximum SAR Test Results</b>	
<b>Annex E Conducted Power</b>	
<b>Annex F Simultaneous Transmission Data</b>	
<b>Annex G DASY Calibration Certificate</b>	

Changed History		
Version	Date	Reason for Change
1.0	2022-04-01	First edition



# 1. SAR Results Summary

The maximum results of Specific Absorption Rate (SAR) found during test as bellows:

<Highest Reported SAR Summary>

Frequency Band		Highest SAR Summary			
		Head (Gap 0mm)	Body-worn (Gap 10mm)	Hotspot (Gap 10mm)	Extremity (Gap 0mm)
		1g SAR (W/kg)			10g SAR (W/kg)
GSM	GSM850	0.821	0.271	0.271	N/A
	GSM1900	0.725	0.169	0.582	N/A
WCDMA	WCDMA II	0.993	0.471	1.096	N/A
	WCDMA IV	0.929	0.369	0.705	N/A
	WCDMA V	0.888	0.225	0.225	N/A
CDMA2000	BC0	0.390	0.272	N/A	0.477
	BC1	0.457	0.823	N/A	0.559
LTE	LTE Band 2	0.872	0.490	0.948	N/A
	LTE Band 5	0.377	0.196	0.196	N/A
	LTE Band 7	0.876	0.639	0.798	N/A
	LTE Band 12/17	0.359	0.180	0.230	N/A
	LTE Band 18	0.647	0.139	0.145	N/A
	LTE Band 19	0.724	0.170	0.170	N/A
	LTE Band 26	0.668	0.146	0.158	N/A
	LTE Band 38	0.796	0.224	0.325	N/A
	LTE Band 40A	0.877	0.217	0.217	N/A
	LTE Band 40B	0.840	0.230	0.282	N/A
5G NR	n41	0.965	0.202	0.608	N/A
	n77	0.958	0.096	0.311	N/A
WLAN	2.4GHz WLAN	0.572	0.092	0.258	N/A
	5GHz WLAN	0.567	0.490	0.490	1.170
2.4GHz Band	Bluetooth	N/A	0.055	0.159	N/A

Highest Simultaneous Transmission SAR <sub>1g</sub> (W/Kg):	1.505 W/kg	Limit(W/kg): 1.6 W/kg
---	------------	-----------------------

**Note:**

1. This device is in compliance with Specific Absorption Rate (SAR) for general population or



REPORT No.: SZ21120450S01

uncontrolled exposure limits (1.6W/kg as averaged over any 1 gram of tissue; specified in FCC 47 CFR part 1 (1.1310) and ANSI/IEEE C95.1-1992), and had been tested in accordance with the measurement methods and procedures specified in IEEE 1528-2013 and FCC KDB publications.

- When the test result is a critical value, we will use the measurement uncertainty give the judgment result based on the 95% confidence intervals.



## 2. Technical Information

**Note:** Provide by applicant.

### 2.1. Applicant and Manufacturer Information

<b>Applicant:</b>	Nubia Technology Co., Ltd.
<b>Applicant Address:</b>	Room 1801, Building 2, Chongwen Park, Nanshan Zhiyuan, No.3370, Liuxian Rd, Nanshan District, Shenzhen City, Guangdong Province, P. R. China
<b>Manufacturer:</b>	Nubia Technology Co., Ltd.
<b>Manufacturer Address:</b>	Room 1801, Building 2, Chongwen Park, Nanshan Zhiyuan, No.3370, Liuxian Rd, Nanshan District, Shenzhen City, Guangdong Province, P. R. China

### 2.2. Equipment under Test (EUT) Description

<b>Product Name:</b>	5G Mobile Phone
<b>EUT IMEI:</b>	860451060022641 860451060022575
<b>Hardware Version:</b>	NX709J_V1AMB
<b>Software Version:</b>	NX709J_UNCommon_V4.01
<b>Frequency Bands:</b>	GSM 850: 824 MHz ~ 849 MHz GSM 1900: 1850 MHz ~ 1910 MHz WCDMA Band II: 1850 MHz ~ 1910 MHz WCDMA Band IV: 1710 MHz ~ 1755 MHz WCDMA Band V: 824 MHz ~ 849 MHz CDMA2000 BC0: 824 MHz ~ 849 MHz CDMA2000 BC1: 1850 MHz ~ 1910 MHz LTE Band 2: 1850 MHz ~ 1910 MHz LTE Band 4: 1710 MHz ~ 1755 MHz LTE Band 5: 824 MHz ~ 849 MHz LTE Band 7: 2500 MHz ~ 2570 MHz LTE Band 12: 699 MHz ~ 716 MHz LTE Band 17: 704 MHz ~ 716 MHz LTE Band 18: 815 MHz ~ 830 MHz LTE Band 19: 830 MHz ~ 845 MHz LTE Band 26: 814 MHz ~ 849 MHz LTE Band 38: 2570 MHz ~ 2620 MHz



	LTE Band 40A: 2305 MHz ~ 2315 MHz LTE Band 40B: 2350 MHz ~ 2360 MHz LTE Band 41: 2496 MHz ~ 2690 MHz LTE Band 66: 1710 MHz ~ 1780 MHz 5G NR n41: 2496 MHz ~ 2690 MHz 5G NR n77: 3700 MHz ~ 3980 MHz WLAN 2.4GHz: 2412 MHz ~ 2462 MHz WLAN 5.2GHz: 5180 MHz ~ 5240 MHz WLAN 5.3GHz: 5260 MHz ~ 5320 MHz WLAN 5.6GHz: 5500 MHz ~ 5720 MHz WLAN 5.8GHz: 5745 MHz ~ 5825 MHz Bluetooth: 2402 MHz ~ 2480 MHz NFC: 13.56 MHz	
<b>Modulation Mode:</b>	GSM/GPRS: GMSK EDGE: 8PSK WCDMA: QPSK, 16QAM CDMA2000 1xRTT: BPSK,QPSK LTE: QPSK, 16QAM, 64QAM 5G NR: DFT-s-OFDM/CP-OFDM, PI/2 BPSK QPSK, 16QAM, 64QAM, 256QAM 802.11b: DSSS 802.11a/g/n-HT20/HT40/ac-VHT20/40/80: OFDM 802.11ax-HEW20/40/80: OFDMA BR+EDR: GFSK(1Mbps), π/4-DQPSK(2Mbps), 8-DPSK(3Mbps) Bluetooth LE: GFSK(1Mbps, 2Mbps) NFC: ASK	
<b>Multi-slot Class:</b>	GPRS: Multi-slot Class 33 EDGE: Multi-slot Class 33	
<b>Operation Class:</b>	Class B	
<b>Carrier Aggregation:</b>	Downlink	
<b>VoLTE Mode:</b>	Support	
<b>VoWi-Fi Mode:</b>	Support	
<b>Hotspot Mode:</b>	Support (5G WLAN only for B1 & B4)	
<b>WLAN MIMO:</b>	Support	
<b>Antenna Type:</b>	WWAN: Fixed Internal Antenna WLAN: PIFA Antenna Bluetooth: PIFA Antenna NFC: Loop Antenna	
<b>SIM Cards Description:</b>	SIM 1	GSM+WCDMA+CDMA2000+LTE+5G NR
	SIM 2	GSM+WCDMA+CDMA2000+LTE+5G NR

**Note:** For more detailed description, please refer to specification or user manual supplied by the



applicant and/or manufacturer.

## 2.3. Environment of Test Site/Conditions

Normal Temperature (NT):	20-25 °C
Relative Humidity:	30-75 %
Air Pressure:	980-1020 hPa

Test Frequency:	GSM 850MHz/1900MHz WCDMA Band II/IV/V CDMA2000 BC0/1 FDD-LTE Band 2/4/5/7/12/17/18/19/26/66 TDD-LTE Band 38/40A/40B/41 5G NR n41/77 WLAN 2.4GHz WLAN 5GHz Bluetooth
Operation Mode:	Call established
Power Level:	GSM 850 MHz Maximum output power(level 5) GSM 1900MHz Maximum output power(level 0) WCDMA Band II/IV/V (All Up Bits) CDMA2000 BC0/1 (All Up Bits) FDD-LTE Band 2/4/5/7/12/17/18/19/26/66 (Maximum output power) TDD-LTE Band 38/40A/40B/41 (Maximum output power) 5G NR n41/77 (Maximum output power) WLAN 2.4GHz WLAN 5GHz Bluetooth

During SAR test, EUT is in Traffic Mode (Channel Allocated) at Normal Voltage Condition. A communication link is set up with a System Simulator (SS) by air link, and a call is established.

The EUT shall use its internal transmitter. The antenna(s), battery and accessories shall be those specified by the Factory. The EUT battery must be fully charged and checked periodically during the test to ascertain uniform power output. If a wireless link is used, the antenna connected to the output of the base station simulator shall be placed at least 50 cm away from the handset.

The signal transmitted by the simulator to the antenna feeding point shall be lower than the output power level of the handset by at least 35 dB.

### 3. Specific Absorption Rate (SAR)

#### 3.1. Introduction

SAR is related to the rate at which energy is absorbed per unit mass in an object exposed to a radio field. The SAR distribution in a biological body is complicated and is usually carried out by experimental techniques or numerical modeling. The standard recommends limits for two tiers of groups, occupational or controlled and general population or uncontrolled, based on a person's awareness and ability to exercise control over his or her exposure. In general, occupational or controlled exposure limits are Middle than the limits for general population or uncontrolled.

#### 3.2. SAR Definition

The SAR definition is the time derivative (rate) of the incremental energy ( $dW$ ) absorbed by(dissipated in) an incremental mass ( $dm$ ) contained in a volume element ( $dv$ ) of a given density. ( $\rho$ ). The equation description is as below:

$$\text{SAR} = \frac{d}{dt} \left( \frac{dW}{dm} \right) = \frac{d}{dt} \left( \frac{dW}{\rho dv} \right)$$

SAR is expressed in units of Watts per kilogram (W/kg).

SAR measurement can be either related to the temperature elevation in tissue by,

$$\text{SAR} = C \left( \frac{\delta T}{\delta t} \right)$$

Where  $C$  is the specific heat capacity,  $\delta T$  is the temperature rise and  $\delta t$  the exposure duration, or related to the electrical field in the tissue by

$$\text{SAR} = \frac{\sigma |E|^2}{\rho}$$

Where  $\sigma$  is the conductivity of the tissue,  $\rho$  is the mass density of the tissue and  $|E|$  is the rmselectrical field strength.

However for evaluating SAR of low power transmitter, electrical field measurement is typically applied.

## 4. RF Exposure Limits

### 4.1. Uncontrolled Environment

Uncontrolled Environments are defined as locations where there is the exposure of individuals who have no knowledge or control of their exposure. The general population/uncontrolled exposure limits are applicable to situations in which the general public may be exposed or in which persons who are exposed as a consequence of their employment may not be made fully aware of the potential for exposure or cannot exercise control over their exposure. Members of the general public would come under this category when exposure is not employment-related; for example, in the case of a wireless transmitter that exposes persons in its vicinity.

### 4.2. Controlled Environment

Controlled Environments are defined as locations where there is exposure that may be incurred by persons who are aware of the potential for exposure, (i.e. as a result of employment or occupation). In general, occupational/controlled exposure limits are applicable to situations in which persons are exposed as a consequence of their employment, who have been made fully aware of the potential for exposure and can exercise control over their exposure. The exposure category is also applicable when the exposure is of a transient nature due to incidental passage through a location where the exposure levels may be higher than the general population/uncontrolled limits, but the exposed person is fully aware of the potential for exposure and can exercise control over his or her exposure by leaving the area or by some other appropriate means.

**Limits for General Population/Uncontrolled Exposure (W/kg)**

Type Exposure	Uncontrolled Environment Limit
Spatial Peak SAR (1g cube tissue for head and trunk)	1.6 W/kg
Spatial Peak SAR (10g cube tissue for limbs)	4.0 W/kg
Spatial Peak SAR (1g cube tissue for whole body)	0.08 W/kg

**Note:**

1. Occupational/Uncontrolled Environments are defined as locations where there is exposure that may be incurred by people who are aware of the potential for exposure (i.e. as a result of employment or occupation).
2. Whole-Body SAR is averaged over the entire body, partial-body SAR is averaged over any 1gram of tissue defined as a tissue volume in the shape of a cube. SAR for hands, wrists, feet and ankles is averaged over any 10 grams of tissue defined as a tissue volume in the shape of a cube.



## 5. Applied Reference Documents


Leading reference documents for testing:

Identity	Document Title	Method Determination /Remark
FCC 47CFR Part 2(2.1093)	Radio Frequency Radiation Exposure Evaluation: Portable Devices	No deviation
IEEE 1528-2013	IEEE Recommended Practice for Determining the Peak Spatial-Average Specific Absorption Rate (SAR) in the Human Head from Wireless Communications Devices: Measurement Techniques	No deviation
KDB 447498 D04v01	General RF Exposure Guidance	No deviation
KDB 248227 D01v02r02	SAR Measurement Procedures for 802.11 Transmitters	No deviation
KDB 865664 D01v01r04	SAR Measurement 100 MHz to 6 GHz	No deviation
KDB 865664 D02v01r02	RF Exposure Reporting	No deviation
KDB 648474 D04v01r03	Handset SAR	No deviation
KDB 941225 D01v03r01	3G SAR MEAUREMENT PROCEDURES	No deviation
KDB 941225 D05v02r05	SAR Evaluation Consideration for LTE Devices	No deviation
KDB 941225 D06v02r01	SAR Evaluation Procedures For Portable Devices With Wireless Router Capabilities	No deviation

**Note 1:** The test item is not applicable.

**Note 2:** Additions to, deviation, or exclusions from the method shall be judged in the "method determination" column of add, deviate or exclude from the specific method shall be explained in the "Remark" of the above table.

## 6. SAR Measurement System



**Fig 6.1 SPEAG DASY System Configurations**

The DASY system for performance compliance tests is illustrated above graphically. This system consists of the following items:

- A standard high precision 6-axis robot with controller, a teach pendant and software.
- A data acquisition electronic (DAE) attached to the robot arm extension.
- A dosimetric probe equipped with an optical surface detector system.
- The electro-optical converter (ECO) performs the conversion between optical and electrical signals
- A measurement server performs the time critical tasks such as signal filtering, control of the robot operation and fast movement interrupts.
- A probe alignment unit which improves the accuracy of the probe positioning.
- A computer operating Windows XP.
- DASY software.
- Remote control with teach pendant and additional circuitry for robot safety such as warming lamps, etc.
- The SAM twin phantom.
- A device holder.
- Tissue simulating liquid.
- Dipole for evaluating the proper functioning of the system.
- Some of the components are described in details in the following sub-sections.

## 6.1. E-Field Probe

The SAR measurement is conducted with the dosimetric probe (manufactured by SPEAG). The probe is specially designed and calibrated for use in liquid with high permittivity. The dosimetric probe has special calibration in liquid at different frequency. This probe has a built in optical surface detection system to prevent from collision with phantom.

### ➤ E-Field Probe Specification

#### <ES3DV3 Probe>

<b>Construction</b>	Symmetrical design with triangular core Built-in optical fiber for surface detection system. Built-in shielding against static charges. PEEK enclosure material (resistant to organic solvents, e.g., DGBE)	
<b>Frequency</b>	10 MHz to 3 GHz; Linearity: $\pm 0.2$ dB	
<b>Directivity</b>	$\pm 0.2$ dB in HSL (rotation around probe axis) $\pm 0.4$ dB in HSL (rotation normal to probe axis)	
<b>Dynamic Range</b>	5 $\mu$ W/g to 100 mW/g; Linearity: $\pm 0.2$ dB	
<b>Dimensions</b>	Overall length: 330 mm (Tip: 16 mm) Tip diameter: 6.8 mm (Body: 12 mm) Distance from probe tip to dipole centers: 2.7 mm	

Fig 6.2 Photo of ES3DV3

#### <EX3DV4 Probe>

<b>Construction</b>	Symmetrical design with triangular core Built-in shielding against static charges PEEK enclosure material (resistant to organic solvents, e.g., DGBE)	
<b>Frequency</b>	10 MHz to 6 GHz; Linearity: $\pm 0.2$ dB	
<b>Directivity</b>	$\pm 0.3$ dB in HSL (rotation around probe axis) $\pm 0.5$ dB in tissue material (rotation normal to probe axis)	
<b>Dynamic Range</b>	10 $\mu$ W/g to 100 mW/g; Linearity: $\pm 0.2$ dB	
<b>Dimensions</b>	Overall length: 330 mm (Tip: 20 mm) Tip diameter: 2.5 mm (Body: 12 mm) Typical distance from probe tip to dipole centers: 1 mm	

Fig 6.3 Photo of EX3DV4

#### ➤ E-Field Probe Calibration

Each probe needs to be calibrated according to a dosimetric assessment procedure with accuracy better than  $\pm 10\%$ . The spherical isotropy shall be evaluated and within  $\pm 0.25$  dB. The sensitivity parameters (NormX, NormY, and NormZ), the diode compression parameter (DCP) and the conversion factor (ConvF) of the probe are tested. The calibration data can be referred to appendix C of this report.

## 6.2. Data Acquisition Electronics (DAE)

The data acquisition electronics(DAE) consists of a highly sensitive electrometer-grade preamplifier with auto-zeroing, a channel and gain-switching multiplexer, a fast16 bit AD-converter and a command decoder and control logic unit. AD-converter and a command decoder and control logic unit. Transmission to the measurement server is accomplished through an optical downlink for data and status information as well as an optical uplink for commands and the clock. The input impedance of the DAE is 200MOhm; the inputs are symmetrical and floating. Common mode rejection is above 80 dB.



Fig 6.4 Photo of DAE

## 6.3. Robot

The SPEAG DASY system uses the high precision robots (DASY4: RX90BL; DASY5: TX90XL) type from Stäubli SA (France). For the 6-axis controller system, the robot controller version (DASY4: CS7MB; DASY5: CS8c) from Stäubli is used. The Stäubli robot series have many features that are important for our application:

High precision (repeatability  $\pm 0.035$  mm)

High reliability (industrial design)

Jerk-free straight movements

Low ELF interference (the closed metallic construction shields against motor control fields)



Fig 6.5 Photo of DASY5

## 6.4. Measurement Server

The measurement server is based on a PC/104 CPU board with CPU (DASY4: 166 MHz, Intel Pentium; DASY5: 400 MHz, Intel Celeron), chip disk (DASY4: 32 MB; DASY5: 128 MB), RAM (DASY4: 64 MB, DASY5: 128 MB). The necessary circuits for communication with the DAE electronic box, as well as the 16 bit AD converter system for optical detection and digital I/O interface are contained on the DASY I/O board, which is directly connected to the PC/104 bus of the CPU board. The measurement server performs all the real-time data evaluation for field measurements and surface detection, controls robot movements and handles safety operations.



Fig 6.6 Photo of Server for DASY5

## 6.5. Light Beam Unit

The light beam switch allows automatic "tooling" of the probe. During the process, the actual position of the probe tip with respect to the robot arm is measured, as well as the probe length and the horizontal probe offset. The software then corrects all movements, such that the robot coordinates are valid for the probe tip.

The repeatability of this process is better than 0.1 mm. If a position has been taught with an aligned probe, the same position will be reached with another aligned probe within 0.1 mm, even if the other probe has different dimensions. During probe rotations, the probe tip will keep its actual position.



Fig. 6.7 Photo of Light Beam

## 6.6. Phantom

### <SAM Twin Phantom>

<b>Shell Thickness</b>	2 ± 0.2 mm (sagging: <1%) Center ear point: 6 ± 0.2 mm	
<b>Filling Volume</b>	Approx. 25 liters	
<b>Dimensions</b>	Length: 1000 mm; Width: 500 mm; Height: adjustable feet	
<b>Measurement Areas</b>	Left Head, Right Head, Flat Phantom	

Fig. 6.8 Photo of SAM Phantom

The bottom plate contains three pair of bolts for locking the device holder. The device holder positions are adjusted to the standard measurement positions in the three sections. A white cover is provided to tap the phantom during off-periods to prevent water evaporation and changes in the liquid parameters. On the phantom top, three reference markers are provided to identify the phantom position with respect to the robot.

## 6.7. Device Holder

### <Device Holder for SAM Twin Phantom>

The SAR in the phantom is approximately inversely proportional to the square of the distance between the source and the liquid surface. For a source at 5 mm distance, a positioning uncertainty of  $\pm 0.5$  mm would produce a SAR uncertainty of  $\pm 20\%$ . Accurate device positioning is therefore crucial for accurate and repeatable measurements. The positions in which the devices must be measured are defined by the standards.

The DASY device holder is designed to cope with different positions given in the standard. It has two scales for the device rotation (with respect to the body axis) and the device inclination (with respect to the line between the ear reference points). The rotation center for both scales is the ear reference point (EPR). Thus the device needs no repositioning when changing the angles.

The DASY device holder is constructed of low-loss POM material having the following dielectric parameters: relative permittivity  $\epsilon = 3$  and loss tangent  $\delta = 0.02$ . The amount of dielectric material has been reduced in the closest vicinity of the device, since measurements have suggested that the influence of the clamp on the test results could thus be lowered.

### <Laptop Extension Kit>

The extension is lightweight and made of POM, acrylic glass and foam. It fits easily on the upper part of the mounting device in place of the phone positioned. The extension is fully compatible with the SAM Twin and ELI phantoms.



Fig 6.9 Device Holder




Fig 6.10 Laptop Extension Kit

## 6.8. Data Storage and Evaluation

### ➤ Data Storage

The DASY software stores the assessed data from the data acquisition electronics as raw data (in microvolt readings from the probe sensors), together with all the necessary software parameters for the data evaluation (probe calibration data, liquid parameters and device frequency and modulation data) in measurement files. The post-processing software evaluates the desired unit and format for output each time the data is visualized or exported. This allows verification of the complete software setup even after the measurement and allows correction of erroneous parameter settings. For example, if a measurement has been performed with an incorrect crest factor parameter in the device setup, the parameter can be corrected afterwards and the data can be reevaluated.

The measured data can be visualized or exported in different units or formats, depending on the selected probe type (e.g., [V/m], [A/m], [mW/g]). Some of these units are not available in certain situations or give meaningless results, e.g., a SAR-output in a non-lose media, will always be zero. Raw data can also be exported to perform the evaluation with other software packages.

### ➤ Data Evaluation

The DASY post-processing software (SEMCAD) automatically executes the following procedures to calculate the field units from the microvolt readings at the probe connector. The parameters used in the evaluation are stored in the configuration modules of the software.

<b>Probe parameters:</b>	- Sensitivity	Norm <sub>i</sub> , a <sub>i0</sub> , a <sub>i1</sub> , a <sub>i2</sub>
	- Conversion factor	ConvF <sub>i</sub>
	- Diode compression point	dcpi
<b>Device parameters:</b>	- Frequency	f
	- Crest factor	cf
<b>Media parameters:</b>	- Conductivity	$\sigma$
	- Density	$\rho$

These parameters must be set correctly in the software. They can be found in the component documents or they can be imported into the software from the configuration files issued for the DASY components. In the direct measuring mode of the multi-meter option, the parameters of the actual system setup are used. In the scan visualization and export modes, the parameters stored in the corresponding document files are used.

The first step of the evaluation is a linearization of the filtered input signal to account for the compression characteristics of the detector diode. The compensation depends on the input signal, the diode type and the DC-transmission factor from the diode to the evaluation electronics. If the



exciting field is pulsed, the crest factor of the signal must be known to correctly compensate for peak power.

The formula for each channel can be given as:

$$V_i = U_i + U_i^2 \times \frac{cf}{dcpi}$$

With  $V_i$  = compensated signal of channel  $i$ , ( $i = x, y, z$ )  
 $U_i$  = input signal of channel  $i$ , ( $i = x, y, z$ )  
 $cf$  = crest factor of exciting field (DASY parameter)  
 $dcpi$  = diode compression point (DASY parameter)

From the compensated input signals, the primary field data for each channel can be evaluated:

$$\text{E-field Probes: } E_i = \sqrt{\frac{V_i}{\text{Norm}_i \times \text{ConvF}}}$$

$$\text{H-field Probes: } H_i = \sqrt{V_i} \times \frac{a_{i0} + a_{i1} + a_{i2}f^2}{f}$$

With  $V_i$  = compensated signal of channel  $i$ , ( $i = x, y, z$ )  
 $\text{Norm}_i$  = sensor sensitivity of channel  $i$ , ( $i = x, y, z$ ),  $\mu\text{V}/(\text{V}/\text{m})^2$  for E-field  
 $\text{Probes ConvF}$  = sensitivity enhancement in solution  
 $a_{ij}$  = sensor sensitivity factors for H-field probes  
 $f$  = carrier frequency [GHz]  
 $E_i$  = electric field strength of channel  $i$  in  $\text{V}/\text{m}$   
 $H_i$  = magnetic field strength of channel  $i$  in  $\text{A}/\text{m}$

The RSS value of the field components gives the total field strength (Hermitian magnitude):

$$E_{\text{tot}} = \sqrt{E_x^2 + E_y^2 + E_z^2}$$

The primary field data are used to calculate the derived field units.

$$\text{SAR} = E_{\text{tot}}^2 \times \frac{\sigma}{\rho \times 1000}$$

with SAR = local specific absorption rate in  $\text{mW}/\text{g}$

$E_{\text{tot}}$  = total field strength in  $\text{V}/\text{m}$   
 $\sigma$  = conductivity in [ $\text{mho}/\text{m}$ ] or [ $\text{Siemens}/\text{m}$ ]  
 $\rho$  = equivalent tissue density in  $\text{g}/\text{cm}^3$

Note that the density is set to 1, to account for actual head tissue density rather than the density of the tissue simulating liquid.



## 6.9. Test Equipment List

Manufacturer	Name of Equipment	Type/Model	Serial No./ SW Version	Calibration	
				Last Cal.	Due Date
SPEAG	750MHz System Validation Kit	D750V3	1173	2021.06.21	2024.06.20
SPEAG	900MHz System Validation Kit	D900V2	1d064	2021.12.17	2024.12.16
SPEAG	1800MHz System Validation Kit	D1800V2	2d158	2021.12.17	2024.12.16
SPEAG	2000MHz System Validation Kit	D2000V2	1050	2021.12.18	2024.12.17
SPEAG	2300MHz System Validation Kit	D2300V2	1107	2020.06.03	2023.06.02
SPEAG	2450MHz System Validation Kit	D2450V2	805	2021.12.17	2024.12.16
SPEAG	2600MHz System Validation Kit	D2600V2	1139	2021.06.25	2024.06.24
SPEAG	3700MHz System Validation Kit	D3700V2	1076	2020.06.03	2023.06.02
SPEAG	3900MHz System Validation Kit	D3900V2	1046	2023.06.02	2023.06.01
SPEAG	5000MHz System Validation Kit	D5GHzV2	1176	2021.12.19	2024.12.18
SPEAG	DOSIMETRIC ASSESSMENT SYSTEM	DASY52	52.10.4.1527	NCR	NCR
SPEAG	Dosimetric E-Field Probe	EX3DV4	3753	2021.07.26	2022.07.25
SPEAG	Dosimetric E-Field Probe	EX3DV4	7608	2022.01.12	2023.01.11
SPEAG	Data Acquisition Electronics	DAE4	480	2021.06.22	2022.06.21
SPEAG	Dielectric Assessment KIT	DAK-3.5	1279	2021.11.03	2022.11.02
SPEAG	SAM Twin Phantom 2	QD 000 P40 CB	TP-1464	NCR	NCR
SPEAG	Phone Positioner	N/A	N/A	NCR	NCR
Anritsu	Network Emulator	MT8820C	6200985414	2021.10.21	2022.10.20
Anritsu	Network Emulator	MT8821C	6261830572	2022.02.14	2023.02.13
Agilent	Network Analyzer	E5071B	MY42404762	2021.03.29	2022.03.28
mini-circuits	Amplifier	ZHL-42W+	608501717	NCR	NCR
mini-circuits	Amplifier	ZVE-8G+	754401735	NCR	NCR
Agilent	Signal Generator	N5182B	MY53050509	2021.03.25	2022.03.24
Agilent	Power Sensor	N8482A	MY41090849	2021.10.21	2022.10.20
Agilent	Power Meter	E4416A	MY45102093	2021.10.21	2022.10.20
Anritsu	Power Sensor	MA2411B	N/A	2021.10.21	2022.10.20
Anritsu	Power Meter	NRVD	101066	2021.10.21	2022.10.20
Agilent	Dual Directional Coupler	778D	50422	NA	NA
MCL	Attenuation	351-218-010	N/A	NA	NA
KTJ	Thermo meter	TA298	N/A	2021.12.21	2022.12.20



SPEAG	Tissue Simulating Liquids	HBBL600-10000V6	24H
-------	---------------------------	-----------------	-----

**Note:**

1. The calibration certificate of DASY can be referred to appendix G of this report.
2. The Insertion Loss calibration of Dual Directional Coupler and Attenuator were characterized via the network analyzer and compensated during system check.
3. The dielectric probe kit was calibrated via the network analyzer, with the specified procedure (calibrated in pure water) and calibration kit (standard) short circuit, before the dielectric measurement. The specific procedure and calibration kit are provided by Speag.
4. In system check we need to monitor the level on the power meter, and adjust the power amplifier level to have precise power level to the dipole; the measured SAR will be normalized to 1W input power according to the ratio of 1W to the input power to the dipole. For system check, the calibration of the power amplifier is deemed not critically required for correct measurement; the power meter is critical and we do have calibration for it.
5. Attenuator insertion loss is calibrated by the network Analyzer, which the calibration is valid, before system check.
6. N.C.R means No Calibration Requirement.

## 7. Tissue Simulating Liquids

For SAR measurement of the field distribution inside the phantom, the phantom must be filled with homogeneous tissue simulating liquid to a depth of at least 15cm. For head SAR testing, the liquid height from the ear reference point (ERP) of the phantom to the liquid top surface is larger than 15cm. For body SAR testing, the liquid height from the center of the flat phantom to the liquid top surface is larger than 15cm, which is shown in Fig. 7.1. For body SAR testing, the liquid height from the center of the flat phantom to the liquid top surface is larger than 15 cm, which is shown in Fig. 7.2. The nominal dielectric values of the tissue simulating liquids in the phantom and the tolerance of 5% are listed in below table.



Fig 7.1 Photo of Liquid Height for Head SAR



Fig 7.2 Photo of Liquid Height for Body SAR

The following table gives the recipes for tissue simulating liquids

Frequency (MHz)	Water (%)	Sugar (%)	Cellulose (%)	Salt (%)	Preventol (%)	DGBE (%)	Conductivity ( $\sigma$ )	Permittivity ( $\epsilon_r$ )
Head								
750	41.1	57.0	0.2	1.4	0.2	0	0.89	41.9
835	40.3	57.9	0.2	1.4	0.2	0	0.90	41.5
1800,1900,2000	55.2	0	0	0.3	0	44.5	1.40	40.0
2450	55.0	0	0	0	0	45.0	1.80	39.2
2600	54.8	0	0	0.1	0	45.1	1.96	39.0
Body								
750	51.7	47.2	0	0.9	0.1	0	0.96	55.5
835	50.8	48.2	0	0.9	0.1	0	0.97	55.2
1800,1900,2000	70.2	0	0	0.4	0	29.4	1.52	53.3
2450	68.6	0	0	0	0	31.4	1.95	52.7
2600	68.1	0	0	0.1	0	31.8	2.16	52.5

Simulating Liquid for 5GHz, Manufactured by SPEAG.

Ingredients	(% by weight)
Water	64~78%
Mineral oil	11~18%
Emulsifiers	9~15%
Additives and Salt	2~3%



**Note:** Please refer to the validation results for dielectric parameters of each frequency band.

The dielectric properties of the tissue simulating liquids were verified prior to the SAR evaluation using a SPEAG Dielectric Assessment KIT and an Agilent Network Analyzer.

**Table 1: Dielectric Performance of Tissue Simulating Liquid**

Frequency (MHz)	Tissue Type	Liquid Temp.(°C)	Conductivity ( $\sigma$ )	Conductivity Target ( $\sigma$ )	Delta ( $\sigma$ ) (%)	Limit (%)	Date
750	HSL	22.1	0.914	0.89	2.70	$\pm 5$	2022.2.22
900	HSL	22.1	0.981	0.97	1.13	$\pm 5$	2022.2.28
1800	HSL	22.1	1.446	1.40	3.29	$\pm 5$	2022.2.28
2000	HSL	22.2	1.455	1.40	3.93	$\pm 5$	2022.3.1
2300	HSL	22.3	1.731	1.67	3.65	$\pm 5$	2022.3.4
2450	HSL	22.3	1.864	1.80	3.56	$\pm 5$	2022.3.8
2600	HSL	22.3	2.013	1.96	2.70	$\pm 5$	2022.3.8
3700	HSL	22.2	3.241	3.12	3.88	$\pm 5$	2022.3.11
3900	HSL	22.2	3.387	3.33	1.71	$\pm 5$	2022.3.11
5250	HSL	22.3	4.792	4.71	1.74	$\pm 5$	2022.3.15
5600	HSL	22.1	5.142	5.07	1.42	$\pm 5$	2022.3.16
5750	HSL	22.1	5.288	5.22	1.30	$\pm 5$	2022.3.16
Frequency (MHz)	Tissue Type	Liquid Temp.(°C)	Permittivity ( $\epsilon_r$ )	Permittivity Target ( $\epsilon_r$ )	Delta ( $\epsilon_r$ ) (%)	Limit (%)	Date
750	HSL	22.1	41.917	41.90	0.04	$\pm 5$	2022.2.22
900	HSL	22.1	41.681	41.50	0.44	$\pm 5$	2022.2.28
1800	HSL	22.1	40.322	40.00	0.81	$\pm 5$	2022.2.28
2000	HSL	22.2	40.195	40.00	0.49	$\pm 5$	2022.3.1
2300	HSL	22.3	39.701	39.50	0.51	$\pm 5$	2022.3.4
2450	HSL	22.3	39.842	39.20	1.64	$\pm 5$	2022.3.8
2600	HSL	22.3	39.493	39.00	1.26	$\pm 5$	2022.3.8
3700	HSL	22.2	38.284	37.70	1.55	$\pm 5$	2022.3.11
3900	HSL	22.2	37.961	37.50	1.23	$\pm 5$	2022.3.11
5250	HSL	22.3	37.851	37.70	0.40	$\pm 5$	2022.3.15
5600	HSL	22.1	35.732	35.50	0.65	$\pm 5$	2022.3.16
5750	HSL	22.1	37.299	37.00	0.81	$\pm 5$	2022.3.16

## 8. SAR System Verification

Each DASY system is equipped with one or more system validation kits. These units, together with the predefined measurement procedures within the DASY software, enable the user to conduct the system performance check and system validation. System validation kit includes a dipole, tripod holder to fix it underneath the flat phantom and a corresponding distance holder.

### 8.1. Purpose of System Performance check

The system performance check verifies that the system operates within its specifications. System and operator errors can be detected and corrected. It is recommended that the system performance check be performed prior to any usage of the system in order to guarantee reproducible results. The system performance check uses normal SAR measurements in a simplified setup with a well characterized source. This setup was selected to give a high sensitivity to all parameters that might fail or vary over time. The system check does not intend to replace the calibration of the components, but indicates situations where the system uncertainty is exceeded due to drift or failure.

### 8.2. System Setup

The output power on dipole port must be calibrated to 24 dBm (250 mW) before dipole is connected. In the simplified setup for system evaluation, the DUT is replaced by a calibrated dipole and the power source is replaced by a continuous wave which comes from a signal generator. The calibrated dipole must be placed beneath the flat phantom section of the SAM twin phantom with the correct distance holder. The distance holder should touch the phantom surface with a light pressure at the reference marking and be oriented parallel to the long side of the phantom. The system check verifies that the system operates within its specifications. It is performed daily or before every SAR measurement. The system check uses normal SAR measurements in the flat section of the phantom with a matched dipole at a specified distance. The system verification setup is shown as below.



Fig 8.1 Photo of Dipole Setup




Fig 8.2 System Setup for System Evaluation



## 8.3. Validation Results

After system check testing, the SAR result will be normalized to 1W forward input power and compared with the reference SAR value derived from validation dipole certificate report. The deviation of system check should be within 10%.

### <Validation Setup>

Frequency (MHz)	Tissue Type	Input Power(mW)	Dipole S/N	Probe S/N	DAE S/N
750	HSL	250	D750V3-1173	3753	480
900	HSL	250	D900V2-1d064	3823	480
1800	HSL	250	D1800V2-2d158	3823	480
2000	HSL	250	D2000V2-1050	3823	480
2300	HSL	250	D2300V2-1107	3823	480
2450	HSL	250	D2450V2-805	3823	480
2600	HSL	250	D2600V2-1139	3823	480
3400	HSL	100	D3400V2-1104	3823	480
3500	HSL	100	D3500V2-1104	3823	480
3700	HSL	100	D3700V2-1079	3823	480
3900	HSL	100	D3900V2-1179	3823	480
4100	HSL	100	D4100V2-1179	3823	480
4200	HSL	100	D4200V2-1017	3823	480
4400	HSL	100	D4400V2-1017	3823	480
4600	HSL	100	D4600V2-1043	3823	480
4800	HSL	100	D4800V2-1039	3823	480
4900	HSL	100	D4900V2-1039	3823	480
5250	HSL	100	D5GHzV2-1176-5750	3823	480
5600	HSL	100	D5GHzV2-1176-5600	3823	480
5750	HSL	100	D5GHzV2-1176-5750	3823	480



## &lt;System Validation&gt;

Frequency (MHz)	Tissue Type	Conductivity ( $\sigma$ )	Permittivity ( $\epsilon_r$ )	CW Signal Validation		
				Sensitivity	Probe Linearity	Probe Isotropy
750	HSL	0.851	42.43	PASS	PASS	PASS
835	HSL	0.898	41.88	PASS	PASS	PASS
1750	HSL	1.386	39.91	PASS	PASS	PASS
1800	HSL	1.449	41.26	PASS	PASS	PASS
1900	HSL	1.435	39.65	PASS	PASS	PASS
2000	HSL	1.451	39.42	PASS	PASS	PASS
2300	HSL	1.764	38.99	PASS	PASS	PASS
2450	HSL	1.863	38.85	PASS	PASS	PASS
2600	HSL	1.973	38.58	PASS	PASS	PASS
3400	HSL	2.88	38.10	PASS	PASS	PASS
3500	HSL	2.91	37.90	PASS	PASS	PASS
3700	HSL	3.05	37.70	PASS	PASS	PASS
3900	HSL	3.15	37.50	PASS	PASS	PASS
4100	HSL	3.25	37.20	PASS	PASS	PASS
4200	HSL	3.34	37.00	PASS	PASS	PASS
4400	HSL	3.58	36.70	PASS	PASS	PASS
4600	HSL	3.70	36.60	PASS	PASS	PASS
4800	HSL	3.82	36.40	PASS	PASS	PASS
4900	HSL	3.96	36.20	PASS	PASS	PASS
5250	HSL	4.528	35.32	PASS	PASS	PASS
5600	HSL	4.905	34.89	PASS	PASS	PASS
5750	HSL	5.077	34.28	PASS	PASS	PASS



Frequency (MHz)	Tissue Type	Conductivity ( $\sigma$ )	Permittivity ( $\epsilon_r$ )	Modulation Signal Validation		
				Mod. Type	Duty Factor	PAR
750	HSL	0.851	42.43	N/A	N/A	N/A
835	HSL	0.898	41.88	GMSK	PASS	N/A
1750	HSL	1.386	39.91	N/A	N/A	N/A
1800	HSL	1.449	41.26	N/A	N/A	N/A
1900	HSL	1.435	39.65	GMSK	PASS	N/A
2000	HSL	1.451	39.42	GMSK	PASS	N/A
2300	HSL	1.764	38.99	OFDM	PASS	PASS
2450	HSL	1.863	38.85	OFDM	PASS	PASS
2600	HSL	1.973	38.58	TDD	PASS	N/A
3400	HSL	2.88	38.10	OFDM	PASS	PASS
3500	HSL	2.91	37.90	OFDM	PASS	PASS
3700	HSL	3.05	37.70	OFDM	PASS	PASS
3900	HSL	3.15	37.50	OFDM	PASS	PASS
4100	HSL	3.25	37.20	OFDM	PASS	PASS
4200	HSL	3.34	37.00	OFDM	PASS	PASS
4400	HSL	3.58	36.70	OFDM	PASS	PASS
4600	HSL	3.70	36.60	OFDM	PASS	PASS
4800	HSL	3.82	36.40	OFDM	PASS	PASS
4900	HSL	3.96	36.20	OFDM	PASS	PASS
5250	HSL	4.528	35.32	OFDM	N/A	PASS
5600	HSL	4.905	34.89	OFDM	N/A	PASS
5750	HSL	5.077	34.28	OFDM	N/A	PASS

**<Validation Results>**

Date	Frequency (MHz)	Tissue Type	Input Power (mW)	Measured 1g SAR (W/kg)	Targeted 1g SAR (W/kg)	Normalized 1g SAR (W/kg)	Deviation (%)
2022.2.22	750	HSL	250	2.74	11.20	10.96	-2.14
2022.2.28	900	HSL	250	2.85	11.20	11.4	1.79
2022.2.28	1800	HSL	250	10.19	39.20	40.76	3.98
2022.3.1	2000	HSL	250	10.54	41.60	42.16	1.35
2022.3.4	2300	HSL	250	12.46	48.40	49.84	2.98
2022.3.8	2450	HSL	250	13.25	52.30	53	1.34
2022.3.8	2600	HSL	250	13.68	54.00	54.72	1.33
2022.3.11	3700	HSL	100	7.01	67.50	70.1	3.85
2022.3.11	3900	HSL	100	6.94	69.90	69.4	-0.72
2022.3.15	5250	HSL	100	7.89	76.70	78.9	2.87
2022.3.16	5600	HSL	100	8.35	80.30	83.5	3.99
2022.3.16	5750	HSL	100	8.23	78.70	82.3	4.57

Date	Frequency (MHz)	Tissue Type	Input Power (mW)	Measured 10g SAR (W/kg)	Targeted 10g SAR (W/kg)	Normalized 10g SAR (W/kg)	Deviation (%)
2022.2.22	750	HSL	250	1.77	7.19	7.08	-1.53
2022.2.28	900	HSL	250	1.81	7.19	7.24	0.70
2022.2.28	1800	HSL	250	5.25	20.10	21	4.48
2022.3.1	2000	HSL	250	5.21	20.70	20.84	0.68
2022.3.4	2300	HSL	250	5.77	23.00	23.08	0.35
2022.3.8	2450	HSL	250	6.11	23.90	24.44	2.26
2022.3.8	2600	HSL	250	6.31	24.50	25.24	3.02
2022.3.11	3700	HSL	100	2.54	24.20	25.4	4.96
2022.3.11	3900	HSL	100	2.39	24.10	23.9	-0.83
2022.3.15	5250	HSL	100	2.28	22.10	22.8	3.17
2022.3.16	5600	HSL	100	2.32	23.30	23.2	-0.43
2022.3.16	5750	HSL	100	2.27	22.50	22.7	0.89

**Note:** System checks the specific test data please see Annex C.

## 9. EUT Testing Position

This EUT was tested in six different positions. They are right cheek/right tilted/left cheek/left tilted for head, Front/Back of the EUT with phantom 10 mm gap, as illustrated below, please refer to Appendix B for the test setup photos.

### 9.1. Handset Reference Points

The vertical centre line passes through two points on the front side of the handset – the midpoint of the width  $w_t$  of the handset at the level of the acoustic output, and the midpoint of the width  $w_b$  of the bottom of the handset.

The horizontal line is perpendicular to the vertical centre line and passes the center of the acoustic output. The horizontal line is also tangential to the handset at point A.

The two lines intersect at point A. Note that for many handsets, point A coincides with the center of the acoustic output; however, the acoustic output may be located elsewhere on the horizontal line. Also note that the vertical centre line is not necessarily parallel to the front face of the handset, especially for clamshell handsets, handsets with flip covers, and other irregularly shaped handsets.



Fig. 9.1 Illustration for Cheek Position




Fig. 9.2 Illustration for Handset Vertical and Horizontal Reference Lines

## 9.2. Positioning for Cheek / Touch

To position the device with the vertical center line of the body of the device and the horizontal line crossing the center piece in a plane parallel to the sagittal plane of the phantom. While maintaining the device in this plane, align the vertical center line with the reference plane containing the three ear and mouth reference point (M: Mouth, RE: Right Ear and LE: Left Ear) and align the center of the ear piece with the line RE-LE.

To move the device towards the phantom with the ear piece aligned with the line LE-RE until the phone touched the ear. While maintaining the device in the reference plane and maintaining the phone contact with the ear, move the bottom of the phone until any point on the front side is in contact with the cheek of the phantom or until contact with the ear is lost (see below figure)




Fig 9.3 Illustration for Cheek Position

### 9.3. Positioning for Ear / 15° Tilt

To position the device in the “cheek” position described above.

While maintaining the device the reference plane described above and pivoting against the ear, moves it outward away from the mouth by an angle of 15 degrees or until contact with the ear is lost (see figure below).



Fig 9.4 Illustration for Tilted Position

### 9.4. SAR Evaluation near the Mouth/Jaw Regions of the Phantom

Antennas located near the bottom of a phone may require SAR measurements around the mouth and jaw regions of the SAM head phantom. This typically applies to clam-shell style phones that are generally longer in the unfolded normal use positions or to certain older style long rectangular phones.

Under these circumstances, the following procedures apply, adopted from the FCC guidance on SAR handsets document FCC KDB Publication 648474 D04v01r03. The SAR required in these regions of SAM should be measured using a flat phantom. The phone should be positioned with a separation distance of 4 mm between the ear reference point (ERP) and the outer surface of the flat phantom shell. While maintaining this distance at the ERP location, the low (bottom) edge of the phone should be lowered from the phantom to establish the same separation distance between the peak SAR locations identified by the truncated partial SAR distribution measured with the SAM phantom. The distance from the peak SAR location to the phone is determined by the straight line passing perpendicularly through the phantom surface. When it is not feasible to maintain 4 mm separation at the ERP while also establishing the required separation at the peak SAR location, the top edge of the phone will be allowed to touch the phantom with a separation < 4 mm at the ERP. The phone should not be tilted to the left or right while placed in this inclined position to the flat phantom.

## 9.5. Body-worn Configurations

The body-worn configurations shall be tested with the supplied accessories (belt-clips, holsters, etc.) attached to the device in normal use configuration.

For body-worn and other configurations a flat phantom shall be used which is comprised of material with electrical properties similar to the corresponding tissues.




Fig 9.5 Illustration for Body Worn Position

## 9.6. Hotspot Mode Exposure Position Conditions

For handsets that support hotspot mode operations, with wireless router capabilities and various web browsing functions, the relevant hand and body exposure conditions are tested according to the hotspot SAR procedures in KDB 941225. A test separation distance of 10 mm is required between the phantom and all surfaces and edges with a transmitting antenna located within 25 mm from that surface or edge. When the form factor of a handset is smaller than 9 cm x 5 cm, a test separation distance of 5 mm (instead of 10 mm) is required for testing hotspot mode. When the separation distance required for body-worn accessory testing is larger than or equal to that tested for hotspot mode, in the same wireless mode and for the same surface of the phone, the hotspot mode SAR data may be used to support body-worn accessory SAR compliance for that particular configuration (surface).




Fig 9.6 Illustration for Hotspot Position

## 10. Measurement Procedures

The measurement procedures are as follows:

### <Conducted power measurement>

- (a) For WWAN power measurement, use base station simulator to configure EUT WWAN transmission in conducted connection with RF cable, at maximum power in each supported wireless interface and frequency band.
- (b) Read the WWAN RF power level from the base station simulator.
- (c) For WLAN/BT power measurement, use engineering software to configure EUT WLAN/BT continuously transmission, at maximum RF power in each supported wireless interface and frequency band.
- (d) Connect EUT RF port through RF cable to the power meter, and measure WLAN/BT output power.

### <SAR measurement>

- (a) Use base station simulator to configure EUT WWAN transmission in radiated connection, and engineering software to configure EUT WLAN/BT continuously transmission, at maximum RF power, in the highest power channel.
- (b) Place the EUT in the positions as Appendix D demonstrates.
- (c) Set scan area, grid size and other setting on the DASY software.
- (d) Measure SAR results for the highest power channel on each testing position.
- (e) Find out the largest SAR result on these testing positions of each band.
- (f) Measure SAR results for other channels in worst SAR testing position if the reported SAR of highest power channel is larger than 0.8 W/kg.

According to the test standard, the recommended procedure for assessing the peak spatial-average SAR value consists of the following steps:

- (a) Power reference measurement.
- (b) Area scan.
- (c) Zoom scan.
- (d) Power drift measurement.

### 10.1. Spatial Peak SAR Evaluation

The procedure for spatial peak SAR evaluation has been implemented according to the test standard. It can be conducted for 1g and 10g, as well as for user-specific masses. The DASY software includes all numerical procedures necessary to evaluate the spatial peak SAR value.

The base for the evaluation is a "cube" measurement. The measured volume must include the 1g and 10g cubes with the highest averaged SAR values. For that purpose, the center of the measured volume is aligned to the interpolated peak SAR value of a previously performed area scan.



The entire evaluation of the spatial peak values is performed within the post-processing engine (SEMCAD). The system always gives the maximum values for the 1g and 10g cubes. The algorithm to find the cube with highest averaged SAR is divided into the following stages:

- (a) Extraction of the measured data (grid and values) from the Zoom Scan.
- (b) Calculation of the SAR value at every measurement point based on all stored data (A/D values and measurement parameters).
- (c) Generation of a high-resolution mesh within the measured volume.
- (d) Interpolation of all measured values from the measurement grid to the high-resolution grid.
- (e) Extrapolation of the entire 3-D field distribution to the phantom surface over the distance from sensor to surface.
- (f) Calculation of the averaged SAR within masses of 1g and 10g.

## 10.2. Power Reference Measurement

The Power Reference Measurement and Power Drift Measurements are for monitoring the power drift of the device under test in the batch process. The minimum distance of probe sensors to surface determines the closest measurement point to phantom surface. This distance cannot be smaller than the distance of sensor calibration points to probe tip as defined in the probe properties.

## 10.3. Area Scan Procedures

Area scans are defined prior to the measurement process being executed with a user defined variable spacing between each measurement point (integral) allowing low uncertainty measurements to be conducted. Scans defined for FCC applications utilize a  $10\text{mm}^2$  step integral, with 1mm interpolation used to locate the peak SAR area used for zoom scan assessments.

When an Area Scan has measured all reachable points, it computes the field maxima founding the scanned area, within a range of the global maximum. The range (in dB) is specified in the standards for compliance testing. For example, a 2 dB range is required in IEEE1528-2003.

## 10.4. Zoom Scan Procedures

Zoom Scans are used to assess the peak spatial SAR values within a cubic averaging volume containing 1 g and 10 g of simulated tissue. A density of  $1000 \text{ kg/m}^3$  is used to represent the head and body tissue density and not the phantom liquid density, in order to be consistent with the definition of the liquid dielectric properties, i.e. the side length of the 1g cube is 10mm, with the side



length of the 10 g cube 21,5mm. The zoom scan integer steps can be user defined so as to reduce uncertainty, but normal practice for typical test applications utilize a physical step of 5x5x7 (8mmx8mmx5mm) providing a volume of 32mm in the X & Y axis, and 30mm in the Z axis.

## 10.5. SAR Averaged Methods

In DASY, the interpolation and extrapolation are both based on the modified Quadratic Sheppard's method. The interpolation scheme combines a least-square fitted function method and a weighted average method which are the two basic types of computational interpolation and approximation.

Extrapolation routines are used to obtain SAR values between the lowest measurement points and the inner phantom surface. The extrapolation distance is determined by the surface detection distance and the probe sensor offset. The uncertainty increases with the extrapolation distance. To keep the uncertainty within 1% for the 1 g and 10 g cubes, the extrapolation distance should not be larger than 5 mm.

## 10.6. Power Drift Monitoring

All SAR testing is under the DUT install full charged battery and transmit maximum output power. In DASY measurement software, the power reference measurement and power drift measurement procedures are used for monitoring the power drift of DUT during SAR test. Both these procedures measure the field at a specified reference position before and after the SAR testing. The software will calculate the field difference in dB. If the power drift more than 5%, the SAR will be retested.

# 11. SAR Test Procedure

## 11.1. General Scan Requirements

Probe boundary effect error compensation is required for measurements with the probe tip closer than half a probe tip diameter to the phantom surface. Both the probe tip diameter and sensor offset distance must satisfy measurement protocols; to ensure probe boundary effect errors are minimized and the higher fields closest to the phantom surface can be correctly measured and extrapolated to the phantom surface for computing 1-g SAR. Tolerances of the post-processing algorithms must be verified by the test laboratory for the scan resolutions used in the SAR measurements, according to the reference distribution functions specified in IEEE Std. 1528-2013.

		$\leq 3$ GHz	$> 3$ GHz
Maximum distance from closest measurement point (geometric center of probe sensors) to phantom surface		$5 \text{ mm} \pm 1 \text{ mm}$	$\frac{1}{2} \cdot \delta \cdot \ln(2) \text{ mm} \pm 0.5 \text{ mm}$
Maximum probe angle from probe axis to phantom surface normal at the measurement location		$30^\circ \pm 1^\circ$	$20^\circ \pm 1^\circ$
		$\leq 2 \text{ GHz: } \leq 15 \text{ mm}$ $2 - 3 \text{ GHz: } \leq 12 \text{ mm}$	$3 - 4 \text{ GHz: } \leq 12 \text{ mm}$ $4 - 6 \text{ GHz: } \leq 10 \text{ mm}$
Maximum area scan spatial resolution: $\Delta x_{\text{Area}}, \Delta y_{\text{Area}}$		When the x or y dimension of the test device, in the measurement plane orientation, is smaller than the above, the measurement resolution must be $\leq$ the corresponding x or y dimension of the test device with at least one measurement point on the test device.	
Maximum zoom scan spatial resolution: $\Delta x_{\text{Zoom}}, \Delta y_{\text{Zoom}}$		$\leq 2 \text{ GHz: } \leq 8 \text{ mm}$ $2 - 3 \text{ GHz: } \leq 5 \text{ mm}^*$	$3 - 4 \text{ GHz: } \leq 5 \text{ mm}^*$ $4 - 6 \text{ GHz: } \leq 4 \text{ mm}^*$
Maximum zoom scan spatial resolution, normal to phantom surface	uniform grid: $\Delta z_{\text{Zoom}}(n)$	$\leq 5 \text{ mm}$	$3 - 4 \text{ GHz: } \leq 4 \text{ mm}$ $4 - 5 \text{ GHz: } \leq 3 \text{ mm}$ $5 - 6 \text{ GHz: } \leq 2 \text{ mm}$
	graded grid	$\Delta z_{\text{Zoom}}(1): \text{ between } 1^{\text{st}} \text{ two points closest to phantom surface}$ $\Delta z_{\text{Zoom}}(n>1): \text{ between subsequent points}$	$\leq 4 \text{ mm}$ $\leq 1.5 \cdot \Delta z_{\text{Zoom}}(n-1) \text{ mm}$
Minimum zoom scan volume	x, y, z	$\geq 30 \text{ mm}$	$3 - 4 \text{ GHz: } \geq 28 \text{ mm}$ $4 - 5 \text{ GHz: } \geq 25 \text{ mm}$ $5 - 6 \text{ GHz: } \geq 22 \text{ mm}$
Note: $\delta$ is the penetration depth of a plane-wave at normal incidence to the tissue medium; see IEEE Std 1528-2013 for details.			
* When zoom scan is required and the <u>reported</u> SAR from the <i>area scan based 1-g SAR estimation</i> procedures of KDB Publication 447498 is $\leq 1.4 \text{ W/kg}$ , $\leq 8 \text{ mm}$ , $\leq 7 \text{ mm}$ and $\leq 5 \text{ mm}$ zoom scan resolution may be applied, respectively, for 2 GHz to 3 GHz, 3 GHz to 4 GHz and 4 GHz to 6 GHz.			

## 11.2. Test Procedure

The Following steps are used for each test position

1. Establish a call with the maximum output power with a base station simulator. The connection between the mobile and the base station simulator is established via air interface.
2. Measurement of the local E-field value at a fixed location. This value serves as a reference value for calculating a possible power drift.
3. Measurement of the SAR distribution with a grid of 8 to 16mm \* 8 to 16 mm and a constant distance to the inner surface of the phantom. Since the sensors cannot directly measure at the inner phantom surface, the values between the sensors and the inner phantom surface are extrapolated. With these values the area of the maximum SAR is calculated by an interpolation scheme.
4. Around this point, a cube of 30 \* 30 \* 30 mm or 32 \* 32 \* 32 mm is assessed by measuring 5 or 8 \* 5 or 8\*4 or 5 mm. With these data, the peak spatial-average SAR value can be calculated.

## 11.3. Description of Interpolation/Extrapolation Scheme

The local SAR inside the phantom is measured using small dipole sensing elements inside a probe body. The probe tip must not be in contact with the phantom surface in order to minimize measurements errors, but the highest local SAR will occur at the surface of the phantom.

An extrapolation is using to determinate this highest local SAR values. The extrapolation is based on a fourth-order least-square polynomial fit of measured data. The local SAR value is then extrapolated from the liquid surface with a 1mm step.

The measurements have to be performed over a limited time (due to the duration of the battery) so the step of measurement is high. It could vary between 5 and 8 mm. To obtain an accurate assessment of the maximum SAR averaged over 10 grams and 1 gram requires a very fine resolution in the three dimensional scanned data array.

## 11.4. Wireless Router

Some battery-operated handsets have the capability to transmit and receive user through simultaneous transmission of WIFI simultaneously with a separate licensed transmitter. The FCC has provided guidance in FCC KDB Publication 941225 D06 v02r01 where SAR test considerations for handsets ( $L \times W \geq 9 \text{ cm} \times 5 \text{ cm}$ ) are based on a composite test separation distance of 10 from the front, back and edges of the device containing transmitting antennas within 2.5cm of their edges,



determined from general mixed use conditions for this type of devices. Since the hotspot SAR results may overlap with the body-worn accessory SAR requirements, the more conservative configurations can be considered, thus excluding some body-worn accessory SAR tests.

When the user enables the personal wireless router functions for the handset, actual operations include simultaneous transmission of both the WIFI transmitter and another licensed transmitter. Both transmitters often do not transmit at the same transmitting frequency and thus cannot be evaluated for SAR under actual use conditions due to the limitations of the SAR assessment probes. Therefore, SAR must be evaluated for each frequency transmission and mode separately and spatially summed with the WIFI transmitter according to FCC KDB Publication 447498 D01v06 publication procedures. The "Portable Hotspot" feature on the handset was NOT activated during SAR assessments, to ensure the SAR measurements were evaluated for a single transmission frequency RF signal at a time.



## 12. SAR Test Configuration

### <GSM Mode>

A summary of these settings are illustrated below:

For GSM850 frequency band, the power control is set to 5 for GSM/GPRS mode (GSMK-CS1) and set to 8 for EDGE mode (MCS5); For GSM1900 frequency band, the power control is set to 0 for GSM/GPRS mode (GSMK-CS1) and set to 2 for EDGE mode (MCS5).

1. Per KDB 447498 D01v06, the maximum output power channel is used for SAR testing and for further SAR test reduction.
2. Per KDB 941225 D01v03r01, SAR test reduction for GSM / GPRS / EDGE modes is determined by the source-based time-averaged output power including tune-up tolerance. The mode with highest specified time-averaged output power should be tested for SAR compliance in the applicable exposure conditions. For modes with the same specified maximum output power and tolerance, the higher number time-slot configuration should be tested. Therefore, the GPRS (4Tx slots) for GSM850/GSM1900 is considered as the primary mode.
3. Other configurations of GSM / GPRS / EDGE are considered as secondary modes.

### Timeslot consignations:

#### Remark:

1. The frame-averaged power is linearly reported the maximum burst averaged power over 8 time slots. The calculated method are shown as below:

The duty cycle "x" of different time slots as below:

1 TX slot is 1/8, 2 TX slots is 2/8, 3 TX slots is 3/8 and 4 TX slots is 4/8

Based on the calculation formula:

Frame-averaged power = Burst averaged power + 10  $\log(x)$

So,

Frame-averaged power (1 TX slot) = Burst averaged power (1 TX slot) - 9.03

Frame-averaged power (2 TX slots) = Burst averaged power (2 TX slots) - 6.02

Frame-averaged power (3 TX slots) = Burst averaged power (3 TX slots) - 4.26

Frame-averaged power (4 TX slots) = Burst averaged power (4 TX slots) - 3.01

2. CS1 coding scheme was used in GPRS conducted power measurements and SAR testing, MCS5 coding scheme was used in EGPRS conducted power measurements and SAR testing (if necessary).

No. of Slots:	Slot 1	Slot 2	Slot 3	Slot 4
Slot Consignation:	1Up 4Down	2Up 3Down	3Up 2Down	4Up 1Down
Duty Cycle:	1:8.3	1:4.15	1:2.77	1:2.08
Correct Factor:	-9.03dB	-6.02dB	-4.26dB	-3.01dB

**<WCDMA Mode>**

Summary of UMTS conducted power measurement:

1. The 3G SAR test reduction procedure is applied, when the maximum output power and tune-up tolerance specified for production units in a secondary mode is  $\leq \frac{1}{4}$  dB higher than the primary mode, SAR measurement is not required for the secondary mode.
2. The following tests were conducted according to the test requirements outlined in 3GPP TS 34.121 specification.
3. The procedures in KDB 941225 D01v03r01 are applied for 3GPP Rel. 6 HSPA to configure the device in the required sub-test mode(s) to determine SAR test exclusion.
4. For HSPA+ devices supporting 16 QAM in the uplink, power measurements procedure is according to the configurations in Table C.11.1.4 of 3GPP TS 34.121-1.
5. Per KDB 941225 D01v03r01, RMC 12.2kbps setting is used to evaluate SAR. The maximum output power and tune-up tolerance specified for production units in HSDPA / HSUPA / DC-HSDPA / HSPA+ is  $\leq \frac{1}{4}$  dB higher than RMC 12.2Kbps or when the highest reported SAR of the RMC12.2Kbps is scaled by the ratio of specified maximum output power and tune-up tolerance of HSDPA / HSUPA / DC-HSDPA / HSPA+ to RMC12.2Kbps and the adjusted SAR is  $\leq 1.2$  W/kg, SAR measurement is not required for HSDPA / HSUPA / DC-HSDPA / HSPA+, and according to the following RF output power, the output power results of the secondary modes (HSDPA / HSUPA / DC-HSDPA / HSPA+) are less than  $\frac{1}{4}$  dB higher than the primary modes; therefore, SAR measurement is not required for HSDPA / HSUPA / DC-HSDPA / HSPA+.
6. A fixed level power reduction is applied for WCDMA Band II when handset open Hotspot mode, the power reduction triggered.

**HSDPA Setup Configuration**

Sub-test	$\beta_c$	$\beta_d$	$\beta_d$ (SF)	$\beta_c/\beta_d$	$\beta_{hs}^{(1)}$	CM (dB) <sup>(2)</sup>
1	2/15	15/15	64	2/15	4/15	0.0
2	12/15 <sup>(3)</sup>	15/15 <sup>(3)</sup>	64	12/15 <sup>(3)</sup>	24/15	1.0
3	15/15	8/15	64	15/8	30/15	1.5
4	15/15	4/15	64	15/4	30/15	1.5

Note 1:  $\Delta_{ACK}, \Delta_{NACK}$  and  $\Delta_{CQI} = 8 \Leftrightarrow A_{hs} = \beta_{hs}/\beta_c = 30/15 \Leftrightarrow \beta_{hs} = 30/15 * \beta_c$   
Note 2: CM = 1 for  $\beta_c/\beta_d = 12/15$ ,  $\beta_{hs}/\beta_c = 24/15$ .  
Note 3: For subtest 2 the  $\beta_c/\beta_d$  ratio of 12/15 for the TFC during the measurement period (TF1, TF0) is achieved by setting the signaled gain factors for the reference TFC (TF1, TF1) to  $\beta_c = 11/15$  and  $\beta_d = 15/15$ .

HSUPA Setup Configuration

Sub-test	$\beta_c$	$\beta_d$	$\beta_d$ (SF)	$\beta_c/\beta_d$	$\beta_{hs}^{(1)}$	$\beta_{ec}$	$\beta_{ed}$	$\beta_{ed}$ (SF)	$\beta_{ed}$ (codes)	CM <sup>(2)</sup> (dB)	MPR (dB)	AG <sup>(4)</sup> Index	E-TFCI
1	11/15 <sup>(3)</sup>	15/15 <sup>(3)</sup>	64	11/15 <sup>(3)</sup>	22/15	209/225	1039/225	4	1	1.0	0.0	20	75
2	6/15	15/15	64	6/15	12/15	12/15	94/75	4	1	3.0	2.0	12	67
3	15/15	9/15	64	15/9	30/15	30/15	$\beta_{ed1}: 47/15$ $\beta_{ed2}: 47/15$	4	2	2.0	1.0	15	92
4	2/15	15/15	64	2/15	4/15	2/15	56/75	4	1	3.0	2.0	17	71
5	15/15 <sup>(4)</sup>	15/15 <sup>(4)</sup>	64	15/15 <sup>(4)</sup>	30/15	24/15	134/15	4	1	1.0	0.0	21	81

Note 1:  $\Delta_{ACK}, \Delta_{NACK}$  and  $\Delta_{CQI} = 8 \Leftrightarrow A_{hs} = \beta_{hs}/\beta_c = 30/15 \Leftrightarrow \beta_{hs} = 30/15 * \beta_c$ .  
Note 2: CM = 1 for  $\beta_c/\beta_d = 12/15, \beta_{hs}/\beta_c = 24/15$ . For all other combinations of DPDCH, DPCCH, HS-DPCCH, E-DPDCH and E-DPCCH the MPR is based on the relative CM difference.  
Note 3: For subtest 1 the  $\beta_c/\beta_d$  ratio of 11/15 for the TFC during the measurement period (TF1, TF0) is achieved by setting the signaled gain factors for the reference TFC (TF1, TF1) to  $\beta_c = 10/15$  and  $\beta_d = 15/15$ .  
Note 4: For subtest 5 the  $\beta_c/\beta_d$  ratio of 15/15 for the TFC during the measurement period (TF1, TF0) is achieved by setting the signaled gain factors for the reference TFC (TF1, TF1) to  $\beta_c = 14/15$  and  $\beta_d = 15/15$ .  
Note 5: Testing UE using E-DPDCH Physical Layer category 1 Sub-test 3 is not required according to TS 25.306 Table 5.1g.  
Note 6:  $\beta_{ed}$  cannot be set directly; it is set by Absolute Grant Value.

**HSPA+ 3GPP release 7 (uplink category 7) 16QAM, Setup Configuration:****Table C.11.1.4:  $\beta$  values for transmitter characteristics tests with HS-DPCCH and E-DCH with 16QAM**

Sub-test	$\beta_c$ (Note 3)	$\beta_d$	$\beta_{HS}$ (Note 1)	$\beta_{ec}$	$\beta_{ed}$ (2xSF2) (Note 4)	$\beta_{ed}$ (2xSF4) (Note 4)	CM (dB) (Note 2)	MPR (dB) (Note 2)	AG Index (Note 4)	E-TFCI (Note 5)	E-TFCI (boost)
1	1	0	30/15	30/15	$\beta_{ed1}: 30/15$ $\beta_{ed2}: 30/15$	$\beta_{ed3}: 24/15$ $\beta_{ed4}: 24/15$	3.5	2.5	14	105	105

Note 1:  $\Delta_{ACK}, \Delta_{NACK}$  and  $\Delta_{CQI} = 30/15$  with  $\beta_{hs} = 30/15 * \beta_c$ .  
Note 2: CM = 3.5 and the MPR is based on the relative CM difference, MPR = MAX(CM-1,0).  
Note 3: DPDCH is not configured, therefore the  $\beta_c$  is set to 1 and  $\beta_d = 0$  by default.  
Note 4:  $\beta_{ed}$  can not be set directly; it is set by Absolute Grant Value.  
Note 5: All the sub-tests require the UE to transmit 2SF2+2SF4 16QAM EDCH and they apply for UE using E-DPDCH category 7. E-DCH TTI is set to 2ms TTI and E-DCH table index = 2. To support these E-DCH configurations DPDCH is not allocated. The UE is signaled to use the extrapolation algorithm.



### DC-HSDPA Setup Configuration

The following tests were completed according to procedures in section 7.3.13 of 3GPP TS34.108 v9.5.0. A summary of these settings are illustrated below:

Downlink Physical Channels are set as per 3GPP TS34.121-1 v9.0.0 E.5.

**Table E.5.0: Levels for HSDPA connection setup**

Parameter During Connection setup	Unit	Value
P-CPICH_Ec/Ior	dB	-10
P-CCPCH and SCH_Ec/Ior	dB	-12
PICH_Ec/Ior	dB	-15
HS-PDSCH	dB	off
HS-SCCH_1	dB	off
DPCH_Ec/Ior	dB	-5
OCNS_Ec/Ior	dB	-3.1

Call is set up as per 3GPP TS34.108 v9.5.0 sub clause 7.3.13

The configurations of the fixed reference channels for HSDPA RF tests are described in 3GPP TS 34.121, annex C for FDD and 3GPP TS 34.122.

Table C.8.1.12: Fixed Reference Channel H-Set 12

Parameter	Unit	Value
Nominal Avg. Inf. Bit Rate	kbps	60
Inter-TTI Distance	TTI's	1
Number of HARQ Processes	Proces ses	6
Information Bit Payload ( $N_{INF}$ )	Bits	120
Number Code Blocks	Blocks	1
Binary Channel Bits Per TTI	Bits	960
Total Available SML's in UE	SML's	19200
Number of SML's per HARQ Proc.	SML's	3200
Coding Rate		0.15
Number of Physical Channel Codes	Codes	1
Modulation		QPSK
Note 1:	The RMC is intended to be used for DC-HSDPA mode and both cells shall transmit with identical parameters as listed in the table.	
Note 2:	Maximum number of transmission is limited to 1, i.e., retransmission is not allowed. The redundancy and constellation version 0 shall be used.	

Inf. Bit Payload	120		
CRC Addition	120	24	CRC
Code Block Segmentation	144		
Turbo-Encoding (R=1/3)	432		12 Tail Bits
1st Rate Matching	432		
RV Selection	960		
Physical Channel Segmentation	960		

Figure C.8.19: Coding rate for Fixed reference Channel H-Set 12 (QPSK)



## &lt;CDMA Mode&gt;

**1xEV-DO Rev. B**

Call box setup procedure

1xEV-DO Release B

1> CMW 500 Signal Generator > 1xEV-DO Taskbar Enable

2> CMW 500 1xEV-DO Signaling Configuration Window >

3> 1xEV-DO Signaling On Window:

Under Access Network Control:

Band Class: BC0: US Cellular

RF Channel: 31

1xEV-DO Power: -70 dBm

4> 1xEV-DO Signaling Configuration Window

Under RF Frequency Band / Channel: Enter Ch. Frequency

➤ Under Carrier Configuration: RF Frequency

For Two Carriers: Low Channel (1013)

	<u>RF Channel</u>	<u>RF Channel Offset</u>
Carrier [0]	31	0
Carrier [1]	1013	982

➤ Under Carrier Configuration: RF Pilot

	<u>Carrier Sector</u>	<u>Active on AN</u>	<u>Assigned to AT</u>
Pilot [0]	C0/S0	✓	✓
	CA/S1	✓	✓

For Three Carriers: Low Channel (1013)

	<u>RF Channel</u>	<u>RF Channel Offset</u>
Carrier [0]	72	0
Carrier [1]	31	-41
Carrier [2]	1013	941

➤ Under Carrier Configuration: RF Pilot

	<u>Carrier Sector</u>	<u>Active on AN</u>	<u>Assigned to AT</u>
Pilot [0]	C0/S0	✓	✓
Pilot [1]	C1/S1	✓	✓
Pilot [2]	C2/S2	✓	✓

**<LTE Mode>****LTE Target MPR level**

The device implements maximum power reduction per 3GPP 36.101 requirements where the MPR target is as below table. The MPR settings are implemented configured into firmware and cannot be disabled by the end user or LTE carrier network.

Modulation	Channel bandwidth / Transmission bandwidth configuration [RB]						MPR Target	3GPP MPR (dB)
	1.4	3.0	5	10	15	20		
	MHz	MHz	MHz	MHz	MHz	MHz		
QPSK	> 5	> 4	> 8	> 12	> 16	> 18	1	≤ 1
16 QAM	≤ 5	≤ 4	≤ 8	≤ 12	≤ 16	≤ 18	1	≤ 1
64 QAM	> 5	> 4	> 8	> 12	> 16	> 18	2	≤ 2

**Note:** The measurement result showed some difference from the target MPR level, due to expected 0.5dB measurement tolerance

**LTE Bands**

LTE Bands	Channel bandwidth / Transmission bandwidth configuration [RB]					
	1.4	3.0	5	10	15	20
MHz	MHz	MHz	MHz	MHz	MHz	MHz
2	√	√	√	√	√	√
4	√	√	√	√	√	√
5	√	√	√	√	N/A	N/A
7	N/A	N/A	√	√	√	√
12	N/A	N/A	√	√	N/A	N/A
17	N/A	N/A	√	√	N/A	N/A
18	N/A	N/A	√	√	√	N/A
19	N/A	N/A	√	√	√	N/A
26	√	√	√	√	√	N/A
38	N/A	N/A	√	√	√	√
40A	N/A	N/A	√	√	N/A	N/A
40B	N/A	N/A	√	√	N/A	N/A
41	N/A	N/A	√	√	√	√
66	√	√	√	√	√	√

**Note:**

1. Per KDB 941225 D05v02r05, when a properly configured base station simulator is used for the SAR and power measurements, spectrum plots for each RB allocation and offset configuration is not required.
2. Per KDB 941225 D05v02r05, start with the largest channel bandwidth and measure SAR for QPSK with 1 RB allocation, using the RB offset and required test channel combination with the highest maximum output power for RB offsets at the upper edge, middle and lower edge of each



required test channel.

3. Per KDB 941225 D05v02r05, 50% RB allocation for QPSK SAR testing follows 1RB QPSK allocation procedure.
4. Per KDB 941225 D05v02r05, for QPSK with 100% RB allocation, SAR is not required when the highest maximum output power for 100 % RB allocation is less than the highest maximum output power in 50% and 1 RB allocations and the highest reported SAR for 1 RB and 50% RB allocation are  $\leq 0.8$  W/kg. Otherwise, SAR is measured for the highest output power channel; and if the reported SAR is  $> 1.45$  W/kg, the remaining required test channels must also be tested.
5. Per KDB 941225 D05v02r05, 16QAM/64QAM output power for each RB allocation configuration is  $>$  not  $\frac{1}{2}$  dB higher than the same configuration in QPSK and the reported SAR for the QPSK configuration is  $\leq 1.45$  W/kg; Per KDB941225 D05v02r05, 16QAM/64QAM SAR testing is not required.
6. Per KDB 941225 D05v02r05, smaller bandwidth output power for each RB allocation configuration is  $>$  not  $\frac{1}{2}$  Db higher than the same configuration in the largest supported bandwidth, and the reported SAR for the largest supported band width is  $\leq 1.45$  W/kg; Per KDB 941225 D05v02r05, smaller bandwidth SAR testing is not required.
7. For LTE B4 / B5 / B7 / B17 the maximum bandwidth does not support three non-overlapping channels, per KDB941225 D05v02r05, when a device supports overlapping channel assignment in a channel bandwidth configuration, the middle channel of the group of overlapping channels should be selected for testing.
8. LTE band 2 / 12 SAR test was covered by Band 25 / 17; according to April 2015 TCB workshop, SAR test for overlapping LTE bands can be reduced if
  - a. The maximum output power, including tolerance, for the smaller band is  $\leq$  the larger band to qualify for the SAR test exclusion.
  - b. The channel bandwidth and other operating parameters for the smaller band are fully supported by the larger band.
9. According to 2017 TCB workshop, for 64 QAM and 16 QAM should be verified by checking the signal constellation with a call box to avoid incorrect maximum power levels due to MPR and other requirements associated with signal modulation, and the following figure is taken from the "Fundamental Measurement >> Modulation Analysis >>constellation" mode of the device connect to the CMW500 base station, therefore, the device 64QAM and 16QAMsignal modulation are correct. Identify if Maximum Power Reduction (MPR) is optional or mandatory, i.e. built-in by design: only mandatory MPR may be considered during SAR testing, when the maximum output power is permanently limited by the MPR implemented within the UE; and only for the applicable RB (resource block) configurations specified in LTE standards: b) A-MPR (additional MPR) must be disabled.
10. Per KDB 447498 D01v06, the reported SAR is the measured SAR value adjusted for maximum tune-up tolerance.
  - a. Tune-up scaling Factor = tune-up limit power (mW) / EUT RF power (mW), where tune-up

limit is the maximum rated power among all production units.

- b. For SAR testing of WLAN signal with non-100% duty cycle, the measured SAR is scaled-up by the duty cycle scaling factor which is equal to "1/(duty cycle)"
- c. For WWAN: Reported SAR(W/kg)= Measured SAR(W/kg)\*Tune-up Scaling Factor
- d. For WLAN/Bluetooth: Reported SAR(W/kg)= Measured SAR(W/kg)\* Duty Cycle scaling factor \* Tune-up scaling factor
- e. For TDD LTE SAR measurement, the duty cycle 1:1.59 (62.9 %) was used to perform testing and considering the theoretical duty cycle of 63.3% for extended cyclic prefix in the uplink, and the theoretical duty cycle of 62.9% for normal cyclic prefix in uplink, a scaling factor of extended cyclic prefix 63.3%/62.9% = 1.006 is applied to scale-up the measured SAR result. The Reported TDD LTE SAR = measured SAR (W/kg)\* Tune-up Scaling Factor\* scaling factor for extended cyclic prefix.

11. Per KDB 447498 D01v06, for each exposure position, testing of other required channels within the operating mode of a frequency band is not required when the reported 1-g or 10-g SAR for the mid-band or highest output power channel is:  $\leq 0.8 \text{ W/kg}$  or  $2.0 \text{ W/kg}$ , for 1-g or 10-g respectively, when the transmission band is  $\leq 100 \text{ MHz}$   $\leq 0.6 \text{ W/kg}$  or  $1.5 \text{ W/kg}$ , for 1-g or 10-g respectively, when the transmission band is between  $100 \text{ MHz}$  and  $200 \text{ MHz}$   $\leq 0.4 \text{ W/kg}$  or  $1.0 \text{ W/kg}$ , for 1-g or 10-g respectively, when the transmission band is  $\geq 200 \text{ MHz}$
12. Per KDB 865664 D01v01r04, for each frequency band, repeated SAR measurement is required only when the measured SAR is  $\geq 0.8 \text{ W/kg}$ .
13. Per KDB 648474 D04v01r03, when the reported SAR for a body-worn accessory measured without a headset connected to the handset is  $\leq 1.2 \text{ W/kg}$ , SAR testing with a headset connected to the handset is not required.

#### **<WLAN 2.4GHz>**

1. SAR is measured for 2.4 GHz 802.11b DSSS using either the fixed test position or, when applicable, the initial test position procedure. SAR test reduction is determined according to the following:
  - a. When the reported SAR of the highest measured maximum output power channel for the exposure configuration is  $\leq 0.8 \text{ W/kg}$ , no further SAR testing is required for 802.11b DSSS in that exposure configuration.
  - b. When the reported SAR is  $> 0.8 \text{ W/kg}$ , SAR is required for that position using the next highest measured output power channel. When any reported SAR is  $> 1.2 \text{ W/kg}$ , SAR is required for the third channel; i.e., all channels require testing.
2. 2.4 GHz 802.11 g/n OFDM are additionally evaluated for SAR if the highest reported SAR for 802.11b, adjusted by the ratio of the OFDM to DSSS specified maximum output power, is  $> 1.2 \text{ W/kg}$ . When SAR is required for OFDM modes in 2.4 GHz band, the Initial Test configuration Procedures should be followed.
3. For held-to-ear and hotspot operations, the initial test position procedures were applied. The test



position with the highest extrapolated peak SAR will be used as the initial test position. When reported SAR for the initial test position is  $\leq 0.4$  W/kg, no additional testing for the remaining test positions was required. Otherwise, SAR is evaluated at the subsequent highest peak SAR positions until the reported SAR result is  $\leq 0.8$  W/kg or all test positions are measured.

4. Justification for test configurations for WLAN per KDB Publication 248227 D02DR02-41929 for 2.4 GHz WI-FI single transmission chain operations, the highest measured maximum output power channel for DSSS was selected for SAR measurement. SAR for OFDM modes (2.4 GHz802.11g/n) was not required due to the maximum allowed powers and the highest reported DSSS SAR.
5. A fixed level power reduction is applied for WiFi when handset operates "held to the body" condition or "held to the ear" condition, the power reduction triggered by audio receiver detection and call establish status.
6. Per KDB 248227 D01v02r02, In the 2.4 GHz band, separate SAR procedures are applied to DSSS and OFDM configurations to simplify DSSS test requirements. SAR is not required for the following 2.4 GHz OFDM conditions:
  - a. When KDB Publication 447498 SAR test exclusion applies to the OFDM configuration.
  - b. When the highest reported SAR for DSSS is adjusted by the ratio of OFDM to DSSS specified maximum output power and the adjusted SAR is  $\leq 1.2$  W/kg.

#### <WLAN 5GHz>

##### A) U-NII-1 and U-NII-2A Bands

For devices that operate in only one of the U-NII-1 and U-NII-2A bands, the normally required SAR procedures for OFDM configurations are applied. For devices that operate in both U-NII bands using the same transmitter and antenna(s), SAR test reduction is determined according to the following:

1. When the same maximum output power is specified for both bands, begin SAR measurement in U-NII-2A band by applying the OFDM SAR requirements. If the highest reported SAR for a test configuration is  $\leq 1.2$  W/kg, SAR is not required for U-NII-1 band for that configuration (802.11 mode and exposure condition); otherwise, both bands are tested independently for SAR.
2. When different maximum output power is specified for the bands, begin SAR measurement in the band with higher specified maximum output power. The highest reported SAR for the tested configuration is adjusted by the ratio of lower to higher specified maximum output power for the two bands. When the adjusted SAR is  $\leq 1.2$  W/kg, SAR is not required for the band with lower maximum output power in that test configuration; otherwise, both bands are tested independently for SAR.
3. The two U-NII bands may be aggregated to support a 160 MHz channel on channel number 50.
4. Without additional testing, the maximum output power for this is limited to the lower of the maximum output power certified for the two bands. When SAR measurement is required for at least one of the bands and the highest reported SAR adjusted by the ratio of specified maximum output power of aggregated to standalone band is  $> 1.2$  W/kg, SAR is required for the 160 MHz



channel. This procedure does not apply to an aggregated band with maximum output higher than the standalone band(s); the aggregated band must be tested independently for SAR. SAR is not required when the 160 MHz channel is operating at a reduced maximum power and also qualifies for SAR test exclusion.

#### **B) U-NII-2C and U-NII-3 Bands**

The frequency range covered by these bands is 380 MHz (5.47 – 5.85 GHz), which requires a minimum of at least two SAR probe calibration frequency points to support SAR measurements. When Terminal Doppler Weather Radar (TDWR) restriction applies, all channels that operate at 5.60 – 5.65 GHz must be included to apply the SAR test reduction and measurement procedures. When the same transmitter and antenna(s) are used for U-NII-2C band and U-NII-3 band or 5.8 GHz band of §15.247, the bands may be aggregated to enable additional channels with 20, 40 or 80 MHz bandwidth to span across the band gap, as illustrated in Appendix B. The maximum output power for the additional band gap channels is limited to the lower of those certified for the bands. Unless band gap channels are permanently disabled, they must be considered for SAR testing. The frequency range covered by these bands is 380 MHz (5.47 – 5.85 GHz), which requires a minimum of at least two SAR probe calibration frequency points to support SAR measurements. To maintain SAR measurement accuracy and to facilitate test reduction, the channels in U-NII-2C band above 5.65 GHz may be grouped with the 5.8 GHz channels in U-NII-3 or §15.247 band to enable two SAR probe calibration frequency points to cover the bands, including the band gap channels. When band gap channels are supported and the bands are not aggregated for SAR testing, band gap channels must be considered independently in each band according to the normally required OFDM SAR measurement and probe calibration frequency points requirements.

#### **C) OFDM Transmission Mode SAR Test Configuration and Channel Selection Requirements**

The initial test configuration for 5 GHz OFDM transmission modes is determined by the 802.11 configuration with the highest maximum output power specified for production units, including tune-up tolerance, in each standalone and aggregated frequency band. SAR for the initial test configuration is measured using the highest maximum output power channel determined by the default power measurement procedures. When multiple configurations in a frequency band have the same specified maximum output power, the initial test configuration is determined according to the following steps applied sequentially.

1. The largest channel bandwidth configuration is selected among the multiple configurations with the same specified maximum output power.
2. If multiple configurations have the same specified maximum output power and largest channel bandwidth, the lowest order modulation among the largest channel bandwidth configurations is selected.



3. If multiple configurations have the same specified maximum output power, largest channel band width and lowest order modulation, the lowest data rate configuration among these configurations is selected.
4. When multiple transmission modes (802.11a/g/n/ac) have the same specified maximum output power, largest channel bandwidth, lowest order modulation and lowest data rate, the lowest order 802.11 mode is selected; i.e., 802.11a is chosen over 802.11n then 802.11ac or 802.11g is chosen over 802.11n. After an initial test configuration is determined, if multiple test channels have the same measured maximum output power, the channel chosen for SAR measurement is determined according to the following. These channel selection procedures apply to both the initial test configuration and subsequent test configuration(s), with respect to the default power measurement procedures or additional power measurements required for further SAR test reduction. The same procedures also apply to subsequent highest output power channel(s) selection.
5. The channel closest to mid-band frequency is selected for SAR measurement.
6. For channels with equal separation from mid-band frequency; for example, high and low channels or two mid-band channels, the higher frequency (number) channel is selected for SAR measurement.

#### D) SAR Test Requirements for OFDM configurations

When SAR measurement is required for 802.11 a/n/ac OFDM configurations, each standalone and frequency aggregated band is considered separately for SAR test reduction. When the same transmitter and antenna(s) are used for U-NII-1 and U-NII-2A bands, additional SAR test reduction applies. When band gap channels between U-NII-2C band and 5.8 GHz U-NII-3 or §15.247 band are supported, the highest maximum output power transmission mode configuration and maximum output power channel across the bands must be used to determine SAR test reduction, according to the initial test configuration and subsequent test configuration requirements. In applying the initial test configuration and subsequent test configuration procedures, the 802.11 transmission configuration with the highest specified maximum output power and the channel within a test configuration with the highest measured maximum output power should be clearly distinguished to apply the procedures.

## 13. Conducted Power List

Remark: The output power was recorded in annex E of this report.

## 14. LTE Carrier Aggregation

### ➤ Carrier Aggregation Configuration

For the device supports bands and bandwidths and configurations are provided as follow table was according to 3GPP.

2CC Downlink Carrier Aggregation				
No.	Combination	MIMO	Restriction	Completely Covered by Measurement Superset
1	CA_2A-2A	2A	-	No
2	CA_4A-4A	4A	-	No
3	CA_5A-5A	5A	-	No

### ➤ LTE Downlink Carrier Aggregation Conducted Power

1. According to KDB941225 D05A v01r02, Uplink maximum output power measurement with downlink carrier aggregation active should be measured, using the highest output channel measured without downlink carrier aggregation, to confirm that uplink maximum output power with downlink carrier aggregation active remains within the specified tune-up tolerance limits and not more than  $\frac{1}{4}$  dB higher than the maximum output measured without downlink carrier aggregation active.
2. Uplink maximum output power with downlink carrier aggregation active does not show more than  $\frac{1}{4}$  dB higher than the maximum output power without downlink carrier aggregation active, therefore SAR evaluation with downlink carrier aggregation active can be excluded.
3. For power measurement were control and acknowledge data is sent on uplink channels that operate identical to specifications when downlink carrier aggregation is inactive.
4. Selected highest measured power when downlink carrier aggregation is inactive for conducted power comparison with downlink carrier aggregation is active, to confirm that when downlink carrier aggregation is active uplink maximum output power remains within the specified tune-up tolerance limits and not more than  $\frac{1}{4}$  dB higher than the maximum output power measured when downlink carrier aggregation inactive.
5. For non-contiguous intra-band CA, the SCC selected to provide maximum separation from the PCC and must remain fully within the downlink transmission band.
6. For Intra-band, contiguous CA, the downlink channels selected to perform the uplink power measurement must satisfy



7. 3GPP channel spacing (5.4.1A of 3GPP TS 36.521 or equivalent) and channel bandwidth (5.4.2A) requirements.

$$\text{Nominal channel spacing} = \left\lceil \frac{BW_{\text{Channel}(1)} + BW_{\text{Channel}(2)} - 0.1|BW_{\text{Channel}(1)} - BW_{\text{Channel}(2)}|}{0.6} \right\rceil 0.3 \text{ [MHz]}$$

8. The output power of CA downlink was recorded in annex E of this report.

## 15. 5G NR EN-DC Consideration

### ➤ General Guidance

1. It is limited to operate at EN-DC (NSA) for 5G NR implementation According to the character of the device. SAR measurement should be performed separately for the limitations of the probe calculation factors.
2. When the EN-DC is active the output power of the LTE anchors is equal or less than the standalone carrier, therefore the LTE output power and SAR were estimated based on the standalone carrier to performed sim-TX analysis with 5G NR, WLAN and Bluetooth.
3. According to October 2020 TCB Workshop publication, EN-DC SAR assessment should follow:
  - a. If the signal uplink 1-g SAR values for each band are both less than 0.8 W/kg and the algebraic summation of the 1-g SAR values are less than 1.45 W/kg no additional measurements need to be performed.
  - b. If one or the signal uplink 1-g SAR values is greater than 0.8 W/kg, instead of algebraically summing the 1-g SAR values, sum up the SAR distributions, similar to the enlarged zoom scan (volume scan) procedures found in FCC KDB Publication 865664 D01. And PAG is required for this case.
  - c. If the algebraic sum of the 1-g SAR values is > 1.45 W/kg additional measurements may have to be made. Submit a KDB inquiry for additional guidance and PAG is required for this case.
  - d. When the algebraic sum of the 1-g SAR values is > 1.6 W/kg, SPLSR analysis procedure should be applied.

### ➤ 5G NR Anchor Combination

5G-NR	EN-DC Combination	LTE Uplink	5G-NR Uplink	SCS (kHz)	Maximum Bandwidth (MHz)
FDD	2A-n41	2A	n41	30	100
FDD	2C-n41	-	-	30	100
FDD	66A-n41	66A	n41	30	100

#### Note:


The EN-DC combination of 2C-n41 only supports downlink transmission.

### ➤ Maximum Power for EN-DC

EN-DC Configuration	LTE Signal Carrier				5G NR		
	Band	BW (MHz)	Maximum Power(dBm)		Band	BW (MHz)	Maximum Power(dBm)
			Standalone	EN-DC Active			
EN-DC_2A-n41	2	20	12.0	25.5	n41	100	26.0
EN-DC_66A-n41	66	20	15.0	25.5	n41	100	26.0

## 16. Hotspot Mode Evaluation Procedure

### ➤ EUT Antenna Location

	
2/3/4G LB Tx: GSM: GSM 850 WCDMA(UMTS): V CDMA2000: BC0 LTE: Band 5/12/17/18/19/26	2/3/4G MHB Tx: GSM: GSM 1900 WCDMA(UMTS): II/IV CDMA2000: BC1 LTE: Band 2/4/7/38/40/41/66

### ➤ EUT Antenna Distance

Antenna Location	Front	Back	Left	Right	Top	Bottom
2/3/4G LB Tx	<5mm	<5mm	<25mm	<25mm	<5mm	>25mm
2/3/4G MHB, N1 Tx	<5mm	<5mm	>25mm	<5mm	<5mm	>25mm
N41/77 Tx/Rx	<5mm	<5mm	>25mm	<5mm	<25mm	>25mm
WIFI 2.4G/5G, BT CH0	<5mm	<5mm	>25mm	<5mm	<5mm	>25mm
WIFI 2.4G/5G, CH1	<5mm	<5mm	>25mm	<5mm	>25mm	>25mm

### ➤ Hotspot Evaluation

Assessment	Hotspot side for SAR Test distance: 10mm					
Antennas	Front	Back	Left	Right	Top	Bottom
2/3/4G LB Tx	Yes	Yes	Yes	Yes	Yes	No
2/3/4G MHB, N1 Tx	Yes	Yes	No	Yes	Yes	No
N41/77 Tx/Rx	Yes	Yes	No	Yes	Yes	No




WIFI 2.4G/5G, BT CH0	Yes	Yes	No	Yes	Yes	No
WIFI 2.4G/5G, CH1	Yes	Yes	No	Yes	No	No

**Note :**

1. The SAR evaluation procedures for Portable Devices with Wireless Router function is according to KDB 941225 D06 Hotspot SAR v02r01.
2. Head/Body-worn/Hotspot mode SAR assessments are required.
3. Referring to KDB 941225 D06, when the overall device length and width are  $\geq 9\text{cm} \times 5\text{cm}$ , the test distance is 10 mm. SAR must be measured for all sides and surfaces with a transmitting antenna located within 25mm from that surface or edge.
4. For WWAN, all of the sides and edges would be tested except the top side.

## 17. Block Diagram of the Tests to be Performed

### 17.1. Head



IEC 228/05

## 17.2. Body




Figure 12b – General procedure



## 18. Test Results List

### 18.1. Test Guidance

1. Per KDB 447498 D01v06, the reported SAR is the measured SAR value adjusted for maximum tune-up tolerance.
  - a. Tune-up scaling Factor = tune-up limit power (mW) / EUT RF power (mW), where tune-up limit is the maximum rated power among all production units.
  - b. For SAR testing of WLAN signal with non-100% duty cycle, the measured SAR is scaled-up by the duty cycle scaling factor which is equal to "1/(duty cycle)".
  - c. For WWAN: Reported SAR(W/kg)= Measured SAR(W/kg)\*Tune-up Scaling Factor.
  - d. For WLAN/Bluetooth: Reported SAR(W/kg)= Measured SAR(W/kg)\* Duty Cycle scaling factor \* Tune-up scaling factor.
2. Per KDB 447498 D01v06, for each exposure position, testing of other required channels within the operating mode of a frequency band is not required when the *reported* 1-g or 10-g SAR for the mid-band or highest output power channel is:
  - a.  $\leq 0.8 \text{ W/kg}$  or  $2.0 \text{ W/kg}$ , for 1-g or 10-g respectively, when the transmission band is  $\leq 100 \text{ MHz}$
  - b.  $\leq 0.6 \text{ W/kg}$  or  $1.5 \text{ W/kg}$ , for 1-g or 10-g respectively, when the transmission band is between  $100 \text{ MHz}$  and  $200 \text{ MHz}$
  - c.  $\leq 0.4 \text{ W/kg}$  or  $1.0 \text{ W/kg}$ , for 1-g or 10-g respectively, when the transmission band is  $\geq 200 \text{ MHz}$
3. Per KDB 865664 D01v01r04, for each frequency band, repeated SAR measurement is required only when the measured SAR is  $\geq 0.8 \text{ W/kg}$ .
4. Per KDB 648474 D04v01r03, when the reported SAR for a body-worn accessory measured without a headset connected to the handset is  $\leq 1.2 \text{ W/kg}$ , SAR testing with a headset connected to the handset is not required.
5. Per KDB648474 D04v01r03, for smart phones with a display diagonal dimension  $> 15.0 \text{ cm}$  or an overall diagonal dimension  $> 16.0 \text{ cm}$ , when hotspot mode applies, 10-g extremity SAR is required only for the surfaces and edges with hotspot mode 1-g reported SAR  $> 1.2 \text{ W/kg}$ , however, when power reduction applies to hotspot mode the measured SAR must be scaled to the maximum output power, including tolerance, allowed for tablet modes to compare with the  $1.2 \text{ W/kg}$  SAR test reduction threshold.
6. Per KDB248227 D01v02r02, a Wi-Fi device must be configured to transmit continuously at the required data rate, channel bandwidth and signal modulation, using the highest transmission duty factor supported by the test mode tools for SAR measurement. The test frequencies established using test mode must correspond to the actual channel frequencies required for operations in the U.S. When 802.11 frame gaps are accounted for in the transmission, a maximum transmission duty factor of 92 - 96% is typically achievable in most test mode configurations. A minimum transmission duty factor of 85% is required to avoid certain hardware and device implementation issues related to wide range SAR scaling. In addition, a periodic

transmission duty factor is required for current generation SAR systems to measure SAR correctly. Unless it is permitted by specific KDB procedures or continuous transmission is specifically restricted by the device, the reported SAR must be scaled to 100% transmission duty factor to determine compliance at the maximum tune-up tolerance limit. When a device is not capable of sustaining continuous transmission or the output can become nonlinear, and it is limited by hardware design and unable to transmit at higher than 85% duty factor, a periodic duty factor within 15% of the maximum duty factor the device is capable of transmitting should be used. The reported SAR must be scaled to the maximum transmission duty factor to determine compliance. Descriptions of the procedures applied to establish the specific duty factor used for SAR testing are required in SAR reports to support the test results.

7. When this device is proximity to human the sensor at the top side will be active automatically and the reduced power level 1 of WWAN applied.
8. The reduced power level 2 will be applied to EN-DC and simultaneous transmission.
9. The Power level condition applied should be follow:

Transmission Condition	Wireless System	Antenna	Head	Body & Extremity
Standalone	WWAN	Top	Reduced Power Level 1	Reduced Power Level 1
	WLAN	-	Full Power	Full Power

Transmission Condition	Wireless System	Antenna	Head	Body & Extremity
EN-DC & Simultaneous	LTE/5G NR	Top	Reduced Power Level 2	Reduced Power Level 2
	WCDMA II	Top	Reduced Power Level 2	Reduced Power Level 2
	WLAN	-	Reduced Power Level 2	Full Power

10. For TDD-LTE Band 40, the entire band is unable to be used that as per 27.5; only 2 paired block (2305 to 2315MHz, 2350 to 2360MHz) are allowed with regards to "TDD" operation. the channel allocation, and bandwidth covert to test channels shall be re-adjusted; furthermore, as per 27.50, the duty cycle must be adjusted that TDD in this band must not exceed 38%. Before testing, the special combination must be set in the base station before the periodic measurement can be carried out.
11. The 5G NR (NSA) SAR measurement procedure should be followed the TCB workshop publication in October 2020:
  - a. If the signal uplink 1-g SAR values for each band are both less than 0.8 W/kg and the algebraic summation of the 1-g SAR values are less than 1.45 W/kg no additional measurements need to be performed.
  - b. If one or the signal uplink 1-g SAR values is greater than 0.8 W/kg, instead of algebraically summing the 1-g SAR values, sum up the SAR distributions, similar to the enlarged zoom scan (volume scan) procedures found in FCC KDB Publication 865664 D01. And PAG is required for this case.



- c. If the algebraic sum of the 1-g SAR values is > 1.45 W/kg additional measurements may have to be made. Submit a KDB inquiry for additional guidance and PAG is required for this case.
- d. When the algebraic sum of the 1-g SAR values is > 1.6 W/kg, SPLSR analysis procedure should be applied.

12. The maximum radiated emission at 3m of NFC that was recorded in SZ21120450W06 which was converted to EIRP is closed to zero, therefore it is not required for RF exposure.



## 18.2. Head SAR Data

### ➤ GSM Head SAR

Plot No.	Band/Mode	Test Position	CH.	Ave. Power (dBm)	Tune-up Limit (dBm)	Tune-up Scaling Factor	Meas. SAR <sub>1g</sub> (W/kg)	Reported SAR <sub>1g</sub> (W/kg)
<b>Sensor on/Reduced Power Level 1</b>								
	GPRS 850(2 TX slots)	Right Cheek	128	30.11	31.00	1.227	0.464	0.570
	GPRS 850(2 TX slots)	Right Tilt	128	30.11	31.00	1.227	0.355	0.436
	GPRS 850(2 TX slots)	Left Cheek	128	30.11	31.00	1.227	0.654	0.803
	GPRS 850(2 TX slots)	Left Tilt	128	30.11	31.00	1.227	0.462	0.567
	GPRS 850(2 TX slots)	Left Cheek	189	30.06	31.00	1.242	0.608	0.755
1#	GPRS 850(2 TX slots)	Left Cheek	251	30.00	31.00	1.259	0.652	0.821
<b>Sensor on/Reduced Power Level 1</b>								
2#	GPRS 1900(2 TX slots)	Right Cheek	810	24.48	25.50	1.265	0.573	0.725
	GPRS 1900(2 TX slots)	Right Tilt	810	24.48	25.50	1.265	0.501	0.634
	GPRS 1900(2 TX slots)	Left Cheek	810	24.48	25.50	1.265	0.402	0.508
	GPRS 1900(2 TX slots)	Left Tilt	810	24.48	25.50	1.265	0.389	0.492

### ➤ WCDMA Head SAR

Plot No.	Band/Mode	Test Position	CH.	Ave. Power (dBm)	Tune-up Limit (dBm)	Tune-up Scaling Factor	Meas. SAR <sub>1g</sub> (W/kg)	Reported SAR <sub>1g</sub> (W/kg)
<b>Sensor on/Reduced Power Level 1</b>								
	Band II/RMC 12.2Kbps	Right Cheek	9538	17.06	18.00	1.242	0.657	0.816
	Band II/RMC 12.2Kbps	Right Tilt	9538	17.06	18.00	1.242	0.401	0.497
3#	Band II/RMC 12.2Kbps	Left Cheek	9538	17.06	18.00	1.242	0.800	0.993
	Band II/RMC 12.2Kbps	Left Tilt	9538	17.06	18.00	1.242	0.323	0.401
	Band II/RMC 12.2Kbps	Right Cheek	9262	16.90	18.00	1.288	0.578	0.745
	Band II/RMC 12.2Kbps	Right Cheek	9400	17.04	18.00	1.247	0.601	0.750
	Band II/RMC 12.2Kbps	Left Cheek	9262	16.90	18.00	1.288	0.606	0.780
	Band II/RMC 12.2Kbps	Left Cheek	9400	17.04	18.00	1.247	0.681	0.849
<b>Sensor on/Reduced Power Level 2 for Simultaneous Transmission</b>								
	Band II/RMC 12.2Kbps	Right Cheek	9538	15.04	16.00	1.247	0.157	0.196
	Band II/RMC 12.2Kbps	Right Tilt	9538	15.04	16.00	1.247	0.101	0.126
	Band II/RMC 12.2Kbps	Left Cheek	9538	15.04	16.00	1.247	0.201	0.251
	Band II/RMC 12.2Kbps	Left Tilt	9538	15.04	16.00	1.247	0.123	0.153
<b>Sensor on/Reduced Power Level 1</b>								
	Band IV/RMC 12.2Kbps	Right Cheek	1513	20.27	21.00	1.183	0.713	0.844



	Band IV/RMC 12.2Kbps	Right Tilt	1513	20.27	21.00	1.183	0.370	0.438
	Band IV/RMC 12.2Kbps	Left Cheek	1513	20.27	21.00	1.183	0.661	0.782
4#	Band IV/RMC 12.2Kbps	Left Tilt	1513	20.27	21.00	1.183	0.785	0.929
	Band IV/RMC 12.2Kbps	Right Cheek	1312	20.24	21.00	1.191	0.689	0.821
	Band IV/RMC 12.2Kbps	Right Cheek	1413	20.14	21.00	1.219	0.708	0.863
	Band IV/RMC 12.2Kbps	Left Tilt	1312	20.24	21.00	1.191	0.691	0.823
	Band IV/RMC 12.2Kbps	Left Tilt	1413	20.14	21.00	1.219	0.719	0.876

**Sensor on/Reduced Power Level 1**

	Band V/RMC 12.2Kbps	Right Cheek	4233	20.18	21.00	1.208	0.309	0.373
	Band V/RMC 12.2Kbps	Right Tilt	4233	20.18	21.00	1.208	0.282	0.341
5#	Band V/RMC 12.2Kbps	Left Cheek	4233	20.18	21.00	1.208	0.735	0.888
	Band V/RMC 12.2Kbps	Left Tilt	4233	20.18	21.00	1.208	0.628	0.759
	Band V/RMC 12.2Kbps	Left Cheek	4132	20.07	21.00	1.239	0.538	0.666
	Band V/RMC 12.2Kbps	Left Cheek	4182	20.06	21.00	1.242	0.590	0.733

**CDMA2000 Head SAR**

Plot No.	Band/Mode	Test Position	CH.	Ave. Power (dBm)	Tune-up Limit (dBm)	Tune-up Scaling Factor	Meas. SAR <sub>1g</sub> (W/kg)	Reported SAR <sub>1g</sub> (W/kg)
<b>Sensor off/Full Power</b>								
	BC0/RC3 SO32 (F+SCH)	Right Cheek	1013	23.79	24.50	1.178	0.221	0.260
	BC0/RC3 SO32 (F+SCH)	Right Tilt	1013	23.79	24.50	1.178	0.197	0.232
6#	BC0/RC3 SO32 (F+SCH)	Left Cheek	1013	23.79	24.50	1.178	0.331	0.390
	BC0/RC3 SO32 (F+SCH)	Left Tilt	1013	23.79	24.50	1.178	0.289	0.340
<b>Sensor on/Reduced Power Level 1</b>								
	BC1/RC3 SO32 (F+SCH)	Right Cheek	600	19.71	20.50	1.199	0.326	0.391
	BC1/RC3 SO32 (F+SCH)	Right Tilt	600	19.71	20.50	1.199	0.309	0.371
7#	BC1/RC3 SO32 (F+SCH)	Left Cheek	600	19.71	20.50	1.199	0.381	0.457
	BC1/RC3 SO32 (F+SCH)	Left Tilt	600	19.71	20.50	1.199	0.310	0.372

**LTE QPSK Head SAR**

Plot No.	Band/Mode	Test Position	CH.	Ave. Power (dBm)	Tune-up Limit (dBm)	Tune-up Scaling Factor	Meas. SAR <sub>1g</sub> (W/kg)	Reported SAR <sub>1g</sub> (W/kg)
<b>Sensor on/Reduced Power Level 1</b>								
8#	LTE Band 2/1RB#0 20M	Right Cheek	18900	18.01	19.00	1.256	0.694	0.872
	LTE Band 2/1RB#0 20M	Right Tilt	18900	18.01	19.00	1.256	0.452	0.568
	LTE Band 2/1RB#0 20M	Left Cheek	18900	18.01	19.00	1.256	0.592	0.744
	LTE Band 2/1RB#0 20M	Left Tilt	18900	18.01	19.00	1.256	0.541	0.680



	LTE Band 2/1RB#0 20M	Right Cheek	18700	17.97	19.00	1.268	0.620	0.786
	LTE Band 2/1RB#0 20M	Right Cheek	19100	17.96	19.00	1.271	0.667	0.847
	LTE Band 2/50RB#0 20M	Right Cheek	18900	17.10	18.00	1.230	0.647	0.796
	LTE Band 2/50RB#0 20M	Right Tilt	18900	17.10	18.00	1.230	0.425	0.523
	LTE Band 2/50RB#0 20M	Left Cheek	18900	17.10	18.00	1.230	0.534	0.657
	LTE Band 2/50RB#0 20M	Left Tilt	18900	17.10	18.00	1.230	0.501	0.616
	LTE Band 2/100RB#0 20M	Right Cheek	18900	16.95	18.00	1.274	0.512	0.652

**Sensor on/Reduced Power Level 2 for EN-DC & Simultaneous Transmission**

	LTE Band 2/1RB#0 20M	Right Cheek	18900	13.07	14.00	1.239	0.174	0.216
	LTE Band 2/1RB#0 20M	Right Tilt	18900	13.07	14.00	1.239	0.113	0.140
	LTE Band 2/1RB#0 20M	Left Cheek	18900	13.07	14.00	1.239	0.148	0.183
	LTE Band 2/1RB#0 20M	Left Tilt	18900	13.07	14.00	1.239	0.135	0.167
	LTE Band 2/50RB#0 20M	Right Cheek	18900	12.16	13.00	1.213	0.117	0.142
	LTE Band 2/50RB#0 20M	Right Tilt	18900	12.16	13.00	1.213	0.077	0.093
	LTE Band 2/50RB#0 20M	Left Cheek	18900	12.16	13.00	1.213	0.097	0.117
	LTE Band 2/50RB#0 20M	Left Tilt	18900	12.16	13.00	1.213	0.091	0.110

**Sensor on/Reduced Power Level 1**

9#	LTE Band 5/1RB#0 10M	Right Cheek	20525	20.14	21.00	1.219	0.309	0.377
	LTE Band 5/1RB#0 10M	Right Tilt	20525	20.14	21.00	1.219	0.271	0.330
	LTE Band 5/1RB#0 10M	Left Cheek	20525	20.14	21.00	1.219	0.305	0.372
	LTE Band 5/1RB#0 10M	Left Tilt	20525	20.14	21.00	1.219	0.268	0.327
	LTE Band 5/25RB#0 10M	Right Cheek	20525	19.19	20.00	1.205	0.226	0.272
	LTE Band 5/25RB#0 10M	Right Tilt	20525	19.19	20.00	1.205	0.198	0.238
	LTE Band 5/25RB#0 10M	Left Cheek	20525	19.19	20.00	1.205	0.223	0.268
	LTE Band 5/25RB#0 10M	Left Tilt	20525	19.19	20.00	1.205	0.196	0.236

**Sensor on/Reduced Power Level 1**

10#	LTE Band 7/1RB#0 20M	Right Cheek	21100	16.54	17.50	1.247	0.702	0.876
	LTE Band 7/1RB#0 20M	Right Tilt	21100	16.54	17.50	1.247	0.635	0.792
	LTE Band 7/1RB#0 20M	Left Cheek	21100	16.54	17.50	1.247	0.612	0.763
	LTE Band 7/1RB#0 20M	Left Tilt	21100	16.54	17.50	1.247	0.561	0.700
	LTE Band 7/1RB#0 20M	Right Cheek	20850	16.49	17.50	1.262	0.683	0.862
	LTE Band 7/1RB#0 20M	Right Cheek	21350	16.43	17.50	1.279	0.659	0.843
	LTE Band 7/50RB#0 20M	Right Cheek	21100	15.63	16.50	1.222	0.640	0.782
	LTE Band 7/50RB#0 20M	Right Tilt	21100	15.63	16.50	1.222	0.514	0.628
	LTE Band 7/50RB#0 20M	Left Cheek	21100	15.63	16.50	1.222	0.514	0.628
	LTE Band 7/50RB#0 20M	Left Tilt	21100	15.63	16.50	1.222	0.470	0.574
	LTE Band 7/100RB#0 20M	Right Cheek	21100	16.54	17.50	1.247	0.602	0.751

**Sensor on/Reduced Power Level 1**



	LTE Band 12/1RB#0 10M	Right Cheek	23095	20.24	21.00	1.191	0.260	0.310
	LTE Band 12/1RB#0 10M	Right Tilt	23095	20.24	21.00	1.191	0.257	0.306
11#	LTE Band 12/1RB#0 10M	Left Cheek	23095	20.24	21.00	1.191	0.301	0.359
	LTE Band 12/1RB#0 10M	Left Tilt	23095	20.24	21.00	1.191	0.278	0.331
	LTE Band 12/25RB#0 10M	Right Cheek	23095	19.11	20.00	1.227	0.213	0.262
	LTE Band 12/25RB#0 10M	Right Tilt	23095	19.11	20.00	1.227	0.211	0.259
	LTE Band 12/25RB#0 10M	Left Cheek	23095	19.11	20.00	1.227	0.247	0.303
	LTE Band 12/25RB#0 10M	Left Tilt	23095	19.11	20.00	1.227	0.228	0.280

**Sensor on/Reduced Power Level 1**

	LTE Band 18/1RB#0 15M	Right Cheek	23925	20.15	21.00	1.216	0.258	0.314
	LTE Band 18/1RB#0 15M	Right Tilt	23925	20.15	21.00	1.216	0.247	0.300
12#	LTE Band 18/1RB#0 15M	Left Cheek	23925	20.15	21.00	1.216	0.532	0.647
	LTE Band 18/1RB#0 15M	Left Tilt	23925	20.15	21.00	1.216	0.411	0.500
	LTE Band 18/36RB#0 15M	Right Cheek	23925	19.13	20.00	1.222	0.188	0.230
	LTE Band 18/36RB#0 15M	Right Tilt	23925	19.13	20.00	1.222	0.180	0.220
	LTE Band 18/36RB#0 15M	Left Cheek	23925	19.13	20.00	1.222	0.388	0.474
	LTE Band 18/36RB#0 15M	Left Tilt	23925	19.13	20.00	1.222	0.300	0.367

**Sensor on/Reduced Power Level 1**

	LTE Band 19/1RB#0 15M	Right Cheek	24075	20.16	21.00	1.213	0.294	0.357
	LTE Band 19/1RB#0 15M	Right Tilt	24075	20.16	21.00	1.213	0.287	0.348
13#	LTE Band 19/1RB#0 15M	Left Cheek	24075	20.16	21.00	1.213	0.597	0.724
	LTE Band 19/1RB#0 15M	Left Tilt	24075	20.16	21.00	1.213	0.476	0.578
	LTE Band 19/36RB#0 15M	Right Cheek	24075	19.15	20.00	1.216	0.218	0.265
	LTE Band 19/36RB#0 15M	Right Tilt	24075	19.15	20.00	1.216	0.212	0.258
	LTE Band 19/36RB#0 15M	Left Cheek	24075	19.15	20.00	1.216	0.442	0.537
	LTE Band 19/36RB#0 15M	Left Tilt	24075	19.15	20.00	1.216	0.352	0.428

**Sensor on/Reduced Power Level 1**

	LTE Band 26/1RB#0 15M	Right Cheek	26865	20.15	21.00	1.216	0.359	0.437
	LTE Band 26/1RB#0 15M	Right Tilt	26865	20.15	21.00	1.216	0.301	0.366
14#	LTE Band 26/1RB#0 15M	Left Cheek	26865	20.15	21.00	1.216	0.549	0.668
	LTE Band 26/1RB#0 15M	Left Tilt	26865	20.15	21.00	1.216	0.441	0.536
	LTE Band 26/1RB#0 15M	Right Cheek	26765	19.12	20.00	1.225	0.284	0.347
	LTE Band 26/36RB#0 15M	Right Tilt	26865	19.12	20.00	1.225	0.238	0.291
	LTE Band 26/36RB#0 15M	Left Cheek	26865	19.12	20.00	1.225	0.434	0.531
	LTE Band 26/36RB#0 15M	Left Tilt	26865	19.12	20.00	1.225	0.348	0.427

**Sensor on/Reduced Power Level 1**

15#	LTE Band 38/1RB#0 20M	Right Cheek	38000	20.33	21.00	1.167	0.678	0.796
	LTE Band 38/1RB#0 20M	Right Tilt	38000	20.33	21.00	1.167	0.494	0.580



	LTE Band 38/1RB#0 20M	Left Cheek	38000	20.33	21.00	1.167	0.371	0.435
	LTE Band 38/1RB#0 20M	Left Tilt	38000	20.33	21.00	1.167	0.451	0.529
	LTE Band 38/50RB#0 20M	Right Cheek	38000	19.12	20.00	1.225	0.505	0.622
	LTE Band 38/50RB#0 20M	Right Tilt	38000	19.12	20.00	1.225	0.362	0.446
	LTE Band 38/50RB#0 20M	Left Cheek	38000	19.12	20.00	1.225	0.332	0.409
	LTE Band 38/50RB#0 20M	Left Tilt	38000	19.12	20.00	1.225	0.274	0.338

**Sensor on/Reduced Power Level 1**

16#	LTE Band 40A/1RB#0 10M	Right Cheek	38750	20.14	21.00	1.219	0.715	0.877
	LTE Band 40A/1RB#0 10M	Right Tilt	38750	20.14	21.00	1.219	0.419	0.514
	LTE Band 40A/1RB#0 10M	Left Cheek	38750	20.14	21.00	1.219	0.380	0.466
	LTE Band 40A/1RB#0 10M	Left Tilt	38750	20.14	21.00	1.219	0.347	0.426
	LTE Band 40A/25RB#0 10M	Right Cheek	38750	19.05	20.00	1.245	0.508	0.636
	LTE Band 40A/25RB#0 10M	Right Tilt	38750	19.05	20.00	1.245	0.297	0.372
	LTE Band 40A/25RB#0 10M	Left Cheek	38750	19.05	20.00	1.245	0.270	0.338
	LTE Band 40A/25RB#0 10M	Left Tilt	38750	19.05	20.00	1.245	0.246	0.308
	LTE Band 40A/50RB#0 10M	Right Cheek	38750	18.87	21.00	1.633	0.515	0.846

**Sensor on/Reduced Power Level 1**

17#	LTE Band 40B/1RB#0 10M	Right Cheek	39200	20.11	21.00	1.227	0.680	0.840
	LTE Band 40B/1RB#0 10M	Right Tilt	39200	20.11	21.00	1.227	0.410	0.506
	LTE Band 40B/1RB#0 10M	Left Cheek	39200	20.11	21.00	1.227	0.399	0.493
	LTE Band 40B/1RB#0 10M	Left Tilt	39200	20.11	21.00	1.227	0.366	0.452
	LTE Band 40B/25RB#0 10M	Right Cheek	39200	19.05	20.00	1.245	0.517	0.647
	LTE Band 40B/25RB#0 10M	Right Tilt	39200	19.05	20.00	1.245	0.312	0.390
	LTE Band 40B/25RB#0 10M	Left Cheek	39200	19.05	20.00	1.245	0.303	0.380
	LTE Band 40B/25RB#0 10M	Left Tilt	39200	19.05	20.00	1.245	0.278	0.348
	LTE Band 40B/50RB#0 10M	Right Cheek	39200	18.87	20.00	1.297	0.518	0.676

**Sensor on/Reduced Power Level 1**

18#	LTE Band 41/1RB#0 20M	Right Cheek	40620	20.26	21.00	1.186	0.641	0.765
	LTE Band 41/1RB#0 20M	Right Tilt	40620	20.26	21.00	1.186	0.485	0.579
	LTE Band 41/1RB#0 20M	Left Cheek	40620	20.26	21.00	1.186	0.367	0.438
	LTE Band 41/1RB#0 20M	Left Tilt	40620	20.26	21.00	1.186	0.469	0.559
	LTE Band 41/50RB#0 20M	Right Cheek	40620	19.23	20.00	1.194	0.462	0.554
	LTE Band 41/50RB#0 20M	Right Tilt	40620	19.23	20.00	1.194	0.349	0.419
	LTE Band 41/50RB#0 20M	Left Cheek	40620	19.23	20.00	1.194	0.264	0.317
	LTE Band 41/50RB#0 20M	Left Tilt	40620	19.23	20.00	1.194	0.338	0.406

**Sensor on/Reduced Power Level 1**

19#	LTE Band 66/1RB#0 20M	Right Cheek	132322	18.27	19.00	1.183	0.548	0.648
	LTE Band 66/1RB#0 20M	Right Tilt	132322	18.27	19.00	1.183	0.309	0.366



REPORT No.: SZ21120450S01

	LTE Band 66/1RB#0 20M	Left Cheek	132322	18.27	19.00	1.183	0.462	0.547
	LTE Band 66/1RB#0 20M	Left Tilt	132322	18.27	19.00	1.183	0.545	0.645
	LTE Band 66/50RB#0 20M	Right Cheek	132322	17.04	18.00	1.247	0.416	0.520
	LTE Band 66/50RB#0 20M	Right Tilt	132322	17.04	18.00	1.247	0.235	0.293
	LTE Band 66/50RB#0 20M	Left Cheek	132322	17.04	18.00	1.247	0.351	0.438
	LTE Band 66/50RB#0 20M	Left Tilt	132322	17.04	18.00	1.247	0.414	0.517

**Sensor on/Reduced Power Level 2 for EN-DC & Simultaneous Transmission**

	LTE Band 66/1RB#0 20M	Right Cheek	132322	15.24	16.00	1.191	0.269	0.320
	LTE Band 66/1RB#0 20M	Right Tilt	132322	15.24	16.00	1.191	0.151	0.180
	LTE Band 66/1RB#0 20M	Left Cheek	132322	15.24	16.00	1.191	0.226	0.270
	LTE Band 66/1RB#0 20M	Left Tilt	132322	15.24	16.00	1.191	0.205	0.244
	LTE Band 66/50RB#0 20M	Right Cheek	132322	14.01	15.00	1.256	0.167	0.209
	LTE Band 66/50RB#0 20M	Right Tilt	132322	14.01	15.00	1.256	0.094	0.118
	LTE Band 66/50RB#0 20M	Left Cheek	132322	14.01	15.00	1.256	0.140	0.176
	LTE Band 66/50RB#0 20M	Left Tilt	132322	14.01	15.00	1.256	0.116	0.146

**➤ 5G NR DFT-s-QPSK Head SAR**

Plot No.	Band/Mode	Test Position	CH.	Ave. Power (dBm)	Tune-up Limit (dBm)	Tune-up Scaling Factor	Meas. SAR <sub>1g</sub> (W/kg)	Reported SAR <sub>1g</sub> (W/kg)
<b>Sensor on/Reduced Power Level 1</b>								
	5G NR n41/1RB#1 100M	Right Cheek	518598	17.48	18.00	1.127	0.752	0.848
	5G NR n41/1RB#1 100M	Right Tilt	518598	17.48	18.00	1.127	0.633	0.714
	5G NR n41/1RB#1 100M	Left Cheek	518598	17.48	18.00	1.127	0.619	0.698
	5G NR n41/1RB#1 100M	Left Tilt	518598	17.48	18.00	1.127	0.601	0.677
20#	5G NR n41/1RB#1 100M	Right Cheek	509202	17.41	18.00	1.146	0.842	0.965
	5G NR n41/1RB#1 100M	Right Cheek	513900	17.38	18.00	1.153	0.758	0.874
	5G NR n41/1RB#1 100M	Right Cheek	523300	17.32	18.00	1.169	0.475	0.555
	5G NR n41/1RB#1 100M	Right Cheek	528000	17.41	18.00	1.146	0.509	0.583
	5G NR n41/135RB#1 100M	Right Cheek	518598	17.18	18.00	1.208	0.693	0.837
	5G NR n41/135RB#1 100M	Right Tilt	518598	17.18	18.00	1.208	0.633	0.765
	5G NR n41/135RB#1 100M	Left Cheek	518598	17.18	18.00	1.208	0.612	0.739
	5G NR n41/135RB#1 100M	Left Tilt	518598	17.18	18.00	1.208	0.566	0.684
	5G NR n41/135RB#1 100M	Right Cheek	509202	17.01	18.00	1.256	0.731	0.918
	5G NR n41/135RB#1 100M	Right Cheek	513900	16.99	18.00	1.262	0.634	0.800
	5G NR n41/135RB#1 100M	Right Cheek	523300	17.13	18.00	1.222	0.406	0.496
	5G NR n41/135RB#1 100M	Right Cheek	528000	17.09	18.00	1.233	0.464	0.572
	5G NR n41/270RB#1 100M	Right Cheek	518598	17.17	18.00	1.211	0.652	0.789
<b>Sensor on/Reduced Power Level 2 for EN-DC &amp; Simultaneous Transmission</b>								

**MORLAB**

Shenzhen Morlab Communications Technology Co., Ltd.  
FL1-3, Building A, FeiYang Science Park, No.8 LongChang Road,  
Block67, BaoAn District, ShenZhen , GuangDong Province, P. R. China

Tel: 86-755-36698555      Fax: 86-755-36698525  
Http://www.morlab.cn      E-mail: service@morlab.cn



	5G NR n41/1RB#1 100M	Right Cheek	518598	11.48	12.00	1.127	0.562	0.633
	5G NR n41/1RB#1 100M	Right Tilt	518598	11.48	12.00	1.127	0.423	0.477
	5G NR n41/1RB#1 100M	Left Cheek	518598	11.48	12.00	1.127	0.414	0.466
	5G NR n41/1RB#1 100M	Left Tilt	518598	11.48	12.00	1.127	0.402	0.453
	5G NR n41/135RB#1 100M	Right Cheek	518598	11.18	12.00	1.208	0.463	0.559
	5G NR n41/135RB#1 100M	Right Tilt	518598	11.18	12.00	1.208	0.423	0.511
	5G NR n41/135RB#1 100M	Left Cheek	518598	11.18	12.00	1.208	0.409	0.494
	5G NR n41/135RB#1 100M	Left Tilt	518598	11.18	12.00	1.208	0.378	0.457

**Sensor on/Reduced Power Level 1**

	5G NR n77/1RB#1 100M	Right Cheek	656000	19.26	20.00	1.186	0.701	0.831
	5G NR n77/1RB#1 100M	Right Tilt	656000	19.26	20.00	1.186	0.654	0.775
	5G NR n77/1RB#1 100M	Left Cheek	656000	19.26	20.00	1.186	0.668	0.792
	5G NR n77/1RB#1 100M	Left Tilt	656000	19.26	20.00	1.186	0.601	0.713
	5G NR n77/1RB#1 100M	Right Cheek	650000	18.98	20.00	1.265	0.516	0.652
	5G NR n77/1RB#1 100M	Right Cheek	653000	18.82	20.00	1.312	0.582	0.763
	5G NR n77/1RB#1 100M	Right Cheek	659000	18.97	20.00	1.268	0.648	0.822
21#	5G NR n77/1RB#1 100M	Right Cheek	662000	19.15	20.00	1.216	0.788	0.958
	5G NR n77/135RB#1 100M	Right Cheek	656000	19.08	20.00	1.236	0.662	0.818
	5G NR n77/135RB#1 100M	Right Tilt	656000	19.08	20.00	1.236	0.641	0.792
	5G NR n77/135RB#1 100M	Left Cheek	656000	19.08	20.00	1.236	0.636	0.786
	5G NR n77/135RB#1 100M	Left Tilt	656000	19.08	20.00	1.236	0.565	0.698
	5G NR n77/135RB#1 100M	Right Cheek	650000	19.07	20.00	1.239	0.491	0.608
	5G NR n77/135RB#1 100M	Right Cheek	653000	19.01	20.00	1.256	0.556	0.698
	5G NR n77/135RB#1 100M	Right Cheek	659000	18.97	20.00	1.268	0.622	0.788
	5G NR n77/135RB#1 100M	Right Cheek	662000	19.00	20.00	1.259	0.742	0.934
	5G NR n77/270RB#1 100M	Right Cheek	656000	18.80	20.00	1.318	0.501	0.660

**➤ WLAN Head SAR**

Plot No.	Band/Mode	Test Position	CH.	Ave. Power (dBm)	Tune-up Limit (dBm)	Tune-up Scaling Factor	Meas. SAR <sub>1g</sub> (W/kg)	Reported SAR <sub>1g</sub> (W/kg)
<b>Full Power for CH0</b>								
	WLAN2.4GHz/802.11b	Right Cheek	1	15.67	16.00	1.079	0.182	0.198
	WLAN2.4GHz/802.11b	Right Tilt	1	15.67	16.00	1.079	0.251	0.273
	WLAN2.4GHz/802.11b	Left Cheek	1	15.67	16.00	1.079	0.442	0.481
	WLAN2.4GHz/802.11b	Left Tilt	1	15.67	16.00	1.079	0.507	0.552
<b>Reduced Power Level 2 for CH0 Simultaneous Transmission</b>								
	WLAN2.4GHz/802.11b	Right Cheek	1	12.67	13.50	1.211	0.084	0.102
	WLAN2.4GHz/802.11b	Right Tilt	1	12.67	13.50	1.211	0.115	0.141



	WLAN2.4GHz/802.11b	Left Cheek	1	12.67	13.50	1.211	0.203	0.248
	WLAN2.4GHz/802.11b	Left Tilt	1	12.67	13.50	1.211	0.233	0.285
<b>Full Power for CH1</b>								
	WLAN2.4GHz/802.11b	Right Cheek	6	15.52	16.00	1.117	0.133	0.150
	WLAN2.4GHz/802.11b	Right Tilt	6	15.52	16.00	1.117	0.086	0.097
22#	WLAN2.4GHz/802.11b	Left Cheek	6	15.52	16.00	1.117	0.508	0.572
	WLAN2.4GHz/802.11b	Left Tilt	6	15.52	16.00	1.117	0.200	0.225
<b>Reduced Power Level 2 for CH1 Simultaneous Transmission</b>								
	WLAN2.4GHz/802.11b	Right Cheek	6	11.52	12.00	1.117	0.103	0.116
	WLAN2.4GHz/802.11b	Right Tilt	6	11.52	12.00	1.117	0.076	0.086
	WLAN2.4GHz/802.11b	Left Cheek	6	11.52	12.00	1.117	0.298	0.336
	WLAN2.4GHz/802.11b	Left Tilt	6	11.52	12.00	1.117	0.189	0.213
<b>Full Power for CH0</b>								
	WLAN5.2GHz/802.11n40	Right Cheek	38	12.98	13.50	1.127	0.139	0.158
	WLAN5.2GHz/802.11n40	Right Tilt	38	12.98	13.50	1.127	0.064	0.073
	WLAN5.2GHz/802.11n40	Left Cheek	38	12.98	13.50	1.127	0.134	0.153
	WLAN5.2GHz/802.11n40	Left Tilt	38	12.98	13.50	1.127	0.142	0.162
<b>Full Power for CH1</b>								
	WLAN5.2GHz/802.11n40	Right Cheek	46	12.31	13.00	1.172	0.192	0.227
	WLAN5.2GHz/802.11n40	Right Tilt	46	12.31	13.00	1.172	0.181	0.214
23#	WLAN5.2GHz/802.11n40	Left Cheek	46	12.31	13.00	1.172	0.219	0.259
	WLAN5.2GHz/802.11n40	Left Tilt	46	12.31	13.00	1.172	0.174	0.206
<b>Full Power for CH0</b>								
	WLAN5.3GHz/802.11a	Right Cheek	60	12.27	13.00	1.183	0.180	0.215
	WLAN5.3GHz/802.11a	Right Tilt	60	12.27	13.00	1.183	0.161	0.192
	WLAN5.3GHz/802.11a	Left Cheek	60	12.27	13.00	1.183	0.197	0.235
	WLAN5.3GHz/802.11a	Left Tilt	60	12.27	13.00	1.183	0.201	0.240
<b>Full Power for CH1</b>								
	WLAN5.3GHz/802.11n40	Right Cheek	62	12.81	13.50	1.172	0.258	0.305
	WLAN5.3GHz/802.11n40	Right Tilt	62	12.81	13.50	1.172	0.246	0.291
24#	WLAN5.3GHz/802.11n40	Left Cheek	62	12.81	13.50	1.172	0.289	0.342
	WLAN5.3GHz/802.11n40	Left Tilt	62	12.81	13.50	1.172	0.251	0.297
<b>Full Power for CH0</b>								
	WLAN5.5GHz/802.11n40	Right Cheek	102	13.03	13.50	1.114	0.163	0.183
	WLAN5.5GHz/802.11n40	Right Tilt	102	13.03	13.50	1.114	0.153	0.172
	WLAN5.5GHz/802.11n40	Left Cheek	102	13.03	13.50	1.114	0.249	0.281
	WLAN5.5GHz/802.11n40	Left Tilt	102	13.03	13.50	1.114	0.312	0.351
<b>Reduced Power Level 2 for CH0 Simultaneous Transmission</b>								



	WLAN5.5GHz/802.11n40	Right Cheek	102	12.03	12.50	1.114	0.105	0.118
	WLAN5.5GHz/802.11n40	Right Tilt	102	12.03	12.50	1.114	0.099	0.111
	WLAN5.5GHz/802.11n40	Left Cheek	102	12.03	12.50	1.114	0.161	0.181
	WLAN5.5GHz/802.11n40	Left Tilt	102	12.03	12.50	1.114	0.202	0.227

**Full Power for CH1**

	WLAN5.5GHz/802.11n20	Right Cheek	120	12.66	13.00	1.081	0.371	0.406
	WLAN5.5GHz/802.11n20	Right Tilt	120	12.66	13.00	1.081	0.358	0.391
25#	WLAN5.5GHz/802.11n20	Left Cheek	120	12.66	13.00	1.081	0.410	0.448
	WLAN5.5GHz/802.11n20	Left Tilt	120	12.66	13.00	1.081	0.219	0.239

**Reduced Power Level 2 for CH1 Simultaneous Transmission**

	WLAN5.5GHz/802.11n20	Right Cheek	120	10.66	11.00	1.081	0.275	0.300
	WLAN5.5GHz/802.11n20	Right Tilt	120	10.66	11.00	1.081	0.265	0.290
	WLAN5.5GHz/802.11n20	Left Cheek	120	10.66	11.00	1.081	0.302	0.330
	WLAN5.5GHz/802.11n20	Left Tilt	120	10.66	11.00	1.081	0.162	0.177

**Full Power for CH0**

	WLAN5.8GHz/802.11n40	Right Cheek	151	13.06	13.50	1.107	0.368	0.412
	WLAN5.8GHz/802.11n40	Right Tilt	151	13.06	13.50	1.107	0.298	0.333
	WLAN5.8GHz/802.11n40	Left Cheek	151	13.06	13.50	1.107	0.417	0.466
26#	WLAN5.8GHz/802.11n40	Left Tilt	151	13.06	13.50	1.107	0.507	0.567

**Reduced Power Level 2 for CH0 Simultaneous Transmission**

	WLAN5.8GHz/802.11n40	Right Cheek	151	12.06	12.50	1.107	0.173	0.193
	WLAN5.8GHz/802.11n40	Right Tilt	151	12.06	12.50	1.107	0.140	0.156
	WLAN5.8GHz/802.11n40	Left Cheek	151	12.06	12.50	1.107	0.181	0.202
	WLAN5.8GHz/802.11n40	Left Tilt	151	12.06	12.50	1.107	0.221	0.247

**Full Power for CH1**

	WLAN5.8GHz/802.11a	Right Cheek	149	12.05	12.50	1.109	0.301	0.337
	WLAN5.8GHz/802.11a	Right Tilt	149	12.05	12.50	1.109	0.289	0.323
	WLAN5.8GHz/802.11a	Left Cheek	149	12.05	12.50	1.109	0.316	0.354
	WLAN5.8GHz/802.11a	Left Tilt	149	12.05	12.50	1.109	0.162	0.181

**Note:**

1. Per KDB 447498 D01v06, for each exposure position, if the highest output power channel Reported SAR  $\leq 0.8\text{W/kg}$ , other channels SAR testing is not necessary.
2. Per KDB 865664 D01v01r04, for each frequency band, repeated SAR measurement is required when the measured SAR is  $\geq 0.8\text{W/kg}$ .
3. Per KDB 941225 D05v02r05, 100% RB allocation SAR measurement is not required when the highest reported SAR for 1 RB and 50% RB allocation are  $\leq 0.8\text{ W/kg}$ .
4. Per KDB 248227 D01v02r02, for 802.11b DSSS, when the reported SAR of the highest measured maximum output power channel for the exposure configuration is  $\leq 0.8\text{ W/kg}$ , no



further SAR testing is required in that exposure configuration.

5. Per KDB 248227 D01v02r02, OFDM SAR is not required when the highest reported SAR for DSSS is adjusted by the ratio of OFDM to DSSS specified maximum output power and the adjusted SAR is  $\leq 1.2$  W/kg.
6. According to KDB 865664 D02v01r02, SAR plot is required for the highest measured SAR in each exposure configuration, wireless mode and frequency band combination.
7. For TDD-LTE, the reported SAR should be scaled with the duty cycle scaling factor 1.006.
8. The 2.4G WLAN reported 1g SAR (W/kg) should be scaled with the duty cycle scaling factor 1.009, 5G WLAN 802.11a with 1.009, 802.11n20 with 1.011 and 802.11n40 with 1.01.

### 18.3. Body SAR Data

#### ➤ GSM Body SAR

Plot No.	Band/Mode	Test Position	CH.	Ave. Power (dBm)	Tune-up Limit (dBm)	Tune-up Scaling Factor	Meas. SAR <sub>1g</sub> (W/kg)	Reported SAR <sub>1g</sub> (W/kg)
<b>Sensor on/Reduced Power Level 1</b>								
	GPRS 850(2 TX slots)	Front Side	128	30.11	31.00	1.227	0.201	0.247
27#	GPRS 850(2 TX slots)	Back Side	128	30.11	31.00	1.227	0.221	0.271
	GPRS 850(2 TX slots)	Left Side	128	30.11	31.00	1.227	0.147	0.180
	GPRS 850(2 TX slots)	Right Side	128	30.11	31.00	1.227	0.100	0.122
	GPRS 850(2 TX slots)	Top Side	128	30.11	31.00	1.227	0.188	0.231
<b>Sensor on/Reduced Power Level 1</b>								
	GPRS 1900(2 TX slots)	Front Side	810	24.48	25.50	1.265	0.114	0.144
28#	GPRS 1900(2 TX slots)	Back Side	810	24.48	25.50	1.265	0.134	0.169
	GPRS 1900(2 TX slots)	Left Side	810	24.48	25.50	1.265	0.111	0.140
	GPRS 1900(2 TX slots)	Right Side	810	24.48	25.50	1.265	0.100	0.126
29#	GPRS 1900(2 TX slots)	Top Side	810	24.48	25.50	1.265	0.460	0.582

#### ➤ WCDMA Body SAR

Plot No.	Band/Mode	Test Position	CH.	Ave. Power (dBm)	Tune-up Limit (dBm)	Tune-up Scaling Factor	Meas. SAR <sub>1g</sub> (W/kg)	Reported SAR <sub>1g</sub> (W/kg)
<b>Sensor on/Reduced Power Level 1</b>								
	Band II/RMC 12.2Kbps	Front Side	9538	17.06	18.00	1.242	0.215	0.267
30#	Band II/RMC 12.2Kbps	Back Side	9538	17.06	18.00	1.242	0.379	0.471
	Band II/RMC 12.2Kbps	Left Side	9538	17.06	18.00	1.242	0.179	0.222
	Band II/RMC 12.2Kbps	Right Side	9538	17.06	18.00	1.242	0.100	0.124
31#	Band II/RMC 12.2Kbps	Top Side	9538	17.06	18.00	1.242	0.883	1.096



	Band II/RMC 12.2Kbps	Top Side	9400	16.90	18.00	1.288	0.779	1.004
	Band II/RMC 12.2Kbps	Top Side	9262	17.04	18.00	1.247	0.637	0.795
<b>Sensor on/Reduced Power Level 2 for Simultaneous Transmission</b>								
	Band II/RMC 12.2Kbps	Front Side	9538	15.04	16.00	1.247	0.042	0.053
	Band II/RMC 12.2Kbps	Back Side	9538	15.04	16.00	1.247	0.075	0.093
	Band II/RMC 12.2Kbps	Left Side	9538	15.04	16.00	1.247	0.035	0.044
	Band II/RMC 12.2Kbps	Right Side	9538	15.04	16.00	1.247	0.020	0.025
	Band II/RMC 12.2Kbps	Top Side	9538	15.04	16.00	1.247	0.174	0.217
<b>Sensor on/Reduced Power Level 1</b>								
	Band IV/RMC 12.2Kbps	Front Side	1513	20.27	21.00	1.183	0.266	0.315
32#	Band IV/RMC 12.2Kbps	Back Side	1513	20.27	21.00	1.183	0.312	0.369
	Band IV/RMC 12.2Kbps	Left Side	1513	20.27	21.00	1.183	0.178	0.211
	Band IV/RMC 12.2Kbps	Right Side	1513	20.27	21.00	1.183	0.131	0.155
33#	Band IV/RMC 12.2Kbps	Top Side	1513	20.27	21.00	1.183	0.596	0.705
<b>Sensor on/Reduced Power Level 1</b>								
	Band V/RMC 12.2Kbps	Front Side	4233	20.18	21.00	1.208	0.164	0.198
34#	Band V/RMC 12.2Kbps	Back Side	4233	20.18	21.00	1.208	0.186	0.225
	Band V/RMC 12.2Kbps	Left Side	4233	20.18	21.00	1.208	0.161	0.194
	Band V/RMC 12.2Kbps	Right Side	4233	20.18	21.00	1.208	0.064	0.077
	Band V/RMC 12.2Kbps	Top Side	4182	20.18	21.00	1.208	0.181	0.219

#### ➤ CDMA2000 Body SAR

Plot No.	Band/Mode	Test Position	CH.	Ave. Power (dBm)	Tune-up Limit (dBm)	Tune-up Scaling Factor	Meas. SAR <sub>1g</sub> (W/kg)	Reported SAR <sub>1g</sub> (W/kg)
<b>Sensor off/Full Power</b>								
35#	BC0/RC3 SO32 (F+SCH)	Front Side	1013	23.79	24.50	1.178	0.231	0.272
	BC0/RC3 SO32 (F+SCH)	Back Side	1013	23.79	24.50	1.178	0.230	0.271
<b>Sensor on/Reduced Power Level 1</b>								
	BC1/RC3 SO32 (F+SCH)	Front Side	600	19.71	20.50	1.199	0.680	0.816
	BC1/RC3 SO32 (F+SCH)	Back Side	600	19.71	20.50	1.199	0.570	0.684
	BC1/RC3 SO32 (F+SCH)	Front Side	25	19.56	20.50	1.242	0.627	0.779
36#	BC1/RC3 SO32 (F+SCH)	Front Side	1175	19.64	20.50	1.219	0.675	0.823



## ➤ LTE QPSK Body SAR

Plot No.	Band/Mode	Test Position	CH.	Ave. Power (dBm)	Tune-up Limit (dBm)	Tune-up Scaling Factor	Meas. SAR <sub>1g</sub> (W/kg)	Reported SAR <sub>1g</sub> (W/kg)
<b>Sensor on/Reduced Power Level 1</b>								
	LTE Band 2/1RB#0 20M	Front Side	18900	18.01	19.00	1.256	0.304	0.382
37#	LTE Band 2/1RB#0 20M	Back Side	18900	18.01	19.00	1.256	0.390	0.490
	LTE Band 2/1RB#0 20M	Left Side	18900	18.01	19.00	1.256	0.224	0.281
	LTE Band 2/1RB#0 20M	Right Side	18900	18.01	19.00	1.256	0.124	0.156
38#	LTE Band 2/1RB#0 20M	Top Side	18900	18.01	19.00	1.256	0.755	0.948
	LTE Band 2/1RB#0 20M	Top Side	18700	17.97	19.00	1.268	0.576	0.730
	LTE Band 2/1RB#0 20M	Top Side	19100	17.96	19.00	1.271	0.703	0.893
	LTE Band 2/50RB#0 20M	Front Side	18900	17.10	18.00	1.230	0.234	0.288
	LTE Band 2/50RB#0 20M	Back Side	18900	17.10	18.00	1.230	0.337	0.415
	LTE Band 2/50RB#0 20M	Left Side	18900	17.10	18.00	1.230	0.181	0.223
	LTE Band 2/50RB#0 20M	Right Side	18900	17.10	18.00	1.230	0.103	0.127
	LTE Band 2/50RB#0 20M	Top Side	18900	17.10	18.00	1.230	0.641	0.789
<b>Sensor on/Reduced Power Level 2 for Simultaneous Transmission</b>								
	LTE Band 2/1RB#0 20M	Front Side	18900	15.05	16.00	1.245	0.085	0.106
	LTE Band 2/1RB#0 20M	Back Side	18900	15.05	16.00	1.245	0.101	0.126
	LTE Band 2/1RB#0 20M	Left Side	18900	15.05	16.00	1.245	0.071	0.088
	LTE Band 2/1RB#0 20M	Right Side	18900	15.05	16.00	1.245	0.053	0.065
	LTE Band 2/1RB#0 20M	Top Side	18900	15.05	16.00	1.245	0.137	0.170
	LTE Band 2/50RB#0 20M	Front Side	18900	14.14	15.00	1.219	0.073	0.088
	LTE Band 2/50RB#0 20M	Back Side	18900	14.14	15.00	1.219	0.091	0.111
	LTE Band 2/50RB#0 20M	Left Side	18900	14.14	15.00	1.219	0.063	0.077
	LTE Band 2/50RB#0 20M	Right Side	18900	14.14	15.00	1.219	0.049	0.059
	LTE Band 2/50RB#0 20M	Top Side	18900	14.14	15.00	1.219	0.117	0.142
<b>Sensor on/Reduced Power Level 1</b>								
	LTE Band 5/1RB#0 10M	Front Side	20525	20.14	21.00	1.219	0.106	0.129
39#	LTE Band 5/1RB#0 10M	Back Side	20525	20.14	21.00	1.219	0.161	0.196
	LTE Band 5/1RB#0 10M	Left Side	20525	20.14	21.00	1.219	0.071	0.087
	LTE Band 5/1RB#0 10M	Right Side	20525	20.14	21.00	1.219	0.057	0.069
	LTE Band 5/1RB#0 10M	Top Side	20525	20.14	21.00	1.219	0.150	0.183
	LTE Band 5/25RB#0 10M	Front Side	20525	19.19	20.00	1.205	0.097	0.117
	LTE Band 5/25RB#0 10M	Back Side	20525	19.19	20.00	1.205	0.135	0.163
	LTE Band 5/25RB#0 10M	Left Side	20525	19.19	20.00	1.205	0.060	0.072
	LTE Band 5/25RB#0 10M	Right Side	20525	19.19	20.00	1.205	0.047	0.057
	LTE Band 5/25RB#0 10M	Top Side	20525	19.19	20.00	1.205	0.123	0.148



Sensor on/Reduced Power Level 1								
	LTE Band 7/1RB#0 10M	Front Side	21100	16.54	17.50	1.247	0.482	0.601
40#	LTE Band 7/1RB#0 10M	Back Side	21100	16.54	17.50	1.247	0.512	0.639
	LTE Band 7/1RB#0 10M	Left Side	21100	16.54	17.50	1.247	0.322	0.402
	LTE Band 7/1RB#0 10M	Right Side	21100	16.54	17.50	1.247	0.102	0.127
41#	LTE Band 7/1RB#0 10M	Top Side	21100	16.54	17.50	1.247	0.640	0.798
	LTE Band 7/50RB#0 10M	Front Side	21100	15.63	16.50	1.222	0.440	0.538
	LTE Band 7/50RB#0 10M	Back Side	21100	15.63	16.50	1.222	0.425	0.519
	LTE Band 7/50RB#0 10M	Left Side	21100	15.63	16.50	1.222	0.271	0.331
	LTE Band 7/50RB#0 10M	Right Side	21100	15.63	16.50	1.222	0.083	0.101
	LTE Band 7/50RB#0 10M	Top Side	21100	15.63	16.50	1.222	0.519	0.634
Sensor on/Reduced Power Level 1								
	LTE Band 12/1RB#0 10M	Front Side	23095	20.24	21.00	1.191	0.118	0.141
42#	LTE Band 12/1RB#0 10M	Back Side	23095	20.24	21.00	1.191	0.151	0.180
	LTE Band 12/1RB#0 10M	Left Side	23095	20.24	21.00	1.191	0.096	0.114
	LTE Band 12/1RB#0 10M	Right Side	23095	20.24	21.00	1.191	0.076	0.091
43#	LTE Band 12/1RB#0 10M	Top Side	23095	20.24	21.00	1.191	0.193	0.230
	LTE Band 12/25RB#0 10M	Front Side	23095	19.11	20.00	1.227	0.112	0.137
	LTE Band 12/25RB#0 10M	Back Side	23095	19.11	20.00	1.227	0.122	0.150
	LTE Band 12/25RB#0 10M	Left Side	23095	19.11	20.00	1.227	0.080	0.098
	LTE Band 12/25RB#0 10M	Right Side	23095	19.11	20.00	1.227	0.064	0.079
	LTE Band 12/25RB#0 10M	Top Side	23095	19.11	20.00	1.227	0.162	0.199
Sensor on/Reduced Power Level 1								
	LTE Band 18/1RB#0 15M	Front Side	23925	20.15	21.00	1.216	0.082	0.099
44#	LTE Band 18/1RB#0 15M	Back Side	23925	20.15	21.00	1.216	0.114	0.139
	LTE Band 18/1RB#0 15M	Left Side	23925	20.15	21.00	1.216	0.061	0.074
	LTE Band 18/1RB#0 15M	Right Side	23925	20.15	21.00	1.216	0.059	0.072
45#	LTE Band 18/1RB#0 15M	Top Side	23925	20.15	21.00	1.216	0.119	0.145
	LTE Band 18/36RB#0 15M	Front Side	23925	19.13	20.00	1.222	0.075	0.092
	LTE Band 18/36RB#0 15M	Back Side	23925	19.13	20.00	1.222	0.096	0.117
	LTE Band 18/36RB#0 15M	Left Side	23925	19.13	20.00	1.222	0.052	0.064
	LTE Band 18/36RB#0 15M	Right Side	23925	19.13	20.00	1.222	0.050	0.061
	LTE Band 18/36RB#0 15M	Top Side	23925	19.13	20.00	1.222	0.097	0.119
Sensor on/Reduced Power Level 1								
	LTE Band 19/1RB#0 15M	Front Side	24075	20.16	21.00	1.213	0.096	0.117
46#	LTE Band 19/1RB#0 15M	Back Side	24075	20.16	21.00	1.213	0.140	0.170
	LTE Band 19/1RB#0 15M	Left Side	24075	20.16	21.00	1.213	0.086	0.104
	LTE Band 19/1RB#0 15M	Right Side	24075	20.16	21.00	1.213	0.049	0.059



47#	LTE Band 19/1RB#0 15M	Top Side	24075	20.16	21.00	1.213	0.140	0.170
	LTE Band 19/36RB#0 15M	Front Side	24075	19.15	20.00	1.216	0.087	0.106
	LTE Band 19/36RB#0 15M	Back Side	24075	19.15	20.00	1.216	0.116	0.141
	LTE Band 19/36RB#0 15M	Left Side	24075	19.15	20.00	1.216	0.071	0.086
	LTE Band 19/36RB#0 15M	Right Side	24075	19.15	20.00	1.216	0.040	0.049
	LTE Band 19/36RB#0 15M	Top Side	24075	19.15	20.00	1.216	0.113	0.137

**Sensor on/Reduced Power Level 1**

	LTE Band 26/1RB#0 15M	Front Side	26865	20.15	21.00	1.216	0.090	0.109
48#	LTE Band 26/1RB#0 15M	Back Side	26865	20.15	21.00	1.216	0.120	0.146
	LTE Band 26/1RB#0 15M	Left Side	26865	20.15	21.00	1.216	0.089	0.108
	LTE Band 26/1RB#0 15M	Right Side	26865	20.15	21.00	1.216	0.037	0.045
49#	LTE Band 26/1RB#0 15M	Top Side	26865	20.15	21.00	1.216	0.130	0.158
	LTE Band 26/36RB#0 15M	Front Side	26865	19.12	20.00	1.225	0.085	0.104
	LTE Band 26/36RB#0 15M	Back Side	26865	19.12	20.00	1.225	0.098	0.120
	LTE Band 26/36RB#0 15M	Left Side	26865	19.12	20.00	1.225	0.073	0.089
	LTE Band 26/36RB#0 15M	Right Side	26865	19.12	20.00	1.225	0.031	0.038
	LTE Band 26/36RB#0 15M	Top Side	26865	19.12	20.00	1.225	0.110	0.135

**Sensor on/Reduced Power Level 1**

50#	LTE Band 38/1RB#0 20M	Front Side	38000	20.33	21.00	1.167	0.191	0.224
	LTE Band 38/1RB#0 20M	Back Side	38000	20.33	21.00	1.167	0.172	0.202
	LTE Band 38/1RB#0 20M	Left Side	38000	20.33	21.00	1.167	0.065	0.076
	LTE Band 38/1RB#0 20M	Right Side	38000	20.33	21.00	1.167	0.035	0.041
51#	LTE Band 38/1RB#0 20M	Top Side	38000	20.33	21.00	1.167	0.277	0.325
	LTE Band 38/50RB#0 20M	Front Side	38000	19.12	20.00	1.225	0.177	0.218
	LTE Band 38/50RB#0 20M	Back Side	38000	19.12	20.00	1.225	0.139	0.171
	LTE Band 38/50RB#0 20M	Left Side	38000	19.12	20.00	1.225	0.053	0.065
	LTE Band 38/50RB#0 20M	Right Side	38000	19.12	20.00	1.225	0.029	0.036
	LTE Band 38/50RB#0 20M	Top Side	38000	19.12	20.00	1.225	0.228	0.281

**Sensor on/Reduced Power Level 1**

52#	LTE Band 40A/1RB#0 10M	Front Side	38750	20.14	21.00	1.219	0.177	0.217
	LTE Band 40A/1RB#0 10M	Back Side	38750	20.14	21.00	1.219	0.127	0.156
	LTE Band 40A/1RB#0 10M	Left Side	38750	20.14	21.00	1.219	0.160	0.196
	LTE Band 40A/1RB#0 10M	Right Side	38750	20.14	21.00	1.219	0.089	0.109
	LTE Band 40A/1RB#0 10M	Top Side	38750	20.14	21.00	1.219	0.175	0.215
	LTE Band 40A/25RB#0 10M	Front Side	38750	19.05	20.00	1.245	0.160	0.200
	LTE Band 40A/25RB#0 10M	Back Side	38750	19.05	20.00	1.245	0.105	0.131
	LTE Band 40A/25RB#0 10M	Left Side	38750	19.05	20.00	1.245	0.135	0.169
	LTE Band 40A/25RB#0 10M	Right Side	38750	19.05	20.00	1.245	0.073	0.091



	LTE Band 40A/25RB#0 10M	Top Side	38750	19.05	20.00	1.245	0.140	0.175
<b>Sensor on/Reduced Power Level 1</b>								
53#	LTE Band 40B/1RB#0 10M	Front Side	39200	20.11	21.00	1.227	0.186	0.230
	LTE Band 40B/1RB#0 10M	Back Side	39200	20.11	21.00	1.227	0.185	0.228
	LTE Band 40B/1RB#0 10M	Left Side	39200	20.11	21.00	1.227	0.176	0.217
	LTE Band 40B/1RB#0 10M	Right Side	39200	20.11	21.00	1.227	0.101	0.125
54#	LTE Band 40B/1RB#0 10M	Top Side	39200	20.11	21.00	1.227	0.228	0.282
	LTE Band 40B/25RB#0 10M	Front Side	39200	19.05	20.00	1.245	0.170	0.213
	LTE Band 40B/25RB#0 10M	Back Side	39200	19.05	20.00	1.245	0.151	0.189
	LTE Band 40B/25RB#0 10M	Left Side	39200	19.05	20.00	1.245	0.145	0.182
	LTE Band 40B/25RB#0 10M	Right Side	39200	19.05	20.00	1.245	0.086	0.108
	LTE Band 40B/25RB#0 10M	Top Side	39200	19.05	20.00	1.245	0.187	0.234
<b>Sensor on/Reduced Power Level 1</b>								
55#	LTE Band 41/1RB#0 20M	Front Side	40620	20.26	21.00	1.186	0.196	0.234
	LTE Band 41/1RB#0 20M	Back Side	40620	20.26	21.00	1.186	0.175	0.209
	LTE Band 41/1RB#0 20M	Left Side	40620	20.26	21.00	1.186	0.068	0.081
	LTE Band 41/1RB#0 20M	Right Side	40620	20.26	21.00	1.186	0.049	0.058
56#	LTE Band 41/1RB#0 20M	Top Side	40620	20.26	21.00	1.186	0.276	0.329
	LTE Band 41/50RB#0 20M	Front Side	40620	19.23	20.00	1.194	0.183	0.220
	LTE Band 41/50RB#0 20M	Back Side	40620	19.23	20.00	1.194	0.142	0.171
	LTE Band 41/50RB#0 20M	Left Side	40620	19.23	20.00	1.194	0.057	0.068
	LTE Band 41/50RB#0 20M	Right Side	40620	19.23	20.00	1.194	0.040	0.048
	LTE Band 41/50RB#0 20M	Top Side	40620	19.23	20.00	1.194	0.227	0.273
<b>Sensor on/Reduced Power Level 1</b>								
	LTE Band 66/1RB#0 20M	Front Side	132322	18.27	19.00	1.183	0.202	0.239
57#	LTE Band 66/1RB#0 20M	Back Side	132322	18.27	19.00	1.183	0.261	0.309
	LTE Band 66/1RB#0 20M	Left Side	132322	18.27	19.00	1.183	0.388	0.459
	LTE Band 66/1RB#0 20M	Right Side	132322	18.27	19.00	1.183	0.126	0.149
58#	LTE Band 66/1RB#0 20M	Top Side	132322	18.27	19.00	1.183	0.549	0.649
	LTE Band 66/50RB#0 20M	Front Side	132322	17.04	18.00	1.247	0.189	0.236
	LTE Band 66/50RB#0 20M	Back Side	132322	17.04	18.00	1.247	0.220	0.274
	LTE Band 66/50RB#0 20M	Left Side	132322	17.04	18.00	1.247	0.311	0.388
	LTE Band 66/50RB#0 20M	Right Side	132322	17.04	18.00	1.247	0.105	0.131
	LTE Band 66/50RB#0 20M	Top Side	132322	17.04	18.00	1.247	0.456	0.569
<b>Sensor on/Reduced Power Level 2 for Simultaneous Transmission</b>								
	LTE Band 66/1RB#0 20M	Front Side	132322	15.24	16.00	1.191	0.040	0.048
	LTE Band 66/1RB#0 20M	Back Side	132322	15.24	16.00	1.191	0.052	0.062
	LTE Band 66/1RB#0 20M	Left Side	132322	15.24	16.00	1.191	0.078	0.092



	LTE Band 66/1RB#0 20M	Right Side	132322	15.24	16.00	1.191	0.025	0.030
	LTE Band 66/1RB#0 20M	Top Side	132322	15.24	16.00	1.191	0.094	0.112
	LTE Band 66/50RB#0 20M	Front Side	132322	14.01	15.00	1.256	0.038	0.047
	LTE Band 66/50RB#0 20M	Back Side	132322	14.01	15.00	1.256	0.044	0.055
	LTE Band 66/50RB#0 20M	Left Side	132322	14.01	15.00	1.256	0.062	0.078
	LTE Band 66/50RB#0 20M	Right Side	132322	14.01	15.00	1.256	0.021	0.026
	LTE Band 66/50RB#0 20M	Top Side	132322	14.01	15.00	1.256	0.082	0.103

## ➤ 5G NR DFT-s-QPSK Body SAR

Plot No.	Band/Mode	Test Position	CH.	Ave. Power (dBm)	Tune-up Limit (dBm)	Tune-up Scaling Factor	Meas. SAR <sub>1g</sub> (W/kg)	Reported SAR <sub>1g</sub> (W/kg)
<b>Sensor on/Reduced Power Level 1</b>								
59#	5G NR n41/1RB#1 100M	Front Side	518598	17.48	18.00	1.127	0.179	0.202
	5G NR n41/1RB#1 100M	Back Side	518598	17.48	18.00	1.127	0.123	0.139
60#	5G NR n41/1RB#1 100M	Right Side	518598	17.48	18.00	1.127	0.539	0.608
	5G NR n41/1RB#1 100M	Top Side	518598	17.48	18.00	1.127	0.097	0.109
	5G NR n41/135RB#1 100M	Front Side	518598	17.18	18.00	1.208	0.141	0.171
	5G NR n41/135RB#1 100M	Back Side	518598	17.18	18.00	1.208	0.097	0.117
	5G NR n41/135RB#1 100M	Right Side	518598	17.18	18.00	1.208	0.426	0.514
	5G NR n41/135RB#1 100M	Top Side	518598	17.18	18.00	1.208	0.077	0.093
<b>Sensor on/Reduced Power Level 2 for Simultaneous Transmission</b>								
	5G NR n41/1RB#1 100M	Front Side	518598	11.48	12.00	1.127	0.104	0.117
	5G NR n41/1RB#1 100M	Back Side	518598	11.48	12.00	1.127	0.071	0.080
	5G NR n41/1RB#1 100M	Right Side	518598	11.48	12.00	1.127	0.313	0.352
	5G NR n41/1RB#1 100M	Top Side	518598	11.48	12.00	1.127	0.056	0.063
	5G NR n41/135RB#1 100M	Front Side	518598	11.18	12.00	1.208	0.082	0.099
	5G NR n41/135RB#1 100M	Back Side	518598	11.18	12.00	1.208	0.056	0.068
	5G NR n41/135RB#1 100M	Right Side	518598	11.18	12.00	1.208	0.247	0.298
	5G NR n41/135RB#1 100M	Top Side	518598	11.18	12.00	1.208	0.044	0.054
<b>Sensor on/Reduced Power Level 1</b>								
61#	5G NR n77/1RB#1 100M	Front Side	656000	19.26	20.00	1.186	0.081	0.096
	5G NR n77/1RB#1 100M	Back Side	656000	19.26	20.00	1.186	0.063	0.075
62#	5G NR n77/1RB#1 100M	Right Side	656000	19.26	20.00	1.186	0.262	0.311
	5G NR n77/1RB#1 100M	Top Side	656000	19.26	20.00	1.186	0.022	0.026
	5G NR n77/135RB#1 100M	Front Side	656000	19.08	20.00	1.236	0.067	0.082
	5G NR n77/135RB#1 100M	Back Side	656000	19.08	20.00	1.236	0.052	0.064
	5G NR n77/135RB#1 100M	Right Side	656000	19.08	20.00	1.236	0.215	0.266
	5G NR n77/135RB#1 100M	Top Side	656000	19.08	20.00	1.236	0.018	0.022



## ➤ WLAN Body SAR

Plot No.	Band/Mode	Test Position	CH.	Ave. Power (dBm)	Tune-up Limit (dBm)	Tune-up Scaling Factor	Meas. SAR <sub>1g</sub> (W/kg)	Reported SAR <sub>1g</sub> (W/kg)
<b>Full Power for CH 0</b>								
	WLAN2.4GHz/802.11b	Front Side	1	15.67	16.50	1.211	0.050	0.061
	WLAN2.4GHz/802.11b	Back Side	1	15.67	16.50	1.211	0.068	0.083
	WLAN2.4GHz/802.11b	Right Side	1	15.67	16.50	1.211	0.110	0.134
	WLAN2.4GHz/802.11b	Top Side	1	15.67	16.50	1.211	0.193	0.236
<b>Full Power for CH 1</b>								
	WLAN2.4GHz/802.11b	Front Side	6	15.52	16.00	1.117	0.078	0.088
63#	WLAN2.4GHz/802.11b	Back Side	6	15.52	16.00	1.117	0.081	0.092
64#	WLAN2.4GHz/802.11b	Right Side	6	15.52	16.00	1.117	0.229	0.258
	WLAN2.4GHz/802.11b	Top Side	6	15.52	16.00	1.117	0.025	0.028
<b>Full Power for CH 0</b>								
	WLAN5.2GHz/802.11n40	Front Side	38	12.98	13.50	1.127	0.061	0.069
65#	WLAN5.2GHz/802.11n40	Back Side	38	12.98	13.50	1.127	0.272	0.310
	WLAN5.2GHz/802.11n40	Right Side	38	12.98	13.50	1.127	0.233	0.265
	WLAN5.2GHz/802.11n40	Top Side	38	12.98	13.50	1.127	0.176	0.200
<b>Full Power for CH 1</b>								
	WLAN5.2GHz/802.11n40	Front Side	46	12.31	13.00	1.172	0.108	0.128
	WLAN5.2GHz/802.11n40	Back Side	46	12.31	13.00	1.172	0.209	0.247
	WLAN5.2GHz/802.11n40	Right Side	46	12.31	13.00	1.172	0.195	0.231
	WLAN5.2GHz/802.11n40	Top Side	46	12.31	13.00	1.172	0.077	0.091
<b>Full Power for CH 0</b>								
	WLAN5.3GHz/802.11a	Front Side	60	12.27	13.00	1.183	0.126	0.150
66#	WLAN5.3GHz/802.11a	Back Side	60	12.27	13.00	1.183	0.398	0.475
<b>Full Power for CH 1</b>								
	WLAN5.3GHz/802.11n40	Front Side	62	12.81	13.50	1.172	0.092	0.109
	WLAN5.3GHz/802.11n40	Back Side	62	12.81	13.50	1.172	0.235	0.278
<b>Full Power for CH 0</b>								
	WLAN5.5GHz/802.11n40	Front Side	102	13.03	13.50	1.114	0.129	0.145
	WLAN5.5GHz/802.11n40	Back Side	102	13.03	13.50	1.114	0.201	0.226
<b>Full Power for CH 1</b>								
	WLAN5.5GHz/802.11n20	Front Side	120	12.66	13.00	1.081	0.114	0.125
67#	WLAN5.5GHz/802.11n20	Back Side	120	12.66	13.00	1.081	0.297	0.325
<b>Full Power for CH 0</b>								
	WLAN5.8GHz/802.11n40	Front Side	151	13.06	13.50	1.107	0.232	0.259
68#	WLAN5.8GHz/802.11n40	Back Side	151	13.06	13.50	1.107	0.438	0.490



	WLAN5.8GHz/802.11n40	Right Side	151	13.06	13.50	1.107	0.393	0.439
	WLAN5.8GHz/802.11n40	Top Side	151	13.06	13.50	1.107	0.364	0.407

**Full Power for CH 1**

	WLAN5.8GHz/802.11a	Front Side	149	12.05	12.50	1.109	0.070	0.078
	WLAN5.8GHz/802.11a	Back Side	149	12.05	12.50	1.109	0.103	0.115
	WLAN5.8GHz/802.11a	Right Side	149	12.05	12.50	1.109	0.094	0.105
	WLAN5.8GHz/802.11a	Top Side	149	12.05	12.50	1.109	0.068	0.077

**Full Power for CH 0**

69#	Bluetooth/DH5	Front Side	39	12.80	13.50	1.175	0.043	0.055
	Bluetooth/DH5	Back Side	39	12.80	13.50	1.175	0.024	0.031
	Bluetooth/DH5	Right Side	39	12.80	13.50	1.175	0.028	0.036
70#	Bluetooth/DH5	Top Side	39	12.80	13.50	1.175	0.125	0.159

**Note:**

1. For TDD-LTE, the reported SAR should be scaled with the duty cycle scaling factor 1.006.
2. The 2.4G WLAN reported 1g SAR (W/kg) should be scaled with the duty cycle scaling factor 1.009, 5G WLAN 802.11a with 1.009, 802.11n20 with 1.011 and 802.11n40 with 1.01.
3. The Bluetooth reported 1g SAR (W/kg) should be scaled with the duty cycle scaling factor 1.085.

## 18.4. Repeated SAR Assessment

### ➤ General Note

In accordance with published RF Exposure KDB procedure 865664 D01 SAR measurement 100 MHz to 6 GHz. These additional measurements are repeated after the completion of all measurements requiring the same head or body tissue-equivalent medium in a frequency band. The test device should be returned to ambient conditions (normal room temperature) with the battery fully charged before it is re-mounted on the device holder for the repeated measurement(s) to minimize any unexpected variations in the repeated results.

1. Repeated measurement is not required when the original highest measured SAR is < 0.80 W/kg;
2. When the original highest measured SAR is  $\geq 0.80$  W/kg, repeat that measurement once.
3. Perform a second repeated measurement only if the ratio of largest to smallest SAR for the original and first repeated measurements is  $> 1.20$  or when the original or repeated measurement is  $\geq 1.45$  W/kg (~ 10% from the 1-g SAR limit).
4. Perform a third repeated measurement only if the original, first or second repeated measurement is  $\geq 1.5$  W/kg and the ratio of largest to smallest SAR for the original, first and second repeated measurements is  $> 1.20$ .

### ➤ Test Results

Plot No.	Band/Mode	Test Position	CH.	Ave. Power (dBm)	Tune-up Limit (dBm)	Tune-up Scaling Factor	Meas. SAR <sub>1g</sub> (W/kg)	Reported SAR <sub>1g</sub> (W/kg)
<b>Sensor on/Reduced Power Level 1</b>								
OR.	Band II/RMC 12.2Kbps	Top Side	9538	17.06	18.00	1.242	0.883	1.096
1 <sup>st</sup>	Band II/RMC 12.2Kbps	Top Side	9538	17.06	18.00	1.242	0.827	1.027

## 18.5. Extremity SAR Assessment

### ➤ General Guidance

1. According to KDB 648747 D04v01r03 The UMPC mini-tablet procedures must also be applied to test the SAR of all surfaces and edges with an antenna located at  $\leq 25$  mm from that surface or edge, in direct contact with a flat phantom, for 10-g extremity SAR according to the body-equivalent tissue dielectric parameters in KDB Publication 865664 D01 to address interactive hand use exposure conditions.
2. When hotspot mode applies, 10-g extremity SAR is required only for the surfaces and edges with hotspot mode 1-g reported SAR  $> 1.2$  W/kg.
3. According to the user manual, the EUT diagonal size is greater than 16cm, therefore the 0mm extremity SAR of WLAN 5GHz is required. There are two types of antennas in this device, only the worst antenna was tested the extremity SAR in this report.

### ➤ Test Results

Plot No.	Band/Mode	Test Position	CH.	Ave. Power (dBm)	Tune-up Limit (dBm)	Tune-up Scaling Factor	Meas. SAR <sub>10g</sub> (W/kg)	Reported SAR <sub>10g</sub> (W/kg)
<b>Sensor off/Full Power</b>								
71#	BC0/RC3 SO32 (F+SCH)	Front Side	1013	23.79	24.50	1.178	0.405	0.477
	BC0/RC3 SO32 (F+SCH)	Back Side	1013	23.79	24.50	1.178	0.247	0.291
<b>72#</b>								
72#	BC1/RC3 SO32 (F+SCH)	Front Side	600	19.71	20.50	1.199	0.466	0.559
	BC1/RC3 SO32 (F+SCH)	Back Side	600	19.71	20.50	1.199	0.287	0.344
<b>73#</b>								
	WLAN5.3GHz/802.11a	Front Side	60	12.27	13.00	1.183	0.063	0.075
73#	WLAN5.3GHz/802.11a	Back Side	60	12.27	13.00	1.183	0.980	1.170
<b>74#</b>								
	WLAN5.3GHz/802.11n40	Front Side	62	12.81	13.50	1.172	0.769	0.910
	WLAN5.3GHz/802.11n40	Back Side	62	12.81	13.50	1.172	0.488	0.578
<b>74#</b>								
	WLAN5.5GHz/802.11n40	Front Side	102	13.03	13.50	1.114	0.042	0.047
74#	WLAN5.5GHz/802.11n40	Back Side	102	13.03	13.50	1.114	0.427	0.481
<b>75#</b>								
	WLAN5.5GHz/802.11n20	Front Side	120	12.66	13.00	1.081	0.208	0.227
	WLAN5.5GHz/802.11n20	Back Side	120	12.66	13.00	1.081	0.158	0.173

### Note:

The 5G WLAN 802.11a reported 1g SAR (W/kg) should be scaled with the duty cycle scaling factor 1.009, 802.11n20 with 1.011 and 802.11n40 with 1.01.



## 19. Simultaneous Transmission Evaluation

### 19.1. Simultaneous Transmission Consideration

No.	Simultaneous Transmission Consideration	Head	Body-Worn	Hotspot
1	WWAN+WLAN 2.4GHz/5GHz(SISO/MIMO)	Yes	Yes	Yes
2	WWAN+WLAN 5.2GHz/5.8GHz(SISO/MIMO)	Yes	Yes	Yes
3	WWAN+WLAN 5.3GHz/5.5GHz(SISO/MIMO)	Yes	Yes	No
4	WWAN+Bluetooth	No	Yes	Yes
5	WLAN 5.2GHz/5.8GHz(CH1)+Bluetooth	No	Yes	Yes
6	WLAN 5.3GHz/5.5GHz(CH1))+Bluetooth	No	Yes	No
7	WWAN+WLAN 5.2GHz/5.8GHz(CH1))+Bluetooth	No	Yes	Yes
8	WWAN+WLAN 5.3GHz/5.5GHz(CH1))+Bluetooth	No	Yes	No

**Note:**

1. When the user enables the personal wireless router functions for the handset, actual operations include simultaneous transmission of the WWAN and WLAN transmitters. The "Portable Hotspot" feature on the handset was NOT activated, to ensure the SAR measurements were evaluated for a single transmission frequency RF signal.
2. The hotspot SAR result may overlap with the body-worn accessory SAR requirements, per KDB 941225 D06, the more conservative configurations can be considered, thus excluding some unnecessary body-worn accessory SAR tests.
3. Simultaneous Transmission SAR evaluation is not required for BT and WLAN 2.4GHz, because the software mechanism have been incorporated to guarantee that the WLAN and Bluetooth transmitters would not simultaneously operate.
4. Per KDB 447498D01v06, simultaneous transmission SAR evaluation procedures is as followed:  
Step 1: If sum of 1 g SAR < 1.6 W/kg, Simultaneous SAR measurement is not required.  
Step 2: If sum of 1 g SAR > 1.6 W/kg, ratio of SAR to peak separation distance for pair of transmitters calculated.  
Step 3: If the ratio of SAR to peak separation distance is  $\leq 0.04$ , Simultaneous SAR measurement is not required.  
Step 4: If the ratio of SAR to peak separation distance is  $> 0.04$ , Simultaneous SAR measurement is required and simultaneous transmission SAR value is calculated.  
(The ratio is determined by:  $(\text{SAR1} + \text{SAR2})^{1.5}/\text{Ri} \leq 0.04$ ,  
Ri is the separation distance between the peak SAR locations for the antenna pair in mm.)
5. 2.4G&5G MIMO SAR were combined with the standalone SAR of CH0 and CH1.
6. When it supports transmit simultaneously at WWAN+WLAN MIMO mode, the co-location SAR of WWAN+WLAN (standalone SAR) would not be recorded in this report.
7. The co-location of WWAN+Bluetooth would not be recorded since it is less than the combination



of WWAN+WLAN+Bluetooth.

8. This device does not support the combination of WWAN+WLAN 2.4GHz+WLAN 5GHz.

## 19.2. Simultaneous Transmission Analysis

Remark: The 5G EN-DC Data and simultaneous transmission data were recorded in annex F.



## 20. Uncertainty Assessment

According to KDB 865664 D01 SAR measurement 100 MHz to 6GHz, when the highest measured 1-g SAR is less than 1.5 W/kg and 10-g extremity SAR less than 3.75 W/kg, the expanded SAR measurement uncertainty must be less than 30% with a confidence interval of k=2. When these conditions are met, extensive SAR measurement uncertainty analysis described in IEEE 1528-2013 is not required in the SAR report and submitted for equipment approval. For this device, both the 1-g SAR is less than 1.5 W/kg and 10-g extremity SAR less than 3.75 W/kg. Therefore the measurement uncertainty table is not required in this report.



## Annex A General Information

### 1. Identification of the Responsible Testing Laboratory

Laboratory Name:	Shenzhen Morlab Communications Technology Co., Ltd.
Laboratory Address:	FL.3, Building A, FeiYang Science Park, No.8 LongChang Road, Block 67, BaoAn District, ShenZhen, GuangDong Province, P. R. China
Telephone:	+86 755 36698555
Facsimile:	+86 755 36698525

### 2. Identification of the Responsible Testing Location

Name:	Shenzhen Morlab Communications Technology Co., Ltd.
Address:	FL.3, Building A, FeiYang Science Park, No.8 LongChang Road, Block 67, BaoAn District, ShenZhen, GuangDong Province, P. R. China

### 3. Facilities and Accreditations

The FCC designation number is CN1192, the test firm registration number is 226174.

#### Note:

The main report is end here and the other Annex (B,C,D,E,F,G) will be submitted separately.

\*\*\*\*\* END OF MAIN REPORT \*\*\*\*\*