

TEST REPORT

Applicant Name : Inrico Technologies Co.,Ltd
Address : A1703, Shenzhen National Engineering Laboratory Building, No. 20 Gaoxin South 7th Road, Shenzhen, China
Report Number : 2504S23848E-RF-00F
FCC ID: 2AV6-BC680

Test Standard (s)

FCC PART 22H; FCC PART 24E; FCC PART 27; FCC PART 90

Sample Description

Product Type: 4G LTE Smart Terminal
Model No.: BC680
Trade Mark: **Inrico®**
Date Received: 2025-04-09
Date of Test: 2025-05-01 to 2025-08-21
Report Date: 2025-08-21


Test Result:	The EUT complied with the standards above.
--------------	--

Prepared and Checked By:



Matt Liang
EMC Engineer

Approved By:



Bob Liao
EMC Engineer

Note: This report must not be used by the customer to claim product certification, approval, or endorsement by A2LA, or any agency of the Federal Government. The information marked "#" is provided by the applicant, the laboratory is not responsible for its authenticity and this information can affect the validity of the result in the test report. Customer model name, addresses, names, trademarks etc. are included but no need marked.
This report cannot be reproduced except in full, without prior written approval of the Company. Unless otherwise stated the results shown in this test report refer only to the sample(s) tested. This report is valid only with a valid digital signature. The digital signature may be available only under the Adobe software above version 7.0.

Shenzhen Accurate Technology Co., Ltd.

Floor 1, KuMaKe Building, Dongzhou Community, Guangming Street, Guangming District, Shenzhen, Guangdong, China.

Tel: +86 755-26503290

Web: www.atc-lab.com

TABLE OF CONTENTS

DOCUMENT REVISION HISTORY	3
GENERAL INFORMATION	4
PRODUCT DESCRIPTION FOR EQUIPMENT UNDER TEST (EUT)	4
OBJECTIVE	5
TEST METHODOLOGY	5
TEST FACILITY	6
MEASUREMENT UNCERTAINTY	6
SYSTEM TEST CONFIGURATION	7
DESCRIPTION OF TEST CONFIGURATION	7
SPECIAL ACCESSORIES	8
EQUIPMENT MODIFICATIONS	8
SUPPORT EQUIPMENT LIST AND DETAILS	8
EXTERNAL I/O CABLE	8
BLOCK DIAGRAM OF TEST SETUP	9
SUMMARY OF TEST RESULTS	10
TEST EQUIPMENT LIST	11
FCC §1.1310-RF EXPOSURE	13
FCC§2.1047-MODULATION CHARACTERISTIC	14
FCC §2.1046, §22.913, §24.232, §27.50, §90.635-RF OUTPUT POWER	15
APPLICABLE STANDARD	15
TEST PROCEDURE	16
TEST DATA	16
FCC §2.1049, §22.917, §22.905, §24.238, §27.53, §90.209-OCCUPIED BANDWIDTH	17
APPLICABLE STANDARD	17
TEST PROCEDURE	17
TEST DATA	17
FCC §2.1051, §22.917, §24.238, §27.53, §90.543, §90.691-SPURIOUS EMISSIONS AT ANTENNA TERMINALS	18
APPLICABLE STANDARD	18
TEST PROCEDURE	18
TEST DATA	18
FCC §2.1053, §22.917, §24.238, §27.53, §90.543, §90.691-SPURIOUS RADIATED EMISSIONS	19
APPLICABLE STANDARD	19
TEST PROCEDURE	19
TEST DATA	21
FCC §22.917, §24.238, §27.53, §90.691-BAND EDGES	32
APPLICABLE STANDARD	32
TEST PROCEDURE	32
TEST DATA	33
FCC §2.1055, §22.355, §24.235, §27.54, §90.213-FREQUENCY STABILITY	34
APPLICABLE STANDARD	34
TEST PROCEDURE	37
TEST DATA	37
APPENDIX	38
EXHIBIT A-EUT PHOTOGRAPHS	39
EXHIBIT B-TEST SETUP PHOTOGRAPHS	40

DOCUMENT REVISION HISTORY

Revision Number	Report Number	Description of Revision	Date of Revision
Rev.00	2504S23848E-RF-00F	Original Report	2025-08-21

GENERAL INFORMATION

Product Description for Equipment under Test (EUT)

Product	4G LTE Smart Terminal
Tested Model	BC680
Voltage Range [#]	AC 100V-240V 50/60Hz for adapter DC 5.0V from USB Type-C port DC 4.35V from desktop charger DC 3.8V from rechargeable battery
Adapter Information [#]	Model: HJ-0502000W2-US Input: 100-240 V~ 50/60Hz 0.3A Output: 5.0V ==2.0A 10.0W
Desktop Charger Information [#]	Model: CI-80E Input: 5V ==2000mA Output: 4.35V ==1000mA

Radio	GSM, WCDMA, LTE
Frequency Range	GSM 850: 824-849MHz(TX); 869-894MHz(RX) PCS 1900: 1850-1910MHz(TX); 1930-1990MHz(RX) WCDMA Band 2: 1850-1910MHz(TX); 1930-1990MHz(RX) WCDMA Band 4: 1710-1755MHz(TX); 2110-2155MHz(RX) WCDMA Band 5: 824-849MHz(TX); 869-894MHz(RX) LTE Band 2: 1850-1910MHz(TX); 1930-1990MHz(RX) LTE Band 4: 1710-1755MHz(TX); 2110-2155MHz(RX) LTE Band 5: 824-849MHz(TX); 869-894MHz(RX) LTE Band 7: 2500-2570MHz(TX); 2620-2690MHz(RX) LTE Band 12: 699-716MHz(TX); 729-746MHz(RX) LTE Band 13: 777-787MHz(TX); 746-756MHz(RX) LTE Band 17: 704-716MHz(TX); 734-746MHz(RX) LTE Band 25: 1850-1915MHz(TX); 1930-1995MHz(RX) LTE Band 26: 814-849MHz(TX); 859-894MHz(RX) LTE Band 38: 2570-2620MHz(TX/RX) LTE Band 41: 2535-2655MHz(TX/RX) LTE Band 66: 1710-1780MHz(TX); 2110-2200MHz(RX)
Modulation Technique	GSM: GMSK, 8PSK WCDMA: BPSK, QPSK, 16QAM , 64QAM LTE: QPSK, 16QAM
Sample Serial Number	315P-6 (For CE&RE Test), 315P-1 (For RF Conducted Test) (Assigned by ATC, Shenzhen)
Sample/EUT Status	Good condition
Normal/Extreme Condition [#]	L.V.: Low Voltage 3.4 V _{DC} N.V.: Normal Voltage 3.8 V _{DC} H.V.: High Voltage 4.35 V _{DC} (Note: the extreme test condition was declared by manufacturer.)

Continued table:

Maximum Average Conducted Output Power	GSM850: 33.66dBm(GMSK), 27.94dBm (8PSK)		
	PCS1900: 30.23dBm(GMSK), 27.12dBm (8PSK)		
	WCDMA B2:23.96dBm	WCDMA B4:22.34dBm	WCDMAB5:24.02dBm
	LTE B2: 23.69dBm	LTE B4: 22.51dBm	LTE B5: 23.12dBm
	LTE B7: 23.15dBm	LTE B12: 23.48dBm	LTE B13: 23.25dBm
	LTE B17: 23.43dBm	LTE B25: 22.75dBm	LTE B26: 23.34dBm
Antenna Specification [#]	LTE B38: 22.83dBm		
	LTE B41: 23.05dBm		
	LTE B66: 22.93dBm		
	Internal Antenna(Antenna Gain provided by the applicant)		
	GSM850/ WCDMA B5/ LTE B5/ LTE B26:-0.53dBi		
	PCS1900/ WCDMA B2/ LTE B2: -0.36dBi		
	WCDMA B4/ LTE B4/ LTE B66:-0.38dBi		
Antenna Specification [#]	LTE B7: 1.13dBi	LTE B12/ LTE B17: -0.67dBi	
	LTE B13: -0.65dBi	LTE B25: -0.36dBi	
	LTE B38: 1.24dBi	LTE B41: 1.32dBi	

Objective

This test report is in accordance with Part 2-Subpart J, Part 22-Subpart H, Part24-Subpart E, Part 27 and Part 90 of the Federal Communication Commission's rules.

The objective is to determine the compliance of the EUT with FCC rules for output power, modulation characteristic, occupied bandwidth, and spurious emission at antenna terminal, spurious radiated emission, frequency stability and band edge.

Test Methodology

All tests and measurements indicated in this document were performed in accordance with the Code of Federal Regulations Title 47 Part 2-Subpart J as well as the following parts:

Part 22 Subpart H - Public Mobile Services
 Part 24 Subpart E - Personal Communication Services
 Part 27 - Miscellaneous Wireless Communications Services
 Part 90 - Private Land Mobile Radio Services

ANSI C63.26-2015: American National Standard for Compliance Testing of Transmitters Used in Licensed Radio Services

All emissions measurement was performed at Shenzhen Accurate Technology Co., Ltd. The radiated testing was performed at an antenna-to-EUT distance of 3 meters.

Unless otherwise stated there are no any additions to, deviations, or exclusions from the method.

Test Facility

The test site used by Shenzhen Accurate Technology Co., Ltd. to collect test data is located on the Floor 1, KuMaKe Building, Dongzhou Community, Guangming Street, Guangming District, Shenzhen, Guangdong, China.

Accredited by American Association for Laboratory Accreditation (A2LA). The Certificate Number is 4297.01.

Measurement Uncertainty

Parameter	Uncertainty	
Occupied Channel Bandwidth	5%	
RF Frequency	0.064*10 ⁻⁷	
RF output power, conducted	0.3 dB	
Unwanted Emission, conducted	1.2 dB	
Emissions, Radiated	9kHz - 30MHz	2.1 dB
	30MHz - 1GHz	4.3 dB
	1GHz - 18GHz	4.9 dB
	18GHz - 26.5GHz	5.2 dB
	26.5GHz - 40GHz	4.6 dB
Temperature	1°C	
Humidity	7%	
Supply voltages	0.4%	

Note: The extended uncertainty given in this report is obtained by combining the standard uncertainty times the coverage factor K with the 95% confidence interval. Otherwise required by the applicant or Product Regulations, Decision Rule in this report did not consider the uncertainty.

SYSTEM TEST CONFIGURATION

Description of Test Configuration

The final qualification test was performed with the EUT operating at normal mode.

Test was performed as below tables:

Frequency band	Bandwidth (MHz)	Test Frequency(MHz)		
		Low	Middle	High
GSM850	0.25	824.2	836.6	848.8
PCS1900	0.25	1850.2	1880.0	1909.8
WCDMA B2	4.2	1852.4	1880.0	1907.6
WCDMA B4	4.2	1712.4	1732.6	1752.6
WCDMA B5	4.2	826.4	836.6	846.6
LTE B2	1.4	1850.7	1880.0	1909.3
	3	1851.5	1880.0	1908.5
	5	1852.5	1880.0	1907.5
	10	1855	1880.0	1905.0
	15	1857.5	1880.0	1902.5
	20	1860.0	1880.0	1900.0
	1.4	1710.7	1732.5	1754.3
LTE B4	3	1711.5	1732.5	1753.5
	5	1712.5	1732.5	1752.5
	10	1715.0	1732.5	1750.0
	15	1717.5	1732.5	1747.5
	20	1720.0	1732.5	1745.0
	1.4	824.7	836.5	848.3
LTE B5	3	825.5	836.5	847.5
	5	826.5	836.5	846.5
	10	829.0	836.5	844.0
	5	2502.5	2535	2567.5
LTE B7	10	2505.0	2535.0	2565.0
	15	2507.5	2535.0	2562.5
	20	2510.0	2535.0	2560.0
	1.4	699.7	707.5	715.3
LTE B12	3	700.5	707.5	714.5
	5	701.5	707.5	713.5
	10	704.0	707.5	711.0
	5	779.5	/	784.5
LTE B13	10	/	782.0	/
	5	706.5	710.0	713.5
LTE B17	10	709.0	710.0	711.0
	1.4	1850.7	1882.5	1914.3
LTE B25	3	1851.5	1882.5	1913.5
	5	1852.5	1882.5	1912.5
	10	1855.0	1882.5	1910.0
	15	1857.5	1882.5	1907.5
	20	1860.0	1882.5	1905.0

Frequency band	Bandwidth (MHz)	Test Frequency(MHz)		
		Low	Middle	High
LTE B26_1 (814MHz-824MHz)	1.4	814.7	/	823.3
	3	815.5	/	822.5
	5	816.5	/	821.5
	10	819.0	/	/
	15	821.5	/	/
LTE B26_2 (824MHz-849MHz)	1.4	824.7	831.5	848.3
	3	825.5	831.5	847.5
	5	826.5	831.5	846.5
	10	829.0	831.5	844.0
	15	831.5	836.5	841.5
LTE B38	5	2572.5	2595.0	2617.5
	10	2575.0	2595.0	2615.0
	15	2577.5	2595.0	2612.5
	20	2580.0	2595.0	2610.0
LTE B41_2 (2535MHz-2655MHz)	5	2537.5	2595.0	2652.5
	10	2540.0	2595.0	2650.0
	15	2542.5	2595.0	2647.5
	20	2545.0	2595.0	2645.0
LTE B66	1.4	1710.7	1745.0	1779.3
	3	1711.5	1745.0	1778.5
	5	1712.5	1745.0	1777.5
	10	1715.0	1745.0	1775.0
	15	1717.5	1745.0	1772.5
	20	1720.0	1745.0	1770.0

Frequency band	Bandwidth (MHz)	Channel Cross 90S and 22H (MHz)
LTE B26_3 (824MHz)	1.4	824.0
	3	824.0
	5	824.0
	10	824.0
	15	824.0

Special Accessories

No special accessory.

Equipment Modifications

No modification was made to the EUT tested.

Support Equipment List and Details


Manufacturer	Description	Model	Serial Number
/	/	/	/

External I/O Cable


Cable Description	Shielding Type	Length (m)	From Port	To
USB Cable	No	1.18	Adapter	EUT

Block Diagram of Test Setup

For Radiated Emissions below 1GHz:



For Radiated Emissions above 1GHz:



SUMMARY OF TEST RESULTS

FCC Rules	Description of Test	Result
§1.1310; §2.1093	RF Exposure(SAR)	Compliance
§2.1046; §22.913(a)(d); §24.232(c)(d); §27.50(b)(c)(d)(h); §90.635	RF Output Power	Compliance
§2.1047	Modulation Characteristics	Not Applicable
§2.1049; §22.905; §22.917; §24.238; §27.53; §90.209	Occupied Bandwidth	Compliance
§2.1051; §22.917(a); §24.238(a); §27.53; §90.543; §90.691	Spurious Emissions at Antenna Terminal	Compliance
§2.1053; §22.917(a); §24.238(a); §27.53 §90.543; §90.691	Field Strength of Spurious Radiation	Compliance
§22.917 (a); §24.238 (a); §27.53; §90.691	Band Edge	Compliance
§2.1055; §22.355; §24.235; §27.54; §90.213	Frequency stability	Compliance

TEST EQUIPMENT LIST

Manufacturer	Description	Model	Serial Number	Calibration Date	Calibration Due Date
Radiated Spurious Emission Test(Below 1GHz)					
Rohde & Schwarz	Test Receiver	ESR	102725	2024/11/08	2025/11/07
SONOMA INSTRUMENT	Amplifier	310N	186131	2025/03/26	2026/03/25
Schwarzbeck	Bilog Antenna	VULB9163	9163-323	2024/08/08	2027/08/07
Schwarzbeck	Bilog Antenna	VULB9163	9163-194	2023/02/14	2026/02/13
Agilent	Signal Generator	N5183A	MY47420360	2024/09/02	2025/09/01
Unknown	RF Coaxial Cable	No.12	N040	2024/10/08	2025/10/07
Unknown	RF Coaxial Cable	No.13	N300	2024/10/08	2025/10/07
Unknown	RF Coaxial Cable	No.14	N800	2024/10/08	2025/10/07
Unknown	RF Coaxial Cable	No.40	/	2024/10/08	2025/10/07
Test Software: e3 191218 (V9)					
Radiated Spurious Emission Test(Above 1GHz)					
Rohde & Schwarz	Spectrum Analyzer	FSV40	101949	2024/10/08	2025/10/07
A.H. Systems, inc.	Preamplifier	PAM-0118	226	2025/03/20	2026/03/19
Schwarzbeck	Horn Antenna	BBHA9120D	837	2023/02/22	2026/02/21
Unknown	RF Coaxial Cable	No.10	N050	2024/10/08	2025/10/07
Unknown	RF Coaxial Cable	No.11	N1000	2024/10/08	2025/10/07
Unknown	RF Coaxial Cable	No.40	/	2024/10/08	2025/10/07
Schwarzbeck	HORN ANTENNA	BBHA9170	9170-359	2023/12/12	2026/12/11
BACL	Amplifier	BACL-1313-A18 40	4012521	2025/05/30	2026/05/29
Agilent	Signal Generator	N5183A	MY47420360	2024/09/02	2025/09/01
Schwarzbeck	Horn Antenna	BBHA9120D	9120D-655	2022/12/26	2025/12/25
PASTERNACK	Horn Antenna	PE9852/2F-20	1120 (ATC-BA-024-1)	2023/01/04	2026/01/03
Unknown	RF Coaxial Cable	No.15	N600	2024/10/08	2025/10/07
Unknown	RF Coaxial Cable	No.16	N650	2024/10/08	2025/10/07
Test Software: e3 191218 (V9)					

Manufacturer	Description	Model	Serial Number	Calibration Date	Calibration Due Date
RF Conducted test					
Rohde & Schwarz	Spectrum Analyzer	FSV-40	101495	2024/10/08	2025/10/07
Rohde & Schwarz	Wideband Radio Communication Tester	CMW500	124441	2024/10/08	2025/10/07
Agilent	10dB Attenuator	8491B	A5825	2024/10/08	2025/10/07
Unknown	RF Coaxial Cable	No.35	/	2024/10/08	2025/10/07
BACL	Temp. & Humid. Chamber	BTH-150-40	30192	2024/10/08	2025/10/07
Mini-Circuits	Power Splitter	ZFRSC-183-S+	SF10944151S	2025/03/26	2026/03/25
UNI-T	DC Power Supply	UTP1306S	2109D0903324	2025/03/26	2026/03/25
Test Software: JDAutoTestSystem V1.0.0					

* **Statement of Traceability:** Shenzhen Accurate Technology Co., Ltd. attests that all calibrations have been performed in accordance to requirements that traceable to National Primary Standards and International System of Units (SI).

FCC §1.1310-RF EXPOSURE

Applicable Standard

FCC§1.1310 and §2.1093.

Test Result

Please refer to the SAR report number: 2504S23848E-SAB.

FCC§2.1047-MODULATION CHARACTERISTIC

According to FCC §2.1047(d), Part 22H&24E&27&90 there is no specific requirement for digital modulation, therefore modulation characteristic is not presented.

FCC §2.1046, §22.913, §24.232, §27.50, §90.635-RF OUTPUT POWER**Applicable Standard**

According to FCC §2.1046 and §22.913(a), the ERP of mobile transmitters and auxiliary test transmitters must not exceed 7 watts.

According to FCC §2.1046 and §24.232(c)(d), mobile and portable stations are limited to 2 watts EIRP and the equipment must employ a means for limiting power to the minimum necessary for successful communications.

The peak-to-average power ratio (PAPR) of the transmitter output power must not exceed 13 dB.

According to §27.50(b), portable stations (hand-held devices) transmitting in the 746-757 MHz, 776-788 MHz, and 805-806 MHz bands are limited to 3 watts ERP.

According to §27.50(c), control and mobile stations in the 698-746 MHz band are limited to 30 watts ERP. Portable stations (hand-held devices) in the 600 MHz uplink band and the 698-746 MHz band, and fixed and mobile stations in the 600 MHz uplink band are limited to 3 watts ERP.

According to §27.50(d), Fixed, mobile, and portable (hand-held) stations operating in the 1710-1755 MHz band and mobile and portable stations operating in the 1695-1710 MHz and 1755-1780 MHz bands are limited to 1 watt EIRP.

According to §27.50(h), the maximum EIRP must not exceed 2Watts (33dBm) for 2496-2690MHz.

According to §90.635, the maximum output power of the transmitter for mobile stations is 100 watts (20 dBw).

Test Procedure

According to ANSI C63.26-2015 Section 5.2.5.5:

In many cases, RF output power limits are specified in terms of the ERP or the EIRP. Typically, ERP is specified when the operating frequency is less than or equal to 1 GHz and EIRP is specified when the operating frequency is greater than 1 GHz. Both are defined as the product of the power supplied to the antenna and its gain (relative to a dipole antenna in the case of ERP, and relative to an isotropic antenna in the case of EIRP); however, when working in decibels (i.e., logarithmic scale), the ERP and EIRP represent the sum of the transmit antenna gain (in dBd or dBi, respectively) and the conducted RF output power (expressed in dB relative to watts or milliwatts).

The relevant equation for determining the maximum ERP or EIRP from the measured RF output power is given in Equation (1) as follows:

$$\text{ERP or EIRP} = P_{\text{Meas}} + G_T$$

Where

ERP or EIRP effective radiated power or equivalent isotropically radiated power, respectively
(expressed in the same units as P_{Meas} , e.g., dBm or dBW)


P_{Meas} measured transmitter output power or PSD, in dBm or dBW

G_T gain of the transmitting antenna, in dBd (ERP) or dBi (EIRP)

According to ANSI C63.26-2015 Section 5.2

Conducted method:

The RF output of the transmitter was connected to the CMW500 through sufficient attenuation.



Note: the path loss (cable loss and attenuator) has including in result.

Test Data

Please refer to the Appendix.

FCC §2.1049, §22.917, §22.905, §24.238, §27.53, §90.209-OCCUPIED BANDWIDTH

Applicable Standard

FCC §2.1049, §22.917, §22.905, §24.238, §27.53, §90.209.


Test Procedure

According to ANSI C63.26-2015 Section 5.4.4

The OBW is the frequency bandwidth such that, below its lower and above its upper frequency limits, the mean powers are each equal to 0.5% of the total mean power of the given emission.

The following procedure shall be used for measuring (99%) power bandwidth:

- a) The spectrum analyzer center frequency is set to the nominal EUT channel center frequency. The frequency span for the spectrum analyzer shall be set wide enough to capture all modulation products including the emission skirts (typically a span of $1.5 \times$ OBW is sufficient).
- b) The nominal IF filter 3 dB bandwidth (RBW) shall be in the range of 1% to 5% of the anticipated OBW, and the VBW shall be set $\geq 3 \times$ RBW.
- c) Set the reference level of the instrument as required to prevent the signal amplitude from exceeding the maximum spectrum analyzer input mixer level for linear operation. See guidance provided in 4.2.3.
NOTE—Step a), step b), and step c) may require iteration to adjust within the specified tolerances.
- d) Set the detection mode to peak, and the trace mode to max-hold.
- e) If the instrument does not have a 99% OBW function, recover the trace data points and sum directly in linear power terms. Place the recovered amplitude data points, beginning at the lowest frequency, in a running sum until 0.5% of the total is reached. Record that frequency as the lower OBW frequency. Repeat the process until 99.5% of the total is reached and record that frequency as the upper OBW frequency. The 99% power OBW can be determined by computing the difference these two frequencies.
- f) The OBW shall be reported and plot(s) of the measuring instrument display shall be provided with the test report. The frequency and amplitude axis and scale shall be clearly labeled. Tabular data can be reported in addition to the plot(s).



Note: the path loss (cable loss and splitter inset loss) among the test frequency range has including in test plot.

Test Data

Please refer to the Appendix.

FCC §2.1051, §22.917, §24.238, §27.53, §90.543, §90.691-SPURIOUS EMISSIONS AT ANTENNA TERMINALS

Applicable Standard


FCC §2.1051, §22.917(a), §24.238(a), §27.53, §90.543, §90.691.

The spectrum was to be investigated to the tenth harmonics of the highest fundamental frequency as specified in § 2.1051.

Test Procedure

According to ANSI C63.26-2015 Section 5.7.4:

The RF output of the transceiver was connected to a spectrum analyzer and simulator through appropriate attenuation. The resolution bandwidth of the spectrum analyzer was set at 1MHz. Sufficient scans were taken to show any out of band emissions up to 10th harmonic.



Note1: the path loss (cable loss and splitter inset loss) among the test frequency range has including in test plot.

Note2: For 30MHz-1GHz test of FCC Part 24 and Part 27, RBW is set to 100 kHz because the margin is much greater than 10 dB.

Offset=10*Log (Reference RBW/Measure RBW)=10*(1MHz/100kHz)=10dB

Test Data

Please refer to the Appendix.

FCC §2.1053, §22.917, §24.238, §27.53, §90.543, §90.691-SPURIOUS RADIATED EMISSIONS**Applicable Standard**

FCC § 2.1053, §22.917(a), §24.238(a), §27.53, §90.543, §90.691.

Test Procedure

According to ANSI C63.26-2015 Section 5.5.3:


●Test setup:

Figure 6—Test site-up for radiated ERP and/or EIRP measurements




Figure 7—Substitution method set-up for radiated emission

● Final radiated emissions testing

- a) Place the EUT in the center of the turntable. The EUT shall be configured to transmit into the standard non-radiating load (for measuring radiated spurious emissions), connected with cables of minimal length unless specified otherwise. If the EUT uses an adjustable antenna, the antenna shall be positioned to the length that produces the worst case emission at the fundamental operating frequency.
- b) Each emission under consideration shall be evaluated:
 - 1) Raise and lower the measurement antenna in accordance 5.5.2, as necessary to enable detection of the maximum emission amplitude relative to measurement antenna height.
 - 2) Rotate the EUT through 360° to determine the maximum emission level relative to the axial position.
 - 3) Return the turntable to the azimuth where the highest emission amplitude level was observed.
 - 4) Vary the measurement antenna height again through 1 m to 4 m again to find the height associated with the maximum emission amplitude.
 - 5) Record the measured emission amplitude level and frequency using the appropriate RBW.
- c) Repeat step b) for each emission frequency with the measurement antenna oriented in both the horizontal and vertical polarizations to determine the orientation that gives the maximum emissions amplitude.
- d) Set-up the substitution measurement with the reference point of the substitution antenna located as near as possible to where the center of the EUT radiating element was located during the initial EUT measurement.
- e) Maintain the previous measurement instrument settings and test set-up, with the exception that the EUT is removed and replaced by the substitution antenna.
- f) Connect a signal generator to the substitution antenna; locate the signal generator so as to minimize any potential influences on the measurement results. Set the signal generator to the frequency where emissions are detected, and set an output power level such that the radiated signal can be detected by the measurement instrument, with sufficient dynamic range relative to the noise floor.
- g) For each emission that was detected and measured in the initial test [i.e., in step b) and step c)]:
 - 1) Vary the measurement antenna height between 1 m to 4 m to maximize the received (measured) signal amplitude.
 - 2) Adjust the signal generator output power level until the amplitude detected by the measurement instrument equals the amplitude level of the emission previously measured directly in step b) and step c).
 - 3) Record the output power level of the signal generator when equivalence is achieved in step 2).
- h) Repeat step e) through step g) with the measurement antenna oriented in the opposite polarization.
- i) Calculate the emission power in dBm referenced to a half-wave dipole using the following equation:
$$Pe = Ps(dBm) - \text{cable loss (dB)} + \text{antenna gain (dBd)}$$
where
Pe = equivalent emission power in dBm
Ps = source (signal generator) power in dBm
NOTE—dBd refers to the measured antenna gain in decibels relative to a half-wave dipole.
- j) Correct the antenna gain of the substitution antenna if necessary to reference the emission power to a half-wave dipole. When using measurement antennas with the gain specified in dBi, the equivalent dipole-referenced gain can be determined from: gain (dBd) = gain (dBi) - 2.15 dB. If necessary, the antenna gain can be calculated from calibrated antenna factor information
- k) Provide the complete measurement results as a part of the test report.

The measurement antenna was placed at a distance of 3 meters from the EUT. During the tests, the receiving antenna height and polarization as well as EUT azimuth were varied in order to identify the maximum level of emissions from the EUT. The test was performed by placing the EUT on 3-orthogonal axis.

The frequency range up to tenth harmonic of the fundamental frequency was investigated.

Test Data

Environmental Conditions

Test Item:	RSE Below 1GHz	RSE Above1GHz
Temperature:	24.4 °C	24.6 °C
Relative Humidity:	55 %	56 %
ATM Pressure:	100.1 kPa	100.2 kPa
Test Engineer:	Colin Lin	Kevin Lv
Test Date:	2025-05-30	2025-07-25
EUT Operation Mode:	Transmitting	Transmitting

Test Result: Compliance, please refer to the below data.

Frequency (MHz)	Receiver Reading (dBm)	Rx Antenna Polar (H/V)	Substituted Factor (dB)	Absolute Level (dBm)	Limit (dBm)	Margin (dB)
GSM 850						
Test Frequency Rang: 30MHz~10GHz						
Low Channel						
823.51	-73.42	H	11.25	-62.17	-13	-49.17
858.91	-73.22	V	11.03	-62.19	-13	-49.19
1648.4	-27.07	H	-1.20	-28.27	-13	-15.27
1648.4	-33.79	V	-1.55	-35.34	-13	-22.34
2472.6	-37.54	H	1.07	-36.47	-13	-23.47
2472.6	-35.04	V	1.40	-33.64	-13	-20.64
Middle Channel						
823.51	-73.15	H	11.25	-61.90	-13	-48.90
858.91	-73.35	V	11.03	-62.32	-13	-49.32
1673.2	-26.24	H	-1.53	-27.77	-13	-14.77
1673.2	-35.53	V	-1.53	-37.06	-13	-24.06
2509.8	-35.51	H	1.07	-34.44	-13	-21.44
2509.8	-38.39	V	0.93	-37.46	-13	-24.46
High Channel						
823.51	-73.91	H	11.25	-62.66	-13	-49.66
858.91	-73.71	V	11.03	-62.68	-13	-49.68
1697.6	-27.46	H	-1.88	-29.34	-13	-16.34
1697.6	-35.88	V	-1.50	-37.38	-13	-24.38
2546.4	-36.99	H	1.48	-35.51	-13	-22.51
2546.4	-38.74	V	1.35	-37.39	-13	-24.39
GSM 1900						
Test Frequency Rang: 30MHz~20GHz						
Low Channel						
823.51	-73.76	H	11.25	-62.51	-13	-49.51
858.91	-73.64	V	11.03	-62.61	-13	-49.61
3700.4	-51.13	H	2.86	-48.27	-13	-35.27
3700.4	-53.80	V	3.34	-50.46	-13	-37.46
Middle Channel						
823.51	-73.43	H	11.25	-62.18	-13	-49.18
858.91	-72.94	V	11.03	-61.91	-13	-48.91
3760	-52.94	H	3.33	-49.61	-13	-36.61
3760	-54.75	V	3.23	-51.52	-13	-38.52
High Channel						
823.51	-73.53	H	11.25	-62.28	-13	-49.28
858.91	-73.10	V	11.03	-62.07	-13	-49.07
3819.6	-52.14	H	3.85	-48.29	-13	-35.29
3819.6	-53.64	V	3.67	-49.97	-13	-36.97

Frequency (MHz)	Receiver Reading (dBm)	Rx Antenna Polar (H/V)	Substituted Factor (dB)	Absolute Level (dBm)	Limit (dBm)	Margin (dB)
WCDMA Band2						
Test Frequency Rang: 30MHz~20GHz						
Low Channel						
815.25	-73.06	H	11.19	-61.87	-13	-48.87
850.66	-72.66	V	10.68	-61.98	-13	-48.98
3704.8	-55.51	H	2.86	-52.65	-13	-39.65
3704.8	-57.66	V	3.31	-54.35	-13	-41.35
Middle Channel						
815.25	-73.47	H	11.19	-62.28	-13	-49.28
850.66	-72.29	V	10.68	-61.61	-13	-48.61
3760	-56.06	H	3.33	-52.73	-13	-39.73
3760	-58.23	V	3.23	-55.00	-13	-42.00
High Channel						
815.25	-73.19	H	11.19	-62.00	-13	-49.00
850.66	-72.37	V	10.68	-61.69	-13	-48.69
3815.2	-55.44	H	3.9	-51.54	-13	-38.54
3815.2	-57.97	V	3.72	-54.25	-13	-41.25
WCDMA Band4,						
Test Frequency Rang: 30MHz~18GHz						
Low Channel						
815.25	-72.63	H	11.19	-61.44	-13	-48.44
850.66	-72.45	V	10.68	-61.77	-13	-48.77
3424.8	-49.92	H	2.25	-47.67	-13	-34.67
3424.8	-57.72	V	2.33	-55.39	-13	-42.39
Middle Channel						
815.25	-72.80	H	11.19	-61.61	-13	-48.61
850.66	-72.74	V	10.68	-62.06	-13	-49.06
3465.2	-51.20	H	2.55	-48.65	-13	-35.65
3465.2	-56.61	V	2.48	-54.13	-13	-41.13
High Channel						
815.25	-72.62	H	11.19	-61.43	-13	-48.43
850.66	-72.62	V	10.68	-61.94	-13	-48.94
3502.2	-50.01	H	2.8	-47.21	-13	-34.21
3502.2	-56.05	V	2.77	-53.28	-13	-40.28

Frequency (MHz)	Receiver Reading (dBm)	Rx Antenna Polar (H/V)	Substituted Factor (dB)	Absolute Level (dBm)	Limit (dBm)	Margin (dB)
WCDMA Band5						
Test Frequency Rang: 30MHz~10GHz						
Low Channel						
815.25	-73.30	H	11.19	-62.11	-13	-49.11
850.66	-72.22	V	10.68	-61.54	-13	-48.54
1652.8	-36.11	H	-1.24	-37.35	-13	-24.35
1652.8	-43.16	V	-1.55	-44.71	-13	-31.71
2479.2	-50.62	H	1.04	-49.58	-13	-36.58
2479.2	-53.33	V	1.26	-52.07	-13	-39.07
Middle Channel						
815.25	-72.91	H	11.19	-61.72	-13	-48.72
850.66	-72.65	V	10.68	-61.97	-13	-48.97
1672.8	-31.91	H	-1.53	-33.44	-13	-20.44
1672.8	-42.22	V	-1.53	-43.75	-13	-30.75
2509.2	-50.06	H	1.07	-48.99	-13	-35.99
2509.2	-52.73	V	0.93	-51.80	-13	-38.80
High Channel						
815.25	-73.31	H	11.19	-62.12	-13	-49.12
850.66	-72.48	V	10.68	-61.80	-13	-48.80
1693.2	-33.33	H	-1.81	-35.14	-13	-22.14
1693.2	-41.13	V	-1.51	-42.64	-13	-29.64
2539.8	-46.86	H	1.41	-45.45	-13	-32.45
2539.8	-51.57	V	1.27	-50.30	-13	-37.30

Frequency (MHz)	Receiver Reading (dBm)	Rx Antenna Polar (H/V)	Substituted Factor (dB)	Absolute Level (dBm)	Limit (dBm)	Margin (dB)
LTEBand2						
Test Frequency Rang: 30MHz~20GHz						
QPSK 1.4MHz Bandwidth_ RB1#0						
Low Channel						
819.19	-72.80	H	11.32	-61.48	-13	-48.48
844.72	-72.09	V	10.43	-61.66	-13	-48.66
3701.4	-57.93	H	2.55	-55.38	-13	-42.38
3701.4	-55.93	V	2.64	-53.29	-13	-40.29
Middle Channel						
819.19	-72.56	H	11.32	-61.24	-13	-48.24
844.72	-71.80	V	10.43	-61.37	-13	-48.37
3760	-56.52	H	3.32	-53.20	-13	-40.20
3760	-57.90	V	3.23	-54.67	-13	-41.67
High Channel						
819.19	-72.69	H	11.32	-61.37	-13	-48.37
844.72	-71.61	V	10.43	-61.18	-13	-48.18
3818.6	-59.66	H	3.65	-56.01	-13	-43.01
3818.6	-57.26	V	3.71	-53.55	-13	-40.55
LTE Band4						
Test Frequency Rang: 30MHz~18GHz						
QPSK 1.4MHz Bandwidth_ RB1#0						
Low Channel						
819.19	-73.07	H	11.32	-61.75	-13	-48.75
844.72	-72.56	V	10.43	-62.13	-13	-49.13
3421.4	-44.12	H	2.41	-41.71	-13	-28.71
3421.4	-51.91	V	2.36	-49.55	-13	-36.55
Middle Channel						
819.19	-73.25	H	11.32	-61.93	-13	-48.93
844.72	-72.33	V	10.43	-61.90	-13	-48.90
3465	-46.50	H	2.53	-43.97	-13	-30.97
3465	-53.71	V	2.48	-51.23	-13	-38.23
High Channel						
819.19	-73.10	H	11.32	-61.78	-13	-48.78
844.72	-71.81	V	10.43	-61.38	-13	-48.38
3508.6	-46.91	H	2.86	-44.05	-13	-31.05
3508.6	-50.65	V	2.82	-47.83	-13	-34.83

Frequency (MHz)	Receiver Reading (dBm)	Rx Antenna Polar (H/V)	Substituted Factor (dB)	Absolute Level (dBm)	Limit (dBm)	Margin (dB)
LTE Band5						
Test Frequency Rang: 30MHz~10GHz						
QPSK 1.4MHz Bandwidth_ RB1#0						
Low Channel						
819.19	-72.64	H	11.32	-61.32	-13	-48.32
844.72	-71.86	V	10.43	-61.43	-13	-48.43
1649.4	-29.67	H	-1.65	-31.32	-13	-18.32
1649.4	-33.76	V	-1.69	-35.45	-13	-22.45
Middle Channel						
819.19	-72.84	H	11.32	-61.52	-13	-48.52
844.72	-72.14	V	10.43	-61.71	-13	-48.71
1673	-30.64	H	-1.51	-32.15	-13	-19.15
1673	-40.60	V	-1.53	-42.13	-13	-29.13
High Channel						
819.19	-72.50	H	11.32	-61.18	-13	-48.18
844.72	-71.49	V	10.43	-61.06	-13	-48.06
1696.6	-33.03	H	-1.32	-34.35	-13	-21.35
1696.6	-39.85	V	-1.29	-41.14	-13	-28.14
LTE Band7						
Test Frequency Rang: 30MHz~26GHz						
QPSK 5MHz Bandwidth_ RB1#0						
Low Channel						
819.19	-72.63	H	11.32	-61.31	-25	-36.31
844.72	-71.61	V	10.43	-61.18	-25	-36.18
5005	-50.25	H	5.91	-44.34	-25	-19.34
5005	-56.16	V	5.88	-50.28	-25	-25.28
4G BAND7, Middle Channel						
819.19	-72.60	H	11.32	-61.28	-25	-36.28
844.72	-72.24	V	10.43	-61.81	-25	-36.81
5070	-48.11	H	6.1	-42.01	-25	-17.01
5070	-54.59	V	6.03	-48.56	-25	-23.56
4G BAND7, High Channel						
819.19	-72.62	H	11.32	-61.30	-25	-36.30
844.72	-71.66	V	10.43	-61.23	-25	-36.23
5135	-47.78	H	6.24	-41.54	-25	-16.54
5135	-51.86	V	6.39	-45.47	-25	-20.47

Frequency (MHz)	Receiver Reading (dBm)	Rx Antenna Polar (H/V)	Substituted Factor (dB)	Absolute Level (dBm)	Limit (dBm)	Margin (dB)
LTE Band12						
Test Frequency Rang: 30MHz~8GHz						
QPSK 1.4MHz Bandwidth_ RB1#0						
Low Channel						
819.19	-73.20	H	11.32	-61.88	-13	-48.88
844.72	-72.45	V	10.43	-62.02	-13	-49.02
1399.4	-46.80	H	-1.34	-48.14	-13	-35.14
1399.4	-52.09	V	-1.56	-53.65	-13	-40.65
Middle Channel						
819.19	-72.59	H	11.32	-61.27	-13	-48.27
844.72	-72.18	V	10.43	-61.75	-13	-48.75
1415	-50.07	H	-1.30	-51.37	-13	-38.37
1415	-54.91	V	-1.41	-56.32	-13	-43.32
High Channel						
819.19	-72.97	H	11.32	-61.65	-13	-48.65
844.72	-71.82	V	10.43	-61.39	-13	-48.39
1430.6	-53.02	H	-1.27	-54.29	-13	-41.29
1430.6	-54.31	V	-1.26	-55.57	-13	-42.57
LTE Band13						
Test Frequency Rang: 30MHz~8GHz						
QPSK 5MHz Bandwidth_ RB1#0						
Low Channel						
819.19	-72.60	H	11.32	-61.28	-13	-48.28
844.72	-71.90	V	10.43	-61.47	-13	-48.47
1559	-40.66	H	-2.28	-42.94	-40	-2.94
1559	-41.55	V	-1.99	-43.54	-40	-3.54
High Channel						
819.19	-72.56	H	11.32	-61.24	-13	-48.24
844.72	-72.00	V	10.43	-61.57	-13	-48.57
1569	-41.10	H	-2.03	-43.13	-40	-3.13
1569	-42.18	V	-1.88	-44.06	-40	-4.06

Frequency (MHz)	Receiver Reading (dBm)	Rx Antenna Polar (H/V)	Substituted Factor (dB)	Absolute Level (dBm)	Limit (dBm)	Margin (dB)
LTE Band17						
Test Frequency Rang: 30MHz~8GHz						
QPSK 5MHz Bandwidth _ RB1#0						
Low Channel						
819.19	-73.41	H	11.32	-62.09	-13	-49.09
844.72	-72.14	V	10.43	-61.71	-13	-48.71
1413	-54.54	H	-1.31	-55.85	-13	-42.85
1413	-54.86	V	-1.43	-56.29	-13	-43.29
Middle Channel						
819.19	-73.25	H	11.32	-61.93	-13	-48.93
844.72	-72.14	V	10.43	-61.71	-13	-48.71
1420	-51.78	H	-1.29	-53.07	-13	-40.07
1420	-59.57	V	-1.36	-60.93	-13	-47.93
High Channel						
819.19	-73.35	H	11.32	-62.03	-13	-49.03
844.72	-72.37	V	10.43	-61.94	-13	-48.94
1427	-52.38	H	-1.28	-53.66	-13	-40.66
1427	-56.05	V	-1.3	-57.35	-13	-44.35
LTE Band25						
Test Frequency Rang: 30MHz~20GHz						
QPSK 1.4MHz Bandwidth _ RB1#0						
Low Channel						
819.19	-73.47	H	11.32	-62.15	-13	-49.15
844.72	-71.96	V	10.43	-61.53	-13	-48.53
3701.4	-52.43	H	2.86	-49.57	-13	-36.57
3701.4	-54.61	V	3.34	-51.27	-13	-38.27
Middle Channel						
819.19	-73.03	H	11.32	-61.71	-13	-48.71
844.72	-71.69	V	10.43	-61.26	-13	-48.26
3765	-54.32	H	3.44	-50.88	-13	-37.88
3765	-56.17	V	3.31	-52.86	-13	-39.86
High Channel						
819.19	-72.53	H	11.32	-61.21	-13	-48.21
844.72	-71.86	V	10.43	-61.43	-13	-48.43
3828.6	-56.25	H	3.65	-52.60	-13	-39.60
3828.6	-55.08	V	3.56	-51.52	-13	-38.52

Frequency (MHz)	Receiver Reading (dBm)	Rx Antenna Polar (H/V)	Substituted Factor (dB)	Absolute Level (dBm)	Limit (dBm)	Margin (dB)
LTE Band26_1(814MHz-824MHz)						
Test Frequency Rang: 30MHz~10GHz						
QPSK 1.4MHz Bandwidth_ RB1#0						
Low Channel						
819.19	-72.63	H	11.32	-61.31	-13	-48.31
844.72	-72.38	V	10.43	-61.95	-13	-48.95
1629.4	-59.40	H	-1.23	-60.63	-13	-47.63
1629.4	-63.89	V	3.27	-60.62	-13	-47.62
High Channel						
819.19	-72.64	H	11.32	-61.32	-13	-48.32
844.72	-72.02	V	10.43	-61.59	-13	-48.59
1646.6	-59.32	H	-1.2	-60.52	-13	-47.52
1646.6	-59.36	V	-1.55	-60.91	-13	-47.91
LTE Band26_2(824MHz-849MHz)						
Test Frequency Rang: 30MHz~10GHz						
QPSK 1.4MHz Bandwidth_ RB1#0						
Low Channel						
819.19	-72.54	H	11.32	-61.22	-13	-48.22
844.72	-71.96	V	10.43	-61.53	-13	-48.53
1649.4	-59.82	H	-1.2	-61.02	-13	-48.02
1649.4	-60.35	V	-1.55	-61.90	-13	-48.90
Middle Channel						
819.19	-72.41	H	11.32	-61.09	-13	-48.09
844.72	-72.48	V	10.43	-62.05	-13	-49.05
1663	-60.72	H	-1.23	-61.95	-13	-48.95
1663	-60.26	V	-1.54	-61.80	-13	-48.80
High Channel						
819.19	-72.88	H	11.32	-61.56	-13	-48.56
844.72	-72.27	V	10.43	-61.84	-13	-48.84
1696.6	-59.19	H	-1.87	-61.06	-13	-48.06
1696.6	-57.92	V	-1.5	-59.42	-13	-46.42

Frequency (MHz)	Receiver Reading (dBm)	Rx Antenna Polar (H/V)	Substituted Factor (dB)	Absolute Level (dBm)	Limit (dBm)	Margin (dB)
LTE Band26_3 (824MHz)						
Test Frequency Rang: 30MHz~10GHz						
QPSK 1.4MHz Bandwidth_ RB1#0						
Cross 90S and 22H Channel						
819.19	-72.44	H	11.32	-61.12	-13	-48.12
844.72	-72.50	V	10.43	-62.07	-13	-49.07
1648	-58.81	H	-1.2	-60.01	-13	-47.01
1648	-59.35	V	-1.55	-60.90	-13	-47.90
LTE Band38						
Test Frequency Rang: 30MHz~27GHz						
QPSK 5MHz Bandwidth_ RB1#0						
Low Channel						
819.19	-72.74	H	11.32	-61.42	-25	-36.42
844.72	-71.56	V	10.43	-61.13	-25	-36.13
5145	-50.79	H	5.14	-45.65	-25	-20.65
5145	-51.57	V	4.98	-46.59	-25	-21.59
Middle Channel						
819.19	-72.99	H	11.32	-61.67	-25	-36.67
844.72	-71.75	V	10.43	-61.32	-25	-36.32
5190	-51.89	H	5.48	-46.41	-25	-21.41
5190	-52.30	V	5.27	-47.03	-25	-22.03
High Channel						
819.19	-72.34	H	11.32	-61.02	-25	-36.02
844.72	-71.86	V	10.43	-61.43	-25	-36.43
5235	-52.40	H	5.91	-46.49	-25	-21.49
5235	-51.51	V	5.64	-45.87	-25	-20.87

Frequency (MHz)	Receiver Reading (dBm)	Rx Antenna Polar (H/V)	Substituted Factor (dB)	Absolute Level (dBm)	Limit (dBm)	Margin (dB)
LTE Band41_2						
Test Frequency Rang: 30MHz~27GHz						
QPSK 5MHz Bandwidth _RB1#0						
Low Channel						
819.19	-73.10	H	11.32	-61.78	-25	-36.78
844.72	-71.96	V	10.43	-61.53	-25	-36.53
5075	-49.73	H	5.16	-44.57	-25	-19.57
5075	-52.36	V	5.27	-47.09	-25	-22.09
Middle Channel						
819.19	-72.55	H	11.32	-61.23	-25	-36.23
844.72	-71.84	V	10.43	-61.41	-25	-36.41
5190	-50.90	H	5.5	-45.40	-25	-20.4
5190	-52.00	V	5.32	-46.68	-25	-21.68
High Channel						
819.19	-72.84	H	11.32	-61.52	-25	-36.52
844.72	-71.70	V	10.43	-61.27	-25	-36.27
5305	-53.85	H	5.81	-48.04	-25	-23.04
5305	-52.82	V	5.93	-46.89	-25	-21.89
LTE Band66						
Test Frequency Rang: 30MHz~18GHz						
QPSK 1.4MHz Bandwidth _ RB1#0						
Low Channel						
819.19	-72.51	H	11.32	-61.19	-13	-48.19
844.72	-72.41	V	10.43	-61.98	-13	-48.98
3421.4	-45.89	H	2.24	-43.65	-13	-30.65
3421.4	-47.91	V	2.33	-45.58	-13	-32.58
Middle Channel						
819.19	-73.28	H	11.32	-61.96	-13	-48.96
844.72	-71.99	V	10.43	-61.56	-13	-48.56
3490	-47.38	H	2.70	-44.68	-13	-31.68
3490	-52.12	V	2.68	-49.44	-13	-36.44
High Channel						
819.19	-73.10	H	11.32	-61.78	-13	-48.78
844.72	-71.91	V	10.43	-61.48	-13	-48.48
3558.6	-49.37	H	3.23	-46.14	-13	-33.14
3558.6	-51.28	V	3.06	-48.22	-13	-35.22

Note 1: Absolute Level = Reading Level + Substituted Factor

Note 2: Substituted Factor = Substituted Level - Cable loss+ Antenna Gain

Note 3: Margin = Absolute Level - Limit

Note 4: The data which below the 20 dB limit was not recorded.

FCC §22.917, §24.238, §27.53, §90.691-BAND EDGES

Applicable Standard

According to §22.917(a), the power of any emissions outside of the authorized operating frequency ranges must be attenuated below the transmitting power (P) by a factor of at least $43 + 10 \log(P)$ dB.

According to §24.238(a), the power of any emissions outside of the authorized operating frequency ranges must be attenuated below the transmitting power (P) by a factor of at least $43 + 10 \log(P)$ dB.

According to §27.53, the power of any emission outside of the authorized operating frequency ranges must be attenuated below the transmitting power (P) by a factor of at least $43 + 10 \log(P)$ dB.


Rule Part 90.691 specifies that “The power of any emission outside of the authorized operating frequency ranges must be attenuated below the transmitting power (P) by a factor of at least $43 + 10 \log(P)$ dB.

Test Procedure

According to ANSI C63.26-2015 Section 5.7.3:

- a) Set the spectrum analyzer center frequency to the block, band, or channel edge frequency.
- b) Set the span wide enough to capture the fundamental emission closest to the authorized block or band edge, and to include all modulation products that spill into the immediately adjacent frequency band. In some cases, it may be possible to set the center frequency and span so as to encompass the fundamental emission and the unwanted out-of-band (band-edge) emissions on either side of the authorized block, band, or channel. This can be accomplished with a single (slow) sweep, if adequate overload protection and sufficient dynamic range can be maintained.
- c) Set the number of points in sweep $\geq 2 \times \text{span} / \text{RBW}$.
- d) Sweep time should be auto for peak detection. For rms detection the sweep time should be set as follows:
 - 1) If the device can be configured to transmit continuously (duty cycle $\geq 98\%$), set the (sweep time) $> (\text{number of points in sweep}) \times (\text{symbol period})$ (e.g., by a factor of $10 \times \text{symbol period} \times \text{number of points}$). Increasing the sweep time (i.e., slowing the sweep speed) will allow for averaging over multiple symbols
 - 2) If the device cannot transmit continuously (duty cycle $< 98\%$), a gated sweep shall be used when possible (i.e., gate triggered such that the analyzer only sweeps when the device is transmitting at full power), set the sweep time $> (\text{number of points in sweep}) \times (\text{symbol period})$ but the sweep time shall always be maintained at a value that is less than or equal to the minimum transmission time.
 - 3) If the device cannot be configured to transmit continuously (duty cycle $< 98\%$) and a free-running sweep must be used, set the sweep time so that the averaging is performed over multiple on/off cycles by setting the sweep time $> (\text{number of points in sweep}) \times (\text{transmitter period})$ (i.e., the transmit on-time + the off-time). The spectrum analyzer readings shall subsequently be corrected by $[10 \log (1/\text{duty cycle})]$. This assumes that the transmission period and duty cycle is relatively constant (duty cycle variation $\leq \pm 2\%$).
 - 4) If the device cannot be configured to transmit continuously and a free-running sweep must be used, and if the transmissions exhibit a non-constant duty cycle (duty cycle variations $> \pm 2\%$), set the sweep time so that the averaging is performed over the on-period by setting the sweep time $> (\text{symbol period}) \times (\text{number of points})$, while also maintaining the sweep time $< (\text{transmitter on-time})$. The trace mode shall be set to max hold, since not every display point will be averaged only over just the on-time. Thus, multiple sweeps (e.g., 100) in maximum hold are necessary to ensure that the maximum power is measured.

- e) The test report shall include the plots of the measuring instrument display and the measured data.
- f) See Annex I for example emission mask plots.



Note: the path loss (cable loss and splitter inset loss) among the test frequency range has including in test plot.

Test Data

Please refer to the Appendix.

FCC §2.1055, §22.355, §24.235, §27.54, §90.213-FREQUENCY STABILITY**Applicable Standard**

FCC §2.1055, §22.355, §24.235, §27.54, §90.213

According to §2.1055, the frequency stability shall be sufficient to ensure that the fundamental emissions stay within the authorized bands of operation.

According to §22.355, the carrier frequency of each transmitter in the Public Mobile Services must be maintained within the tolerances given in Table below:

Table C-1—Frequency Tolerance for Transmitters in the Public Mobile Services

Frequency range (MHz)	Base, fixed (ppm)	Mobile >3 watts (ppm)	Mobile ≤3 watts (ppm)
25 to 50	20.0	20.0	50.0
50 to 450	5.0	5.0	50.0
450 to 512	2.5	5.0	5.0
821 to 896	1.5	2.5	2.5
928 to 929	5.0	n/a	n/a
929 to 960	1.5	n/a	n/a
2110 to 2220	10.0	n/a	n/a

According to §24.235&§27.54, the frequency stability shall be sufficient to ensure that the fundamental emissions stays within the authorized frequency block.

According to §90.213, (a) unless noted elsewhere, transmitters used in the services governed by this part must have a minimum frequency stability as specified in the following table.

Table 1 to § 90.213(a)–Minimum Frequency Stability

[Parts per million (ppm)]

Frequency range (MHz)	Fixed and base stations	Mobile stations	
		Over 2 watts output power	2 watts or less output power
Below 25	^{1 2 3} 100	100	200
25–50	20	20	50
72–76	5		50
150–174	^{5 11} 5	⁶ 5	^{4 6} 50
216–220	1.0		1.0
220–222 ¹²	0.1	1.5	1.5
421–512	^{7 11 14} 2.5	⁸ 5	⁸ 5
806–809	¹⁴ 1.0	1.5	1.5
809–824	¹⁴ 1.5	2.5	2.5
851–854	1.0	1.5	1.5
854–869	1.5	2.5	2.5
896–901	¹⁴ 0.1	1.5	1.5
902–928	2.5	2.5	2.5
902–928 ¹³	2.5	2.5	2.5
929–930	1.5		
935–940	0.1	1.5	1.5
1427–1435	⁹ 300	300	300
Above 2450 ¹⁰			

¹ Fixed and base stations with over 200 watts transmitter power must have a frequency stability of 50 ppm except for equipment used in the Public Safety Pool where the frequency stability is 100 ppm.

² For single sideband operations below 25 MHz, the carrier frequency must be maintained within 50 Hz of the authorized carrier frequency.

³ Travelers information station transmitters operating from 530–1700 kHz and transmitters exceeding 200 watts peak envelope power used for disaster communications and long distance circuit operations pursuant to [§ 90.242](#) and [90.264](#) must maintain the carrier frequency to within 20 Hz of the authorized frequency.

⁴ Stations operating in the 154.45 to 154.49 MHz or the 173.2 to 173.4 MHz bands must have a frequency stability of 5 ppm.

⁵ In the 150–174 MHz band, fixed and base stations with a 12.5 kHz channel bandwidth must have a frequency stability of 2.5 ppm. Fixed and base stations with a 6.25 kHz channel bandwidth must have a frequency stability of 1.0 ppm.

⁶ In the 150–174 MHz band, mobile stations designed to operate with a 12.5 kHz channel bandwidth or designed to operate on a frequency specifically designated for itinerant use or designed for low-power operation of two watts or less, must have a frequency stability of 5.0 ppm. Mobile stations designed to operate with a 6.25 kHz channel bandwidth must have a frequency stability of 2.0 ppm.

⁷ In the 421–512 MHz band, fixed and base stations with a 12.5 kHz channel bandwidth must have a frequency stability of 1.5 ppm. Fixed and base stations with a 6.25 kHz channel bandwidth must have a frequency stability of 0.5 ppm.

⁸ In the 421–512 MHz band, mobile stations designed to operate with a 12.5 kHz channel bandwidth must have a frequency stability of 2.5 ppm. Mobile stations designed to operate with a 6.25 kHz channel bandwidth must have a frequency stability of 1.0 ppm.

⁹ Fixed stations with output powers above 120 watts and necessary bandwidth less than 3 kHz must operate with a frequency stability of 100 ppm. Fixed stations with output powers less than 120 watts and using time-division multiplex, must operate with a frequency stability of 500 ppm.

¹⁰ Frequency stability for DSRCS equipment in the 5895–5925 MHz band is specified in [subpart M of this part](#). For all other equipment, frequency stability is to be specified in the station authorization.

¹¹ Paging transmitters operating on paging-only frequencies must operate with frequency stability of 5 ppm in the 150–174 MHz band and 2.5 ppm in the 421–512 MHz band.

¹² Mobile units may utilize synchronizing signals from associated base stations to achieve the specified carrier stability.

¹³ Fixed non-multilateration transmitters with an authorized bandwidth that is more than 40 kHz from the band edge, intermittently operated hand-held readers, and mobile transponders are not subject to frequency tolerance restrictions.

¹⁴ Control stations may operate with the frequency tolerance specified for associated mobile frequencies.

(b) For the purpose of determining the frequency stability limits, the power of a transmitter is considered to be the maximum rated output power as specified by the manufacturer.

Test Procedure

According to ANSI C63.26-2015 Section 5.6:

Frequency stability is a measure of the frequency drift due to temperature and supply voltage variations, with reference to the frequency measured at +20 °C and rated supply voltage.

The operating carrier frequency shall be set up in accordance with the manufacturer's published operation and instruction manual prior to the commencement of these tests. No adjustment of any frequency determining circuit element shall be made subsequent to this initial set-up. Frequency stability is tested:

- a) At 10 °C intervals of temperatures between -30 °C and +50 °C at the manufacturer's rated supply voltage, and
- b) At +20 °C temperature and $\pm 15\%$ supply voltage variations. If a product is specified to operate over a range of input voltage then the -15% variation is applied to the lowermost voltage and the +15% is applied to the uppermost voltage.

During the test all necessary settings, adjustments and control of the EUT have to be performed without disturbing the test environment, i.e., without opening the environmental chamber. The frequency stabilities can be maintained to a lesser temperature range provided that the transmitter is automatically inhibited from operating outside the lesser temperature range. For handheld equipment that is only capable of operating from internal batteries and the supply voltage cannot be varied, the frequency stability tests shall be performed at the nominal battery voltage and the battery end point voltage specified by the manufacturer. An external supply voltage can be used and set at the internal battery nominal voltage, and again at the battery operating end point voltage which shall be specified by the equipment manufacturer.

If an unmodulated carrier is not available, the mean frequency of a modulated carrier can be obtained by using a frequency counter with gating time set to an appropriately large multiple of bit periods (gating time depending on the required accuracy). Full details on the choice of values shall be included in the test report.



Test Data

Please refer to the Appendix.

APPENDIX

Frequency band	Remark
GSM	Refer to the 2504S23848E-RF-00F-Appendix A-GSM.
WCDMA	Refer to the 2504S23848E-RF-00F-Appendix B-WCDMA.
LTE	Refer to the 2504S23848E-RF-00F-Appendix C-LTE.

EXHIBIT A-EUT PHOTOGRAPHS

Please refer to the Annex: 2504S23848E-RF EUT EXTERNAL PHOTOGRAPHS and 2504S23848E-RF EUT INTERNAL PHOTOGRAPHS.

EXHIBIT B-TEST SETUP PHOTOGRAPHS

Please refer to the Attachment: 2504S23848E-RF-00F TEST SETUP PHOTOGRAPHS.

******* END OF REPORT *******