

RF Exposure Report

FCC-ID: 2AMG8WT-RT8501

RF Exposure Measurement

The limit for Maximum Permissible Exposure (MPE) specified in FCC 1.1310 is followed. The gain of the antennas used in the product is extracted from the Antenna data sheets provided and also the maximum total power input to the antenna is measured. Through the Friis transmission formula and the maximum gain of the antenna, we can calculate the distance, away from the product, where the limit of MPE is reached.

Although the Friis Transmission formula is far field assumption, the calculated result of that is an over-prediction for near field power density. It is taken as worst case to specify the safety range.

RF Exposure Limit

According to FCC 1.1310: The criteria listed in the following table shall be used to evaluate the environmental impact of the human exposure to radio-frequency (RF) radiation as specified in 1.1307 (b)

Frequency Range (MHz)	Electric Field Strength (V/m)	Magnetic Field Strength (A/m)	Power Density (mW/cm ²)
Limits for Occupational / controlled Exposures			
300 - 1500	--	--	F/300
1500 – 100000	--	--	5.0
Limits for General population / Uncontrolled Exposure			
300 - 1500	--	--	F/1500
1500 – 100000	--	--	1.0
Limits for Maximum Permissible Exposure (MPE)			

F= Frequency in MHz

Friss Formula

Friss Transmission Formula: $P_d = (P_{out} * G) / (4\pi r^2)$

Where

P_d = power density in mW/cm^2

P_{out} = output power to antenna in mW

G = gain of antenna in linear scale

$\pi = 3.1416$

R = Distance between observation point and the center of radiator in cm

If we know the maximum gain of the antenna and the total output power to the antenna, through calculation, we will know MPE value at distance 20cm.

EUT Operation condition

EUT was enabled to transmit and receive at lowest, middle and highest channels.

Classification

The antenna of this product, under normal use condition, is at least 20cm away from the body of the user. Warning statement to the user for keeping at least 20cm or more separation distance from the antenna should be included in the User manual. So, this device is classified as Mobile device.

2.4G WIFI

Mode	802.11b/g/n20: 2412-2462MHz 802.11n40: 2422-2452MHz
Detector	PEAK
802.11b	12±1dBm
802.11g	11±1dBm
802.11n20	14±1dBm
802.11n40	13±1dBm

Note: 802.11b/g is SISO technology

802.11n20/n40 is MIMO technology

ANT Gain (G)

Antenna number: 2*Dipole

Antenna A gain : 5dBi

Antenna B gain : 5dBi

SISO technology Directional gain= 5dBi

(gain of antenna in linear scale=3.162)

MIMO technology Directional gain= 8.01dBi

(gain of antenna in linear scale=6.324)

Protocol	ANT Gain(gain of antenna in linear scale)	Channel Frequency (MHz)	Output Power to Antenna (dBm)	Output Power to Antenna (mW)	Power Density (mW/cm ²)	Limit (mW/cm ²)
802.11 b	3.162	2412	13	19. 9526	0. 01256	1
802.11 g	3.162	2412	12	15. 8489	0. 00997	1
802.11 n20	6.324	2412	15	31. 6228	0. 03981	1
802.11 n40	6.324	2422	14	25. 1189	0. 03162	1

5G WIFI

ANT Gain (G)

Mode	IEEE 802.11a/ n/ac(HT20) 5.180GHz-5.240GHz IEEE 802.11n/ac(HT40) 5.190GHz-5.310GHz IEEE 802.11ac(HT80) 5.210GHz
Detector	PEAK
802.11 a(HT20)	15±1dBm
802.11 n/ac(HT20)	18±1dBm
802.11 n/ac(HT40)	17±1dBm
802.11 ac(HT80)	17±1dBm

Note: 802.11 a(HT20) is SISO technology

802.11 n/ac(HT20), 802.11 n/ac(HT40), 802.11 ac(HT80)

is MIMO technology

ANT Gain (G)

Antenna number: 2*Dipole

Antenna A gain : 5dBi

Antenna B gain : 5dBi

SISO technology Directional gain= 5dBi

(gain of antenna in linear scale=3.162)

MIMO technology Directional gain= 8.01dBi

(gain of antenna in linear scale=6.324)

Protocol	ANT Gain(gain of antenna in linear	Channel Frequency (MHz)	Output Power to Antenna (dBm)	Output Power to Antenna (mW)	Power Density (mW/cm ²)	Limit (mW/cm ²)
802.11 a(HT20)	3.162	5240	16	39. 8107	0. 02506	1
802.11 n/ac(HT20)	6.324	5240	19	79. 4328	0. 09999	1
802.11 n/ac(HT40)	6.324	5230	18	63. 0957	0. 07942	1
802.11 ac(HT80)	6.324	5210	18	63. 0957	0. 07942	1

5G WIFI

ANT Gain (G)

Mode	IEEE 802.11a/ n/ac(HT20)5.745GHz-5.825GHz IEEE 802.11a/ n/ac(HT40)5.755GHz-5.795GHz IEEE 802.11ac(HT80) 5.775GHz
Detector	PEAK
802.11 a (HT20)	10±1dBm
802.11 a/n/ac(HT20)	13±1dBm
802.11 n/ac(HT40)	13±1dBm
802.11 ac(HT80)	12±1dBm

Note: 802.11 a(HT20) is SISO technology

802.11 n/ac(HT20), 802.11 n/ac(HT40), 802.11 ac(HT80)

is MIMO technology

ANT Gain (G)

Antenna number: 2*Dipole

Antenna A gain : 5dBi

Antenna B gain : 5dBi

SISO technology Directional gain= 5dBi

(gain of antenna in linear scale=3.162)

MIMO technology Directional gain= 8.01dBi

(gain of antenna in linear scale=6.324)

Protocol	ANT Gain(gain of antenna in linear scale)	Channel Frequency (MHz)	Output Power to Antenna (dBm)	Output Power to Antenna (mW)	Power Density (mW/cm ²)	Limit (mW/cm ²)
802.11	3.162	5745	11	12. 5893	0. 00792	1
802.11 a/n/ac(HT20)	6.324	5745	14	25. 1189	0. 03162	1
802.11 n/ac(HT40)	6.324	5755	14	25. 1189	0. 03162	1
802.11	6.324	5775	13	19. 9526	0. 02512	1

Note:2.4G WIFI & 5G WIFI are Simultaneous launch,

2.4G WIFI Max Power Density + 5G WIFI Max Power Density = 0.03981 + 0.09999

1

1

1

1

=0.1398(mW/cm²)<1mW/cm², Meet the limit requirements