

正面

反面

HiBy Music App R2 II works better together with the HiBy Music Android / iOS app. It supports WiFi music transfer and transmits songs on mobile phones, computers and tablets to the R2 II via a shared WiFi. HiByLink remote control function connects to and controls the R2 II via mobile phone Bluetooth. Change tracks, select songs, manage songs remotely. Scan the QR code here to download the HiBy Music app. 	USB DAC 1. Please go to the official website(www.hiby.com) to download the driver zip file and guidance. 2. To use the R2 II as USB DAC, you need to be set "USB mode" to "Audio" in the system settings and connect to the computer with the supplied USB data cable. Portal capabilities 1. R2 II as a Bluetooth sound card: USB → R2 II → Bluetooth headphones; when using the R2 II as a USB DAC, you can also use Bluetooth headphones / speakers to listen	to the music; supports LDAC 96kHz, and UAT at the maximum of 192kHz; 2. R2 II as a digital source from Bluetooth input: Bluetooth audio → R2 II → USB audio; when connected to e.g. your smartphone via Bluetooth audio, the R2 II can also be a high quality digital audio; supports coaxial digital output, or USB Audio output, supports LDAC 96kHz, and UAT at the maximum of 192kHz; 3. R2 II as a digital source from WiFi input: Using DLNA on the Android system (BubbleUPnP and other apps), or AirPlay on the iOS system (integrated in system	slide-up menu), send music via WiFi to the R2 II, which can then become a lossless quality digital audio source; supports coaxial digital output, or USB Audio output. Wireless capabilities 1. WiFi: Support 2.4GHz WiFi Support. music transmission via WiFi, HiByLink (requires HiBy Music app), DLNA, Airplay, OTA online update, internet radio; TIDAL and Qobuz streaming apps (appear when system language other than simplified Chinese is selected). 2. Bluetooth: Supports Bluetooth 5.1,	supports a variety of high-definition Bluetooth protocols including UAT, LDAC,aptX and so on. Firmware update 1.OTA upgrade: Turn on WiFi in wireless settings and connect to WiFi, tap "Systemsettings"→"Firmware update"→ "Via OTA". Then the R2 II will get updated. 2.Manual update: Go to official website (www.hiby.com) to download the corresponding firmware, place R2II.upt in the root directory of micro SD card (i.e.outside of any subdirectories),insert the micro SD card into the R2 II, tap "System	settings" → "Firmware update" → " via SD-card". Then the R2 II will get updated. For further in-depth operation instructions, please scan the following QRcode: 	FCC WARNING "This device complies with Part 15 of the FCC Rules.Operation is subject to the following two conditions:(1)this device may not cause harmful interference, and(2)this device must accept any interference received. Includinginterference:that may cause undesired operation changes or modifications not expressly approved by the partyresponsible for compliance could void the user's authority to operate the equipment.NOTE: This equipment is a Class B digital device, pursuant to Part 15.005 of the FCC Rules. These limitsare designed to provide reasonableprotection against harmful interference in residential installation.This equipment generates uses and can radiate radiofrequencyenergy and, if not installed and used in accordance withtheinstructions, may cause harmful interference to radiocommunications.However,there is no guarantee that interferencewill not occur in a particularinstallation. If this equipment,do not scan be determined. HiBy red capat interference by one or more of the following measures: Reorient or relocate the receiving antenna. — Increase the separation between the equipment and receiver. — Connect the equipment into an outlet on a circuit different from that to whichthe receiver is connected. — Consult the dealer or an experienced radio/TV technician for help. FCC Radiation Exposure Statement: The device has been evaluated to meet general RF exposure requirement. The device can be used in portable exposure condition withoutrestriction."
Cautions 1. Do not repair, disassemble, or place the product in a place with water. 2. When the product is not used for a long time, it is necessary to periodically charge the product to ensure battery life. 3. When you use the headphones, you will not be able to hear the external environment. For your safety, please avoid using the headphones in a dangerous environment. 4. Charging with a charger with too high voltage may damage the device. Please choose a recommended charger to charge. 5. Hold the power button for 30 seconds to force restart the device if the system crashes.	注意事項 ● 不可擅自維修、拆卸和將產品放在有水的地方。 ● 當長期沒有使用本產品時，需要定期給產品充電，以保证電池壽命。 ● 請配用电压过高的充电器有可能会损坏机器，请选择标有使用的充电器进行充电。 ● 长期发生音频导致耳机时，可尝试长按电源键30秒，强制重启机器。 电池使用注意事项 ● 如果电池长时间没有使用存在危险。 ● 充电时请避免受潮或避免发热的情况发生。 ● 充电时请避免受潮或避免发热的情况发生。 ● 电池（电池包或充电电池）不得暴露在阳光、火源或液体接触环境中。 ● 请避免将使用电源适配器供电，避免因影响使用导致CCC认证失效及被要求更改电源适配器。	想知道我们更多产品信息？ To learn more  WeChat 微信关注  Weibo-SINA 微博关注  Facebook 脸书关注	HiBy官方直营店 HiBy Official Online Store  官方天猫店Tmall https://mall.tmall.com  官方京东商城JD.com https://mall.jd.com/index-852084.html  国内官网Website www.hiby.com	全國售後 請撥打 400-8820-032 或 直接諮詢您購買的店舖 Global after-sales service Please contact us at service@hiby.com or directly contact the store you purchased from.	东莞市敬动电子科技有限公司 服务热线：400-8820-032 / 086-769-23182216 官方网址：www.hiby.com 电子邮箱：service@hiby.com 生产地址：东莞市南城街道宏伟三路39号聚龙大厦12楼 DONGGUAN SMARTACTION TECHNOLOGY CO.,LTD. TEL: 0086-769-23182216 Website: www.hiby.com Email: service@hiby.com Address: Room 1201, Lianjing Commercial Building, No.39, Hongwei 3rd Road,Nancheng District, Dongguan, Guangdong, China	