

INSTRUCTION MANUAL

PA-1200



INDEX

OPERATION.....	1
GENERAL USE INSTRUCTIONS.....	2
SPECIFICATIONS.....	3
CONTROLS AND CONNECTIONS.....	3

OPERATION

1. Prior to switching on, turn volume down to minimum.
2. Connect the audio source to the appropriate input socket.
3. Connect to the mains supply.
4. Switch on the audio source, followed by the active speaker.
5. Set the volume with the applicable control.
6. Adjust the bass + treble.
7. Bluetooth connection instruction

Select “BT” mode of the mp3
 Open Bluetooth function on your pairing device and find PA15.
 Select PA15 to complet pairing.
 Input passwort “0000” if ask for
 Select the song and play through your mobile

INSTRUCTIONS

Do not overload the box to avoid damage to the speaker.
 Do not place an open fire (candles etc) on top or next to the box - FIRE HAZARD
 Only connect to an earthed mains outlet of 120V 60Hz.
 For indoor use only. If the box is used outdoors,you need to make sure that no humidity can enter the box.
 When not in use,unplug the unit from the mains.
 Unplug the unit from the mains prior to checking or replacing fuse.
 Make sure that the box is placed on a stable,strong surface.
 The boxes can be hung. Use only strong and approved mounting material.During the mounting, make sure that nobody is standing below the mounting area.
 Do not place liquids on the box and protect it against humidity. Humidity can shorten the life time considerably.
 Only use suitable means of transportation if you want to move the box - BEWARE OF YOUR BACK!!
 Always unplug the unit during a thunderstorm or when it is not use.
 If the unit has not been used for a long period of time, condensation can occur inside the housing. Please let the unit reach room temperature prior to use.
 Never try to repair the unit yourself. It does not contain any user serviceable parts.
 Run the mains lead in such a way that nobody can fall over it and nothing can be put in it.
 Set the unit to the lowest volume prior to switching it on.
 Keep the unit out of the reach of children.

SPECIFICATIONS

	3*6.5” Speaker box
System	Active 2-way fullrange
Woofer	3*6.5”
Tweeter	1”
Impedance	4 ohm
Frequency Range	78Hz-18KHz
Sensitivity	90dB(+/-2dB)V
Connector	XLR/6.35mm/RCA
Mic Input Level	≤15mV
Line input/output level	≥250m

CONTROLS LOCATION



1. LCD screen

2. Mp3 control

MODE:USB/SD/BT convertor

▶|| :Play / Pause

⌚ :Repeat one / Repeat all / Random

Long hold to search lower/ higher station manually

⏮ :Previous Song

Long press for fast rewind

⏭ :Next Song

Long press for fast forward

3. SD card input

4. USB input

5. MIC level control

6. Line input level control

7. Volume control

8. Clip LED indicator

9. Power LED indicator

10. XLR microphone1 input

11. 6.35mm microphone2 input

12. XLR line input

13. RCA phone(R+L) line input

14. 3.5mm line input

15. XLR line output

16. LED Light Switch(ON/OFF)

- 17.120V
- 18.Main power switch
- 19.Fused IEC mains inlet

FCC Statement

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions:(1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

RSS-Gen Issue 3 December 2010" & "CNR-Gen 3e édition Décembre 2010:

- English:

This device complies with Industry Canada licence-exempt RSS standard(s). Operation is subject to the following two conditions: (1) This device may not cause interference, and (2) This device must accept any interference, including interference that may cause undesired operation of the device.

- French:

Le présent appareil est conforme aux CNR d'Industrie Canada applicables aux appareils radio exempts de licence.

L'exploitation est autorisée aux deux conditions suivantes:

- (1) l'appareil ne doit pas produire de brouillage, et
- (2) l'utilisateur de l'appareil doit accepter tout brouillage radioélectrique subi, même si le brouillage est susceptible d'en compromettre le fonctionnement.