1:1

180mm

90mm

Power Folio Instruction Manual

Please read the following carefully before using the device to ensure safe and proper usage.

Package Content:

1x Power bank
1x 2-in-1 iPhone and Android USB C charging cable
1x User Manual



Note: The power bank will be sucked together with case by the magnets inside the power bank and case.

Specifications:

Capacity: 10000mAh/3.7V
Input (USB-C): 5V/3A , 9V/2A , 12V/1.5A
Output: total 22.5W
Output (USB-C): 5V/3A , 9V/2.22A , 12V/1.67A
Wireless: 5W/7.5W/10W/15W Max with magnetic
USB-C+ Wireless: 5V/3A
LED display

Charging your device using your power bank:

IMPORTANT: Before using your power bank for the first time, fully charge it (when powered on, the LED displays 100%).

Connect the supplied 2-in-1 cable (or the cable that came with your device) to the power bank's USB port and to your device. Then begin charging.

During charging of your device, the percentage of battery's power will gradually decrease as your device receives power, when the power bank is low in power, the percentage will flash and go out automatically until all the power is used up.

The green charging icon in the LED display will light up once you enter fast charging mode.

正面（Front）

Checking Your Power bank Battery's Charging Status

Momentarily press the power button on your power bank and the percentage of battery life remaining will appear on the LED display, 100% means that the power bank battery is fully charged, while 5% or under indicates that it's almost empty. Know before you go!

If you see the percentage is flashing, the battery status is less than 5%. Please recharge the power bank.

Recharging your power bank:

To recharge your power bank, use the supplied 2-in-1 cable to connect its USB-C port to a USB wall charging adapter. While recharging the power bank, the last digit of the percentage will blink. If there is one digit flashing, the charging is not completed. Once the power bank is fully charged, the 100% is displayed.

The green charging icon in LED will light up once you enter fast charging mode.

NOTE: For best results, do not connect the power bank to a computer's USB port. We recommend using a wall charging adapter that supports fast charging protocols such as QC or PD.

Wireless charging:

Press and release the button, when the red LED remains illuminated, place your wireless charging compatible smartphone on the charging surface with magnet, the blue LED ndicator will light up once the unit enters wireless charging mode.

To stop the wireless charging function, press the button twice quickly or simply remove the smartphone.

If the smartphone that supports wireless charging is not detected within 30s, the unit will automatically turn off the wireless output. It will automatically turn off if no load is detected within one minute.

Note: it can support wireless charging when the notebook is open or close, you should make sure the wireless icon in notebook and power bank are positioned correctly. We suggest you remove the protective case when the notebook is close during charging.

Security advice:

Attention
-Incorrect usage can cause explosions / danger of chemical burns.
-Damaged batteries can cause chemical burns when they come in contact with human skin.
-Do not disassemble the item
-Never throw the item or parts of it into fre
-Never expose the item to high temperature changes Hot/Cold, humidity or liquids
-Do not use if the items or parts of it are damaged
-Store in a clean and dry space
-To maintain battery good health t, the item should be recharged every 6 months. Battery will loose capacity when stored without charging.
-If the product gets very hot, please disconnect the item and do not use it.
-Do not put any bare metal objects on the surface of wireless charger when it is operating.

背面（Back）

180 x 90mm 70g书纸 双面印刷 对折1次

1:1

FCC STATEMENT :

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:

(1) This device may not cause harmful interference, and

(2) This device must accept any interference received, including interference that may cause undesired operation.

Warning:Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

NOTE:This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules.These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation.If this equipment does cause harmful interference to radio or television reception,which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:
Reorient or relocate the receiving antenna.
Increase the separation between the equipment and receiver .
Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
Consult the dealer or an experienced radio/TV technician for help.

FCC Radiation Exposure Statement:

The device has been evaluated to meet general RF exposure requirement. The device can be used in portable exposure condition without restriction.

FCC

FCC STATEMENT

标准说明书	JMTek	图号	NP100-SMS-JMT001	版次	第1版	材料		颜色		单位	mm
		型号	NP100	日期	240522	设计	Steven	批准		客户回签	
		料号		第三角度投影				第 1 张共 1 张			