

Smart Switch User manual

Alexa TUTORIAL

Google Home TUTORIAL

Attention:

1. Please scan QR code by camera or 2. QR Code Reader don't support the QR code with right edge. 3. Please set your home WIFI account name and passwords use numeric and letters. 4. Don't use special symbols.

1

1.Installation
Separate the upper and lower parts from the switch by screwdriver.

See the picture below

(Noted:Distinguish between each corresponding slot)

2

2a. Without neutral wire version(No neutral wire is required on the switch) according to the following diagram wiring.

1-Neutral wire.
2-Live wire.
3-Switch.
4-Capacitor,it must be connected to L1 and Neutral wire.
5.6.7.8-Lighting.They're between L1,L2,L3,L4 and Neutral wire.

2b. With neutral wire version (Neutral wire is required on the switch)according to the following diagram wiring.

1-Neutral wire.
2-Live wire.
3-Switch.
4.5.6.7-Lighting.They're between L1,L2,L3,L4 and Neutral wire.

1Gang Smart Switch

Rated voltage: 100-240V
Wifi type: 2.4Ghz
Operating temperature: -10~45℃
Rated power: 1000-2400
Load current: 10A
SIZE:72*118*35mm

2Gang Smart Switch

Rated voltage: 100-240V
Wifi type: 2.4Ghz
Operating temperature: -10~45℃
Rated power: 1000-2400
Load current: 10A
SIZE:72*118*35mm

3Gang Smart Switch

Rated voltage: 100-240V
Wifi type: 2.4Ghz
Operating temperature: -10~45℃
Rated power: 1000-2400
Load current: 10A
SIZE:72*118*35mm

4Gang Smart Switch

Rated voltage: 100-240V
Wifi type: 2.4Ghz
Operating temperature: -10~45℃
Rated power: 1000-2400
Load current: 10A
SIZE:72*118*35mm

Indicator Light

L1 button L2 button
L3 button L4 button

3. Fix the switch onto wall.
3.1 Put the switch lower parts into switch box in the wall.
3.2 Mount the two side screws.
3.3 Install the upper top case (install from up above).
3.4 Cover the upper top case into switch.
3.5 Turn on electricity, and then LED light will be flashed quickly for pairing.

3

4. Indicator light status.

4.1. The WIFI indicator light went out.
-The switch is connected succeed with mobile phone APP.
4.2. The WIFI indicator light blinking slowly.
- The switch is not connected to the network.
4.3. The WIFI indicator light flash continuously and quickly.
- The switch is currently on the status of matching with mobile phone APP.
4.4. The WIFI indicator light flash 1 time every 3 seconds.
-The switch is into AP pairing Mode.
4.5. How to reset the switch ?
-Long press any button for 10-12seconds.

4.6. How to download App?
Scan the QR code below or search for doodle intelligence in the IOS APP store or Google play.

IOS & Android System

4

5. Setting doodle SMART APP. How to Register and Login?

5.1 Download or Scan the QR Code and install Smart Life App.
5.2 Once download or Scan the QR Code, the App will ask you to register your device.

Register

China 186
Mobile number or email address
Phone verification code
Next

5.3 Enter your phone number or email which you prefer and select the country you live in.
5.4 Obtain verification code.
5.5 Enter verification code.
5.6 Set Password.

Enter verification code

Set Password
9-30 characters, including letters and numbers
Completed

5

5.7 Create family.
5.8 Enter the family name and select the room.
5.9 Family create successfully.

Add family

Family Name: JASON
Family Location: Set location
Smart devices in rooms:
Living Room
Bedroom
Second Bedroom
Dining Room
Family created successfully
View family Completed

6

6. Switch pairing.

6.1 First the phone needs to turn on.
6.2 Connect the switch with power.
6.3 Open App and tap Add Device or upper right corner "+". The APP interface will pop up a window: discover the devices to be added, you can choose to add/do not add, or select "Switch" to add.

Welcome Home

All Devices
Living Room Bedroom
Add Device

Welcome Home

All Devices
Living Room Bedroom
Devices to be added: 1
WSD4-1
Do not add Go to add

7

6.5 Select "+" then entering the WIFI password.

Add Device

Bluetooth device
WSD4-1
Enter Wi-Fi Password
2.4GHz 5GHz
Only 2.4G Wi-Fi networks are supported
DianLing840 Any
Cancel Confirm

8

6.6 Waiting for the connection and it is finished connection.

Add Device

Connecting...
2%
Please your mobile phone, and device as close as possible
Device found
Signal strength: Strong (Good)
Connecting device

Added successfully
WSD4-1
Devices added successfully
Living Room Bedroom
Second Bedroom
Dining Room Kitchen
Study Room

9

FCC Warning

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:
(1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.
NOTE 1: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:
- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

NOTE 2: Any changes or modifications to this unit not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.
RF Exposure Statement
To maintain compliance with FCC's RF Exposure guidelines, This equipment should be installed and operated with minimum 20cm between the radiator and your body. This device and its antenna(s) must not be co-located or operation in conjunction with any other antenna or transmitter

10

11

12

13