










11B_Ant1_2462_30~1000




11B_Ant1_2462_1000~26500




11G_Ant1_2412_0~Reference




11G_Ant1_2412_30~1000




11G_Ant1_2412_1000~26500




11G_Ant1_2437_0~Reference




11G_Ant1_2437_30~1000




11G_Ant1_2437_1000~26500




11G_Ant1_2462_0~Reference




11G_Ant1_2462_30~1000




11G_Ant1_2462_1000~26500




11N20SISO_Ant1_2412_0~Reference




11N20SISO_Ant1_2412_30~1000




11N20SISO_Ant1_2412_1000~26500




11N20SISO_Ant1_2437_0~Reference







11N20SISO_Ant1_2462_30~1000




11N20SISO_Ant1_2462_1000~26500




11N40SISO_Ant1_2422_0~Reference




11N40SISO_Ant1_2422_30~1000




11N40SISO_Ant1_2422_1000~26500




11N40SISO_Ant1_2437_0~Reference




11N40SISO_Ant1_2437_30~1000




11N40SISO_Ant1_2437_1000~26500




11N40SISO_Ant1_2452_0~Reference



11N40SISO_Ant1_2452_30~1000




11N40SISO_Ant1_2452_1000~26500



10. Duty Cycle

10.1. Block diagram of test setup



10.2. Limit

Just for Report.

10.3. Test procedure

- (1) Connected the EUT's antenna port to the Spectrum Analyzer by suitable attenuator, The cable loss and attenuator loss have been put into spectrum analyzer as amplitude offset.
set the Spectrum Analyzer as below:
 - Centre Frequency: The centre frequency of the middle hopping channel.
 - Resolution BW: 10 MHz.
 - Video BW: 10 MHz.
 - Span: Zero span.
 - Detector: Peak.
 - Trace Mode: Clear Write.
 - Sweep: Video Trigger
- (2) When the trace is complete, measure the sending time of 1 burst and the duty cycle of 1 burst cycle.
- (3) Calculate dwell time follow below formula:
Duty cycle= Pulse's on time / Burst cycle


10.4. Test result

Test Engineer:	Haofeng	Test Site:	RF Measurement System 3#
Ambient Condition:	24.4℃,45.2%RH	Test Date:	2024.05.31-2024.05.31
Test Power Supply:	DC 3.3V	Sample Number:	S24041013-001


Test Mode	Antenna	Frequency [MHz]	Transmission Duration [ms]	Transmission Period [ms]	Duty Cycle [%]
11B	Ant1	2412	8.40	43.40	19.35
		2437	8.40	43.40	19.35
		2462	8.40	43.40	19.35
11G	Ant1	2412	1.40	14.00	10.00
		2437	1.40	14.00	10.00
		2462	1.40	14.00	10.00
11N20SISO	Ant1	2412	1.30	13.10	9.92
		2437	1.30	13.10	9.92
		2462	1.30	13.10	9.92
11N40SISO	Ant1	2422	0.60	6.50	9.23
		2437	0.60	6.50	9.23
		2452	0.60	6.50	9.23

10.5. Test graphs







11G_Ant1_2437




11G_Ant1_2462




11N20SISO_Ant1_2412




11N20SISO_Ant1_2437




11N20SISO_Ant1_2462




11N40SISO_Ant1_2422



11N40SISO_Ant1_2437



11N40SISO_Ant1_2452



11. Antenna Requirements

11.1. Limit

For intentional device, according to FCC 47 CFR Section 15.203, an intentional radiator shall be designed to ensure that no antenna other than that furnished by the responsible party shall be used with the device. And according to FCC 47 CFR Section 15.247 (b), if transmitting antennas of directional gain greater than 6 dBi are used, the power shall be reduced by the amount in dB that the directional gain of the antenna exceeds 6 dBi.

For intentional device, according to RSS-Gen issue 5 section 6.8.

The applicant for equipment certification shall provide a list of all antenna types that may be used with the transmitter, where applicable (i.e. for transmitters with detachable antenna), indicating the maximum permissible antenna gain (in dBi) and the required impedance for each antenna. The test report shall demonstrate the compliance of the transmitter with the limit for maximum equivalent isotropically radiated power (e.i.r.p.) specified in the applicable RSS, when the transmitter is equipped with any antenna type, selected from this list.

11.2. Result

The antenna used for this product as Antenna information described in section 2.1 of the report, and there is no other antenna than that furnished by the responsible party shall be used with the device.

12.Radiated Emission

12.1. Test equipment

Equipment	Manufacturer	Model No.	Serial No.	Cal Due To
RF cable	Zhongke Junchuang	JCT26S-NJ-NJ-1.5M	DDT-ZC02762	2025/04/01
Pre-amplifier	COM-POWER	PAM-118A	DDT-ZC01293	2024/07/15
Pre-amplifier	COM-POWER	PAM-840A	DDT-ZC01693	2025/04/01
RF cable	Yuhu Technology	JCTB810-NJ-NJ-9M	DDT-ZC02538	2025/04/01
Trilog Broadband Antenna	Schwarzbeck	VULB 9163	DDT-ZC02050	2024/07/12
RF cable	Yuhu Technology	ZT26S-SMAJ-SMAJ-1M	DDT-ZC02037	2025/04/01
Broad-Band Horn Antenna	Schwarzbeck	BBHA 9170	DDT-ZC00506	2025/04/26
ELECTRIC AND MAGNETIC FIELD ANALYZER	Narda	EHP-200A	DDT-ZC01401	2024/09/21
PSA Series Spectrum Analyzer	Agilent	E4447A	DDT-ZC00517	2025/04/01
RF Cable	N/A	W13.02 AP1-X2	DDT-ZC04023	2025/04/01
Active Loop Antenna	Schwarzbeck	FMZB1519	DDT-ZC00524	2025/09/11
High Pass filter	Xi'an Xingbo	XBLBQ-GTA67	DDT-ZC02179	2025/04/23
RF Cable	N/A	W24.02 HL-562	DDT-ZC04022	2025/04/01
Micro-Tronics filters	REBES	BRM50716	DDT-ZC03240	/
High pass filter	Micro-Tronics	HPM50102	DDT-ZC00561	2025/04/23
EMI TEST RECEIVER	R&S	ESU26	DDT-ZC01909	2025/04/01
High pass filter	Micro-Tronics	HPM50108	DDT-ZC00560	2025/04/23
Micro-Tronics filters	REBES	BRM50702	DDT-ZC03242	/
Hochgewinn-Hornantenne	SCHWARZBEC K	BBHA 9120 D	DDT-ZC02129	2025/09/18

12.2. Block diagram of test setup

