

RF Exposure Evaluation

Limits

The criteria listed in the following table shall be used to evaluate the environment impact of human exposure to radio frequency (RF) radiation as specified in 1.1307(b)

Limits for Maximum Permissible Exposure (MPE)

| Frequency range (MHz) | Electric field strength (V/m) | Magnetic field strength (A/m) | Power density (mW/cm ²) | Averaging time (minutes) |
|---|-------------------------------|-------------------------------|-------------------------------------|--------------------------|
| (A) Limits for Occupational/Controlled Exposures | | | | |
| 0.3–3.0 | 614 | 1.63 | *(100) | 6 |
| 3.0–30 | 1842/f | 4.89/f | *(900/f ²) | 6 |
| 30–300 | 61.4 | 0.163 | 1.0 | 6 |
| 300–1500 | | | f/300 | 6 |
| 1500–100,000 | | | 5 | 6 |
| (B) Limits for General Population/Uncontrolled Exposure | | | | |
| 0.3–1.34 | 614 | 1.63 | *(100) | 30 |
| 1.34–30 | 824/f | 2.19/f | *(180/f ²) | 30 |
| 30–300 | 27.5 | 0.073 | 0.2 | 30 |
| 300–1500 | | | f/1500 | 30 |
| 1500–100,000 | | | 1.0 | 30 |

f = frequency in MHz

Friis transmission formula: $Pd = (Pout \cdot G) / (4 \cdot \pi \cdot r^2)$

Where

Pd = power density in mW/cm², **Pout** = output power to antenna in mW;

G = gain of antenna in linear scale, **Pi** = 3.1416;

R = distance between observation point and center of the radiator in cm

Pd is the limit of MPE, 1 mW/cm². If we know the maximum gain of the antenna and the total power input to the antenna, through the calculation, we will know the distance r where the MPE limit is reached.

Test Procedure

Software provided by client enabled the EUT to transmit and receive data at lowest, middle and highest channel individually.

Test Result of RF Exposure Evaluation

For BLE mode

| Channel(MHz) | Output power to antenna (mW) | Power Density at R=20cm (mW/cm ²) | Limit (mW/cm ²) | Result |
|--------------|------------------------------|---|-----------------------------|--------|
| 2480.00 | 0.166 | 0.000066 | 1.0 | PASS |

Remark:

Field strength = 90.43dBuV/m @3m

Ant gain =3.0dBi, so Ant numeric gain=2

So $pt = \{ [10(90.43/20)/106 \times 3]^{2/30} \times 1000 \text{ mW} = 0.166\text{mW}$

For WiFi mode

| Channel | Output power to antenna (mW) | Power Density at R=20cm (mW/cm ²) | Limit (mW/cm ²) | Result |
|-------------------|------------------------------|---|-----------------------------|--------|
| Lowest (2412MHz) | 54.58 | 0.0217 | 1.0 | PASS |
| Middle (2437MHz) | 53.70 | 0.0213 | 1.0 | PASS |
| Highest (2462MHz) | 48.53 | 0.0193 | 1.0 | PASS |

Remark: antenna gain=3dBi