

Shenzhen Apeman Innovations Technology Co.,Ltd.

TEST REPORT

SCOPE OF WORK
EMC TESTING-PA10

REPORT NUMBER
190507011GZU-001

ISSUE DATE [REVISED DATE]
26-July-2019 [-----]

PAGES
116

DOCUMENT CONTROL NUMBER
FCC WIFI-d
© 2017 INTERTEK



TEST REPORT

Block E, No.7-2 Guang Dong
Software Science Park, Caipin Road,
Guangzhou Science City, GETDD
Guangzhou, China

Telephone: 86-20-8213 9688
Facsimile: 86-20-3205 7538
www.intertek.com

Applicant Name & : Shenzhen Apeman Innovations Technology Co.,Ltd.
Address : Building P11, Huanancheng, Longgang District, Shenzhen ,China
Manufacturing Site : Same as applicant
Intertek Report No: 190507011GZU-001
FCC ID: 2ARER-PA10

Test standards**47 CFR PART 15 Subpart C: 2018 section 15.247****Sample Description**

Product : Smart Plug
Model No. : PA10
Electrical Rating : 120Vac, 60Hz
Serial No. : Not Labeled
Date Received : 01 July 2019
Date Test Conducted : 01 July 2019-24 July 2019

Prepared and Checked By



Daniel He

Project Engineer

Intertek Guangzhou

Approved By:



Helen Ma

Helen Ma

Team Leader

Intertek Guangzhou

This report is for the exclusive use of Intertek's Client and is provided pursuant to the agreement between Intertek and its Client. Intertek's responsibility and liability are limited to the terms and conditions of the agreement. Intertek assumes no liability to any party, other than to the Client in accordance with the agreement, for any loss, expense or damage occasioned by the use of this report. Only the Client is authorized to permit copying or distribution of this report and then only in its entirety. Any use of the Intertek name or one of its marks for the sale or advertisement of the tested material, product or service must first be approved in writing by Intertek. The observations and test results in this report are relevant only to the sample tested. This report by itself does not imply that the material, product, or service is or has ever been under an Intertek certification program.

TEST REPORT**CONTENT**

TEST REPORT	1
CONTENT	3
1.0 TEST RESULT SUMMARY	4
2.0 GENERAL DESCRIPTION	5
2.1 PRODUCT DESCRIPTION	5
2.2 RELATED SUBMITTAL(S) GRANTS	6
2.3 TEST METHODOLOGY	6
2.4 TEST FACILITY	6
3.0 SYSTEM TEST CONFIGURATION	6
3.1 JUSTIFICATION	6
3.2 EUT EXERCISING SOFTWARE	7
3.3 SPECIAL ACCESSORIES	7
3.4 MEASUREMENT UNCERTAINTY	8
3.5 EQUIPMENT MODIFICATION	8
3.6 SUPPORT EQUIPMENT LIST AND DESCRIPTION	9
4.0 MEASUREMENT RESULTS	10
4.1 ANTENNA REQUIREMENT	10
4.2 6 DB BANDWIDTH (DTS BANDWIDTH)	11
4.3 MAXIMUM PEAK CONDUCTED OUTPUT POWER	19
4.4 PEAK POWER SPECTRAL DENSITY	27
4.5 OUT OF BAND CONDUCTED EMISSIONS	35
4.6 OUT OF BAND RADIATED EMISSIONS	49
4.7 RADIATED EMISSIONS IN RESTRICTED BANDS	50
4.8 BAND EDGES REQUIREMENT	107
4.9 CONDUCTED EMISSION TEST	113
5.0 TEST EQUIPMENT LIST	116

TEST REPORT

1.0 TEST RESULT SUMMARY

Test Item	Test Requirement	Test Method	Result
Antenna Requirement	FCC PART 15 C section 15.247 (c) and Section 15.203	FCC PART 15 C section 15.247 (c) and Section 15.203	PASS
6 dB Bandwidth (DTS bandwidth)	FCC PART 15 C section 15.247 (a)(2)	ANSI C63.10: Clause 11.8	PASS
Maximum Peak Conducted Output Power	FCC PART 15 C section 15.247(b)(3)	ANSI C63.10: Clause 11.9.1.2	PASS
Peak Power Spectral Density	FCC PART 15 C section 15.247(e)	ANSI C63.10: Clause 11.10.2	PASS
Out of Band Conducted Emissions	FCC PART 15 C section 15.209 &15.247(d)	ANSI C63.10: Clause 11.11	PASS
Out of Band Radiated Emission	FCC PART 15 C section 15.209 &15.247(d)	ANSI C63.10: Clause 11.11, 6.4, 6.5 and 6.6	N/A
Radiated Emissions in Restricted Bands	FCC PART 15 C section 15.209 &15.247(d)	ANSI C63.10: Clause 11.12.1, 6.4, 6.5 and 6.6	PASS
Band Edges Measurement	FCC PART 15 C section 15.247 (d) &15.205	ANSI C63.10: Clause 11.11 and 11.13	PASS
Conducted Emissions at Mains Terminals	FCC PART 15 C section 15.207	ANSI C63.10: Clause 6.2	PASS
Remark: N/A: not applicable. Refer to the relative section for the details. EUT: In this whole report EUT means Equipment Under Test. Tx: In this whole report Tx (or tx) means Transmitter. Rx: In this whole report Rx (or rx) means Receiver. RF: In this whole report RF means Radio Frequency. ANSI C63.10: the detail version is ANSI C63.10:2013 in the whole report			

TEST REPORT

2.0 General Description

2.1 Product Description

Operating Frequency:	2412 MHz to 2462 MHz for 802.11b/g/n(HT20)
Type of Modulation:	2422 MHz to 2452 MHz for 802.11n(HT40)
	802.11b: DSSS(CCK)
	802.11g: OFDM(BPSK/QPSK/16QAM/64QAM)
	802.11n: OFDM (BPSK/QPSK/16QAM/64QAM)
Transmit Data Rate:	802.11b: 1/2/5.5/11 Mbps
	802.11g: 6/9/12/18/24/36/48/54 Mbps
	802.11n(HT20): 6.5/13/19.5/26/39/52/58.5/65Mbps/72.2Mbps
	802.11n(HT40):13.5/27/40.5/54/81/108/121.5/135Mbps
Number of Channels	11 Channels for 802.11b/g/n(HT20)
	7 Channels for 802.11n(HT40)
Channel Separation:	5 MHz
Antenna Type	PCB Layout
Antenna gain	2dBi
EUT Power Supply:	120Vac, 60Hz

EUT channels and frequencies list:

For 802.11b/g/n(HT20): test frequencies are lowest channel 1: 2412 MHz, middle channel 6: 2437 MHz and highest channel 11: 2462 MHz.

For 802.11n(HT40): test frequencies are lowest channel 3: 2422 MHz, middle channel 6: 2437 MHz and highest channel 9: 2452 MHz.

Channel	Frequency (MHz)	Channel	Frequency (MHz)
1	2412	7	2442
2	2417	8	2447
3	2422	9	2452
4	2427	10	2457
5	2432	11	2462
6	2437	/	

TEST REPORT

2.2 Related Submittal(s) Grants

This is an application for certification of:
DTS- Part 15 Digital Transmission Systems (WIFI transmitter portion)

Remaining portions are subject to the following procedures:
1. Receiver portion of WIFI: exempt from technical requirement of this Part.

2.3 Test Methodology

Both AC mains line-conducted and radiated emission measurements were performed according to the procedures in ANSI C63.10. Radiated emission measurement was performed in semi-anechoic chamber and conducted emission measurement was performed in shield room. For radiated emission measurement, preliminary scans and final tests were performed in the semi-anechoic chamber to determine the worst case modes. All radiated tests were performed at an antenna to EUT distance of 3 meters, unless stated otherwise.

2.4 Test Facility

All tests were performed at:
Room102/104, No 203, KeZhu Road, Science City, GETDD Guangzhou, China
Except Conducted Emissions was performed at:
Block E, No.7-2 Guang Dong Software Science Park, Caipin Road, Guangzhou Science City, GETDD Guangzhou, China

A2LA Certificate Number 0078.10
Intertek Testing Services Shenzhen Ltd. Guangzhou Branch is accredited by A2LA and Listed in FCC website. FCC accredited test labs may perform both Certification testing under Parts 15 and 18 and Declaration of Conformity testing.

3.0 System Test Configuration

3.1 Justification

For emissions testing, the equipment under test (EUT) setup to transmit continuously to simplify the measurement methodology. Care was taken to ensure proper power supply voltages during testing. During testing, it was powered by 120Vac supply.

TEST REPORT

The signal is maximized through rotation. The antenna height and polarization are varied during the search for maximum signal level. The antenna height is varied from 1 to 4 meters. Radiated emissions are taken at three meters unless the signal level is too low for measurement at that distance. If necessary, a pre-amplifier is used and/or the test is conducted at a closer distance.

All readings are extrapolated back to the equivalent three meter reading using inverse scaling with distance. The spurious emissions more than 20 dB below the permissible value are not reported.

For an intentional radiator, the spectrum shall be investigated from the lowest radio frequency signal generated in the device, without going below 9 kHz, up to at least the frequency shown in the following table:

Frequency range of radiated emission measurements

Lowest frequency generated in the device	Upper frequency range of measurement
9 kHz to below 10 GHz	10th harmonic of highest fundamental frequency or to 40 GHz, whichever is lower
At or above 10 GHz to below 30 GHz	5th harmonic of highest fundamental frequency or to 100 GHz, whichever is lower
At or above 30 GHz	5th harmonic of highest fundamental frequency or to 200 GHz, whichever is lower, unless otherwise specified

Number of fundamental frequencies to be tested in EUT transmit band

Frequency range in which device operates	Number of frequencies	Location in frequency range of operation
1 MHz or less	1	Middle
1 MHz to 10 MHz	2	1 near top and 1 near bottom
More than 10 MHz	3	1 near top, 1 near middle and 1 near bottom

3.2 EUT Exercising Software

N/A

3.3 Special Accessories

No special accessories used.

TEST REPORT

3.4 Measurement Uncertainty

No.	Item	Measurement Uncertainty
1	20 dB Bandwidth	2.3%
	6dB Bandwidth	
	99% Bandwidth	
2	Carrier Frequencies Separated	2.3%
3	Dwell Time	1.2%
4	Maximum Peak Conducted Output Power	1.5dB
5	Peak Power Spectral Density	1.5dB
6	Out of Band Conducted Emissions	1.5dB
7	Band edges measurement	1.5dB
8	Radiated Emissions	4.7 dB (25 MHz-1 GHz)
		4.8 dB (1 GHz-18 GHz)
		5.21dB (18GHz-26GHz)
9	Conducted Emissions at Mains Terminals	2.58dB
10	Temperature	0.5 °C
11	Humidity	0.4 %
12	Time	1.2%

The measurement uncertainty describes the overall uncertainty of the given measured value during the operation of the EUT.

Measurement uncertainty is calculated in accordance with ETSI TR 100 028-2001.

The measurement uncertainty is given with a confidence of 95%, k=2.

When determining of the test conclusion, the Measurement Uncertainty of test has been considered.

Uncertainty and Compliance – Unless the standard specifically states that measured values are to be extended by the measurement uncertainty in determining compliance, all compliance determinations are based on the actual measured value

3.5 Equipment Modification

Any modifications installed previous to testing by Shenzhen Apeman Innovations Technology Co.,Ltd.will be incorporated in each production model sold / leased in the United States.

No modifications were installed by Intertek Testing Services Shenzhen Ltd. Guangzhou Branch.

TEST REPORT**3.6 Support Equipment List and Description**

This product was tested with corresponding support equipment as below:

Support Equipment:

Description	Manufacturer	Model No.	SN/Version	Supplied by
Fix frequency software	--	UI_mptool_1	V15	Client
Notebook	HP	T430	--	Intertek
Incandescent light bulb	--	--	100W	Intertek
AC cable	--	--	0.8m (unscreened)	Intertek
Antenna cable	RF-02	SMA	0.2 m(shielded)	Intertek

TEST REPORT**4.0 Measurement Results****4.1 Antenna Requirement**

Standard requirement:

15.203 requirement:

For intentional device. According to 15.203 an intentional radiator shall be designed to Ensure that no antenna other than that furnished by the responsible party shall be used with the device.

15.247(c) (1)(i) requirement:

(i) Systems operating in the 2400-2483.5 MHz bands that are used exclusively for fixed. Point-to-point operations may employ transmitting antennas with directional gain greater than 6 dBi provided the maximum conducted output power of the intentional radiator is reduced by 1 dB for every 3 dB that the directional gain of the antenna exceeds 6 dBi.

EUT Antenna


The antenna is an integral antenna and no consideration of replacement. The best case gain of the antenna is 2 dBi.



TEST REPORT

4.2 6 dB Bandwidth (DTS bandwidth)

Test Requirement:	FCC Part 15 C section 15.247 (a)(2)Systems using digital modulation techniques may operate in the 902-928 MHz, 2400-2483.5MHz, and 5725-5850 MHz bands. The minimum 6 dB bandwidth shall be at least 500 kHz.
Test Method:	ANSI C63.10: Clause 11.8
Test Status:	Pre-Scan has been conducted to determine the worst-case mode from all possible combinations between available modulations, data rates and antenna ports (if EUT with antenna diversity architecture). Following channel(s) was (were) selected for the final test as listed below.
Test Configuration:	



Test Procedure:

1. Remove the antenna from the EUT and then connect a low attention attenuation RF cable (cable loss =1 dB) from the antenna port to the spectrum.
2. Set the spectrum analyzer:
 - a) Set RBW = 100 kHz
 - b) Set the VBW $\geq [3 \times \text{RBW}]$
 - c) Detector = peak.
 - d) Trace mode = max hold.
 - e) Sweep = auto couple
 - f) Allow the trace to stabilize.
 - g) Measure the maximum width of the emission that is constrained by the frequencies associated with the two outermost amplitude points (upper and lower frequencies) that are attenuated by 6 dB relative to the maximum level measured in the fundamental emission.
 - h) Span=2*BW~5*BW
3. Repeat until all the test status is investigated.

TEST REPORT

4. Report the worst case.

Used Test Equipment List

Spectrum Analyzer. Refer to Clause 5 Test Equipment List for details.

Channel No.	Frequency (MHz)	Mode	Data Rate	Measured 6dB bandwidth (MHz)	Limit	Result
1	2412	802.11b	1 Mbps	10.060	≥500KHz	Pass
6	2437		1 Mbps	10.060		Pass
11	2462		1 Mbps	10.056		Pass
1	2412	802.11g	6 Mbps	16.340	≥500KHz	Pass
6	2437		6 Mbps	16.340		Pass
11	2462		6 Mbps	16.344		Pass
1	2412	802.11n (HT20)	6.5 Mbps	17.224	≥500KHz	Pass
6	2437		6.5 Mbps	17.320		Pass
11	2462		6.5 Mbps	16.984		Pass
3	2422	802.11n (HT40)	13.5 Mbps	34.720	≥500KHz	Pass
6	2437		13.5 Mbps	34.728		Pass
9	2452		13.5 Mbps	34.304		Pass


Test result: The unit does meet the FCC requirements.

TEST REPORT


Result plot as follows:

802.11b mode with 1Mbps data rate

Channel 1: 2.412GHz




Channel 6: 2.437GHz:




TEST REPORT

Channel 11: 2.462GHz:




802.11g mode with 6Mbps data rate

Channel 1: 2.412GHz:




TEST REPORT

Channel 6: 2.437GHz:




Channel 11: 2.462GHz:




TEST REPORT

802.11n(HT20) mode with 6.5Mbps data rate

Channel 1: 2.412GHz:




Channel 6: 2.437GHz:




TEST REPORT

Channel 11: 2.462GHz:




802.11n(HT40) mode with 13.5Mbps data rate

Channel 3: 2.422GHz:




TEST REPORT

Channel 6: 2.437GHz:




Channel 9: 2.452GHz:



TEST REPORT

4.3 Maximum Peak Conducted Output Power

Test Requirement:	FCC Part 15 C section 15.247 (b)(3) For systems using digital modulation in the 902-928 MHz, 2400-2483.5 MHz, and 5725-5850 MHz bands: 1 Watt. Except as shown in paragraph (c) of this section, if transmitting antennas of directional gain greater than 6 dBi are used, the conducted output power from the intentional radiator shall be reduced below the stated values in paragraphs (b) (1), (b) (2), and (b) (3) of this section, as appropriate, by the amount in dB that the directional gain of the antenna exceeds 6 dBi.
Test Method:	ANSI C63.10: Clause 11.9.1.2(Integrated band power method)
Test Status:	Pre-Scan has been conducted to determine the worst-case mode from all possible combinations between available modulations, data rates and antenna ports (if EUT with antenna diversity architecture). Following channel(s) was (were) selected for the final test as listed below.
Test Configuration:	



Test Procedure:

1. Remove the antenna from the EUT and then connect a low attention attenuation RF cable (cable loss =1 dB) from the antenna port to the spectrum.
2. Set the spectrum analyzer:
 - a) Set the RBW = 1 MHz.
 - b) Set the VBW \geq [3 \times RBW].
 - c) Set the span \geq [1.5 \times DTS bandwidth].
 - d) Detector = peak.
 - e) Sweep time = auto couple.
 - f) Trace mode = max hold.
 - g) Allow trace to fully stabilize.
 - h) Use the instrument's band/channel power measurement function with the band limits set equal to the DTS bandwidth edges.

TEST REPORT

3. Repeat until all the test status is investigated.
4. Report the worst case.

Used Test Equipment List

Spectrum Analyzer. Refer to Clause 5 Test Equipment List for details.

Test result:

Channel No.	Frequency (MHz)	Mode	Data Rate	Measured Channel Power (dBm)	Limit	Result
1	2412	802.11b	1 Mbps	16.33	1W (30dBm)	Pass
6	2437		1 Mbps	16.72		Pass
11	2462		1 Mbps	17.02		Pass
1	2412		6 Mbps	18.97		Pass
6	2437		6 Mbps	19.27		Pass
11	2462		6 Mbps	19.45		Pass
1	2412		6.5 Mbps	18.40		Pass
6	2437		6.5 Mbps	18.66		Pass
11	2462		6.5 Mbps	18.77		Pass
3	2422	802.11n (HT40)	13.5 Mbps	18.98		Pass
6	2437		13.5 Mbps	19.38		Pass
9	2452		13.5 Mbps	19.58		Pass

Remark:

Cable loss=1.0 dB

Remark: Level = Read Level + Cable Loss


The unit does meet the FCC requirements.

TEST REPORT


Result plot as follows:

802.11b mode with 1Mbps data rate

Channel 1: 2.412GHz:




Channel 6: 2.437GHz:




TEST REPORT

Channel 11: 2.462GHz:




802.11g mode with 6Mbps data rate

Channel 1: 2.412GHz:




TEST REPORT

Channel 6: 2.437GHz:




Channel 11: 2.462GHz:




TEST REPORT

802.11n(HT20) mode with 6.5Mbps data rate

Channel 1: 2.412GHz:




Channel 6: 2.437GHz:




TEST REPORT

Channel 11: 2.462GHz:




802.11n(HT40) mode with 13.5Mbps data rate

Channel 3: 2.422GHz:




TEST REPORT

Channel 6: 2.437GHz:



Channel 9: 2.452GHz:



Test result: The unit does meet the FCC requirements.


TEST REPORT**4.4 Peak Power Spectral Density**

Test Requirement: FCC Part 15 C section 15.247
(e) For digitally modulated systems, the power spectral density conducted from the intentional radiator to the antenna shall not be greater than 8 dBm in any 3 kHz band during any time interval of continuous transmission.
This power spectral density shall be determined in accordance with the provisions of paragraph (b) of this section. The same method of determining the conducted output power shall be used to determine the power spectral density.

Test Method: ANSI C63.10: Clause 11.10.2

Test Status: Pre-Scan has been conducted to determine the worst-case mode from all possible combinations between available modulations, data rates and antenna ports (if EUT with antenna diversity architecture). Following channel(s) was (were) selected for the final test as listed below.

Test Configuration:

**Test Procedure:**

1. Remove the antenna from the EUT and then connect a low attention attenuation RF cable(cable loss =1 dB) from the antenna port to the spectrum analyzer or power meter.
2. Set the spectrum analyzer:
 - a) Set analyzer center frequency to DTS channel center frequency.
 - b) Set the span= $1.5 \times$ DTS bandwidth.
 - c) Set the RBW to $3 \text{ kHz} \leqslant \text{RBW} \leqslant 100 \text{ kHz}$.
 - d) Set the VBW $\geqslant [3 \times \text{RBW}]$.
 - e) Detector = peak.
 - f) Sweep time = auto couple.
 - g) Trace mode = max hold.
 - h) Allow trace to fully stabilize.

TEST REPORT

- i) Use the peak marker function to determine the maximum amplitude level within the RBW.
- j) If measured value exceeds requirement, then reduce RBW (but no less than 3 kHz) and repeat.
3. Measure the Power Spectral Density of the test frequency with special test status.
4. Repeat until all the test status is investigated.
5. Report the worst case.

Used Test Equipment List

Spectrum Analyzer. Refer to Clause 5 Test Equipment List for details.

Test result:

Channel No.	Frequency (MHz)	Mode	Data Rate	Measured Peak Power Spectral Density (dBm/3kHz)	Limit	Result
1	2412	802.11b	1 Mbps	-2.74	8dBm/ 3 KHz	Pass
6	2437		1 Mbps	-2.96		Pass
11	2462		1 Mbps	-3.06		Pass
1	2412	802.11g	6 Mbps	-18.01	8dBm/ 3 KHz	Pass
6	2437		6 Mbps	-18.00		Pass
11	2462		6 Mbps	-17.85		Pass
1	2412	802.11n (HT20)	6.5 Mbps	-18.05	8dBm/ 3 KHz	Pass
6	2437		6.5 Mbps	-17.96		Pass
11	2462		6.5 Mbps	-17.81		Pass
3	2422	802.11n (HT40)	13.5 Mbps	-17.95	8dBm/ 3 KHz	Pass
6	2437		13.5 Mbps	-17.87		Pass
9	2452		13.5 Mbps	-17.84		Pass


Test result: Level = Read Level + Cable Loss (1B).

TEST REPORT


Result plot as follows:

802.11b mode with 1Mbps data rate

Channel 1: 2.412GHz:




Channel 6: 2.437GHz:




TEST REPORT

Channel 11: 2.462GHz:




802.11g mode with 6Mbps data rate

Channel 1: 2.412GHz:




TEST REPORT

Channel 6: 2.437GHz:




Channel 11: 2.462GHz:




TEST REPORT

802.11n(HT20) mode with 6.5Mbps data rate

Channel 1: 2.412GHz:




Channel 6: 2.437GHz:




TEST REPORT

Channel 11: 2.462GHz:




802.11n(HT40) mode with 13.5Mbps data rate

Channel 3: 2.422GHz:




TEST REPORT

Channel 6: 2.437GHz:



Channel 9: 2.452GHz:



TEST REPORT

4.5 Out of Band Conducted Emissions


Test Requirement: FCC Part 15 C section 15.247

(d) In any 100 kHz bandwidth outside the frequency band in which the spread spectrum or digitally modulated intentional radiator is operating. The radio frequency power that is produced by the intentional radiator shall be at least 20 dB below that in the 100 kHz bandwidth within the band that contains the highest level of the desired power. Based on either an RF conducted or a radiated measurement. Provided the transmitter demonstrates compliance with the peak conducted power limits.

Test Method: ANSI C63.10: Clause 11.11

Test Status: Pre-Scan has been conducted to determine the worst-case mode from all possible combinations between available modulations, data rates and antenna ports (if EUT with antenna diversity architecture).
 Following channel(s) was (were) selected for the final test as listed below.

Test Configuration:



Test Procedure:

1. Remove the antenna from the EUT and then connect a low RF cable (cable loss =1dB) from the antenna port to the spectrum analyzer or power meter.
2. Establish a reference level by using the following procedure:
 - a) Set instrument center frequency to DTS channel center frequency.
 - b) Set the span to $\geq 1.5 \times$ DTS bandwidth.
 - c) Set the RBW = 100 kHz.
 - d) Set the VBW $\geq [3 \times RBW]$.
 - e) Detector = peak.
 - f) Sweep time = auto couple.
 - g) Trace mode = max hold.
 - h) Allow trace to fully stabilize.
 - i) Use the peak marker function to determine the maximum PSD level.

TEST REPORT

Note that the channel found to contain the maximum PSD level can be used to establish the reference level

3. Emission level measurement
 - a) Set the center frequency and span to encompass frequency range to be measured.
 - b) Set the RBW = 100 kHz.
 - c) Set the VBW $\geq [3 \times \text{RBW}]$.
 - d) Detector = peak.
 - e) Sweep time = auto couple.
 - f) Trace mode = max hold.
 - g) Allow trace to fully stabilize.
 - h) Use the peak marker function to determine the maximum amplitude level.
4. Measure the Conducted unwanted Emissions of the test frequency with special test status.
5. Repeat until all the test status is investigated.
6. Report the worst case.

Used Test Equipment List


Spectrum Analyzer. Refer to Clause 5 Test Equipment List for details.

TEST REPORT

Result plot as follows:

802.11b mode with 1Mbps data rate


Channel 1: 2.412GHz:



In any 100kHz bandwidth, the Conducted Spurious Emissions from 30 MHz to 25 GHz were greater than 20dB below the peak emission within the band that contains the highest level of the desired power.

TEST REPORT


Channel 6: 2.437GHz:



In any 100kHz bandwidth, the Conducted Spurious Emissions from 30 MHz to 25 GHz were greater than 20dB below the peak emission within the band that contains the highest level of the desired power.

TEST REPORT

Channel 11:2.462 GHz:




In any 100kHz bandwidth, the Conducted Spurious Emissions from 30 MHz to 25 GHz were greater than 20dB below the peak emission within the band that contains the highest level of the desired power.

TEST REPORT

802.11g mode with 6Mbps data rate


Channel 1: 2.412GHz:



In any 100kHz bandwidth, the Conducted Spurious Emissions from 30 MHz to 25 GHz were greater than 20dB below the peak emission within the band that contains the highest level of the desired power.

TEST REPORT


Channel 6: 2.437GHz:



In any 100kHz bandwidth, the Conducted Spurious Emissions from 30 MHz to 25 GHz were greater than 20dB below the peak emission within the band that contains the highest level of the desired power.

TEST REPORT

Channel 11: 2.462 GHz:




In any 100kHz bandwidth, the Conducted Spurious Emissions from 30 MHz to 25 GHz were greater than 20dB below the peak emission within the band that contains the highest level of the desired power.

TEST REPORT

802.11n(HT20) mode with 6.5Mbps data rate


Channel 1: 2.412GHz:



In any 100kHz bandwidth, the Conducted Spurious Emissions from 30 MHz to 25 GHz were greater than 20dB below the peak emission within the band that contains the highest level of the desired power.

TEST REPORT


Channel 6: 2.437GHz:



In any 100kHz bandwidth, the Conducted Spurious Emissions from 30 MHz to 25 GHz were greater than 20dB below the peak emission within the band that contains the highest level of the desired power.

TEST REPORT


Channel 11:2.462 GHz:



In any 100kHz bandwidth, the Conducted Spurious Emissions from 30 MHz to 25 GHz were greater than 20dB below the peak emission within the band that contains the highest level of the desired power.

TEST REPORT


802.11n(HT40) mode with 13.5Mbps data rate
Channel 3: 2.422GHz:



In any 100kHz bandwidth, the Conducted Spurious Emissions from 30 MHz to 25 GHz were greater than 20dB below the peak emission within the band that contains the highest level of the desired power.

TEST REPORT


Channel 6: 2.437GHz:



In any 100kHz bandwidth, the Conducted Spurious Emissions from 30 MHz to 25 GHz were greater than 20dB below the peak emission within the band that contains the highest level of the desired power.

TEST REPORT

Channel 9: 2.452 GHz:



In any 100kHz bandwidth, the Conducted Spurious Emissions from 30 MHz to 25 GHz were greater than 20dB below the peak emission within the band that contains the highest level of the desired power.

TEST REPORT

4.6 Out of Band Radiated Emissions

For out of band radiated emissions into Non-Restricted Frequency Bands were performed at a 3m separation distance to determine whether these emissions complied with the 20dB attenuation requirement.

- Not required, since all emissions are more than 20dB below fundamental
- See attached data sheet

TEST REPORT

4.7 Radiated Emissions in Restricted Bands

Test Requirement:	FCC Part 15 C section 15.247 (d) In addition, radiated emissions which fall in the restricted bands, as defined in Section 15.205(a), must also comply with the radiated emission limits specified in Section 15.209(a) (see Section 15.205(c)).
Test Method:	ANSI C63.10: Clause 11.12.1, 6.4, 6.5 and 6.6
Test Status:	Pre-Scan has been conducted to determine the worst-case mode from all possible combinations between available modulations, data rates and antenna ports (if EUT with antenna diversity architecture). Following channel(s) was (were) selected for the final test as listed below.
Test site:	Measurement Distance: 3m (Semi-Anechoic Chamber)
Limit:	40.0 dB μ V/m between 30MHz & 88MHz; 43.5 dB μ V/m between 88MHz & 216MHz; 46.0 dB μ V/m between 216MHz & 960MHz; 54.0 dB μ V/m above 960MHz.
Detector:	For Peak and Quasi-Peak value: RBW = 1 MHz for $f \geq 1$ GHz, 200 Hz for 9 kHz to 150 kHz 9 kHz for 150 kHz to 30 MHz 120 kHz for 30 MHz to 1GHz VBW \geq RBW Sweep = auto Detector function = peak for $f \geq 1$ GHz, QP for $f < 1$ GHz Trace = max hold
Field Strength Calculation:	For AV value: RBW = 1 MHz for $f \geq 1$ GHz, 100 kHz for $f < 1$ GHz VBW=10 Hz Sweep = auto Trace = max hold The field strength is calculated by adding the reading on the Spectrum Analyzer to the factors associated with preamplifiers (if any), antennas, cables, pulse desensitization and average factors (when specified limit is in average and measurements are made with peak detectors). A sample calculation is included below: FS = RA + AF + CF - AG + PD + AV FS = RA + Correct Factor + AV FS = Field Strength in dB μ V/m
Where:	

TEST REPORT

RA = Receiver Amplitude (including preamplifier) in dB μ V

AF = Antenna Factor in dB

CF = Cable Attenuation Factor in dB

AG = Amplifier Gain in dB

PD = Pulse Desensitization in dB

AV = Average Factor in -dB

Correct Factor = AF + CF - AG + PD

In the radiated emission table which follows, the reading shown on the data table may reflect the preamplifier gain. An example of the calculations, where the reading does not reflect the preamplifier gain, follows:

FS = RA + AF + CF - AG + PD + AV

Assume a receiver reading of 62.0 dB μ V is obtained. The antenna factor of 7.4 dB and cable factor of 1.6 dB is added. The amplifier gain of 29 dB is subtracted. The pulse desensitization factor of the spectrum analyzer was 0 dB, and the resultant average factor was -10 dB. The net field strength for comparison to the appropriate emission limit is 32 dB μ V/m.

RA = 62.0 dB μ V

AF = 7.4 dB

CF = 1.6 dB

AG = 29.0 dB

PD = 0 dB

AV = -10 dB

Correct Factor = 7.4 + 1.6 - 29.0 + 0 = -20 dB

FS = 62 + (-20) + (-10) = 32 dB μ V/m

Remark: Above the 1GHz, spectrum used the RBW



1MHz(1/RBW=1us) for test, which is shorter than the width of one pulse, so PD=0dB

Section 15.205 Restricted bands of operation.

(a) Except as shown in paragraph (d) of this section. Only spurious emissions are permitted in any of the frequency bands listed below:


TEST REPORT

MHz	MHz	MHz	GHz
0.090 - 0.110	16.42 - 16.423	399.9 - 410	4.5 - 5.15
10.495 - 0.505	16.69475 - 16.69525	608 - 614	5.35 - 5.46
2.1735 - 2.1905	16.80425 - 16.80475	960 - 1240	7.25 - 7.75
4.125 - 4.128	25.5 - 25.67	1300 - 1427	8.025 - 8.5
4.17725 - 4.17775	37.5 - 38.25	1435 - 1626.5	9.0 - 9.2
4.20725 - 4.20775	73 - 74.6	1645.5 - 1646.5	9.3 - 9.5
6.215 - 6.218	74.8 - 75.2	1660 - 1710	10.6 - 12.7
6.26775 - 6.26825	108 - 121.94	1718.8 - 1722.2	13.25 - 13.4
6.31175 - 6.31225	123 - 138	2200 - 2300	14.47 - 14.5
8.291 - 8.294	149.9 - 150.05	2310 - 2390	15.35 - 16.2
8.362 - 8.366	156.52475 -	2483.5 - 2500	17.7 - 21.4
8.37625 - 8.38675	156.52525	2655 - 2900	22.01 - 23.12
8.41425 - 8.41475	156.7 - 156.9	3260 - 3267	23.6 - 24.0
12.29 - 12.293	162.0125 - 167.17	3332 - 3339	31.2 - 31.8
12.51975 - 12.52025	167.72 - 173.2	3345.8 - 3358	36.43 - 36.5
12.57675 - 12.57725	240 - 285	3600 - 4400	
13.36 - 13.41	322 - 335.4		

TEST REPORT**Test Configuration:**1) 9 kHz to 30 MHz emissions:2) 30 MHz to 1 GHz emissions:

TEST REPORT

3) 1 GHz to 40 GHz emissions:



Test Procedure:

Test site with RF absorbing material covering the ground plane that met the site validation criterion called out in CISPR 16-1-4:2010 was used to perform radiated emission test above 1 GHz.

The receiver was scanned from 9 kHz to 25 GHz. When an emission was found, the table was rotated to produce the maximum signal strength. An initial pre-scan was performed for in peak detection mode using the receiver. The EUT was measured for both the Horizontal and Vertical polarities and performed a pre-test three orthogonal planes. For intentional radiators, measurements of the variation of the input power or the radiated signal level of the fundamental frequency component of the emission, as appropriate, shall be performed with the supply voltage varied between 85% and 115% of the nominal rated supply voltage. The worst case emissions were reported.

Used Test Equipment List:

3m Semi-Anechoic Chamber, EMI Test Receiver (9 kHz~7 GHz), Signal and Spectrum Analyzer (10 Hz~40 GHz), Loop antenna (9 kHz-30 MHz). TRILOG Super Broadband test Antenna(30 MHz-3 GHz) (RX), Double-Ridged Waveguide Horn Antenna (800 MHz-18 GHz)(RX) and High Frequency Antenna & preamplifier(18 GHz~26.5 GHz) (RX). Refer to Clause 5 Test Equipment List for details.

TEST REPORT

802.11b mode with 1Mbps data rate


9 kHz~30 MHz Field Strength of Unwanted Emissions. Quasi-Peak Measurement

The measurements with active loop antenna were greater than 20dB below the limit, so the test data were not recorded in the test report.

Test at Channel 1 (2.412 GHz) in transmitting status

30 MHz~1 GHz Spurious Emissions. Quasi-Peak Measurement

Horizontal:




Frequency (MHz)	Receiver Reading Level (dB μ V)	Correction factors (dB/m)	Emission Level (dB μ V/m)	Limit (dB μ V/m)
192.24	18.9	12.1	31.0	43.5
240.24	26.4	14.7	41.1	46.0
336.40	16.6	16.3	32.9	46.0

Remark:

1. Corr. (dB) = Antenna Factor (dB) + Cable Loss (dB)
2. Quasi Peak (dB μ V/m) = Corr. (dB) + Read Level (dB μ V)
3. Margin (dB) = Limit QPK (dB μ V/m) – Quasi Peak (dB μ V/m)

TEST REPORT

Vertical:



Frequency (MHz)	Receiver Reading Level (dB μ V)	Correction factors (dB/m)	Emission Level (dB μ V/m)	Limit (dB μ V/m)
30.72	16.4	10.9	27.3	40.0
40.92	14.6	13.6	28.2	40.0
240.12	14.6	14.7	29.3	46.0

Remark:

1. Corr. (dB) = Antenna Factor (dB) + Cable Loss (dB)
2. Quasi Peak (dB μ V/m) = Corr. (dB) + Read Level (dB μ V)
3. Margin (dB) = Limit QPK (dB μ V/m) – Quasi Peak (dB μ V/m)

TEST REPORT

1~25 GHz Radiated Emissions.

PK Measurement:

Frequency (MHz)	PK Reading Level (dB μ V)	Correction factors (dB/m)	PK Emission Level (dB μ V/m)	PK Limit (dB μ V/m)	Antenna polarization
4823.88	45.1	-0.5	44.6	74	Horizontal
7235.31	42.8	3.4	46.2	74	Horizontal
9648.06	47.3	6.3	53.6	74	Horizontal
4823.88	45.8	-0.5	45.3	74	Vertical
7235.31	43.0	3.4	46.4	74	Vertical
9648.06	48.4	6.3	54.7	74	Vertical

AV Measurement:

Frequency (MHz)	AV Reading Level (dB μ V)	Correction factors (dB/m)	AV Emission Level (dB μ V/m)	AV Limit (dB μ V/m)	Antenna polarization
4823.88	/	-0.5	/	54	Horizontal
7235.31	/	3.4	/	54	Horizontal
9648.06	/	6.3	/	54	Horizontal
4823.88	/	-0.5	/	54	Vertical
7235.31	/	3.4	/	54	Vertical
9648.06	35.3	6.3	41.6	54	Vertical

The field strength is calculated by adding the Antenna Factor, Cable Factor & Preamplifier. The basic equation with a sample calculation is as follows:

Final Test Level = Receiver Reading + Correction Factor

Correction Factor = Antenna Factor + Cable Loss - Preamplifier Factor.

Remark:

Harmonic Emissions was tested with filter (Product name: MICRO-TRONICS, model name:


BRM50702), other radiated emissions were found below the reference noise level

When Peak emission level was below AV limit, the AV emission level was not recorded.

TEST REPORT

Band Edge test Restricted Bands

Horizontal



Frequency (MHz)	PK Reading Level (dB μ V)	Correction factors (dB/m)	PK Emission Level (dB μ V/m)	Limit (dB μ V/m)
2388.63	45.5	-2.3	43.2	74.0

Remark:


Final Test Level = Receiver Reading + Correction Factor

Correction Factor = Antenna Factor + Cable Loss – Preamplifier Factor.

When Peak emission level was below AV limit, the AV emission level was not recorded.

TEST REPORT

Vertical



Frequency (MHz)	PK Reading Level (dB μ V)	Correction factors (dB/m)	PK Emission Level (dB μ V/m)	Limit (dB μ V/m)
2388.63	43.2	-2.3	40.9	74.0

Remark:

Final Test Level = Receiver Reading + Correction Factor


Correction Factor = Antenna Factor + Cable Loss – Preamplifier Factor.

When Peak emission level was below AV limit, the AV emission level was not recorded.

TEST REPORT

Test at Channel 6 (2.437 GHz) in transmitting status.
 30 MHz~1 GHz Radiated Emissions. Quasi-Peak Measurement


Horizontal:



Frequency (MHz)	Receiver Reading Level (dB μ V)	Correction factors (dB/m)	Emission Level (dB μ V/m)	Limit (dB μ V/m)
191.88	20.9	12.1	33.0	43.5
240.00	29.5	14.7	44.2	46.0
335.92	16.0	16.3	32.3	46.0

TEST REPORT

Vertical:



Frequency (MHz)	Receiver Reading Level (dB μ V)	Correction factors (dB/m)	Emission Level (dB μ V/m)	Limit (dB μ V/m)
122.64	15.0	10.4	25.4	43.5
232.84	7.4	14.4	21.8	46.0
336.04	6.8	16.3	23.1	46.0

Remark:

1. Corr. (dB) = Antenna Factor (dB) + Cable Loss (dB)
2. Quasi Peak (dB μ V/m) = Corr. (dB) + Read Level (dB μ V)
3. Margin (dB) = Limit QPK (dB μ V/m) - Quasi Peak (dB μ V/m)

TEST REPORT
1~25 GHz Radiated Emissions. Peak & Average Measurement
PK Measurement:

Frequency (MHz)	PK Reading Level (dB μ V)	Correction factors (dB/m)	PK Emission Level (dB μ V/m)	PK Limit (dB μ V/m)	Antenna polarization
4873.94	46.6	-0.5	46.1	74	Horizontal
7308.44	42.9	3.8	46.7	74	Horizontal
9748.00	46.1	6.8	52.9	74	Horizontal
4873.94	45.6	-0.5	45.1	74	Vertical
7308.44	42.4	3.8	46.2	74	Vertical
9748.00	45.6	6.8	52.4	74	Vertical

AV Measurement:

Frequency (MHz)	AV Reading Level (dB μ V)	Correction factors (dB/m)	AV Emission Level (dB μ V/m)	AV Limit (dB μ V/m)	Antenna polarization
4873.94	/	-0.5	/	54	Horizontal
7308.44	/	3.8	/	54	Horizontal
9748.00	/	6.8	/	54	Horizontal
4873.94	/	-0.5	/	54	Vertical
7308.44	/	3.8	/	54	Vertical
9748.00	/	6.8	/	54	Vertical

The field strength is calculated by adding the Antenna Factor, Cable Factor & Preamplifier. The basic equation with a sample calculation is as follows:

Final Test Level = Receiver Reading + Correction Factor

Correction Factor = Antenna Factor + Cable Loss - Preamplifier Factor.


Remark:

Harmonic Emissions was tested with filter (Product name: MICRO-TRONICS, model name: BRM50702), other radiated emissions were found below the reference noise level
 When Peak emission level was below AV limit, the AV emission level was not recorded.

TEST REPORT

Test at Channel 11 (2.462 GHz) in transmitting status
 30 MHz~1 GHz Radiated Emissions .Quasi-Peak Measurement

Horizontal:




Frequency (MHz)	Receiver Reading Level (dB μ V)	Correction factors (dB/m)	Emission Level (dB μ V/m)	Limit (dB μ V/m)
192.00	21.0	12.1	33.1	43.5
240.01	27.1	14.7	41.8	46.0
335.44	17.4	16.3	33.7	46.0

Remark:

1. Corr. (dB) = Antenna Factor (dB) + Cable Loss (dB)
2. Quasi Peak (dB μ V/m) = Corr. (dB) + Read Level (dB μ V)
3. Margin (dB) = Limit QPK (dB μ V/m) – Quasi Peak (dB μ V/m)

TEST REPORT

Vertical:



Frequency (MHz)	Receiver Reading Level (dB μ V)	Correction factors (dB/m)	Emission Level (dB μ V/m)	Limit (dB μ V/m)
120.32	17.1	10.9	28.0	43.5
173.44	11.3	10.8	22.1	43.5
228.00	9.0	14.2	23.2	46.0

Remark:

1. Corr. (dB) = Antenna Factor (dB) + Cable Loss (dB)
2. Quasi Peak (dB μ V/m) = Corr. (dB) + Read Level (dB μ V)
3. Margin (dB) = Limit QPK (dB μ V/m) – Quasi Peak (dB μ V/m)

TEST REPORT
1~25 GHz Radiated Emissions. Peak & Average Measurement
PK Measurement:

Frequency (MHz)	PK Reading Level (dB μ V)	Correction factors (dB/m)	PK Emission Level (dB μ V/m)	PK Limit (dB μ V/m)	Antenna polarization
4924.00	45.3	-0.5	44.8	74	Horizontal
7385.50	42.0	4.2	46.2	74	Horizontal
9848.13	46.4	7.3	53.7	74	Horizontal
4924.00	44.6	-0.5	44.1	74	Vertical
7385.50	41.7	4.2	45.9	74	Vertical
9848.13	44.6	7.3	51.9	74	Vertical

AV Measurement:

Frequency (MHz)	AV Reading Level (dB μ V)	Correction factors (dB/m)	AV Emission Level (dB μ V/m)	AV Limit (dB μ V/m)	Antenna polarization
4924.00	/	-0.5	/	54	Horizontal
7385.50	/	4.2	/	54	Horizontal
9848.13	/	7.3	/	54	Horizontal
4924.00	/	-0.5	/	54	Vertical
7385.50	/	4.2	/	54	Vertical
9848.13	/	7.3	/	54	Vertical

The field strength is calculated by adding the Antenna Factor, Cable Factor & Preamplifier. The basic equation with a sample calculation is as follows:

Final Test Level = Receiver Reading + Correction Factor

Correction Factor = Antenna Factor + Cable Loss - Preamplifier Factor.

Remark:


Harmonic Emissions was tested with filter (Product name: MICRO-TRONICS, model name: BRM50702), other radiated emissions were found below the reference noise level

When Peak emission level was below AV limit, the AV emission level was not recorded.

TEST REPORT

Band Edge test Restricted Bands

Horizontal



Frequency (MHz)	PK Reading Level (dB μ V)	Correction factors (dB/m)	PK Emission Level (dB μ V/m)	Limit (dB μ V/m)
2484.00	45.4	-2.1	43.3	74.0

Remark:


Final Test Level = Receiver Reading + Correction Factor

Correction Factor = Antenna Factor + Cable Loss – Preamplifier Factor.

When Peak emission level was below AV limit, the AV emission level was not recorded.

TEST REPORT

Vertical



Frequency (MHz)	PK Reading Level (dB μ V)	Correction factors (dB/m)	PK Emission Level (dB μ V/m)	Limit (dB μ V/m)
2493.33	46.5	-2.1	44.4	74.0

Remark:

Final Test Level = Receiver Reading + Correction Factor

Correction Factor = Antenna Factor + Cable Loss – Preamplifier Factor.

When Peak emission level was below AV limit, the AV emission level was not recorded.

TEST REPORT

802.11g mode with 6Mbps data rate


9 kHz~30 MHz Field Strength of Unwanted Emissions. Quasi-Peak Measurement

The measurements with active loop antenna were greater than 20dB below the limit, so the test data were not recorded in the test report.

Test at Channel 1 (2.412 GHz) in transmitting status

30 MHz~1 GHz Spurious Emissions .Quasi-Peak Measurement

Horizontal:




Frequency (MHz)	Receiver Reading Level (dBµV)	Correction factors (dB/m)	Emission Level (dBµV/m)	Limit (dBµV/m)
143.72	19.9	9.7	29.6	43.5
240.00	28.3	14.7	43.0	46.0
336.04	17.7	16.3	34.0	46.0

Remark:

1. Corr. (dB) = Antenna Factor (dB) + Cable Loss (dB)
2. Quasi Peak (dBµV/m) = Corr. (dB) + Read Level (dBµV)
3. Margin (dB) = Limit QPK (dBµV/m) – Quasi Peak (dBµV/m)

TEST REPORT

Vertical:



Frequency (MHz)	Receiver Reading Level (dBµV)	Correction factors (dB/m)	Emission Level (dBµV/m)	Limit (dBµV/m)
141.92	12.5	9.7	22.2	43.5
189.80	9.3	11.9	21.2	43.5
232.24	8.9	14.4	23.3	46.0

Remark:

1. Corr. (dB) = Antenna Factor (dB) + Cable Loss (dB)
2. Quasi Peak (dBµV/m) = Corr. (dB) + Read Level (dBµV)
3. Margin (dB) = Limit QPK (dBµV/m) – Quasi Peak (dBµV/m)

TEST REPORT

1~25 GHz Radiated Emissions.

PK Measurement:

Frequency (MHz)	PK Reading Level (dB μ V)	Correction factors (dB/m)	PK Emission Level (dB μ V/m)	PK Limit (dB μ V/m)	Antenna polarization
4823.88	46.7	-0.5	46.2	74	Horizontal
7236.34	43.3	3.4	46.7	74	Horizontal
9648.06	47.4	6.3	53.7	74	Horizontal
4823.88	46.4	-0.5	45.9	74	Vertical
7236.34	43.1	3.4	46.5	74	Vertical
9648.06	45.5	6.3	51.8	74	Vertical

AV Measurement:

Frequency (MHz)	AV Reading Level (dB μ V)	Correction factors (dB/m)	AV Emission Level (dB μ V/m)	AV Limit (dB μ V/m)	Antenna polarization
4823.88	/	-0.5	/	54	Horizontal
7236.34	/	3.4	/	54	Horizontal
9648.06	/	6.3	/	54	Horizontal
4823.88	/	-0.5	/	54	Vertical
7236.34	/	3.4	/	54	Vertical
9648.06	/	6.3	/	54	Vertical

The field strength is calculated by adding the Antenna Factor, Cable Factor & Preamplifier. The basic equation with a sample calculation is as follows:

Final Test Level = Receiver Reading + Correction Factor

Correction Factor = Antenna Factor + Cable Loss - Preamplifier Factor.

Remark:

Harmonic Emissions was tested with filter (Product name: MICRO-TRONICS, model name:


BRM50702), other radiated emissions were found below the reference noise level

When Peak emission level was below AV limit, the AV emission level was not recorded.

TEST REPORT

Band Edge test Restricted Bands

Horizontal



Frequency (MHz)	PK Reading Level (dB μ V)	Correction factors (dB/m)	PK Emission Level (dB μ V/m)	Limit (dB μ V/m)
2390.00	47.2	-2.3	44.9	74.0

Remark:


Final Test Level = Receiver Reading + Correction Factor

Correction Factor = Antenna Factor + Cable Loss – Preamplifier Factor.

When Peak emission level was below AV limit, the AV emission level was not recorded.

TEST REPORT

Vertical



Frequency (MHz)	PK Reading Level (dB μ V)	Correction factors (dB/m)	PK Emission Level (dB μ V/m)	Limit (dB μ V/m)
2390.00	42.7	-2.3	40.4	74.0

Remark:

Final Test Level = Receiver Reading + Correction Factor


Correction Factor = Antenna Factor + Cable Loss – Preamplifier Factor.

When Peak emission level was below AV limit, the AV emission level was not recorded.

TEST REPORT

Test at Channel 6 (2.437 GHz) in transmitting status
 30 MHz~1 GHz Radiated Emissions. Quasi-Peak Measurement


Horizontal:



Frequency (MHz)	Receiver Reading Level (dB μ V)	Correction factors (dB/m)	Emission Level (dB μ V/m)	Limit (dB μ V/m)
192.00	20.7	12.1	32.8	43.5
240.02	28.1	14.7	42.8	46.0
336.04	17.6	16.3	33.9	46.0

TEST REPORT

Vertical:



Frequency (MHz)	Receiver Reading Level (dB μ V)	Correction factors (dB/m)	Emission Level (dB μ V/m)	Limit (dB μ V/m)
121.16	17.1	10.7	27.8	43.5
143.96	16.6	9.7	26.3	43.5
239.52	13.4	14.7	28.1	46.0

Remark:

1. Corr. (dB) = Antenna Factor (dB) + Cable Loss (dB)
2. Quasi Peak (dB μ V/m) = Corr. (dB) + Read Level (dB μ V)
3. Margin (dB) = Limit QPK (dB μ V/m) - Quasi Peak (dB μ V/m)

TEST REPORT

1~25 GHz Radiated Emissions. Peak & Average Measurement

PK Measurement:

Frequency (MHz)	PK Reading Level (dB μ V)	Correction factors (dB/m)	PK Emission Level (dB μ V/m)	PK Limit (dB μ V/m)	Antenna polarization
4873.94	46.8	-0.5	46.3	74	Horizontal
7308.45	41.9	3.8	45.7	74	Horizontal
9748.19	47.4	6.8	54.2	74	Horizontal
4873.94	46.6	-0.5	46.1	74	Vertical
7308.45	42.6	3.8	46.4	74	Vertical
9748.19	47.6	6.8	54.4	74	Vertical

AV Measurement:

Frequency (MHz)	AV Reading Level (dB μ V)	Correction factors (dB/m)	AV Emission Level (dB μ V/m)	AV Limit (dB μ V/m)	Antenna polarization
4873.94	/	-0.5	/	54	Horizontal
7308.45	/	3.8	/	54	Horizontal
9748.19	45.3	6.8	52.1	54	Horizontal
4873.94	/	-0.5	/	54	Vertical
7308.45	/	3.8	/	54	Vertical
9748.19	35.1	6.8	41.9	54	Vertical

The field strength is calculated by adding the Antenna Factor, Cable Factor & Preamplifier. The basic equation with a sample calculation is as follows:

Final Test Level = Receiver Reading + Correction Factor

Correction Factor = Antenna Factor + Cable Loss - Preamplifier Factor.

Remark:


Harmonic Emissions was tested with filter (Product name: MICRO-TRONICS, model name: BRM50702), other radiated emissions were found below the reference noise level

When Peak emission level was below AV limit, the AV emission level was not recorded.

TEST REPORT

Test at Channel 11 (2.462 GHz) in transmitting status
 30 MHz~1 GHz Radiated Emissions .Quasi-Peak Measurement

Horizontal:




Frequency (MHz)	Receiver Reading Level (dB μ V)	Correction factors (dB/m)	Emission Level (dB μ V/m)	Limit (dB μ V/m)
192.00	20.5	12.1	32.6	43.5
240.00	26.5	14.7	41.2	46.0
335.32	17.2	16.3	33.5	46.0

Remark:

1. Corr. (dB) = Antenna Factor (dB) + Cable Loss (dB)
2. Quasi Peak (dB μ V/m) = Corr. (dB) + Read Level (dB μ V)
3. Margin (dB) = Limit QPK (dB μ V/m) – Quasi Peak (dB μ V/m)

TEST REPORT

Vertical:



Frequency (MHz)	Receiver Reading Level (dB μ V)	Correction factors (dB/m)	Emission Level (dB μ V/m)	Limit (dB μ V/m)
119.36	15.6	11.1	26.7	43.5
140.96	13.4	9.6	23.0	43.5
240.00	13.9	14.7	28.6	46.0

Remark:

1. Corr. (dB) = Antenna Factor (dB) + Cable Loss (dB)
2. Quasi Peak (dB μ V/m) = Corr. (dB) + Read Level (dB μ V)
3. Margin (dB) = Limit QPK (dB μ V/m) – Quasi Peak (dB μ V/m)

TEST REPORT
1~25 GHz Radiated Emissions. Peak & Average Measurement
PK Measurement:

Frequency (MHz)	PK Reading Level (dB μ V)	Correction factors (dB/m)	PK Emission Level (dB μ V/m)	PK Limit (dB μ V/m)	Antenna polarization
4924.00	46.3	-0.5	45.8	74	Horizontal
7385.51	41.9	4.2	46.1	74	Horizontal
9848.13	47.1	7.3	54.4	74	Horizontal
4924.00	46.7	-0.5	46.2	74	Vertical
7385.51	41.5	4.2	45.7	74	Vertical
9848.13	45.2	7.3	52.5	74	Vertical

AV Measurement:

Frequency (MHz)	AV Reading Level (dB μ V)	Correction factors (dB/m)	AV Emission Level (dB μ V/m)	AV Limit (dB μ V/m)	Antenna polarization
4924.00	/	-0.5	/	54	Horizontal
7385.51	/	4.2	/	54	Horizontal
9848.13	45.0	7.3	52.3	54	Horizontal
4924.00	/	-0.5	/	54	Vertical
7385.51	/	4.2	/	54	Vertical
9848.13	/	7.3	/	54	Vertical

The field strength is calculated by adding the Antenna Factor, Cable Factor & Preamplifier. The basic equation with a sample calculation is as follows:

Final Test Level = Receiver Reading + Correction Factor

Correction Factor = Antenna Factor + Cable Loss - Preamplifier Factor.


Remark:

Harmonic Emissions was tested with filter (Product name: MICRO-TRONICS, model name: BRM50702), other radiated emissions were found below the reference noise level
 When Peak emission level was below AV limit, the AV emission level was not recorded.

TEST REPORT

Band Edge test Restricted Bands

Horizontal



Frequency (MHz)	PK Reading Level (dB μ V)	Correction factors (dB/m)	PK Emission Level (dB μ V/m)	Limit (dB μ V/m)
2484.83	47.7	-2.1	45.6	74.0

Remark:


Final Test Level = Receiver Reading + Correction Factor

Correction Factor = Antenna Factor + Cable Loss – Preamplifier Factor.

When Peak emission level was below AV limit, the AV emission level was not recorded.

TEST REPORT

Vertical



Frequency (MHz)	PK Reading Level (dB μ V)	Correction factors (dB/m)	PK Emission Level (dB μ V/m)	Limit (dB μ V/m)
2488.00	45.7	-2.1	43.6	74.0

Remark:

Final Test Level = Receiver Reading + Correction Factor

Correction Factor = Antenna Factor + Cable Loss – Preamplifier Factor.

When Peak emission level was below AV limit, the AV emission level was not recorded.

TEST REPORT

802.11n (HT20) mode with 6.5Mbps data rate


9 kHz~30 MHz Field Strength of Unwanted Emissions. Quasi-Peak Measurement

The measurements with active loop antenna were greater than 20dB below the limit, so the test data were not recorded in the test report.

Test at Channel 1 (2.412 GHz) in transmitting status

30 MHz~1 GHz Spurious Emissions .Quasi-Peak Measurement

Horizontal:




Frequency (MHz)	Receiver Reading Level (dBµV)	Correction factors (dB/m)	Emission Level (dBµV/m)	Limit (dBµV/m)
191.16	20.4	12.1	32.5	43.5
240.00	27.7	14.7	42.4	46.0
335.32	17.0	16.3	33.3	46.0

Remark:

1. Corr. (dB) = Antenna Factor (dB) + Cable Loss (dB)
2. Quasi Peak (dBµV/m) = Corr. (dB) + Read Level (dBµV)
3. Margin (dB) = Limit QPK (dBµV/m) – Quasi Peak (dBµV/m)

TEST REPORT

Vertical:



Frequency (MHz)	Receiver Reading Level (dB μ V)	Correction factors (dB/m)	Emission Level (dB μ V/m)	Limit (dB μ V/m)
120.56	16.7	10.8	27.5	43.5
223.16	8.0	13.9	21.9	46.0
335.32	8.5	16.3	24.8	46.0

Remark:

1. Corr. (dB) = Antenna Factor (dB) + Cable Loss (dB)
2. Quasi Peak (dB μ V/m) = Corr. (dB) + Read Level (dB μ V)
3. Margin (dB) = Limit QPK (dB μ V/m) – Quasi Peak (dB μ V/m)

TEST REPORT

1~25 GHz Radiated Emissions.

PK Measurement:

Frequency (MHz)	PK Reading Level (dB μ V)	Correction factors (dB/m)	PK Emission Level (dB μ V/m)	PK Limit (dB μ V/m)	Antenna polarization
4823.87	46.4	-0.5	45.9	74	Horizontal
7236.32	42.9	3.4	46.3	74	Horizontal
9648.06	47.9	6.3	54.2	74	Horizontal
4823.87	46.8	-0.5	46.3	74	Vertical
7236.32	43.4	3.4	46.8	74	Vertical
9648.06	45.5	6.3	51.8	74	Vertical

AV Measurement:

Frequency (MHz)	AV Reading Level (dB μ V)	Correction factors (dB/m)	AV Emission Level (dB μ V/m)	AV Limit (dB μ V/m)	Antenna polarization
4823.87	/	-0.5	/	54	Horizontal
7236.32	/	3.4	/	54	Horizontal
9648.06	44.8	6.3	51.1	54	Horizontal
4823.87	/	-0.5	/	54	Vertical
7236.32	/	3.4	/	54	Vertical
9648.06	/	6.3	/	54	Vertical

The field strength is calculated by adding the Antenna Factor, Cable Factor & Preamplifier. The basic equation with a sample calculation is as follows:

Final Test Level = Receiver Reading + Correction Factor

Correction Factor = Antenna Factor + Cable Loss - Preamplifier Factor.

Remark:

Harmonic Emissions was tested with filter (Product name: MICRO-TRONICS, model name:


BRM50702), other radiated emissions were found below the reference noise level

When Peak emission level was below AV limit, the AV emission level was not recorded.

TEST REPORT

Band Edge test Restricted Bands

Horizontal



Frequency (MHz)	PK Reading Level (dB μ V)	Correction factors (dB/m)	PK Emission Level (dB μ V/m)	Limit (dB μ V/m)
2390.00	47.6	-2.3	45.3	74.0

Remark:


Final Test Level = Receiver Reading + Correction Factor

Correction Factor = Antenna Factor + Cable Loss – Preamplifier Factor.

When Peak emission level was below AV limit, the AV emission level was not recorded.

TEST REPORT

Vertical



Frequency (MHz)	PK Reading Level (dB μ V)	Correction factors (dB/m)	PK Emission Level (dB μ V/m)	Limit (dB μ V/m)
2390.00	44.7	-2.3	42.4	74.0

Remark:

Final Test Level = Receiver Reading + Correction Factor


Correction Factor = Antenna Factor + Cable Loss – Preamplifier Factor.

When Peak emission level was below AV limit, the AV emission level was not recorded.

TEST REPORT

Test at Channel 6 (2.437 GHz) in transmitting status
 30 MHz~1 GHz Radiated Emissions .Quasi-Peak Measurement


Horizontal:



Frequency (MHz)	Receiver Reading Level (dB μ V)	Correction factors (dB/m)	Emission Level (dB μ V/m)	Limit (dB μ V/m)
191.64	21.1	12.1	33.2	43.5
240.00	26.3	14.7	41.0	46.0
336.04	16.9	16.3	33.2	46.0

TEST REPORT

Vertical:



Frequency (MHz)	Receiver Reading Level (dB μ V)	Correction factors (dB/m)	Emission Level (dB μ V/m)	Limit (dB μ V/m)
121.56	19.5	10.6	30.1	43.5
192.00	12.9	12.1	25.0	43.5
240.00	17.0	14.7	31.7	46.0

Remark:

1. Corr. (dB) = Antenna Factor (dB) + Cable Loss (dB)
2. Quasi Peak (dB μ V/m) = Corr. (dB) + Read Level (dB μ V)
3. Margin (dB) = Limit QPK (dB μ V/m) – Quasi Peak (dB μ V/m)

TEST REPORT
1~25 GHz Radiated Emissions. Peak & Average Measurement
PK Measurement:

Frequency (MHz)	PK Reading Level (dB μ V)	Correction factors (dB/m)	PK Emission Level (dB μ V/m)	PK Limit (dB μ V/m)	Antenna polarization
4873.94	46.3	-0.5	45.8	74	Horizontal
7308.47	42.3	3.8	46.1	74	Horizontal
9748.19	46.1	6.8	52.9	74	Horizontal
4873.94	47.2	-0.5	46.7	74	Vertical
7308.47	42.7	3.8	46.5	74	Vertical
9748.19	46.3	6.8	53.1	74	Vertical

AV Measurement:

Frequency (MHz)	AV Reading Level (dB μ V)	Correction factors (dB/m)	AV Emission Level (dB μ V/m)	AV Limit (dB μ V/m)	Antenna polarization
4873.94	/	-0.5	/	54	Horizontal
7308.47	/	3.8	/	54	Horizontal
9748.19	/	6.8	/	54	Horizontal
4873.94	/	-0.5	/	54	Vertical
7308.47	/	3.8	/	54	Vertical
9748.19	/	6.8	/	54	Vertical

The field strength is calculated by adding the Antenna Factor, Cable Factor & Preamplifier. The basic equation with a sample calculation is as follows:

Final Test Level = Receiver Reading + Correction Factor

Correction Factor = Antenna Factor + Cable Loss - Preamplifier Factor.

Remark:


Harmonic Emissions was tested with filter (Product name: MICRO-TRONICS, model name: BRM50702), other radiated emissions were found below the reference noise level

When Peak emission level was below AV limit, the AV emission level was not recorded.

TEST REPORT

Test at Channel 11 (2.462 GHz) in transmitting status
 30 MHz~1 GHz Radiated Emissions .Quasi-Peak Measurement

Horizontal:




Frequency (MHz)	Receiver Reading Level (dB μ V)	Correction factors (dB/m)	Emission Level (dB μ V/m)	Limit (dB μ V/m)
192.00	20.4	12.1	32.5	43.5
240.01	27.0	14.7	41.7	46.0
336.04	16.7	16.3	33.0	46.0

Remark:

1. Corr. (dB) = Antenna Factor (dB) + Cable Loss (dB)
2. Quasi Peak (dB μ V/m) = Corr. (dB) + Read Level (dB μ V)
3. Margin (dB) = Limit QPK (dB μ V/m) – Quasi Peak (dB μ V/m)

TEST REPORT

Vertical:



Frequency (MHz)	Receiver Reading Level (dBµV)	Correction factors (dB/m)	Emission Level (dBµV/m)	Limit (dBµV/m)
122.52	16.0	10.5	26.5	43.5
134.88	13.9	9.3	23.2	43.5
239.88	13.7	14.7	28.4	46.0

Remark:

1. Corr. (dB) = Antenna Factor (dB) + Cable Loss (dB)
2. Quasi Peak (dBµV/m) = Corr. (dB) + Read Level (dBµV)
3. Margin (dB) = Limit QPK (dBµV/m) - Quasi Peak (dBµV/m)

TEST REPORT

1~25 GHz Radiated Emissions. Peak & Average Measurement

PK Measurement:

Frequency (MHz)	PK Reading Level (dB μ V)	Correction factors (dB/m)	PK Emission Level (dB μ V/m)	PK Limit (dB μ V/m)	Antenna polarization
4924.00	46.7	-0.5	46.2	74	Horizontal
7385.52	41.6	4.2	45.8	74	Horizontal
9848.13	46.2	7.3	53.5	74	Horizontal
4924.00	46.6	-0.5	46.1	74	Vertical
7385.52	42.5	4.2	46.7	74	Vertical
9848.13	46.3	7.3	53.6	74	Vertical

AV Measurement:

Frequency (MHz)	AV Reading Level (dB μ V)	Correction factors (dB/m)	AV Emission Level (dB μ V/m)	AV Limit (dB μ V/m)	Antenna polarization
4924.00	/	-0.5	/	54	Horizontal
7385.52	/	4.2	/	54	Horizontal
9848.13	/	7.3	/	54	Horizontal
4924.00	/	-0.5	/	54	Vertical
7385.52	/	4.2	/	54	Vertical
9848.13	/	7.3	/	54	Vertical

The field strength is calculated by adding the Antenna Factor, Cable Factor & Preamplifier. The basic equation with a sample calculation is as follows:

Final Test Level = Receiver Reading + Correction Factor

Correction Factor = Antenna Factor + Cable Loss - Preamplifier Factor.


Remark:

Harmonic Emissions was tested with filter (Product name: MICRO-TRONICS, model name: BRM50702), other radiated emissions were found below the reference noise level
 When Peak emission level was below AV limit, the AV emission level was not recorded.

TEST REPORT

Band Edge test Restricted Bands

Horizontal



Frequency (MHz)	PK Reading Level (dB μ V)	Correction factors (dB/m)	PK Emission Level (dB μ V/m)	Limit (dB μ V/m)
2484.33	49.4	-2.1	47.3	74.0

Remark:


Final Test Level = Receiver Reading + Correction Factor

Correction Factor = Antenna Factor + Cable Loss – Preamplifier Factor.

When Peak emission level was below AV limit, the AV emission level was not recorded.

TEST REPORT

Vertical



Frequency (MHz)	PK Reading Level (dB μ V)	Correction factors (dB/m)	PK Emission Level (dB μ V/m)	Limit (dB μ V/m)
2495.00	47.7	-2.1	45.6	74.0

Remark:

Final Test Level = Receiver Reading + Correction Factor

Correction Factor = Antenna Factor + Cable Loss – Preamplifier Factor.

When Peak emission level was below AV limit, the AV emission level was not recorded.

TEST REPORT

802.11n (HT40) mode with 13.5Mbps data rate


9 kHz~30 MHz Field Strength of Unwanted Emissions. Quasi-Peak Measurement

The measurements with active loop antenna were greater than 20dB below the limit, so the test data were not recorded in the test report.

Test at Channel 3 (2.422 GHz) in transmitting status

30 MHz~1 GHz Spurious Emissions .Quasi-Peak Measurement

Horizontal:




Frequency (MHz)	Receiver Reading Level (dBµV)	Correction factors (dB/m)	Emission Level (dBµV/m)	Limit (dBµV/m)
192.00	21.2	12.1	33.3	43.5
239.52	26.0	14.7	40.7	46.0
335.32	15.8	16.3	32.1	46.0

Remark:

1. Corr. (dB) = Antenna Factor (dB) + Cable Loss (dB)
2. Quasi Peak (dBµV/m) = Corr. (dB) + Read Level (dBµV)
3. Margin (dB) = Limit QPK (dBµV/m) – Quasi Peak (dBµV/m)

TEST REPORT

Vertical:



Frequency (MHz)	Receiver Reading Level (dB μ V)	Correction factors (dB/m)	Emission Level (dB μ V/m)	Limit (dB μ V/m)
119.60	16.4	11.0	27.4	43.5
200.84	8.5	12.9	21.4	43.5
336.16	6.4	16.3	22.7	46.0

Remark:

1. Corr. (dB) = Antenna Factor (dB) + Cable Loss (dB)
2. Quasi Peak (dB μ V/m) = Corr. (dB) + Read Level (dB μ V)
3. Margin (dB) = Limit QPK (dB μ V/m) – Quasi Peak (dB μ V/m)

TEST REPORT

1~25 GHz Radiated Emissions.

PK Measurement:

Frequency (MHz)	PK Reading Level (dB μ V)	Correction factors (dB/m)	PK Emission Level (dB μ V/m)	PK Limit (dB μ V/m)	Antenna polarization
4843.94	45.8	-0.5	45.3	74	Horizontal
7264.38	42.7	3.4	46.1	74	Horizontal
9688.19	48.1	6.3	54.4	74	Horizontal
4843.94	45.4	-0.5	44.9	74	Vertical
7264.38	41.7	3.4	45.1	74	Vertical
9688.19	46.1	6.3	52.4	74	Vertical

AV Measurement:

Frequency (MHz)	AV Reading Level (dB μ V)	Correction factors (dB/m)	AV Emission Level (dB μ V/m)	AV Limit (dB μ V/m)	Antenna polarization
4843.94	/	-0.5	/	54	Horizontal
7264.38	/	3.4	/	54	Horizontal
9688.19	41.0	6.3	47.3	54	Horizontal
4843.94	/	-0.5	/	54	Vertical
7264.38	/	3.4	/	54	Vertical
9688.19	/	6.3	/	54	Vertical

The field strength is calculated by adding the Antenna Factor, Cable Factor & Preamplifier. The basic equation with a sample calculation is as follows:

Final Test Level = Receiver Reading + Correction Factor

Correction Factor = Antenna Factor + Cable Loss - Preamplifier Factor.

Remark:

Harmonic Emissions was tested with filter (Product name: MICRO-TRONICS, model name:


BRM50702), other radiated emissions were found below the reference noise level

When Peak emission level was below AV limit, the AV emission level was not recorded.

TEST REPORT

Band Edge test Restricted Bands

Horizontal



Frequency (MHz)	PK Reading Level (dB μ V)	Correction factors (dB/m)	PK Emission Level (dB μ V/m)	Limit (dB μ V/m)
2386.30	50.5	-2.3	48.2	74.0

Remark:


Final Test Level = Receiver Reading + Correction Factor

Correction Factor = Antenna Factor + Cable Loss – Preamplifier Factor.

When Peak emission level was below AV limit, the AV emission level was not recorded.

TEST REPORT

Vertical



Frequency (MHz)	PK Reading Level (dB μ V)	Correction factors (dB/m)	PK Emission Level (dB μ V/m)	Limit (dB μ V/m)
2386.30	45.8	-2.3	43.5	74.0

Remark:

Final Test Level = Receiver Reading + Correction Factor


Correction Factor = Antenna Factor + Cable Loss – Preamplifier Factor.

When Peak emission level was below AV limit, the AV emission level was not recorded.

TEST REPORT

Test at Channel 6 (2.437 GHz) in transmitting status
 30 MHz~1 GHz Radiated Emissions .Quasi-Peak Measurement


Horizontal:



Frequency (MHz)	Receiver Reading Level (dB μ V)	Correction factors (dB/m)	Emission Level (dB μ V/m)	Limit (dB μ V/m)
191.64	20.2	12.1	32.3	43.5
240.00	26.9	14.7	41.6	46.0
335.44	17.7	16.3	34.0	46.0

TEST REPORT

Vertical:



Frequency (MHz)	Receiver Reading Level (dB μ V)	Correction factors (dB/m)	Emission Level (dB μ V/m)	Limit (dB μ V/m)
118.40	14.6	11.3	25.9	43.5
224.00	8.4	14.0	22.4	46.0
336.16	8.0	16.3	24.3	46.0

Remark:

1. Corr. (dB) = Antenna Factor (dB) + Cable Loss (dB)
2. Quasi Peak (dB μ V/m) = Corr. (dB) + Read Level (dB μ V)
3. Margin (dB) = Limit QPK (dB μ V/m) – Quasi Peak (dB μ V/m)

TEST REPORT
1~25 GHz Radiated Emissions. Peak & Average Measurement
PK Measurement:

Frequency (MHz)	PK Reading Level (dB μ V)	Correction factors (dB/m)	PK Emission Level (dB μ V/m)	PK Limit (dB μ V/m)	Antenna polarization
4873.94	45.8	-0.5	45.3	74	Horizontal
7308.46	41.9	3.8	45.7	74	Horizontal
9748.19	50.3	6.8	57.1	74	Horizontal
4873.94	46.3	-0.5	45.8	74	Vertical
7308.46	42.4	3.8	46.2	74	Vertical
9748.19	45.9	6.8	52.7	74	Vertical

AV Measurement:

Frequency (MHz)	AV Reading Level (dB μ V)	Correction factors (dB/m)	AV Emission Level (dB μ V/m)	AV Limit (dB μ V/m)	Antenna polarization
4873.94	/	-0.5	/	54	Horizontal
7308.46	/	3.8	/	54	Horizontal
9748.19	44.0	6.8	50.8	54	Horizontal
4873.94	/	-0.5	/	54	Vertical
7308.46	/	3.8	/	54	Vertical
9748.19	/	6.8	/	54	Vertical

The field strength is calculated by adding the Antenna Factor, Cable Factor & Preamplifier. The basic equation with a sample calculation is as follows:

Final Test Level = Receiver Reading + Correction Factor

Correction Factor = Antenna Factor + Cable Loss - Preamplifier Factor.

Remark:


Harmonic Emissions was tested with filter (Product name: MICRO-TRONICS, model name: BRM50702), other radiated emissions were found below the reference noise level

When Peak emission level was below AV limit, the AV emission level was not recorded.

TEST REPORT

Test at Channel 7 (2.452 GHz) in transmitting status
 30 MHz~1 GHz Radiated Emissions .Quasi-Peak Measurement

Horizontal:




Frequency (MHz)	Receiver Reading Level (dB μ V)	Correction factors (dB/m)	Emission Level (dB μ V/m)	Limit (dB μ V/m)
191.64	19.3	12.1	31.4	43.5
240.00	26.7	14.7	41.4	46.0
335.44	18.6	16.3	34.9	46.0

Remark:

1. Corr. (dB) = Antenna Factor (dB) + Cable Loss (dB)
2. Quasi Peak (dB μ V/m) = Corr. (dB) + Read Level (dB μ V)
3. Margin (dB) = Limit QPK (dB μ V/m) – Quasi Peak (dB μ V/m)

TEST REPORT

Vertical:



Frequency (MHz)	Receiver Reading Level (dBµV)	Correction factors (dB/m)	Emission Level (dBµV/m)	Limit (dBµV/m)
118.76	13.6	11.2	24.8	43.5
138.52	13.6	9.5	23.1	43.5
239.52	15.0	14.7	29.7	46.0

Remark:

1. Corr. (dB) = Antenna Factor (dB) + Cable Loss (dB)
2. Quasi Peak (dBµV/m) = Corr. (dB) + Read Level (dBµV)
3. Margin (dB) = Limit QPK (dBµV/m) – Quasi Peak (dBµV/m)

TEST REPORT

1~25 GHz Radiated Emissions. Peak & Average Measurement

PK Measurement:

Frequency (MHz)	PK Reading Level (dB μ V)	Correction factors (dB/m)	PK Emission Level (dB μ V/m)	PK Limit (dB μ V/m)	Antenna polarization
4903.94	45.3	-0.5	44.8	74	Horizontal
7355.47	42.7	4.2	46.9	74	Horizontal
9808.19	46.1	7.3	53.4	74	Horizontal
4903.94	45.7	-0.5	45.2	74	Vertical
7355.47	42.5	4.2	46.7	74	Vertical
9808.19	45.8	7.3	53.1	74	Vertical

AV Measurement:

Frequency (MHz)	AV Reading Level (dB μ V)	Correction factors (dB/m)	AV Emission Level (dB μ V/m)	AV Limit (dB μ V/m)	Antenna polarization
4903.94	/	-0.5	/	54	Horizontal
7355.47	/	4.2	/	54	Horizontal
9808.19	/	7.3	/	54	Horizontal
4903.94	/	-0.5	/	54	Vertical
7355.47	/	4.2	/	54	Vertical
9808.19	/	7.3	/	54	Vertical

The field strength is calculated by adding the Antenna Factor, Cable Factor & Preamplifier. The basic equation with a sample calculation is as follows:

Final Test Level = Receiver Reading + Correction Factor

Correction Factor = Antenna Factor + Cable Loss - Preamplifier Factor.


Remark:

Harmonic Emissions was tested with filter (Product name: MICRO-TRONICS, model name: BRM50702), other radiated emissions were found below the reference noise level
 When Peak emission level was below AV limit, the AV emission level was not recorded.

TEST REPORT

Band Edge test Restricted Bands

Horizontal



Frequency (MHz)	PK Reading Level (dB μ V)	Correction factors (dB/m)	PK Emission Level (dB μ V/m)	Limit (dB μ V/m)
2484.50	53.6	-2.1	51.5	74.0

Remark:


Final Test Level = Receiver Reading + Correction Factor

Correction Factor = Antenna Factor + Cable Loss – Preamplifier Factor.

When Peak emission level was below AV limit, the AV emission level was not recorded.

TEST REPORT

Vertical



Frequency (MHz)	PK Reading Level (dBμV)	Correction factors (dB/m)	PK Emission Level (dBμV/m)	Limit (dBμV/m)
2492.50	47.9	-2.1	45.8	74.0

Remark:


Final Test Level = Receiver Reading + Correction Factor

Correction Factor = Antenna Factor + Cable Loss - Preamplifier Factor.

When Peak emission level was below AV limit, the AV emission level was not recorded.

TEST REPORT**4.8 Band Edges Requirement**

Test Requirement:	FCC Part 15 C section 15.247
	(d) In any 100 kHz bandwidth outside the frequency band in which the spread spectrum or digitally modulated intentional radiator is operating. The radio frequency power that is produced by the intentional radiator shall be at least 20 dB below that in the 100 kHz bandwidth within the band that contains the highest level of the desired power. Based on either an RF conducted or a radiated measurement. Provided the transmitter demonstrates compliance with the peak conducted power limits.
Frequency Band:	2400 MHz to 2483.5 MHz
Test Method:	ANSI C63.10: Clause 11.11 and 11.13
Test Status:	Pre-Scan has been conducted to determine the worst-case mode from all possible combinations between available modulations, data rates and antenna ports (if EUT with antenna diversity architecture). Following channel(s) was (were) selected for the final test as listed below.
Test Configuration:	For Band Edges Emission in Radiated mode, Please refer to clause 4.7



Test Procedure: For Band Edges Emission in Radiated mode, Please refer to clause 4.7

1. Remove the antenna from the EUT and then connect a low RF cable from the antenna port to the spectrum analyzer.
 - a) Set instrument center frequency to the frequency of the emission to be measured (must be within 2 MHz of the authorized band edge).
 - b) Set the center frequency and span to encompass frequency range to be measured.
 - c) RBW = 100 kHz.
 - d) VBW $\geq [3 \times \text{RBW}]$.
 - e) Detector = peak.
 - f) Sweep time = auto.

TEST REPORT

- g) Trace mode = max hold.
- h) Allow sweep to continue until the trace stabilizes (required measurement time may increase for low-duty-cycle applications).
- i) For radiated Band-edge emissions within a restricted band and within 2 MHz of an authorized band edge, integration method is considered.

2. Repeat until all the test status is investigated.
3. Report the worst case.

Used Test Equipment List:


3m Semi-Anechoic Chamber, EMI Test Receiver (9 kHz~7 GHz), Signal and Spectrum Analyzer (10 Hz~40 GHz), Loop antenna (9 kHz-30 MHz). TRILOG Super Broadband test Antenna(30 MHz-3 GHz) (RX), Double-Ridged Waveguide Horn Antenna (800 MHz-18 GHz)(RX) and High Frequency Antenna & preamplifier(18 GHz~26.5 GHz) (RX). Refer to Clause 5 Test Equipment List for details.

TEST REPORT


Result plots as follows:

802.11b mode with 1 Mbps data rate

Channel1: 2.412 GHz




Channel 11: 2.462 GHz




TEST REPORT

802.11g mode with 6 Mbps data rate

Channel1: 2.412 GHz




Channel 11: 2.462 GHz




TEST REPORT
802.11n(HT20) mode with 6.5Mbps data rate

Channel 1: 2.412 GHz




Channel 11: 2.462 GHz




TEST REPORT

802.11n(HT40) mode with 13.5Mbps data rate

Channel 3: 2.422 GHz




Channel 9: 2.452 GHz



TEST REPORT

4.9 Conducted Emission Test

Test Configuration:



Test Setup and Procedure:

Test was performed according to ANSI C63.10 Clause 6.2. The EUT was set to achieve the maximum emission level. The mains terminal disturbance voltage was measured with the EUT in a shielded room. The EUT was connected to AC power source through an Artificial Mains Network which provides a 50Ω linear impedance. Artificial hand is used if appropriate (for handheld apparatus). The load/control terminal disturbance voltage was measured with passive voltage probe if appropriate.

The table-top EUT was placed on a 0.8m high non-metallic table above earthed ground plane (Ground Reference Plane). And for floor standing EUT, was placed on a 10mm high non-metallic supported on GRP. The EUT keeps a distance of at least 0.8m from any other of the metallic surface. The Artificial Mains Network is situated at a distance of 0.8m from the EUT.

During the test, mains lead of EUT excess 0.8m was folded back and forth parallel to the lead so as to form a horizontal bundle with a length between 0.3m and 0.4m

The bandwidth of test receiver was set at 9 kHz. The frequency range from 150 kHz to 30MHz was checked.

Remark: Pre-test has been conducted to determine the worst-case mode from all possible combinations between available modulations, and record the worst-case as b mode (2412MHz) with 1Mbps data rate


TEST REPORT

Test Data and Curve

At main terminal: Pass

Tested Wire: Live

Operation Mode: transmitting mode



EDIT PEAK LIST (Final Measurement Results)				
Trace1:	FCC15QP			
Trace2:	FCC15AV			
Trace3:	---			
TRACE	FREQUENCY	LEVEL dBµV	DELTA	LIMIT dB
1 Quasi Peak	194 kHz	36.53 L1	-27.33	
1 Quasi Peak	346 kHz	33.27 L1	-25.78	
1 Quasi Peak	442 kHz	31.68 L1	-25.33	


Remark:

1. Corr. (dB) = LISN Factor (dB) + Cable Loss (dB)
2. Level (dBµV) = Corr. (dB) + Read Level (dBµV)
3. Delta Limit (dB) = Level (dBµV)-Limit (dBµV)

TEST REPORT

Tested Wire: Neutral

Operation Mode: transmitting mode



EDIT PEAK LIST (Final Measurement Results)				
TRACE	FREQUENCY	LEVEL dB μ V	DELTA LIMIT dB	
1	Quasi Peak 426 kHz	32.06 L1	-25.26	
1	Quasi Peak 694 kHz	32.93 L1	-23.06	
2	Average 698 kHz	29.42 L1	-16.57	
2	Average 822 kHz	25.94 L1	-20.05	
2	Average 4.198 MHz	15.15 L1	-30.84	
1	Quasi Peak 4.266 MHz	20.35 L1	-35.64	

Remark:

1. Corr. (dB) = LISN Factor (dB) + Cable Loss (dB)
2. Level (dB μ V) = Corr. (dB) + Read Level (dB μ V)
3. Delta Limit (dB) = Level (dB μ V)-Limit (dB μ V)

TEST REPORT
5.0 Test Equipment List

Radiated Emission/Radio					
Equipment No.	Equipment	Model	Manufacturer	Cal. Due date (YYYY-MM-DD)	Calibration Interval
EM030-04	3m Semi-Anechoic Chamber	9×6×6 m ³	ETS-LINDGREN	4/9/2020	1Y
EM031-02	EMI Test Receiver (9 kHz~7 GHz)	R&S ESR7	R&S	2/28/2020	1Y
EM031-03	Signal and Spectrum Analyzer (10 Hz~40 GHz)	R&S FSV40	R&S	9/9/2019	1Y
EM011-04	Loop antenna (9 kHz-30 MHz)	HFH2-Z2	R&S	6/24/2020	1Y
EM061-03	TRILOG Super Broadband test Antenna (30 MHz-1.5 GHz) (TX)	VULB 9161	SCHWARZBECK	6/22/2020	1Y
EM033-01	TRILOG Super Broadband test Antenna(30 MHz-3 GHz) (RX)	VULB 9163	SCHWARZBECK	9/20/2019	1Y
EM033-02	Double-Ridged Waveguide Horn Antenna (800 MHz-18 GHz)(RX)	R&S HF907	R&S	6/22/2020	1Y
EM033-03	High Frequency Antenna & preamplifier(18 GHz~26.5 GHz) (RX)	R&S SCU-26	R&S	4/26/2020	1Y
EM033-04	High Frequency Antenna & preamplifier (26 GHz-40 GHz)	R&S SCU-40	R&S	4/26/2020	1Y
EM031-02-01	Coaxial cable(9 kHz-1 GHz)	N/A	R&S	4/9/2020	1Y
EM033-02-02	Coaxial cable(1 GHz-18 GHz)	N/A	R&S	4/9/2020	1Y
EM033-04-02	Coaxial cable(18 GHz~40 GHz)	N/A	R&S	4/18/2020	1Y
EM031-01	Signal Generator (9 kHz~6 GHz)	SMB100A	R&S	7/18/2020	1Y
EM085-02	Signal Generator (10MHz-40GHz)	68369B	Wiltron	7/19/2019	1Y
EM040-01	Band Reject/Notch Filter	WRHFV	Wainwright	N/A	1Y
EM040-02	Band Reject/Notch Filter	WRCGV	Wainwright	N/A	1Y
EM040-03	Band Reject/Notch Filter	WRCGV	Wainwright	N/A	1Y
EM022-03	2.45 GHz Filter	BRM50702	Micro-Tronics	5/16/2020	1Y
SA016-16	Programmable Temperature & Humidity Test Chamber	MHU-800LJ	TERCHY	10/10/2019	1Y
SA016-22	Climatic Test Chamber	C7-1500	Vötsch	11/1/2019	1Y
SA012-74	Digital Multimeter	FLUKE175	FLUKE	10/10/2019	1Y
EM010-01	Regulated DC Power supply	PAB-3003A	GUANHUA	N/A	1Y
SA040-22	Regulated DC Power supply	IT6721	ITECH	9/9/2019	1Y
EM084-06	Audio Analyzer	8903B	HP	4/18/2020	1Y
EM045-01-01	EMC32 software (RE/RS)	V10.01.00	R&S	N/A	N/A
EM045-01-09	EMC32 software (328/893)	V9.26.01	R&S	N/A	N/A

Conducted emission at the mains terminals

Equipment No.	Equipment	Model	Manufacturer	Cal. Due date (YYYY-MM-DD)	Calibration Interval
EM080-05	EMI receiver	ESCI	R&S	7/18/2020	1Y
EM006-05	LISN	ENV216	R&S	6/16/2020	1Y
EM006-06	LISN	ENV216	R&S	9/9/2019	1Y
EM006-06-01	Coaxial cable	/	R&S	4/7/2020	1Y
EM004-04	EMC shield Room	8m×3m×3m	Zhongyu	1/13/2020	1Y

****End of the test report*****