



RF TEST REPORT

Product Name: PeriPage Mini Printer

Model Name: ALD-P810, P81, ALD-P800, P80, ALD-P820, P82, ALD-Y200, A40, P40, ALD-P830, P83, ALD-P840, P84

FCC ID: 2ASPY-ALD-P810

Issued For : Xiamen Ilead Tek Co., Ltd.

Room 01, Unit 2101, No.50 Chengyi North Street, Software Park Phase III, Xiamen, Fujian, China

Issued By : Shenzhen LGT Test Service Co., Ltd.

Room 205, Building 13, Zone B, Zhenxiong Industrial Park, No.177, Renmin West Road, Jinsha, Kengzi Street, Pingshan District, Shenzhen, Guangdong, China

Report Number: LGT25D143HA01

Sample Received Date: Apr. 22, 2025

Date of Test: Apr. 22, 2025 ~ May 23, 2025

Date of Issue: May 23, 2025

The test report is effective only with both signature and specialized stamp. This report shall not be reproduced except in full without the written approval of the Laboratory. The results in this report only apply to the tested sample.



TEST REPORT CERTIFICATION

Applicant: Xiamen Ilead Tek Co., Ltd.
Address: Room 01, Unit 2101, No.50 Chengyi North Street, Software Park
Phase III, Xiamen, Fujian, China
Manufacturer: Xiamen Ilead Tek Co., Ltd.
Address: Room 01, Unit 2101, No.50 Chengyi North Street, Software Park
Phase III, Xiamen, Fujian, China
Factory: XIAMEN WEITERUL ELECTRONIC TECHNOLOGY CO., LTD
Address: 302, 3rd Floor, 402, 4th Floor, No.883-1, Lianting Road, Xiamen Torch
High-tech Zone(Xiang an)Industrial Zone
Product Name: PeriPage Mini Printer
Trademark: PeriPage, PeriMonkey
Model Name: ALD-P810, P81, ALD-P800, P80, ALD-P820, P82, ALD-Y200, A40,
P40, ALD-P830, P83, ALD-P840, P84
Sample Status: Normal

| APPLICABLE STANDARDS | |
|--|--------------|
| STANDARD | TEST RESULTS |
| FCC 47 CFR §2.1093 KDB 447498 D01 General RF Exposure Guidance v06 | PASS |

Prepared by:

Zane Shan

Zane Shan
Engineer

Approved by:

Vita Li

Vita Li
Technical Director





TABLE OF CONTENTS

| | |
|---|----------|
| 1 . GENERAL INFORMATION | 5 |
| 1.1 GENERAL DESCRIPTION OF THE EUT | 5 |
| 1.2 TEST LABORATORY | 5 |
| 2 . FCC 47CFR § 2.1093 REQUIREMENT | 6 |
| 2.1 TEST STANDARDS | 6 |
| 2.2 LIMIT | 6 |
| 2.3 TEST RESULT | 8 |



Revision History

| Rev. | Issue Date | Revisions |
|------|--------------|---------------|
| 00 | May 23, 2025 | Initial Issue |
| | | |



1. GENERAL INFORMATION

1.1 GENERAL DESCRIPTION OF THE EUT

| | | |
|-------------------|--|--------------|
| Product Name: | PeriPage Mini Printer | |
| Model Name: | ALD-P810 | |
| Series Model: | P81, ALD-P800, P80, ALD-P820, P82, ALD-Y200, A40, P40, ALD-P830, P83, ALD-P840, P84 | |
| Model Difference: | The only differences lie in the model naming based on the sales market, the printed patterns on the exterior surface, the injection molding colors on the exterior, and the exterior decoration. The rest, such as the internal structure, electrical schematic diagram, working mode, and key components that affect safety and electromagnetic compatibility performance, are all the same. This has no impact on the safety and electromagnetic compatibility performance of the product. | |
| Frequency Bands: | Bluetooth | 2402-2480MHz |
| Rating: | Input: DC 5V 2A | |
| Battery: | Capacity: 1500mAh Rated Voltage: 7.4V | |
| Hardware Version: | P81(YC3122)_V1_0_250214 | |
| Software Version: | V3.17_SD | |

1.2 TEST LABORATORY

| | |
|----------------------------|--|
| Company Name: | Shenzhen LGT Test Service Co., Ltd. |
| Address: | Room 205, Building 13, Zone B, Zhenxiong Industrial Park, No.177, Renmin West Road, Jinsha, Kengzi Street, Pingshan District, Shenzhen, Guangdong, China |
| Accreditation Certificate: | A2LA Certificate No.: 6727.01 |
| | FCC Registration No.: 746540 |
| | CAB ID: CN0136 |



2. FCC 47CFR §2.1093 REQUIREMENT

2.1 TEST STANDARDS

The limit for Maximum Permissible Exposure (MPE) specified in KDB 447498 D01 General RF Exposure Guidance v06 is followed. The gain of the antennas used in the product is extracted from the Antenna data sheets provided and also the maximum total power input to the antenna is measured. Through the Friis transmission formula and the maximum gain of the antenna, we can calculate the distance, away from the product, where the limit of MPE is reached.

Although the Friis Transmission formula is far field assumption, the calculated result of that is an over-prediction for near field power density. It is taken as worst case to specify the safety range.

2.2 LIMIT

Approximate SAR Test Exclusion Power Thresholds at Selected Frequencies and Test Separation Distances are illustrated in the following Table.

| MHz | 5 | 10 | 15 | 20 | 25 | mm |
|------|-----|-----|-----|-----|-----|---|
| 150 | 39 | 77 | 116 | 155 | 194 | SAR Test Exclusion Threshold (mW) |
| 300 | 27 | 55 | 82 | 110 | 137 | |
| 450 | 22 | 45 | 67 | 89 | 112 | |
| 835 | 16 | 33 | 49 | 66 | 82 | |
| 900 | 16 | 32 | 47 | 63 | 79 | |
| 1500 | 12 | 24 | 37 | 49 | 61 | |
| 1900 | 11 | 22 | 33 | 44 | 54 | |
| 2450 | 10 | 19 | 29 | 38 | 48 | |
| 3600 | 8 | 16 | 24 | 32 | 40 | |
| 5200 | 7 | 13 | 20 | 26 | 33 | |
| 5400 | 6 | 13 | 19 | 26 | 32 | |
| 5800 | 6 | 12 | 19 | 25 | 31 | |
| | | | | | | |
| MHz | 30 | 35 | 40 | 45 | 50 | mm |
| 150 | 232 | 271 | 310 | 349 | 387 | SAR Test Exclusion Threshold (mW) |
| 300 | 164 | 192 | 219 | 246 | 274 | |
| 450 | 134 | 157 | 179 | 201 | 224 | |
| 835 | 98 | 115 | 131 | 148 | 164 | |
| 900 | 95 | 111 | 126 | 142 | 158 | |
| 1500 | 73 | 86 | 98 | 110 | 122 | |
| 1900 | 65 | 76 | 87 | 98 | 109 | |
| 2450 | 57 | 67 | 77 | 86 | 96 | |
| 3600 | 47 | 55 | 63 | 71 | 79 | |
| 5200 | 39 | 46 | 53 | 59 | 66 | |
| 5400 | 39 | 45 | 52 | 58 | 65 | |
| 5800 | 37 | 44 | 50 | 56 | 62 | |



The 1-g and 10-g SAR test exclusion thresholds for 100 MHz to 6 GHz at test separation distances ≤ 50 mm are determined by:

$$[(\text{max. power of channel, including tune-up tolerance, mW}) / (\text{min. test separation distance, mm})] \cdot [\sqrt{f(\text{GHz})}] \leq 3.0 \text{ for 1-g SAR and } \leq 7.5 \text{ for 10-g extremity SAR, where } f(\text{GHz}) \text{ is the RF channel transmit frequency in GHz.}$$

Power and distance are rounded to the nearest mW and mm before calculation

The result is rounded to one decimal place for comparison

The test exclusions are applicable only when the minimum test separation distance is ≤ 50 mm and for transmission frequencies between 100 MHz and 6 GHz. When the minimum test separation distance is < 5 mm, a distance of 5 mm is applied to determine SAR test exclusion.



2.3 TEST RESULT

Turn up Result

| Mode | Turn up Power |
|----------|---------------|
| BT-GFSK | 3.5±1dBm |
| BLE-GFSK | -3±1dBm |

The MPE result of worst mode:

| RF Function | Frequency (MHz) | Max Turn up Power (dBm) | Max Turn up Power (mW) | Estimated SAR | Limit | Ratio | Result |
|-------------|-----------------|-------------------------|------------------------|---------------|-------|-------|--------|
| BT | 2402 | 4.50 | 2.82 | 0.874 | 3 | 0.291 | Pass |
| BLE | 2402 | -2.00 | 0.63 | 0.196 | 3 | 0.065 | Pass |

Note:

1. The Maximum Power Density is less than the limit, complies with the exemption requirements.

※※※※※END OF THE REPORT※※※※※