


Smart Switch User Manual



This new designed glass panel wireless touch smart switch is designed with WiFi+RF. To replace traditional switches with a variety of ways to control. Now one new smart feature as remote control. You can control the switch by the app and control on/off and relay status. And a scratch resistance glass panel. Glass panel is scratch resistance and easy to clean.

Note: Button sound on and off: no button operations before operations begin within 6 seconds. Then press switch button for 4 times and then Di-Di-Di-Di for 2 times for success operation.

Safety Information

Risk of Electric Shock-Electricity can cause personal injury or property damage if handled improperly! If you are not sure about any part of these instructions, please seek professional help from a qualified electrician.

Technical Parameters

Model: WS-EU-RF / WS-US-RF
Working voltage: 100~240V AC, 50Hz/60Hz
Max. total current: 10A (pure resistive load)
Max. load current: 2.5A (inductive and capacitive load)
Max. Load Power: depends on voltage
Wireless type: WiFi 2.4GHz+433MHz
Working temperature: 0°C~40°C
Power supply: AC/DC 12V
Warnings:
Turn off the power at the circuit breaker and test that power is off before wiring.

Product Description

This new designed glass panel wireless touch smart switch is designed with WiFi+RF. To replace traditional switches with a variety of ways to control. Now one new smart feature as remote control. You can control the switch by the app and control on/off and relay status. And a scratch resistance glass panel. Glass panel is scratch resistance and easy to clean.

Note: Button sound on and off: no button operations before operations begin within 6 seconds. Then press switch button for 4 times and then Di-Di-Di-Di for 2 times for success operation.


Installation

Step 1

- Make sure that the power at the circuit breaker is off before Neutral Wire is required. Confirm the wall box contains a Neutral Wire (typically white). If the wall box doesn't have a Neutral Wire, find another location at your home or call a licensed electrician to install the Neutral Wire.
- The wire colors indicated in this manual are the usual colors and may differ in some houses.
- Ensure the wire conductors are securely fastened to each wire.
- If you don't have any wiring experience, please call a professional electrician.

Step 2

- Turn off the power at the circuit breaker and use the electrical tester to test the power.
- Ensure the switch is off before wiring.



Step 3

- Mount the switch with the provided screws and snap the wall plate on it.

Step 4

- Turn the power back on at the circuit breaker and then switch the light.

1. Registration or Log in

- Download "Smart Life" Application
- Enter the Register/Login interface, tap "Register" to create an account by entering your phone number to get verification code and "Set password". Choose "Log in" if you already have a Smart Life account.

2. Configure the APP to the switch


- Preparation: Make sure the switch has been connected with WiFi successfully (the power must be connected to WiFi and is able to connect to the Internet).
- Note:** The switch only supports 2.4G network. If you have connected 5G network, please disconnect 5G network firstly and connect 2.4G network.
- 3. WiFi link method:**
Press and hold the WiFi code (new/Updated)
1. Make sure your phone is connected to WiFi and Bluetooth



2. Open Smart Life/Tuya App and Click "+", then the prompt page will automatically show on the screen. Click "Go to add".

3. Select the device you want to add and click "Add"

4. Enter WiFi Password and click "Confirm", waiting for completing the connection.



5. Add the device successfully, you can edit the name of the device to enter the device page by click "Done"

6. How to reset/repair WiFi code
Press the switch button for 6 times, and hold on the 6th time, then release until you hear Di-Di-Di-Di (3 times), and the blue light will flash 3 times, then release again and fast after 3 seconds. Reset/Repair is successful.

7. Remote radio frequency (RF)link method:



4. Choose the switch that you want to associate to and then choose the switch button that you want to control the same light.



5. Then go back to previous page, you will see two items in the dropdown: your main switch, the other is the one you associate just now.
Note: Please confirm the associated switch is enabled.



6. Now you are able to control your light with two switches. Do not associate another button in the same switch for multi-control.



7. If you want to add another third or more smart switches to control your light, just repeat the steps above. And you will see the result as below when you associate another new switch.



Set your Echo speaker by Alexa APP

1. If you have finished installing Smart Life, just open Alexa App, log into your Alexa account with password.

2. Click the menu on the top left—click "settings", choose "Set up a new device"(choose a device like Echo).

Note: When below page appears, long press the small dot on your Echo device until the light turns to yellow. Then click "Continue" on the App.

3. Turn on your WiFi and wait for a few minutes. After watching an introduction video, click "next step", then it will enter Home page automatically. Now the Echo has been connected to WiFi successfully.

Enter Smart Life Skill in Alexa APP

Then input the user name and password of Smart Life APP that you have previously registered.
Now you can use your Alexa to control your Smart devices

