

MPE REPORT

FCC ID: 2ATYS-BTAAX100

Date of issue: July 26, 2019

Report Number: MTi19062103-14E2

Sample Description: Smart car charge

Model(s): BTAAX100

Applicant: AAMP GLOBAL

Address: 15500 Lightwave Drive, Clearwater, Florida 33760

Date of Test: June 26, 2019 to July 26, 2019

Shenzhen Microtest Co., Ltd.

<http://www.mtitest.com>

This test report is valid for the tested samples only. It cannot be reproduced except in full without prior written consent of Shenzhen Microtest Co., Ltd.

TEST RESULT CERTIFICATION	
Applicant's name:	AAMP GLOBAL
Address:	15500 Lightwave Drive, Clearwater, Florida 33760
Manufacture's Name:	Shenzhen Sowye Technology Co., Ltd.
Address:	2F, A9 Building, Longwangmiao Industrial, East District, Baishixia, Fuyong, Bao'an, Shenzhen, 518103, Guangdong, China
Product name:	Smart car charge
Trademark:	N/A
Model and/or type reference ..:	BTAAX100
Serial Model.....:	N/A
RF Exposure Procedures.....:	KDB 447498 D01 v06

This device described above has been tested by Shenzhen Microtest Co., Ltd and the test results show that the equipment under test (EUT) is in compliance with the FCC requirements. And it is applicable only to the tested sample identified in the report.

Tested by:



Jone Lee

July 26, 2019

Reviewed by:



Blue Zheng

July 26, 2019

Approved by:



Smith Chen

July 26, 2019

RF EXPOSURE EVALUATION

According to FCC 1.1310: The criteria listed in the following table shall be used to evaluate the environment impact of human exposure to radio frequency (RF) Radiation as specified in §1.1307(b)

Limits for Maximum Permissible Exposure (MPE)

Frequency range (MHz)	Electric field strength (V/m)	Magnetic field strength (A/m)	Power density (mW/cm ²)	Averaging time (minutes)
(A) Limits for Occupational/Controlled Exposure				
0.3-3.0	614	1.63	*100	6
3.0-30	1842/f	4.89/f	*900/f ²	6
30-300	61.4	0.163	1.0	6
300-1,500			f/300	6
1,500-100,000			5	6
(B) Limits for General Population/Uncontrolled Exposure				
0.3-1.34	614	1.63	*100	30
1.34-30	824/f	2.19/f	*180/f ²	30
30-300	27.5	0.073	0.2	30
300-1,500			f/1500	30
1,500-100,000			1.0	30

f = frequency in MHz * = Plane-wave equivalent power density

MPE Calculation Method

Friis transmission formula: $P_d = (P_{out} * G) / (4 * \pi * R^2)$

Where

Pd= Power density in mW/cm²

Pout=output power to antenna in mW

G= Numeric gain of the antenna relative to isotropic antenna

Pi=3.1415926

R= distance between observation point and center of the radiator in cm(20cm)

Pd the limit of MPE, 1mW/cm². If we know the maximum gain of the antenna and total power input to the antenna, through the calculation, we will know the distance where the MPE limit is reached.

Measurement Result

BT:

Operation Frequency: 2402-2480MHz,

Power density limited: 1mW/ cm²

Antenna Type: BT Antenna: PCB Antenna;

BT antenna gain: -0.58dBi

R=20cm

mW=10^(dBm/10)

antenna gain Numeric=10^(dBi/10)= 10^(-0.58/10)=0.87

Channel Freq. (MHz)	modulation	conducted power	Tune-up power (dBm)	Max		Antenna		Evaluation result (mW/cm ²)	Power density Limits (mW/cm ²)			
		(dBm)		tune-up power		Gain						
				(dBm)	(mW)	(dBi)	Numeric					
2402	GFSK	-2.55	-2±1	-1	0.794	-0.58	0.87	0.0001	1			
2441		-2.219	-2±1	-1	0.794	-0.58	0.87	0.0001	1			
2480		-1.793	-2±1	-1	0.794	-0.58	0.87	0.0001	1			
2402	$\pi/4$ - DQPSK	-0.783	0±1	1	1.259	-0.58	0.87	0.0002	1			
2441		-0.558	0±1	1	1.259	-0.58	0.87	0.0002	1			
2480		0.067	0±1	1	1.259	-0.58	0.87	0.0002	1			
2402	8DPSK	-0.409	0±1	1	1.259	-0.58	0.87	0.0002	1			
2441		-0.2	0±1	1	1.259	-0.58	0.87	0.0002	1			
2480		0.027	0±1	1	1.259	-0.58	0.87	0.0002	1			

Conclusion:

For the max result: 0.0002≤ 1.0 for 1g SAR, No SAR is required.

----END OF REPORT----