



Power reduction mechanism verification

According to the May 2017 TCBC Workshop, Demonstration of proper functioning of the detection and triggering mechanisms is required to support the corresponding RF exposure conditions. The verification is through a base station simulator is used to establish a conducted RF connection and monitor output power under different operating conditions related to the power reduction mechanisms. Detail of power reduction mechanisms referring to Operational Description

1. Power Verification Procedure

The power verification was performed according to the following procedure:

1. A base station simulator was used to establish a conducted RF connection and the output power was monitored. The power measurements were confirmed to be within expected tolerances for all states before and after a power reduction mechanism was triggered.
2. Step 1 was repeated for all relevant modes and frequency bands for the mechanism being investigated.
3. Steps 1 and 2 were repeated for all individual power reduction mechanisms and combinations thereof. For the combination cases, one mechanism was switched to a 'triggered' state at a time; powers were confirmed to be within tolerances after each additional mechanism was activated.

General Note:

1. This device uses different Device State Indices (DSI) to configure different time averaged power levels based on certain exposure scenarios as the following table.

Exposure Condition	DSI	Trigger Conditions
Head SAR- Standalone	DSI 2	Receiver on
Head SAR - Simultaneous	DSI 6	Receiver On+WLAN
Hotspot	DSI 1	Hotspot On
Body worn/Extremity SAR - Standalone	DSI 0	Receiver Off
Body worn/Extremity SAR - Simultaneous	DSI 4	Receiver Off+WLAN

2. Select the bands with the largest power reduction for power verification:
 - a. Establish voice call and audio routed through the earpiece to monitor output power under head power states.
 - Tradition voice over IP CMRS operations for LTE
 - LTE Band 7 is set at 'highest BW, 1RB, RB Offset = 0, QPSK.'
 - b. Establish data connection monitor hotspot power state.
 - LTE Band 42 is set at 'highest BW, 1RB, RB Offset = 0, QPSK.'
 - c. Establish data connection monitor body worn power state.
 - LTE Band 42 is set at 'highest BW, 1RB, RB Offset = 0, QPSK.'
 - Body Detect mechanism was performed for the in-hand and on a stationary object (placed on a table)
 - d. Establish data connection monitor extremity power state.
 - LTE Band 42 is set at 'highest BW, 1RB, RB Offset = 0, QPSK.'
 - Body Detect mechanism was performed for the in-hand and on a stationary object (placed on a table).
3. In this power validation purpose is to demonstrate of proper functioning of the detection and triggering mechanisms to support the corresponding RF exposure conditions.
4. Verification performed for one technology/Band to demonstrate that the power reduction applies for same technology/band and call origination.



2. Verification output Power Results

Head exposure conditions

Head Exposure condition		Output Power for Voice Call			
Ear acoustic output Status:		ON		OFF	
Power state		WWAN DS12		WWAN	
Wireless technology	Antenna	Measured (dBm)	Max. Tune-up (dBm)	Measured (dBm)	Max. Tune-up (dBm)
LTE Band 7	Ant 4	17.43	18.5	23.25	24.5

Hotspot exposure condition

Hotspot exposure condition		Output Power for data connection			
Wifi Hotspot Status		OFF		ON	
Power state		WWAN DS11		WWAN	
		WiFi Standalone		WiFi Simultaneous	
Wireless Technology	Antenna	Measured (dBm)	Max. Tune-up (dBm)	Measured (dBm)	Max. Tune-up (dBm)
LTE Band 42	Ant 4	19.48	20.5	23.38	24.5

Body worn exposure condition

Body Worn exposure condition		Output Power (data connection)			
Power state		WWAN DS10		WWAN	
Wireless Technology	Antenna	Measured (dBm)	Max. Tune-up (dBm)	Measured (dBm)	Max. Tune-up (dBm)
LTE Band 42	Ant 4	19.48	20.5	23.38	24.5

Extremity exposure condition

Extremity exposure condition		Output Power (data connection)			
Power state		WWAN DS10		WWAN	
Wireless Technology	Antenna	Measured (dBm)	Max. Tune-up (dBm)	Measured (dBm)	Max. Tune-up (dBm)
LTE Band 42	Ant 4	19.48	20.5	23.38	24.5