
RF EXPOSURE EVALUATION

EUT Specification

EUT	EdgeUTech
Model Name	EdgeUTech
Frequency band (Operating)	<input type="checkbox"/> WLAN: 2.412GHz ~ 2.462GHz <input type="checkbox"/> WLAN: 5.18GHz ~ 5.32GHz / 5.50GHz ~ 5.70GHz <input type="checkbox"/> WLAN: 5.745GHz ~ 5825GHz <input checked="" type="checkbox"/> Others: 2.402~2.480GHz & 2405~2475MHz & 13.56MHz
Device category	<input checked="" type="checkbox"/> Portable (<20cm separation) <input type="checkbox"/> Mobile (>20cm separation) <input type="checkbox"/> Others _____
Antenna diversity	<input type="checkbox"/> Single antenna <input checked="" type="checkbox"/> Multiple antennas <input type="checkbox"/> Tx diversity <input type="checkbox"/> Rx diversity <input type="checkbox"/> Tx/Rx diversity
Max. output power	BEL: -0.086 dBm (0.981mW) 2.4G: 93.73 dBuV/m (-1.53dBm)(0.71mW) 13.56MHz: 85.22 dBuV/m (-10.038dBm)(0.1mW)
Antenna gain	BEL: -2 dBi 2.4G: 5 dBi 13.56MHz: 1.2 dBi
Evaluation applied	<input type="checkbox"/> MPE Evaluation <input checked="" type="checkbox"/> SAR Evaluation

Standard Requirement

Portable Device

According to §15.247(i) and §1.1307b(1), systems operating under the provisions of this section shall be operated in a manner that ensures that the public is not exposed to radio frequency energy levels in excess of the Commission's guidelines. See KDB 447498 D01 General RF Exposure Guidance V6, section 4.3.1.

The 1-g and 10-g SAR test exclusion thresholds for 100 MHz to 6 GHz at test separation distances ≤ 50 mm are determined by:

$[(\text{max. power of channel, including tune-up tolerance, mW}) / (\text{min. test separation distance, mm})] \cdot [\sqrt{f(\text{GHz})}] \leq 3.0 \text{ for 1-g SAR and } \leq 7.5 \text{ for 10-g extremity SAR,}^{16}$ where

- $f(\text{GHz})$ is the RF channel transmit frequency in GHz
- Power and distance are rounded to the nearest mW and mm before calculation¹⁷
- The result is rounded to one decimal place for comparison

The test exclusions are applicable only when the minimum test separation distance is ≤ 50 mm and for transmission frequencies between 100 MHz and 6 GHz. When the minimum test separation distance is < 5 mm, a distance of 5 mm is applied to determine SAR test exclusion.

Measurement Result

BLE:

Channel (MHz)	Max output power (dBm)	Tune up tolerance (dBm)	Max Tune Up Power (dBm)	Max Tune Up Power (mW)	Distance (mm)	Calculation results	Limit
2480	-0.086	± 1	0.914	1.234	5	0.39	3

2.4G wireless:

Channel (MHz)	Max power (dBuV/m)	Max output power (dBm)	Tune up tolerance (dBm)	Max Tune Up Power (dBm)	Max Tune Up Power (mW/cm ²)	Distance (mm)	Calculation results	Limit
2405	93.73	-1.53	± 1	-0.53	0.886	5	0.275	3

$$E = EIRP - 20 \log D + 104.8$$

Where:

E= electric field strength in dBuV/m

EIRP= equivalent isotropic radiated power in dBm

D= specified measurement distance in meters

$$EIRP = E - 104.8 + 20 \log D = 93.73 - 104.8 + 20 \log 3 = -1.53 \text{ dbm}$$

Note 1: Calculation Value = [(max. power of channel, mW)/(min. test separation distance, mm)] \cdot [$\sqrt{f(\text{GHz})}$].

$$\text{For example: } 0.886/5 \cdot \sqrt{2.405} = 0.275 \leq 3.0$$

NFC:

Channel (MHz)	Max power (dBuV/m)	Max output power (dBm)	Tune up tolerance (dBm)	Max Tune Up Power (dBm)	Max Tune Up Power (mW/cm ²)	Distance (mm)	Calculation results	Limit
13.56	85.22	-10.04	± 1	-9.04	0.125	5	0.003	3

$$E = EIRP - 20 \log D + 104.8$$

Where:

E= electric field strength in dBuV/m

EIRP= equivalent isotropic radiated power in dBm

D= specified measurement distance in meters

$$EIRP = E - 104.8 + 20 \log D = 85.22 - 104.8 + 20 \log 3 = -10.04 \text{ dbm}$$

Note 1: Calculation Value = [(max. power of channel, mW)/(min. test separation distance, mm)] • [$\sqrt{f(\text{GHz})}$].

$$\text{Fox example: } 0.125/5 * \sqrt{0.01356} = 0.003 \leq 3.0$$

Max Simultaneous transmission:

$$\text{BLE} + 2.4\text{Gwireless} + \text{NFC} = 0.39 + 0.275 + 0.003 = 0.668 \leq 3.0$$

According to KDB447498 D01 V6, threshold at which no SAR required is ≤ 3.0 for 1-g SAR, separation distance is 5mm, and no simultaneous SAR measurement is required.

The SAR measurement is not necessary.