


WHAT'S INCLUDED

For WUUK Base Station

WUUK Smart Doorbell Pro

For WUUK Smart Doorbell Pro



1 Minute Installation: Apply 3M VHB Tape
Better Prepare The Surface for Strong Bond


Initial tape application to surfaces at temperatures below 50°F (10°C) is not recommended. If you are in a cold area, warm up the tape by using a hairdryer or other tools.



1. Peel off the red foil that has the 3M VHB tape on it, and attach the backplate to where you want to sit your doorbell.
2. Press hard on the backplate for 5 seconds.
3. Let it be there and stand for at least 24 hours so the 3M VHB tape can sink into the surface and build the strongest bond.


PRODUCT OVERVIEW

WUUK Base Station



If you choose to use the built-in battery for power or do not have AC wires in place, please add this page.

Note: Make sure the wires go through the backplate.




If you have trouble connecting the wires coming out of your wall to the back of your WUUK Doorbell, use the provided wire extensions and wire nuts.

Feed all the wires, and the wire nuts, if you need them, into your wall.

WUUK Smart Doorbell Pro


Battery-powered



Screw On (Optional)

*For installing on porous & uneven surface such as concrete, stone, limestone, brick. Or you choose to install this way.

Install anchors – on stucco, brick, or concrete (Optional)




Mark 4 drill hole positions using the doorbell mounting plate provided. Use a bit to drill holes in your wall and install the anchors.

Screw it in – on particleboard, wood, and paints

Recommended Drill Bit Size: 4mm

Secure your WUUK Doorbell backplate on the wall using the four screws provided.

How the System Works




FINAL STEP: HOOK WUUK SMART DOORBELL PRO


Make sure the WUUK Doorbell is powered on - you can press the call button a few times and check if the Base Station is ringing. If not, please power it on until you hear "Hello, WUUK".

Then hang the WUUK Doorbell PRO onto the wall mount.

Match the top hole on the backplate first, then snap the bottom. Press the lower part of the doorbell until you hear a slight clicking sound.



CONNECTING WUUK BASE STATION TO THE INTERNET




UNDERSTAND THE INDICATOR LIGHT




SETTING UP THE SYSTEM




CHARGING THE WUUK SMART DOORBELL PRO




WUUK Smart Doorbell Pro




CUSTOMER SERVICE




FIND A GOOD MOUNTING SPOT




SAFETY STATEMENT



Height and Location



Declaration of Conformity



MOUNT THE WUUK SMART DOORBELL PRO

Choose The Way You Want to Install The Doorbell

	2x VHB	Screws	Both
Metals, glass, ceramics, plastics, PVC	✓		
Particleboard, wood, paints (finished surfaces)	✓	✓	✓
Concrete, stone, limestone, brick, porous & uneven surfaces	✓	✓	✓
Stucco, masonry, stucco, pebble finish		✓	

Smart Doorbell Pro Kit (Battery-powered)



WUUK Y0210说明书 风琴折页 80*80

:

FCC WARNING

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

Any changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation.

If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

To maintain compliance with FCC's RF Exposure guidelines, This equipment should be installed and operated with minimum 20cm distance between the radiator and your body: Use only the supplied antenna.