

使用说明书

使用指南

安全正确使用产品

- 除电池移除和更换外,请勿自行拆卸或改装产品。
- 请勿使用快充手机充电器对键盘进行充电
- 请勿将产品浸入任何液体中,或暴露在炎热或潮湿的环境中。
- 如果将产品暴露于超出既定温度范围的环境中,则切断电源设备,直至温度在指定的操作温度范围内达到稳定。
- 本产品仅可使用随附的电源。不得在雷雨天气时为产品充电。
- 使用此产品请搭配所列出/认证的ITE电脑和附件。
- 此产品不适合儿童使用,14岁以下儿童为非预期用户。
- 如果使用产品长时间重复单一动作,则可能导致手部、手腕、胳膊、肩部、颈部或背部的神经、肌腱或肌肉损伤,如果存在疼痛、麻木、酸软无力、肿胀、灼痛、抽筋或僵硬等症状,请向合格的专业保健人士咨询。
- 在正常和合理可预见的操作条件下,本产品不存在安全隐患。如果产品运行不正常,请致电支持人员。如需任何服务或维修,请务必向产品送回相关部门。
- 未经明确批准而对本产品进行的任何改装或改造都将导致用户丧失操作本设备的权利和产品保修失效。

充电说明

请在使用产品之前阅读手册

- 1.建议使用电脑USB接口对键盘进行充电
- 2.请勿使用快充手机充电器对键盘充电
- 3.请勿使用劣质非标电源适配器对键盘进行充电
- 4.请勿使用过压过流电源适配器对键盘进行充电
- 5.充电时请远离高温设备
- 6.使用的过程中不要对键盘进行充电
- 7.充电时指示灯亮充电完成后灯关熄灭
- 8.长时间不使用时请关闭电源开关。

包装清单

- ① 无线键盘 X1
- ② 操作说明书 X1
- ③ 彩盒包装 X1
- ④ 数据线 X1
- ⑤ 双头接收器 X1

产品说明

基本参数

产品名称	KB338
适应系统	Android / Windows / iOS
连接方式	BT 3.0+BT5.0+2.4G
工作电压	3.1-4.2V
工作距离	10米以内
电池容量	500mAh/背光
充电时间	2-3小时
调制系统	GFSK
产品尺寸	247X 153 X 8MM

多媒体功能键

返回主页	上一曲	※+	亮度+
搜索	播放/暂停	锁屏	
全选	下一曲	屏幕键盘	
复制	音量-	语言切换	
粘贴	音量+	Fn	FN复合功能
剪切	※-	亮度-	

FN+Q——>安卓系统;
 FN+C= 断开蓝牙连接或配对模式;
 FN+W——>Win系统;
 FN+E——>iOS系统
 FN+①——>BT3.0;
 FN+②——>BT5.0;
 FN+③——>2.4G

FN+1/2/3任意切换三个蓝牙连接通道,Power蓝灯常亮三秒成功,即可同时记忆连接三个蓝牙设备;
背光
 背光开关:背光键 3 档
 1档,短按,打开背光,可再按 手动切换背光颜色,“白/蓝/青/紫/绿/黄/红/白”;
 2档,再按,自动背光,每 5 秒七色背光自动切换,
 “白/蓝/青/紫/绿/黄/红/白”
 3档,再按,关闭背光。
 注:60秒无操作键盘,背光灭,再按键唤醒背光;键盘回连后,记忆最近背光色彩;
 WIN 系统下显示桌面
 手动模式:即1档,调节背光亮度,灯泡键 按住,再按一下上键 □=亮度加;灯泡键 按住再按一下下键 □=亮度减;

注意

- 1.在长期不使用时,我们建议关闭键盘,以延长电池的寿命
- 2.为了获得更长的电池使用寿命,建议电源灯闪烁时才给键盘充电,每次充电时间最好不少于2小时

USER MANUAL

USER GUIDE

USE THE PRODUCT SAFELY AND CORRECTLY

- Do not disassemble or modify the product except for battery removal and replacement.
- Do not disassemble or attempt to repair this product, as doing so may result in radiation damage.
- Do not immerse the product in any liquid or expose it to hot or humid conditions.
- If the product is exposed to an environment beyond the specified temperature range, the power supply device is cut off until the temperature is at the specified temperature.
- Do not charge the keyboard during use.
- The indicator light is on when charging and the light is off after charging is completed.
- Turn off the power switch when not in use for a long time.
- This product can only use the included power supply. Do not modify the power supply. Do not charge the product during a thunderstorm.
- Use this product with listed/certified ITE computers and accessories.
- This product is not intended for children and children under the age of 14 are not intended users.
- If a single action is repeated for a long time with the product, it may cause the hands, wrists, arms, shoulders, neck or back. Nerve, muscle carving or muscle injury. If there is pain, numbness, soreness, swelling, burning, cramping or stiffness. Please consult a qualified health care professional for any symptoms.
- Under normal and reasonably foreseeable operating conditions, this product does not present a safety hazard. If the product is not functioning properly, please call support. If you need any service or repair, be sure to return the product to the relevant department.
- Any modification or modification of the product without express approval will result in the user losing the right to use the equipment. Rights and product warranties are void.

CHARGING INSTRUCTIONS

PLEASE READ THE MANUAL BEFORE USING THE PRODUCT

1. It is recommended to use the computer USB port to charge the keyboard
2. Do not use the fast charger to charge the keyboard
3. Do not use poor quality non-standard power adapter to charge the keyboard
4. Do not use the overvoltage and overcurrent power adapter to charge the keyboard
5. Keep away from high temperature devices when charging
6. Do not charge the keyboard during use
7. The indicator light is on when charging and the light is off after charging is completed
8. Turn off the power switch when not in use for a long time.

PACKING LIST

- ① Wireless keyboard X1
- ② User manual X1
- ③ Color box packing X1
- ④ USB cable X1
- ⑤ Dual Connector X1

PRODUCT DESCRIPTION

PRODUCT PARAMETER

PRODUCT NAME	KB338
COMPATIBLE SYSTEM	Android / Windows / iOS
CONNECTION MODE	BT 3.0+BT5.0+2.4G
OPERATING VOLTAGE	3.1-4.2V
WORKING DISTANCE	Within 10 meters
BATTERY CAPACITY	500mAh/RGB
CHARGING TIME	2-3 hours
MODULATION SYSTEM	GFSK
PRODUCT SIZE	247X 153 X 8MM

MULTIMEDIA FUNCTION KEY

Return to main page	Previous song	※+	Brightness +
search	Play/pause	Lock screen	
select all	Next song	On-screen keyboard	
copy	Volume -	Language switching	
paste	Volume +	Fn	FN composite function
shear	※-	Brightness -	

FN+C= Disconnect Bluetooth connection or pairing mode
 FN+Control= On-screen keyboard
 FN+Space= Language switching
 FN+Q——>Android system;
 FN+W——>Win system;
 FN+E——>iOS system
 FN+①——>BT3.0;
 FN+②——>BT5.0;
 FN+③——>2.4G;
 Note: Switch successfully Bluetooth blue light flash three times

CHANNEL SWITCHING

FN+1/2/3 can arbitrarily switch three Bluetooth connection channels. If the Power blue light is steady on for 3 seconds, it can connect three Bluetooth devices simultaneously.
BACKLIGHT
 Backlight switch: Backlight key 3
 1, press to turn on the backlight, and press again to manually switch the backlight color “white/blue/cyan/purple/green/yellow/red/white”;
 2, press again, automatic backlight, every 5 seconds seven color backlight automatic switch; “white/blue/cyan/purple/green/yellow/red/white”
 3, press again to turn off the backlight.
 Note: No keyboard operation for 60 seconds, the backlight is off, press the button again to wake up the backlight; Keyboard back connected, memory recently backlit color; Windows, the desktop is displayed.

Manual mode: that is, 1 gear, adjust the brightness of the backlight, bulb key 按住, then press the up key □= brightness; Bulb key 按住 and press down the key □= brightness reduction.

PAY ATTENTION

1. When not in use for a long time, we recommend turning off the keyboard to extend the battery life
2. In order to obtain a longer battery life, it is recommended to charge the keyboard only when the power lamp is blinking. It is better to charge the keyboard for no less than 2 hours each time

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation.

If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.

- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.

- Consult the dealer or an experienced radio/TV technician for help.

Warning: changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

The device has been evaluated to meet general RF exposure requirement, the device can be used in portable exposure condition without restriction.