

**RF Exposure Evaluation****FCC ID: 2AY37-E8**

According to KDB447498 D01 General RF Exposure Guidance v06, Clause 4.3.1(a)

**EUT Specification**

EUT	Baseus True Wireless Earphones
Model/Type reference:	Baseus Bowie E8
Listed Model(s):	/
Frequency band (Operating)	<input checked="" type="checkbox"/> BT: 2.402GHz ~ 2.480GHz <input checked="" type="checkbox"/> BLE: 2.402GHz ~ 2.480GHz <input type="checkbox"/> WLAN: 2.412GHz ~ 2.462GHz <input type="checkbox"/> Others _____
Device category	<input checked="" type="checkbox"/> Portable (<5mm separation) <input type="checkbox"/> Mobile (>20cm separation) <input type="checkbox"/> Fixed (>20cm separation) <input type="checkbox"/> Others _____
Antenna diversity	<input checked="" type="checkbox"/> Single antenna <input type="checkbox"/> Multiple antennas <input type="checkbox"/> Tx diversity <input type="checkbox"/> Rx diversity <input type="checkbox"/> Tx/Rx diversity
Antenna gain (Max)	0.8dBi

**Limit**

For 100 MHz to 6 GHz and test separation distances  $\leq$  50 mm, the 1-g and 10-g SAR test exclusion thresholds are determined by the following:

$[(\text{max. power of channel, including tune-up tolerance, mW}) / (\text{min. test separation distance, mm})] \cdot [\sqrt{f_{(\text{GHz})}}] \leq 3.0$  for 1-g SAR, and  $\leq 7.5$  for 10-g extremity SAR

Where

$f_{(\text{GHz})}$  is the RF channel transmit frequency in GHz

-Power and distance are rounded to the nearest mW and mm before calculation

-The result is rounded to one decimal place for comparison

-The values 3.0 and 7.5 are referred to as numeric thresholds in step b) below

The test exclusions are applicable only when the minimum test separation distance is  $\leq$  50 mm, and for transmission frequencies between 100 MHz and 6 GHz. When the minimum test separation distance is  $<$  5 mm, a distance of 5 mm according to 4.1 f) is applied to determine SAR test exclusion.

**Measurement Result**

Mode	Channel Frequency (MHz)	Max. Measured Power (dBm)	Max. Tune up Power (dBm)	Result	Limit
8-DPSK	2480	-1.14	0	0.373	3.0
BLE 1M	2402	-3.84	-3	0.188	3.0

Note:

1. Calculate by Worst-case mode.
2. Max. Tune Up Power by Manufacturer's Declaration, and Max. Tune Up Power is used to calculate.
3. For a more detailed features description, please refer to the RF Test Report.

\*\*\*\*\*THE END\*\*\*\*\*