

TOVEENEN

Long Range Remote Control Outlet

500ft • 15A • 3000W

USER GUIDE

Contact Customer Service: support@toveenen.com

Manufacturer: Shenzhen SYG Technologies Co., Ltd.

Address: Room 402, Dunbeixincun 2-46, Longhua, Shenzhen, China

Product Warranty

This product has a one-year warranty. If you have any questions about product or use, please contact us.

Features & Specification

- Ultra-long wireless range over 500ft. Range can reach 1000ft in open space
- Remote can work through concrete walls and floors
- Every remote outlet has Independent coding without conflict
- NON-WATERPROOF

Wireless Range	500ft ~ 1000ft
Rated Current	15 Amp
Input Voltage	AC 85V~265V 50/60Hz
Load Capacity	Resistive load: 3000W (e.g. incandescent light, heater) Inductive load: 1000W (e.g. pump, Motor, LED lamp)
Battery Type	12V 23A

Operating Instructions

1. Plug the remote outlet into a socket or wall outlet
2. Control on/off: Remote controller or pressing the button of outlet
3. Indicator light of remote outlet will show on/off status. ON: Red, OFF: Green

Pairing/Learning Instructions

One outlet can pair 3 remotes at most. One remote can pair multiple outlets.

1. Plug the remote outlet into an electrical socket.
2. Press and hold the button of remote outlet for 5 seconds, the Indicator light of outlet will flash, then release the button.
3. Press and hold 'ON' button of remote for about 2s until you hear a click sound from the outlet, then release 'ON' button.
4. Press and hold 'OFF' button of remote for about 2s until you hear a click sound from the outlet, then release 'OFF' button.
5. Pairing complete. Now newly added remote can control the remote outlet.

Remove all outlet-pairing (Reset outlet)

- Plug this outlet into a power strip → Turn off the power to outlet → Press and hold the button of outlet (don't release) → Turn on the power to outlet. The Indicator light of outlet will flash green. Wait for 5 seconds until the Indicator light shows red. → Release the button. Reset complete.
- After the reset, you'll need to re-pair the remote.

FCC Statement

This device complies with part 15 of the FCC rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

Caution: Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
 - Increase the separation between the equipment and receiver.
 - Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help important announcement

Radiation Exposure Statement

The device has been evaluated to meet general RF exposure requirement. The device can be used in portable exposure condition without restriction.