








































Appendix B. AC Conducted Emission Test Results





Test Engineer :	Yuki Tang	Temperature :	22~24°C
		Relative Humidity :	44~50%
Test Voltage :	120Vac / 60Hz	Phase :	Neutral
Remark :	All emissions not reported here are more than 10 dB below the prescribed limit.		



Site : CO02-SZ
Condition : FCC 15C_QP LISN_2024-N-1 NEUTRAL

	Freq	Level	Over	Limit	Read	LISN	Cable	Remark
	MHz	dBuV	Limit	Line	Level	Factor	Loss	
			dB	dBuV	dBuV	dB	dB	
1	0.15	35.14	-20.77	55.91	15.39	9.74	10.01	Average
2	0.15	50.74	-15.17	65.91	30.99	9.74	10.01	QP
3	0.17	34.03	-21.09	55.12	14.30	9.72	10.01	Average
4	0.17	48.73	-16.39	65.12	29.00	9.72	10.01	QP
5	0.18	36.22	-18.42	54.64	16.50	9.71	10.01	Average
6	0.18	49.72	-14.92	64.64	30.00	9.71	10.01	QP
7	0.19	35.11	-18.82	53.93	15.39	9.70	10.02	Average
8 *	0.19	49.41	-14.52	63.93	29.69	9.70	10.02	QP
9	0.22	28.71	-24.17	52.88	8.99	9.69	10.03	Average
10	0.22	43.51	-19.37	62.88	23.79	9.69	10.03	QP
11	0.52	27.40	-18.60	46.00	7.60	9.69	10.11	Average
12	0.52	37.10	-18.90	56.00	17.30	9.69	10.11	QP

Note:

- Level(dBμV) = Read Level(dBμV) + LISN Factor(dB) + Cable Loss(dB)
- Over Limit(dB) = Level(dBμV) – Limit Line(dBμV)



Appendix C Radiated Spurious Emission Test Data

Test Engineer :	HuaCong Liang	Relative Humidity :	48~49%
		Temperature :	24-25°C

Radiated Spurious Emission Test Modes

Mode	Band (MHz)	Antenna	Modulation	Channel	Frequency	Data Rate	RU	Remark
Mode 1	2400-2483.5	SISO	802.11b	01	2412	1Mbps	-	-
Mode 2	2400-2483.5	SISO	802.11b	06	2437	1Mbps	-	-
Mode 3	2400-2483.5	SISO	802.11b	11	2462	1Mbps	-	-
Mode 4	2400-2483.5	SISO	802.11g	01	2412	6Mbps	-	-
Mode 5	2400-2483.5	SISO	802.11g	06	2437	6Mbps	-	-
Mode 6	2400-2483.5	SISO	802.11g	11	2462	6Mbps	-	-
Mode 7	2400-2483.5	SISO	802.11n HT20	01	2412	MCS0	-	-
Mode 8	2400-2483.5	SISO	802.11n HT20	06	2437	MCS0	-	-
Mode 9	2400-2483.5	SISO	802.11n HT20	11	2462	MCS0	-	-
Mode 10	2400-2483.5	SISO	802.11n HT40	03	2422	MCS0	-	-
Mode 11	2400-2483.5	SISO	802.11n HT40	09	2452	MCS0	-	-
Mode 12	2400-2483.5	SISO	802.11g	01	2412	6Mbps	LF	-
Mode 13	2400-2483.5	SISO	802.11g	02	2417	6Mbps	-	-
Mode 14	2400-2483.5	SISO	802.11g	10	2457	6Mbps	-	-
Mode 15	2400-2483.5	SISO	802.11n HT20	2	2417	MCS0	-	-
Mode 16	2400-2483.5	SISO	802.11n HT20	10	2457	MCS0	-	-
Mode 17	2400-2483.5	SISO	802.11n HT40	06	2437	MCS0	-	-



Summary of each worse mode

Mode	Modulation	Ch.	Freq. (MHz)	Level (dBuV/m)	Limit (dBuV/m)	Margin (dB)	Pol.	Peak Avg.	Result	Remark
1	802.11b	01	2386.96	48.54	54	-5.46	H	AVERAGE	Pass	Band Edge
1	802.11b	01	4824.00	47.39	54.00	-6.61	V	Average	Pass	Harmonic
2	802.11b	06	-	-	-	-	-	-	-	Band Edge
2	802.11b	06	4874.00	47.13	54.00	-6.87	H	Average	Pass	Harmonic
3	802.11b	11	2486.852	50.82	54	-3.18	H	AVERAGE	Pass	Band Edge
3	802.11b	11	4924.00	46.91	54.00	-7.09	H	Average	Pass	Harmonic
4	802.11g	01	2389.95	50.88	54.00	-3.12	H	AVERAGE	Pass	Band Edge
4	802.11g	01	4824.00	35.31	54.00	-18.69	V	Average	Pass	Harmonic
5	802.11g	06	-	-	-	-	-	-	-	Band Edge
5	802.11g	06	4874.00	38.06	54.00	-15.94	V	Average	Pass	Harmonic
6	802.11g	11	2483.51	50.42	54.00	-3.58	H	AVERAGE	Pass	Band Edge
6	802.11g	11	4924.00	36.40	54.00	-17.60	V	Average	Pass	Harmonic
7	802.11n HT20	01	2389.82	50.28	54.00	-3.72	H	AVERAGE	Pass	Band Edge
7	802.11n HT20	01	4824.00	35.05	54.00	-18.95	V	Average	Pass	Harmonic
8	802.11n HT20	06	-	-	-	-	-	-	-	Band Edge
8	802.11n HT20	06	4874.00	36.77	54.00	-17.23	V	Average	Pass	Harmonic
9	802.11n HT20	11	2483.51	50.64	54.00	-3.36	H	AVERAGE	Pass	Band Edge
9	802.11n HT20	11	7386.00	43.51	74.00	-30.49	V	Peak	Pass	Harmonic
10	802.11n HT40	03	2389.97	50.83	54.00	-3.17	H	AVERAGE	Pass	Band Edge
10	802.11n HT40	03	-	-	-	-	-	-	-	Harmonic
11	802.11n HT40	09	2484.74	49.55	54.00	-4.45	H	AVERAGE	Pass	Band Edge
11	802.11n HT40	09	-	-	-	-	-	-	-	Harmonic
12	802.11n HT40	03	33.88	24.98	40.00	-15.02	V	Peak	Pass	LF
13	802.11g	02	2389.82	49.97	54.00	-4.03	H	AVERAGE	Pass	Band Edge
13	802.11g	02	-	-	-	-	-	-	-	Harmonic
14	802.11g	10	2483.62	48.68	54.00	-5.32	H	AVERAGE	Pass	Band Edge
14	802.11g	10	-	-	-	-	-	-	-	Harmonic
15	802.11n HT20	2	2388.78	48.26	54.00	-5.74	H	AVERAGE	Pass	Band Edge
15	802.11n HT20	2	-	-	-	-	-	-	-	Harmonic
16	802.11n HT20	10	2483.83	48.46	54.00	-5.54	H	AVERAGE	Pass	Band Edge
16	802.11n HT20	10	-	-	-	-	-	-	-	Harmonic
17	802.11n HT40	06	2389.88	50.31	54.00	-3.69	H	AVERAGE	Pass	Band Edge
17	802.11n HT40	06	-	-	-	-	-	-	-	Harmonic





Mode	1																																																																																	
	Band Edge																																																																																	
	2400-2483.5_802.11b_CH01_2412MHz																																																																																	
ANT	SISO																																																																																	
Pol.	Horizontal	Fundamental																																																																																
Peak	Level (dBuV/m) Date: 2025-01-03 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>2387.22</td><td>55.11</td><td>74.00</td><td>-18.89</td><td>53.60</td><td>30.43</td><td>4.79</td><td>33.71</td><td>122</td><td>68</td><td>PEAK</td></tr></tbody></table>		Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	2387.22	55.11	74.00	-18.89	53.60	30.43	4.79	33.71	122	68	PEAK	Level (dBuV/m) Date: 2025-01-03 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>2412.00</td><td>106.92</td><td>-----</td><td>-----</td><td>105.31</td><td>30.45</td><td>4.82</td><td>33.66</td><td>122</td><td>68</td><td>PEAK</td></tr></tbody></table>		Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	2412.00	106.92	-----	-----	105.31	30.45	4.82	33.66	122	68	PEAK
		Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																									
Freq	Level	Line	Margin	Level	Factor	Loss	Factor																																																																											
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																									
1	2387.22	55.11	74.00	-18.89	53.60	30.43	4.79	33.71	122	68	PEAK																																																																							
	Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																										
Freq	Level	Line	Margin	Level	Factor	Loss	Factor																																																																											
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																									
1	2412.00	106.92	-----	-----	105.31	30.45	4.82	33.66	122	68	PEAK																																																																							
Avg	Level (dBuV/m) Date: 2025-01-03 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>2386.96</td><td>48.54</td><td>54.00</td><td>-5.46</td><td>47.03</td><td>30.43</td><td>4.79</td><td>33.71</td><td>122</td><td>68</td><td>AVERAGE</td></tr></tbody></table>		Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	2386.96	48.54	54.00	-5.46	47.03	30.43	4.79	33.71	122	68	AVERAGE	Level (dBuV/m) Date: 2025-01-03 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>2412.00</td><td>104.05</td><td>-----</td><td>-----</td><td>102.44</td><td>30.45</td><td>4.82</td><td>33.66</td><td>122</td><td>68</td><td>AVERAGE</td></tr></tbody></table>		Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	2412.00	104.05	-----	-----	102.44	30.45	4.82	33.66	122	68	AVERAGE
	Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																										
Freq	Level	Line	Margin	Level	Factor	Loss	Factor																																																																											
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																									
1	2386.96	48.54	54.00	-5.46	47.03	30.43	4.79	33.71	122	68	AVERAGE																																																																							
	Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																										
Freq	Level	Line	Margin	Level	Factor	Loss	Factor																																																																											
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																									
1	2412.00	104.05	-----	-----	102.44	30.45	4.82	33.66	122	68	AVERAGE																																																																							





Mode	1																																																																																										
	Band Edge																																																																																										
	2400-2483.5_802.11b_CH01_2412MHz																																																																																										
ANT	SISO																																																																																										
Pol.	Vertical						Fundamental																																																																																				
Peak	Level (dBuV/m) Date: 2025-01-03 Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>2386.57</td><td>50.48</td><td>74.00</td><td>-23.52</td><td>48.97</td><td>30.43</td><td>4.79</td><td>33.71</td><td>396</td><td>360</td><td>PEAK</td></tr></table>							Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	2386.57	50.48	74.00	-23.52	48.97	30.43	4.79	33.71	396	360	PEAK	Level (dBuV/m) Date: 2025-01-03 Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>2412.00</td><td>99.61</td><td>-----</td><td>-----</td><td>98.00</td><td>30.45</td><td>4.82</td><td>33.66</td><td>396</td><td>360</td><td>PEAK</td></tr></table>						Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	2412.00	99.61	-----	-----	98.00	30.45	4.82	33.66	396	360	PEAK
		Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																		
Freq	Level	Line	Margin	Level	Factor	Loss	Factor																																																																																				
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																		
1	2386.57	50.48	74.00	-23.52	48.97	30.43	4.79	33.71	396	360	PEAK																																																																																
	Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																			
Freq	Level	Line	Margin	Level	Factor	Loss	Factor																																																																																				
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																		
1	2412.00	99.61	-----	-----	98.00	30.45	4.82	33.66	396	360	PEAK																																																																																
Avg	Level (dBuV/m) Date: 2025-01-03 Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>2386.57</td><td>42.29</td><td>54.00</td><td>-11.71</td><td>40.78</td><td>30.43</td><td>4.79</td><td>33.71</td><td>396</td><td>360</td><td>AVERAGE</td></tr></table>							Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	2386.57	42.29	54.00	-11.71	40.78	30.43	4.79	33.71	396	360	AVERAGE	Level (dBuV/m) Date: 2025-01-03 Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>2412.00</td><td>96.82</td><td>-----</td><td>-----</td><td>95.21</td><td>30.45</td><td>4.82</td><td>33.66</td><td>396</td><td>360</td><td>AVERAGE</td></tr></table>						Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	2412.00	96.82	-----	-----	95.21	30.45	4.82	33.66	396	360	AVERAGE
		Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																		
Freq	Level	Line	Margin	Level	Factor	Loss	Factor																																																																																				
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																		
1	2386.57	42.29	54.00	-11.71	40.78	30.43	4.79	33.71	396	360	AVERAGE																																																																																
	Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																			
Freq	Level	Line	Margin	Level	Factor	Loss	Factor																																																																																				
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																		
1	2412.00	96.82	-----	-----	95.21	30.45	4.82	33.66	396	360	AVERAGE																																																																																



Mode	1																																																																																																													
	Harmonic																																																																																																													
	2400-2483.5_802.11b_CH01_2412MHz																																																																																																													
ANT	SISO																																																																																																													
Pol.	Horizontal					Vertical																																																																																																								
Peak Avg																																																																																																														
	<table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>4824.00</td><td>49.04</td><td>74.00</td><td>-24.96</td><td>72.69</td><td>33.83</td><td>7.75</td><td>65.23</td><td>330</td><td>122 Peak</td></tr><tr><td>2</td><td>4824.00</td><td>45.40</td><td>54.00</td><td>-8.60</td><td>69.05</td><td>33.83</td><td>7.75</td><td>65.23</td><td>330</td><td>122 Average</td></tr></tbody></table>						Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	4824.00	49.04	74.00	-24.96	72.69	33.83	7.75	65.23	330	122 Peak	2	4824.00	45.40	54.00	-8.60	69.05	33.83	7.75	65.23	330	122 Average	<table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>4824.00</td><td>51.04</td><td>74.00</td><td>-22.96</td><td>74.69</td><td>33.83</td><td>7.75</td><td>65.23</td><td>100</td><td>88 Peak</td></tr><tr><td>2</td><td>4824.00</td><td>47.39</td><td>54.00</td><td>-6.61</td><td>71.04</td><td>33.83</td><td>7.75</td><td>65.23</td><td>100</td><td>88 Average</td></tr></tbody></table>						Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	4824.00	51.04	74.00	-22.96	74.69	33.83	7.75	65.23	100	88 Peak	2	4824.00	47.39	54.00	-6.61	71.04	33.83	7.75	65.23	100	88 Average
		Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																																						
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																																						
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																																																																																					
1	4824.00	49.04	74.00	-24.96	72.69	33.83	7.75	65.23	330	122 Peak																																																																																																				
2	4824.00	45.40	54.00	-8.60	69.05	33.83	7.75	65.23	330	122 Average																																																																																																				
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																																							
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																																						
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																																																																																					
1	4824.00	51.04	74.00	-22.96	74.69	33.83	7.75	65.23	100	88 Peak																																																																																																				
2	4824.00	47.39	54.00	-6.61	71.04	33.83	7.75	65.23	100	88 Average																																																																																																				



Mode	2																																																																																																																																			
	Harmonic																																																																																																																																			
	2400-2483.5_802.11b_CH06_2437MHz																																																																																																																																			
ANT	SISO																																																																																																																																			
Pol.	Horizontal					Vertical																																																																																																																														
Peak Avg																																																																																																																																				
	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line Margin</th><th>Level Factor</th><th>Loss Factor</th><th></th><th></th><th></th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>4874.00</td><td>50.95</td><td>74.00</td><td>-23.05</td><td>74.58</td><td>33.85</td><td>7.77</td><td>65.25</td><td>312</td><td>124 Peak</td></tr><tr><td>2</td><td>4874.00</td><td>47.13</td><td>54.00</td><td>-6.87</td><td>70.76</td><td>33.85</td><td>7.77</td><td>65.25</td><td>312</td><td>124 Average</td></tr><tr><td>3</td><td>7311.00</td><td>43.48</td><td>74.00</td><td>-30.52</td><td>62.90</td><td>36.30</td><td>8.93</td><td>64.65</td><td>--</td><td>-- Peak</td></tr></table>						Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line Margin	Level Factor	Loss Factor				Remark	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	4874.00	50.95	74.00	-23.05	74.58	33.85	7.77	65.25	312	124 Peak	2	4874.00	47.13	54.00	-6.87	70.76	33.85	7.77	65.25	312	124 Average	3	7311.00	43.48	74.00	-30.52	62.90	36.30	8.93	64.65	--	-- Peak	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line Margin</th><th>Level Factor</th><th>Loss Factor</th><th></th><th></th><th></th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>4874.00</td><td>51.04</td><td>74.00</td><td>-22.96</td><td>74.67</td><td>33.85</td><td>7.77</td><td>65.25</td><td>100</td><td>70 Peak</td></tr><tr><td>2</td><td>4874.00</td><td>46.88</td><td>54.00</td><td>-7.12</td><td>70.51</td><td>33.85</td><td>7.77</td><td>65.25</td><td>100</td><td>70 Average</td></tr><tr><td>3</td><td>7311.00</td><td>45.51</td><td>74.00</td><td>-28.49</td><td>64.93</td><td>36.30</td><td>8.93</td><td>64.65</td><td>--</td><td>-- Peak</td></tr></table>						Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line Margin	Level Factor	Loss Factor				Remark	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	4874.00	51.04	74.00	-22.96	74.67	33.85	7.77	65.25	100	70 Peak	2	4874.00	46.88	54.00	-7.12	70.51	33.85	7.77	65.25	100	70 Average	3	7311.00	45.51	74.00	-28.49	64.93	36.30	8.93	64.65	--	-- Peak
		Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																																																												
	Freq	Level	Line Margin	Level Factor	Loss Factor				Remark																																																																																																																											
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																																																											
1	4874.00	50.95	74.00	-23.05	74.58	33.85	7.77	65.25	312	124 Peak																																																																																																																										
2	4874.00	47.13	54.00	-6.87	70.76	33.85	7.77	65.25	312	124 Average																																																																																																																										
3	7311.00	43.48	74.00	-30.52	62.90	36.30	8.93	64.65	--	-- Peak																																																																																																																										
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																																																													
Freq	Level	Line Margin	Level Factor	Loss Factor				Remark																																																																																																																												
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																																																											
1	4874.00	51.04	74.00	-22.96	74.67	33.85	7.77	65.25	100	70 Peak																																																																																																																										
2	4874.00	46.88	54.00	-7.12	70.51	33.85	7.77	65.25	100	70 Average																																																																																																																										
3	7311.00	45.51	74.00	-28.49	64.93	36.30	8.93	64.65	--	-- Peak																																																																																																																										





Mode	3																																																																																	
	Band Edge																																																																																	
	2400-2483.5_802.11b_CH11_2462MHz																																																																																	
ANT	SISO																																																																																	
Pol.	Horizontal	Fundamental																																																																																
Peak	Level (dBuV/m) Date: 2025-01-03 Frequency (MHz) <table><thead><tr><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>cm</th><th>deg</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>2487.57</td><td>58.11</td><td>74.00</td><td>-15.89</td><td>56.22</td><td>30.49</td><td>4.93</td><td>33.53</td><td>335</td><td>89</td><td>PEAK</td></tr></tbody></table>	Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor	cm	deg	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	2487.57	58.11	74.00	-15.89	56.22	30.49	4.93	33.53	335	89	PEAK	Level (dBuV/m) Date: 2025-01-03 Frequency (MHz) <table><thead><tr><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>cm</th><th>deg</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>2462.00</td><td>107.33</td><td>-----</td><td>-----</td><td>105.53</td><td>30.48</td><td>4.89</td><td>33.57</td><td>335</td><td>89</td><td>PEAK</td></tr></tbody></table>	Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor	cm	deg	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	2462.00	107.33	-----	-----	105.53	30.48	4.89	33.57	335	89	PEAK
	Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																										
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	cm	deg																																																																									
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																									
1	2487.57	58.11	74.00	-15.89	56.22	30.49	4.93	33.53	335	89	PEAK																																																																							
Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																											
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	cm	deg																																																																									
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																									
1	2462.00	107.33	-----	-----	105.53	30.48	4.89	33.57	335	89	PEAK																																																																							
Avg	Level (dBuV/m) Date: 2025-01-03 Frequency (MHz) <table><thead><tr><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>cm</th><th>deg</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>2486.85</td><td>50.82</td><td>54.00</td><td>-3.18</td><td>48.94</td><td>30.49</td><td>4.92</td><td>33.53</td><td>335</td><td>89</td><td>AVERAGE</td></tr></tbody></table>	Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor	cm	deg	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	2486.85	50.82	54.00	-3.18	48.94	30.49	4.92	33.53	335	89	AVERAGE	Level (dBuV/m) Date: 2025-01-03 Frequency (MHz) <table><thead><tr><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>cm</th><th>deg</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>2462.00</td><td>104.61</td><td>-----</td><td>-----</td><td>102.81</td><td>30.48</td><td>4.89</td><td>33.57</td><td>335</td><td>89</td><td>AVERAGE</td></tr></tbody></table>	Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor	cm	deg	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	2462.00	104.61	-----	-----	102.81	30.48	4.89	33.57	335	89	AVERAGE
Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																											
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	cm	deg																																																																									
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																									
1	2486.85	50.82	54.00	-3.18	48.94	30.49	4.92	33.53	335	89	AVERAGE																																																																							
Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																											
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	cm	deg																																																																									
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																									
1	2462.00	104.61	-----	-----	102.81	30.48	4.89	33.57	335	89	AVERAGE																																																																							



Mode	3																																																																																										
	Band Edge																																																																																										
	2400-2483.5_802.11b_CH11_2462MHz																																																																																										
ANT	SISO																																																																																										
Pol.	Vertical						Fundamental																																																																																				
Peak	Level (dBuV/m) Date: 2025-01-03 PEAK_BE_74 <table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>2486.89</td><td>52.37</td><td>74.00</td><td>-21.63</td><td>50.49</td><td>30.49</td><td>4.92</td><td>33.53</td><td>327</td><td>360</td><td>PEAK</td></tr></tbody></table>							Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	2486.89	52.37	74.00	-21.63	50.49	30.49	4.92	33.53	327	360	PEAK	Level (dBuV/m) Date: 2025-01-03 PEAK_74 <table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>2462.00</td><td>98.99</td><td>-----</td><td>-----</td><td>97.19</td><td>30.48</td><td>4.89</td><td>33.57</td><td>327</td><td>360</td><td>PEAK</td></tr></tbody></table>						Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	2462.00	98.99	-----	-----	97.19	30.48	4.89	33.57	327	360	PEAK
		Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																		
Freq	Level	Line	Margin	Level	Factor	Loss	Factor																																																																																				
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																		
1	2486.89	52.37	74.00	-21.63	50.49	30.49	4.92	33.53	327	360	PEAK																																																																																
	Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																			
Freq	Level	Line	Margin	Level	Factor	Loss	Factor																																																																																				
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																		
1	2462.00	98.99	-----	-----	97.19	30.48	4.89	33.57	327	360	PEAK																																																																																
Avg	Level (dBuV/m) Date: 2025-01-03 AVG_BE_54 <table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>2486.81</td><td>43.91</td><td>54.00</td><td>-10.09</td><td>42.03</td><td>30.49</td><td>4.92</td><td>33.53</td><td>327</td><td>360</td><td>AVERAGE</td></tr></tbody></table>							Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	2486.81	43.91	54.00	-10.09	42.03	30.49	4.92	33.53	327	360	AVERAGE	Level (dBuV/m) Date: 2025-01-03 AVG_54 <table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>2462.00</td><td>96.09</td><td>-----</td><td>-----</td><td>94.29</td><td>30.48</td><td>4.89</td><td>33.57</td><td>327</td><td>360</td><td>AVERAGE</td></tr></tbody></table>						Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	2462.00	96.09	-----	-----	94.29	30.48	4.89	33.57	327	360	AVERAGE
		Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																		
Freq	Level	Line	Margin	Level	Factor	Loss	Factor																																																																																				
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																		
1	2486.81	43.91	54.00	-10.09	42.03	30.49	4.92	33.53	327	360	AVERAGE																																																																																
	Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																			
Freq	Level	Line	Margin	Level	Factor	Loss	Factor																																																																																				
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																		
1	2462.00	96.09	-----	-----	94.29	30.48	4.89	33.57	327	360	AVERAGE																																																																																







Mode	3																																																																																																																																											
	Harmonic																																																																																																																																											
	2400-2483.5_802.11b_CH11_2462MHz																																																																																																																																											
ANT	SISO																																																																																																																																											
Pol.	Horizontal						Vertical																																																																																																																																					
Peak Avg																																																																																																																																												
	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line Margin</th><th>Level Factor</th><th>Loss Factor</th><th></th><th></th><th></th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>4924.00</td><td>50.67</td><td>74.00</td><td>-23.33</td><td>74.28</td><td>33.87</td><td>7.79</td><td>65.27</td><td>122</td><td>324</td><td>Peak</td></tr><tr><td>2</td><td>4924.00</td><td>46.91</td><td>54.00</td><td>-7.09</td><td>70.52</td><td>33.87</td><td>7.79</td><td>65.27</td><td>122</td><td>324</td><td>Average</td></tr><tr><td>3</td><td>7386.00</td><td>43.64</td><td>74.00</td><td>-30.36</td><td>62.76</td><td>36.30</td><td>9.17</td><td>64.59</td><td>--</td><td>--</td><td>Peak</td></tr></table>							Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line Margin	Level Factor	Loss Factor				Remark	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	4924.00	50.67	74.00	-23.33	74.28	33.87	7.79	65.27	122	324	Peak	2	4924.00	46.91	54.00	-7.09	70.52	33.87	7.79	65.27	122	324	Average	3	7386.00	43.64	74.00	-30.36	62.76	36.30	9.17	64.59	--	--	Peak	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line Margin</th><th>Level Factor</th><th>Loss Factor</th><th></th><th></th><th></th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>4924.00</td><td>50.39</td><td>74.00</td><td>-23.61</td><td>74.00</td><td>33.87</td><td>7.79</td><td>65.27</td><td>100</td><td>82</td><td>Peak</td></tr><tr><td>2</td><td>4924.00</td><td>46.13</td><td>54.00</td><td>-7.87</td><td>69.74</td><td>33.87</td><td>7.79</td><td>65.27</td><td>100</td><td>82</td><td>Average</td></tr><tr><td>3</td><td>7386.00</td><td>45.66</td><td>74.00</td><td>-28.34</td><td>64.78</td><td>36.30</td><td>9.17</td><td>64.59</td><td>--</td><td>--</td><td>Peak</td></tr></table>							Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line Margin	Level Factor	Loss Factor				Remark	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	4924.00	50.39	74.00	-23.61	74.00	33.87	7.79	65.27	100	82	Peak	2	4924.00	46.13	54.00	-7.87	69.74	33.87	7.79	65.27	100	82	Average	3	7386.00	45.66	74.00	-28.34	64.78	36.30	9.17	64.59	--	--	Peak
		Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																																																																				
	Freq	Level	Line Margin	Level Factor	Loss Factor				Remark																																																																																																																																			
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																																																																			
1	4924.00	50.67	74.00	-23.33	74.28	33.87	7.79	65.27	122	324	Peak																																																																																																																																	
2	4924.00	46.91	54.00	-7.09	70.52	33.87	7.79	65.27	122	324	Average																																																																																																																																	
3	7386.00	43.64	74.00	-30.36	62.76	36.30	9.17	64.59	--	--	Peak																																																																																																																																	
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																																																																					
Freq	Level	Line Margin	Level Factor	Loss Factor				Remark																																																																																																																																				
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																																																																			
1	4924.00	50.39	74.00	-23.61	74.00	33.87	7.79	65.27	100	82	Peak																																																																																																																																	
2	4924.00	46.13	54.00	-7.87	69.74	33.87	7.79	65.27	100	82	Average																																																																																																																																	
3	7386.00	45.66	74.00	-28.34	64.78	36.30	9.17	64.59	--	--	Peak																																																																																																																																	





Mode	4																																																																																											
	Band Edge																																																																																											
	2400-2483.5_802.11g_CH01_2412MHz																																																																																											
ANT	SISO																																																																																											
Pol.	Horizontal						Fundamental																																																																																					
Peak	Level (dBuV/m) Date: 2025-01-04 Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>2389.95</td><td>64.74</td><td>74.00</td><td>-9.26</td><td>63.20</td><td>30.44</td><td>4.80</td><td>33.70</td><td>122</td><td>70</td><td>PEAK</td></tr></table>							Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	2389.95	64.74	74.00	-9.26	63.20	30.44	4.80	33.70	122	70	PEAK	Level (dBuV/m) Date: 2025-01-04 Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>2412.00</td><td>106.54</td><td>-----</td><td>-----</td><td>104.93</td><td>30.45</td><td>4.82</td><td>33.66</td><td>122</td><td>70</td><td>PEAK</td></tr></table>							Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	2412.00	106.54	-----	-----	104.93	30.45	4.82	33.66	122	70	PEAK
		Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																				
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																				
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																																																																			
1	2389.95	64.74	74.00	-9.26	63.20	30.44	4.80	33.70	122	70	PEAK																																																																																	
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																					
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																				
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																																																																			
1	2412.00	106.54	-----	-----	104.93	30.45	4.82	33.66	122	70	PEAK																																																																																	
Avg	Level (dBuV/m) Date: 2025-01-04 Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>2389.95</td><td>50.88</td><td>54.00</td><td>-3.12</td><td>49.34</td><td>30.44</td><td>4.80</td><td>33.70</td><td>122</td><td>70</td><td>AVERAGE</td></tr></table>							Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	2389.95	50.88	54.00	-3.12	49.34	30.44	4.80	33.70	122	70	AVERAGE	Level (dBuV/m) Date: 2025-01-04 Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>2412.00</td><td>99.48</td><td>-----</td><td>-----</td><td>97.87</td><td>30.45</td><td>4.82</td><td>33.66</td><td>122</td><td>70</td><td>AVERAGE</td></tr></table>							Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	2412.00	99.48	-----	-----	97.87	30.45	4.82	33.66	122	70	AVERAGE
		Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																				
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																				
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																																																																			
1	2389.95	50.88	54.00	-3.12	49.34	30.44	4.80	33.70	122	70	AVERAGE																																																																																	
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																					
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																				
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																																																																			
1	2412.00	99.48	-----	-----	97.87	30.45	4.82	33.66	122	70	AVERAGE																																																																																	





Mode	4																																																																																											
	Band Edge																																																																																											
	2400-2483.5_802.11g_CH01_2412MHz																																																																																											
ANT	SISO																																																																																											
Pol.	Vertical						Fundamental																																																																																					
Peak	 Date: 2025-01-04 <table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>2389.69</td><td>57.98</td><td>74.00</td><td>-16.02</td><td>56.44</td><td>30.44</td><td>4.80</td><td>33.70</td><td>396</td><td>360</td><td>PEAK</td></tr></tbody></table>							Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor			MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	2389.69	57.98	74.00	-16.02	56.44	30.44	4.80	33.70	396	360	PEAK	 Date: 2025-01-04 <table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>2412.00</td><td>98.86</td><td>-----</td><td>-----</td><td>97.26</td><td>30.45</td><td>4.82</td><td>33.67</td><td>396</td><td>360</td><td>PEAK</td></tr></tbody></table>							Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor			MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	2412.00	98.86	-----	-----	97.26	30.45	4.82	33.67	396	360	PEAK
		Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																			
Freq	Level	Line	Margin	Level	Factor	Loss	Factor																																																																																					
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																																																																			
1	2389.69	57.98	74.00	-16.02	56.44	30.44	4.80	33.70	396	360	PEAK																																																																																	
	Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																				
Freq	Level	Line	Margin	Level	Factor	Loss	Factor																																																																																					
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																																																																			
1	2412.00	98.86	-----	-----	97.26	30.45	4.82	33.67	396	360	PEAK																																																																																	
Avg	 Date: 2025-01-04 <table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>2389.82</td><td>44.82</td><td>54.00</td><td>-9.18</td><td>43.28</td><td>30.44</td><td>4.80</td><td>33.70</td><td>396</td><td>360</td><td>AVERAGE</td></tr></tbody></table>							Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor			MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	2389.82	44.82	54.00	-9.18	43.28	30.44	4.80	33.70	396	360	AVERAGE	 Date: 2025-01-04 <table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>2412.00</td><td>91.59</td><td>-----</td><td>-----</td><td>89.99</td><td>30.45</td><td>4.82</td><td>33.67</td><td>396</td><td>360</td><td>AVERAGE</td></tr></tbody></table>							Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor			MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	2412.00	91.59	-----	-----	89.99	30.45	4.82	33.67	396	360	AVERAGE
		Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																			
Freq	Level	Line	Margin	Level	Factor	Loss	Factor																																																																																					
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																																																																			
1	2389.82	44.82	54.00	-9.18	43.28	30.44	4.80	33.70	396	360	AVERAGE																																																																																	
	Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																				
Freq	Level	Line	Margin	Level	Factor	Loss	Factor																																																																																					
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																																																																			
1	2412.00	91.59	-----	-----	89.99	30.45	4.82	33.67	396	360	AVERAGE																																																																																	







Mode	4																																																																																																													
	Harmonic																																																																																																													
	2400-2483.5_802.11g_CH01_2412MHz																																																																																																													
ANT	SISO																																																																																																													
Pol.	Horizontal										Vertical																																																																																																			
Peak Avg	Date: 2025-01-05  <table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th></th></tr></thead><tbody><tr><td>1</td><td>4824.00</td><td>40.88</td><td>74.00</td><td>-33.12</td><td>64.53</td><td>33.83</td><td>7.75</td><td>65.23</td></tr><tr><td></td><td></td><td></td><td></td><td></td><td>--</td><td>--</td><td>--</td><td>Peak</td></tr></tbody></table>											Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB		1	4824.00	40.88	74.00	-33.12	64.53	33.83	7.75	65.23						--	--	--	Peak	Date: 2025-01-05  <table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th></th></tr></thead><tbody><tr><td>1</td><td>4824.00</td><td>44.20</td><td>74.00</td><td>-29.80</td><td>67.85</td><td>33.83</td><td>7.75</td><td>65.23</td></tr><tr><td>2</td><td>4824.00</td><td>35.31</td><td>54.00</td><td>-18.69</td><td>58.96</td><td>33.83</td><td>7.75</td><td>65.23</td></tr><tr><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td>Average</td></tr></tbody></table>		Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB		1	4824.00	44.20	74.00	-29.80	67.85	33.83	7.75	65.23	2	4824.00	35.31	54.00	-18.69	58.96	33.83	7.75	65.23									Average
		Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																																						
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																																						
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB																																																																																																							
1	4824.00	40.88	74.00	-33.12	64.53	33.83	7.75	65.23																																																																																																						
					--	--	--	Peak																																																																																																						
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																																							
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																																						
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB																																																																																																							
1	4824.00	44.20	74.00	-29.80	67.85	33.83	7.75	65.23																																																																																																						
2	4824.00	35.31	54.00	-18.69	58.96	33.83	7.75	65.23																																																																																																						
								Average																																																																																																						







Mode	5																																																																																																																																																								
	Harmonic																																																																																																																																																								
	2400-2483.5_802.11g_CH06_2437MHz																																																																																																																																																								
ANT	SISO																																																																																																																																																								
Pol.	Horizontal										Vertical																																																																																																																																														
Peak Avg	 Level (dBuV/m) Date: 2025-01-04 <table><tr><th colspan="2"></th><th colspan="2">Limit</th><th colspan="2">Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th rowspan="2">Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th><th></th><th></th></tr><tr><td>1</td><td>4874.00</td><td>44.25</td><td>74.00</td><td>-29.75</td><td>67.88</td><td>33.85</td><td>7.77</td><td>65.25</td><td>260</td><td>116</td><td>Peak</td></tr><tr><td>2</td><td>4874.00</td><td>36.47</td><td>54.00</td><td>-17.53</td><td>60.10</td><td>33.85</td><td>7.77</td><td>65.25</td><td>260</td><td>116</td><td>Average</td></tr><tr><td>3</td><td>7311.00</td><td>43.12</td><td>74.00</td><td>-30.88</td><td>62.54</td><td>36.30</td><td>8.93</td><td>64.65</td><td>--</td><td>--</td><td>Peak</td></tr></table>												Limit		Read		Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor				MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg			1	4874.00	44.25	74.00	-29.75	67.88	33.85	7.77	65.25	260	116	Peak	2	4874.00	36.47	54.00	-17.53	60.10	33.85	7.77	65.25	260	116	Average	3	7311.00	43.12	74.00	-30.88	62.54	36.30	8.93	64.65	--	--	Peak	 Level (dBuV/m) Date: 2025-01-04 <table><tr><th colspan="2"></th><th colspan="2">Limit</th><th colspan="2">Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th rowspan="2">Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th><th></th><th></th></tr><tr><td>1</td><td>4874.00</td><td>46.25</td><td>74.00</td><td>-27.75</td><td>69.88</td><td>33.85</td><td>7.77</td><td>65.25</td><td>248</td><td>344</td><td>Peak</td></tr><tr><td>2</td><td>4874.00</td><td>38.06</td><td>54.00</td><td>-15.94</td><td>61.69</td><td>33.85</td><td>7.77</td><td>65.25</td><td>248</td><td>344</td><td>Average</td></tr><tr><td>3</td><td>7311.00</td><td>44.84</td><td>74.00</td><td>-29.16</td><td>64.26</td><td>36.30</td><td>8.93</td><td>64.65</td><td>--</td><td>--</td><td>Peak</td></tr></table>			Limit		Read		Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor				MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg			1	4874.00	46.25	74.00	-27.75	69.88	33.85	7.77	65.25	248	344	Peak	2	4874.00	38.06	54.00	-15.94	61.69	33.85	7.77	65.25	248	344	Average	3	7311.00	44.84	74.00	-29.16	64.26	36.30	8.93	64.65	--	--	Peak
			Limit		Read		Ant	Cable	Preamp	APos	TPos	Remark																																																																																																																																													
	Freq	Level	Line	Margin	Level	Factor	Loss	Factor																																																																																																																																																	
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																																																																															
1	4874.00	44.25	74.00	-29.75	67.88	33.85	7.77	65.25	260	116	Peak																																																																																																																																														
2	4874.00	36.47	54.00	-17.53	60.10	33.85	7.77	65.25	260	116	Average																																																																																																																																														
3	7311.00	43.12	74.00	-30.88	62.54	36.30	8.93	64.65	--	--	Peak																																																																																																																																														
		Limit		Read		Ant	Cable	Preamp	APos	TPos	Remark																																																																																																																																														
Freq	Level	Line	Margin	Level	Factor	Loss	Factor																																																																																																																																																		
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																																																																																
1	4874.00	46.25	74.00	-27.75	69.88	33.85	7.77	65.25	248	344	Peak																																																																																																																																														
2	4874.00	38.06	54.00	-15.94	61.69	33.85	7.77	65.25	248	344	Average																																																																																																																																														
3	7311.00	44.84	74.00	-29.16	64.26	36.30	8.93	64.65	--	--	Peak																																																																																																																																														





Mode	6										
	Band Edge										
	2400-2483.5_802.11g_CH11_2462MHz										
ANT	SISO										
Pol.	Horizontal										
Peak	Fundamental										
	Level (dBuV/m) Date: 2025-01-04  PEAK_BE_74 Freq Level Limit Line Margin Read Level Ant Cable Preamp APos TPos Remark MHz dBuV/m dBuV/m dB dBuV dB/m dB dB cm deg 1 2483.51 66.94 74.00 -7.06 65.06 30.49 4.92 33.53 100 70 PEAK										
	Level (dBuV/m) Date: 2025-01-04  PEAK_74 Freq Level Limit Line Margin Read Level Ant Cable Preamp APos TPos Remark MHz dBuV/m dBuV/m dB dBuV dB/m dB dB cm deg 1 2462.00 105.55 ----- 103.76 30.48 4.89 33.58 100 70 PEAK										
Avg	Level (dBuV/m) Date: 2025-01-04  AVG_BE_54 Freq Level Limit Line Margin Read Level Ant Cable Preamp APos TPos Remark MHz dBuV/m dBuV/m dB dBuV dB/m dB dB cm deg 1 2483.51 50.42 54.00 -3.58 48.54 30.49 4.92 33.53 100 70 AVERAGE										
	Level (dBuV/m) Date: 2025-01-04  AVG_54 Freq Level Limit Line Margin Read Level Ant Cable Preamp APos TPos Remark MHz dBuV/m dBuV/m dB dBuV dB/m dB dB cm deg 1 2462.00 98.38 ----- 96.59 30.48 4.89 33.58 100 70 AVERAGE										



Mode	6																																																																																											
	Band Edge																																																																																											
	2400-2483.5_802.11g_CH11_2462MHz																																																																																											
ANT	SISO																																																																																											
Pol.	Vertical						Fundamental																																																																																					
Peak	 Date: 2025-01-04 <table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>2483.55</td><td>60.41</td><td>74.00</td><td>-13.59</td><td>58.53</td><td>30.49</td><td>4.92</td><td>33.53</td><td>337</td><td>360</td><td>PEAK</td></tr></table>							Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor			MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	2483.55	60.41	74.00	-13.59	58.53	30.49	4.92	33.53	337	360	PEAK	 Date: 2025-01-04 <table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>2462.00</td><td>100.01</td><td>-----</td><td>-----</td><td>98.21</td><td>30.48</td><td>4.89</td><td>33.57</td><td>337</td><td>360</td><td>PEAK</td></tr></table>							Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor			MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	2462.00	100.01	-----	-----	98.21	30.48	4.89	33.57	337	360	PEAK
		Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																			
Freq	Level	Line	Margin	Level	Factor	Loss	Factor																																																																																					
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																																																																			
1	2483.55	60.41	74.00	-13.59	58.53	30.49	4.92	33.53	337	360	PEAK																																																																																	
	Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																				
Freq	Level	Line	Margin	Level	Factor	Loss	Factor																																																																																					
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																																																																			
1	2462.00	100.01	-----	-----	98.21	30.48	4.89	33.57	337	360	PEAK																																																																																	
Avg	 Date: 2025-01-04 <table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>2484.69</td><td>44.92</td><td>54.00</td><td>-9.08</td><td>43.04</td><td>30.49</td><td>4.92</td><td>33.53</td><td>337</td><td>360</td><td>AVERAGE</td></tr></table>							Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor			MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	2484.69	44.92	54.00	-9.08	43.04	30.49	4.92	33.53	337	360	AVERAGE	 Date: 2025-01-04 <table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>2462.00</td><td>92.74</td><td>-----</td><td>-----</td><td>90.94</td><td>30.48</td><td>4.89</td><td>33.57</td><td>337</td><td>360</td><td>AVERAGE</td></tr></table>							Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor			MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	2462.00	92.74	-----	-----	90.94	30.48	4.89	33.57	337	360	AVERAGE
		Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																			
Freq	Level	Line	Margin	Level	Factor	Loss	Factor																																																																																					
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																																																																			
1	2484.69	44.92	54.00	-9.08	43.04	30.49	4.92	33.53	337	360	AVERAGE																																																																																	
	Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																				
Freq	Level	Line	Margin	Level	Factor	Loss	Factor																																																																																					
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																																																																			
1	2462.00	92.74	-----	-----	90.94	30.48	4.89	33.57	337	360	AVERAGE																																																																																	



Mode	6																																																																																																																																											
	Harmonic																																																																																																																																											
	2400-2483.5_802.11g_CH11_2462MHz																																																																																																																																											
ANT	SISO																																																																																																																																											
Pol.	Horizontal						Vertical																																																																																																																																					
Peak Avg																																																																																																																																												
	<table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>4924.00</td><td>45.03</td><td>74.00</td><td>-28.97</td><td>68.64</td><td>33.87</td><td>7.79</td><td>65.27</td><td>236</td><td>169</td><td>Peak</td></tr><tr><td>2</td><td>4924.00</td><td>36.40</td><td>54.00</td><td>-17.60</td><td>60.01</td><td>33.87</td><td>7.79</td><td>65.27</td><td>236</td><td>169</td><td>Average</td></tr><tr><td>3</td><td>7386.00</td><td>44.14</td><td>74.00</td><td>-29.86</td><td>63.26</td><td>36.30</td><td>9.17</td><td>64.59</td><td>--</td><td>--</td><td>Peak</td></tr></tbody></table>							Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	4924.00	45.03	74.00	-28.97	68.64	33.87	7.79	65.27	236	169	Peak	2	4924.00	36.40	54.00	-17.60	60.01	33.87	7.79	65.27	236	169	Average	3	7386.00	44.14	74.00	-29.86	63.26	36.30	9.17	64.59	--	--	Peak	<table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>4924.00</td><td>44.63</td><td>74.00</td><td>-29.37</td><td>68.24</td><td>33.87</td><td>7.79</td><td>65.27</td><td>100</td><td>82</td><td>Peak</td></tr><tr><td>2</td><td>4924.00</td><td>36.40</td><td>54.00</td><td>-17.60</td><td>60.01</td><td>33.87</td><td>7.79</td><td>65.27</td><td>100</td><td>82</td><td>Average</td></tr><tr><td>3</td><td>7386.00</td><td>44.02</td><td>74.00</td><td>-29.98</td><td>63.14</td><td>36.30</td><td>9.17</td><td>64.59</td><td>--</td><td>--</td><td>Peak</td></tr></tbody></table>							Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	4924.00	44.63	74.00	-29.37	68.24	33.87	7.79	65.27	100	82	Peak	2	4924.00	36.40	54.00	-17.60	60.01	33.87	7.79	65.27	100	82	Average	3	7386.00	44.02	74.00	-29.98	63.14	36.30	9.17	64.59	--	--	Peak
		Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																																																																				
	Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																																																																			
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																																																																																																																			
1	4924.00	45.03	74.00	-28.97	68.64	33.87	7.79	65.27	236	169	Peak																																																																																																																																	
2	4924.00	36.40	54.00	-17.60	60.01	33.87	7.79	65.27	236	169	Average																																																																																																																																	
3	7386.00	44.14	74.00	-29.86	63.26	36.30	9.17	64.59	--	--	Peak																																																																																																																																	
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																																																																					
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																																																																				
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																																																																																																																			
1	4924.00	44.63	74.00	-29.37	68.24	33.87	7.79	65.27	100	82	Peak																																																																																																																																	
2	4924.00	36.40	54.00	-17.60	60.01	33.87	7.79	65.27	100	82	Average																																																																																																																																	
3	7386.00	44.02	74.00	-29.98	63.14	36.30	9.17	64.59	--	--	Peak																																																																																																																																	





Mode	7																																																																																											
	Band Edge																																																																																											
	2400-2483.5_802.11n HT20_CH01_2412MHz																																																																																											
ANT	SISO																																																																																											
Pol.	Horizontal						Fundamental																																																																																					
Peak	Level (dBuV/m) Date: 2025-01-04 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>2389.82</td><td>67.01</td><td>74.00</td><td>-6.99</td><td>65.47</td><td>30.44</td><td>4.80</td><td>33.70</td><td>100</td><td>290</td><td>PEAK</td></tr></tbody></table>							Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	2389.82	67.01	74.00	-6.99	65.47	30.44	4.80	33.70	100	290	PEAK	Level (dBuV/m) Date: 2025-01-04 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>2412.00</td><td>104.05</td><td>-----</td><td>-----</td><td>102.43</td><td>30.45</td><td>4.83</td><td>33.66</td><td>100</td><td>290</td><td>PEAK</td></tr></tbody></table>							Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	2412.00	104.05	-----	-----	102.43	30.45	4.83	33.66	100	290	PEAK
		Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																				
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																				
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																																																																			
1	2389.82	67.01	74.00	-6.99	65.47	30.44	4.80	33.70	100	290	PEAK																																																																																	
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																					
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																				
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																																																																			
1	2412.00	104.05	-----	-----	102.43	30.45	4.83	33.66	100	290	PEAK																																																																																	
Avg	Level (dBuV/m) Date: 2025-01-04 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>2389.82</td><td>50.28</td><td>54.00</td><td>-3.72</td><td>48.74</td><td>30.44</td><td>4.80</td><td>33.70</td><td>100</td><td>290</td><td>AVERAGE</td></tr></tbody></table>							Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	2389.82	50.28	54.00	-3.72	48.74	30.44	4.80	33.70	100	290	AVERAGE	Level (dBuV/m) Date: 2025-01-04 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>2412.00</td><td>96.66</td><td>-----</td><td>-----</td><td>95.05</td><td>30.45</td><td>4.82</td><td>33.66</td><td>100</td><td>290</td><td>AVERAGE</td></tr></tbody></table>							Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	2412.00	96.66	-----	-----	95.05	30.45	4.82	33.66	100	290	AVERAGE
		Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																				
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																				
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																																																																			
1	2389.82	50.28	54.00	-3.72	48.74	30.44	4.80	33.70	100	290	AVERAGE																																																																																	
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																					
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																				
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																																																																			
1	2412.00	96.66	-----	-----	95.05	30.45	4.82	33.66	100	290	AVERAGE																																																																																	





Mode	7	
	Band Edge	
	2400-2483.5_802.11n_HT20_CH01_2412MHz	
ANT	SISO	
Pol.	Vertical	Fundamental
Peak	Level (dBuV/m) Date: 2025-01-04 1 2389.82 57.59 74.00 -16.41 56.05 30.44 4.80 33.70 300 191 PEAK	Level (dBuV/m) Date: 2025-01-04 1 2412.00 98.10 ----- 96.50 30.45 4.82 33.67 300 191 PEAK
	Level (dBuV/m) Date: 2025-01-04 1 2389.82 57.59 74.00 -16.41 56.05 30.44 4.80 33.70 300 191 PEAK	Level (dBuV/m) Date: 2025-01-04 1 2412.00 98.10 ----- 96.50 30.45 4.82 33.67 300 191 PEAK
Avg	Level (dBuV/m) Date: 2025-01-04 1 2389.82 43.86 54.00 -10.14 42.32 30.44 4.80 33.70 300 191 AVERAGE	Level (dBuV/m) Date: 2025-01-04 1 2412.00 90.70 ----- 89.09 30.45 4.82 33.66 300 191 AVERAGE
	Level (dBuV/m) Date: 2025-01-04 1 2389.82 43.86 54.00 -10.14 42.32 30.44 4.80 33.70 300 191 AVERAGE	Level (dBuV/m) Date: 2025-01-04 1 2412.00 90.70 ----- 89.09 30.45 4.82 33.66 300 191 AVERAGE



Mode	7																																																																																																															
	Harmonic																																																																																																															
	2400-2483.5_802.11n HT20_CH01_2412MHz																																																																																																															
ANT	SISO																																																																																																															
Pol.	Horizontal						Vertical																																																																																																									
Peak Avg																																																																																																																
	<table><tr><th colspan="2"></th><th colspan="2">Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th rowspan="3">Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Loss</th><th>Factor</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>4824.00</td><td>42.00</td><td>74.00</td><td>-32.00</td><td>65.65</td><td>33.83</td><td>7.75</td><td>65.23</td><td>--</td><td>--</td><td>Peak</td></tr></table>								Limit		Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Loss	Factor	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	dB	cm	deg	1	4824.00	42.00	74.00	-32.00	65.65	33.83	7.75	65.23	--	--	Peak	<table><tr><th colspan="2"></th><th colspan="2">Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th rowspan="3">Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Loss</th><th>Factor</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>4824.00</td><td>43.20</td><td>74.00</td><td>-30.80</td><td>66.85</td><td>33.83</td><td>7.75</td><td>65.23</td><td>264</td><td>346</td><td>Peak</td></tr><tr><td>2</td><td>4824.00</td><td>35.05</td><td>54.00</td><td>-18.95</td><td>58.70</td><td>33.83</td><td>7.75</td><td>65.23</td><td>264</td><td>346</td><td>Average</td></tr></table>								Limit		Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Loss	Factor	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	dB	cm	deg	1	4824.00	43.20	74.00	-30.80	66.85	33.83	7.75	65.23	264	346	Peak	2	4824.00	35.05	54.00	-18.95	58.70	33.83	7.75	65.23	264	346	Average
			Limit		Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																																					
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Loss	Factor																																																																																																							
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	dB	cm	deg																																																																																																						
1	4824.00	42.00	74.00	-32.00	65.65	33.83	7.75	65.23	--	--	Peak																																																																																																					
		Limit		Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																																						
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Loss	Factor																																																																																																							
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	dB	cm		deg																																																																																																					
1	4824.00	43.20	74.00	-30.80	66.85	33.83	7.75	65.23	264	346	Peak																																																																																																					
2	4824.00	35.05	54.00	-18.95	58.70	33.83	7.75	65.23	264	346	Average																																																																																																					







Mode	8																																																																											
	Harmonic																																																																											
	2400-2483.5_802.11n HT20_CH06_2437MHz																																																																											
ANT	SISO																																																																											
Pol.	Horizontal						Vertical																																																																					
Peak Avg																																																																												
	<table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr></thead><tbody><tr><td></td><td>MHz</td><td>dBuV/m</td><td>dBuV/m</td><td>dB</td><td>dBuV</td><td>dB/m</td><td>dB</td><td>cm</td><td>deg</td></tr><tr><td>1</td><td>4874.00</td><td>45.25</td><td>74.00</td><td>-28.75</td><td>68.88</td><td>33.85</td><td>7.77</td><td>65.25</td><td>220</td><td>115</td><td>Peak</td></tr><tr><td>2</td><td>4874.00</td><td>36.44</td><td>54.00</td><td>-17.56</td><td>60.07</td><td>33.85</td><td>7.77</td><td>65.25</td><td>220</td><td>115</td><td>Average</td></tr><tr><td>3</td><td>7311.00</td><td>44.73</td><td>74.00</td><td>-29.27</td><td>64.15</td><td>36.30</td><td>8.93</td><td>64.65</td><td>--</td><td>--</td><td>Peak</td></tr></tbody></table>													Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	4874.00	45.25	74.00	-28.75	68.88	33.85	7.77	65.25	220	115	Peak	2	4874.00	36.44	54.00	-17.56	60.07	33.85	7.77	65.25	220	115	Average	3	7311.00	44.73	74.00	-29.27	64.15	36.30	8.93	64.65	--	--	Peak
		Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																				
	Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																			
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																																																			
1	4874.00	45.25	74.00	-28.75	68.88	33.85	7.77	65.25	220	115	Peak																																																																	
2	4874.00	36.44	54.00	-17.56	60.07	33.85	7.77	65.25	220	115	Average																																																																	
3	7311.00	44.73	74.00	-29.27	64.15	36.30	8.93	64.65	--	--	Peak																																																																	
<table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr></thead><tbody><tr><td></td><td>MHz</td><td>dBuV/m</td><td>dBuV/m</td><td>dB</td><td>dBuV</td><td>dB/m</td><td>dB</td><td>cm</td><td>deg</td></tr><tr><td>1</td><td>4874.00</td><td>45.25</td><td>74.00</td><td>-28.75</td><td>68.88</td><td>33.85</td><td>7.77</td><td>65.25</td><td>313</td><td>120</td><td>Peak</td></tr><tr><td>2</td><td>4874.00</td><td>36.77</td><td>54.00</td><td>-17.23</td><td>60.40</td><td>33.85</td><td>7.77</td><td>65.25</td><td>313</td><td>120</td><td>Average</td></tr><tr><td>3</td><td>7311.00</td><td>44.01</td><td>74.00</td><td>-29.99</td><td>63.43</td><td>36.30</td><td>8.93</td><td>64.65</td><td>--</td><td>--</td><td>Peak</td></tr></tbody></table>													Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	4874.00	45.25	74.00	-28.75	68.88	33.85	7.77	65.25	313	120	Peak	2	4874.00	36.77	54.00	-17.23	60.40	33.85	7.77	65.25	313	120	Average	3	7311.00	44.01	74.00	-29.99	63.43	36.30	8.93	64.65	--	--	Peak	
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																					
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																				
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																																																			
1	4874.00	45.25	74.00	-28.75	68.88	33.85	7.77	65.25	313	120	Peak																																																																	
2	4874.00	36.77	54.00	-17.23	60.40	33.85	7.77	65.25	313	120	Average																																																																	
3	7311.00	44.01	74.00	-29.99	63.43	36.30	8.93	64.65	--	--	Peak																																																																	





Mode	9																																																																																											
	Band Edge																																																																																											
	2400-2483.5_802.11n HT20_CH11_2462MHz																																																																																											
ANT	SISO																																																																																											
Pol.	Horizontal						Fundamental																																																																																					
Peak	Level (dBuV/m) Date: 2025-01-04 140 122.5 105.0 87.5 70.0 52.5 35.0 17.5 0 2462 2469.6 2477.2 2484.8 2492.4 2500 Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>2483.62</td><td>66.86</td><td>74.00</td><td>-7.14</td><td>64.98</td><td>30.49</td><td>4.92</td><td>33.53</td><td>200</td><td>65</td><td>PEAK</td></tr></table>							Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	2483.62	66.86	74.00	-7.14	64.98	30.49	4.92	33.53	200	65	PEAK	Level (dBuV/m) Date: 2025-01-04 140 122.5 105.0 87.5 70.0 52.5 35.0 17.5 0 1000 1400 1800 2200 2600 3000 Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>2462.00</td><td>103.46</td><td>-----</td><td>-----</td><td>101.68</td><td>30.48</td><td>4.88</td><td>33.58</td><td>200</td><td>65</td><td>PEAK</td></tr></table>							Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	2462.00	103.46	-----	-----	101.68	30.48	4.88	33.58	200	65	PEAK
		Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																				
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																				
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																																																																			
1	2483.62	66.86	74.00	-7.14	64.98	30.49	4.92	33.53	200	65	PEAK																																																																																	
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																					
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																				
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																																																																			
1	2462.00	103.46	-----	-----	101.68	30.48	4.88	33.58	200	65	PEAK																																																																																	
Avg	Level (dBuV/m) Date: 2025-01-04 140 122.5 105.0 87.5 70.0 52.5 35.0 17.5 0 2462 2469.6 2477.2 2484.8 2492.4 2500 Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>2483.51</td><td>50.64</td><td>54.00</td><td>-3.36</td><td>48.76</td><td>30.49</td><td>4.92</td><td>33.53</td><td>200</td><td>65</td><td>AVERAGE</td></tr></table>							Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	2483.51	50.64	54.00	-3.36	48.76	30.49	4.92	33.53	200	65	AVERAGE	Level (dBuV/m) Date: 2025-01-04 140 122.5 105.0 87.5 70.0 52.5 35.0 17.5 0 1000 1400 1800 2200 2600 3000 Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>2462.00</td><td>96.60</td><td>-----</td><td>-----</td><td>94.81</td><td>30.48</td><td>4.89</td><td>33.58</td><td>200</td><td>65</td><td>AVERAGE</td></tr></table>							Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	2462.00	96.60	-----	-----	94.81	30.48	4.89	33.58	200	65	AVERAGE
		Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																				
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																				
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																																																																			
1	2483.51	50.64	54.00	-3.36	48.76	30.49	4.92	33.53	200	65	AVERAGE																																																																																	
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																					
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																				
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																																																																			
1	2462.00	96.60	-----	-----	94.81	30.48	4.89	33.58	200	65	AVERAGE																																																																																	



Mode	9																																																																																
	Band Edge																																																																																
	2400-2483.5_802.11n_HT20_CH11_2462MHz																																																																																
ANT	SISO																																																																																
Pol.	Vertical						Fundamental																																																																										
Peak																																																																																	
		Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor			MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	2483.89	61.47	74.00	-12.53	59.59	30.49	4.92	33.53	326	360	PEAK	<table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>2462.00</td><td>99.42</td><td>-----</td><td>-----</td><td>97.62</td><td>30.48</td><td>4.89</td><td>33.57</td><td>326</td><td>360</td><td>PEAK</td></tr></tbody></table>		Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor			MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	2462.00	99.42	-----	-----	97.62	30.48	4.89	33.57	326	360	PEAK
	Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																									
Freq	Level	Line	Margin	Level	Factor	Loss	Factor																																																																										
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																																																								
1	2483.89	61.47	74.00	-12.53	59.59	30.49	4.92	33.53	326	360	PEAK																																																																						
	Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																									
Freq	Level	Line	Margin	Level	Factor	Loss	Factor																																																																										
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																																																								
1	2462.00	99.42	-----	-----	97.62	30.48	4.89	33.57	326	360	PEAK																																																																						
Avg																																																																																	
	<table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>2483.58</td><td>46.42</td><td>54.00</td><td>-7.58</td><td>44.54</td><td>30.49</td><td>4.92</td><td>33.53</td><td>326</td><td>360</td><td>AVERAGE</td></tr></tbody></table>		Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor			MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	2483.58	46.42	54.00	-7.58	44.54	30.49	4.92	33.53	326	360	AVERAGE	<table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>2462.00</td><td>91.18</td><td>-----</td><td>-----</td><td>89.38</td><td>30.48</td><td>4.89</td><td>33.57</td><td>326</td><td>360</td><td>AVERAGE</td></tr></tbody></table>		Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor			MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	2462.00	91.18	-----	-----	89.38	30.48	4.89	33.57	326	360
	Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																									
Freq	Level	Line	Margin	Level	Factor	Loss	Factor																																																																										
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																																																								
1	2483.58	46.42	54.00	-7.58	44.54	30.49	4.92	33.53	326	360	AVERAGE																																																																						
	Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																									
Freq	Level	Line	Margin	Level	Factor	Loss	Factor																																																																										
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																																																								
1	2462.00	91.18	-----	-----	89.38	30.48	4.89	33.57	326	360	AVERAGE																																																																						



Mode	9																																																																																																																		
	Harmonic																																																																																																																		
	2400-2483.5_802.11n HT20_CH11_2462MHz																																																																																																																		
ANT	SISO																																																																																																																		
Pol.	Horizontal						Vertical																																																																																																												
Peak Avg																																																																																																																			
	<table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr></thead><tbody><tr><td></td><td>MHz</td><td>dBuV/m</td><td>dBuV/m</td><td>dB</td><td>dBuV</td><td>dB/m</td><td>dB</td><td>dB</td><td>cm</td><td>deg</td></tr><tr><td>1</td><td>4924.00</td><td>41.15</td><td>74.00</td><td>-32.85</td><td>64.76</td><td>33.87</td><td>7.79</td><td>65.27</td><td>--</td><td>--</td><td>Peak</td></tr><tr><td>2</td><td>7386.00</td><td>43.50</td><td>74.00</td><td>-30.50</td><td>62.62</td><td>36.30</td><td>9.17</td><td>64.59</td><td>--</td><td>--</td><td>Peak</td></tr></tbody></table>							Limit	Read	Ant	Cable	Preamp	APos	TPos	Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	4924.00	41.15	74.00	-32.85	64.76	33.87	7.79	65.27	--	--	Peak	2	7386.00	43.50	74.00	-30.50	62.62	36.30	9.17	64.59	--	--	Peak	<table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr></thead><tbody><tr><td></td><td>MHz</td><td>dBuV/m</td><td>dBuV/m</td><td>dB</td><td>dBuV</td><td>dB/m</td><td>dB</td><td>dB</td><td>cm</td><td>deg</td></tr><tr><td>1</td><td>4924.00</td><td>43.00</td><td>74.00</td><td>-31.00</td><td>66.61</td><td>33.87</td><td>7.79</td><td>65.27</td><td>--</td><td>--</td><td>Peak</td></tr><tr><td>2</td><td>7386.00</td><td>43.51</td><td>74.00</td><td>-30.49</td><td>62.63</td><td>36.30</td><td>9.17</td><td>64.59</td><td>--</td><td>--</td><td>Peak</td></tr></tbody></table>						Limit	Read	Ant	Cable	Preamp	APos	TPos	Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	4924.00	43.00	74.00	-31.00	66.61	33.87	7.79	65.27	--	--	Peak	2	7386.00	43.51	74.00	-30.49	62.63	36.30	9.17	64.59	--	--	Peak
		Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																																											
	Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																																										
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																																									
1	4924.00	41.15	74.00	-32.85	64.76	33.87	7.79	65.27	--	--	Peak																																																																																																								
2	7386.00	43.50	74.00	-30.50	62.62	36.30	9.17	64.59	--	--	Peak																																																																																																								
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																																												
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																																											
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																																									
1	4924.00	43.00	74.00	-31.00	66.61	33.87	7.79	65.27	--	--	Peak																																																																																																								
2	7386.00	43.51	74.00	-30.49	62.63	36.30	9.17	64.59	--	--	Peak																																																																																																								



Mode	10																																																																																											
	Band Edge - L																																																																																											
	2400-2483.5_802.11n HT40_CH03_2422MHz																																																																																											
ANT	SISO																																																																																											
Pol.	Horizontal						Fundamental																																																																																					
Peak	Level (dBuV/m) Date: 2024-12-24 130 113.8 97.5 81.3 65.0 48.8 32.5 16.3 0 2310 2332.4 2354.8 2377.2 2399.6 2422 Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>2389.74</td><td>64.05</td><td>74.00</td><td>-9.95</td><td>62.51</td><td>30.44</td><td>4.80</td><td>33.70</td><td>100</td><td>75</td><td>PEAK</td></tr></table>							Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	2389.74	64.05	74.00	-9.95	62.51	30.44	4.80	33.70	100	75	PEAK	Level (dBuV/m) Date: 2024-12-24 130 113.8 97.5 81.3 65.0 48.8 32.5 16.3 0 1000 1400 1800 2200 2600 3000 Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>2422.00</td><td>100.67</td><td>-----</td><td>-----</td><td>99.04</td><td>30.45</td><td>4.83</td><td>33.65</td><td>100</td><td>75</td><td>PEAK</td></tr></table>							Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	2422.00	100.67	-----	-----	99.04	30.45	4.83	33.65	100	75	PEAK
		Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																				
	Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																			
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																																																																			
1	2389.74	64.05	74.00	-9.95	62.51	30.44	4.80	33.70	100	75	PEAK																																																																																	
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																					
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																				
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																																																																			
1	2422.00	100.67	-----	-----	99.04	30.45	4.83	33.65	100	75	PEAK																																																																																	
Avg	Level (dBuV/m) Date: 2024-12-24 130 113.8 97.5 81.3 65.0 48.8 32.5 16.3 0 2310 2332.4 2354.8 2377.2 2399.6 2422 Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>2389.97</td><td>50.83</td><td>54.00</td><td>-3.17</td><td>49.29</td><td>30.44</td><td>4.80</td><td>33.70</td><td>100</td><td>75</td><td>AVERAGE</td></tr></table>							Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	2389.97	50.83	54.00	-3.17	49.29	30.44	4.80	33.70	100	75	AVERAGE	Level (dBuV/m) Date: 2024-12-24 130 113.8 97.5 81.3 65.0 48.8 32.5 16.3 0 1000 1400 1800 2200 2600 3000 Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>2422.00</td><td>93.72</td><td>-----</td><td>-----</td><td>92.09</td><td>30.45</td><td>4.83</td><td>33.65</td><td>100</td><td>75</td><td>AVERAGE</td></tr></table>							Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	2422.00	93.72	-----	-----	92.09	30.45	4.83	33.65	100	75	AVERAGE
		Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																				
	Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																			
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																																																																			
1	2389.97	50.83	54.00	-3.17	49.29	30.44	4.80	33.70	100	75	AVERAGE																																																																																	
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																					
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																				
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																																																																			
1	2422.00	93.72	-----	-----	92.09	30.45	4.83	33.65	100	75	AVERAGE																																																																																	



Mode	10									
	Band Edge - R									
	2400-2483.5_802.11n HT40_CH03_2422MHz									
ANT	SISO									
Pol.	Horizontal					Fundamental				
Peak	<									







Mode	10																																																																																									
	Band Edge - L																																																																																									
	2400-2483.5_802.11n HT40_CH03_2422MHz																																																																																									
ANT	SISO																																																																																									
Pol.	Vertical					Fundamental																																																																																				
Peak	Level (dBuV/m) Date: 2024-12-24 130 113.8 97.5 81.3 65.0 48.8 32.5 16.3 0 2310 2332.4 2354.8 2377.2 2399.6 2422 Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>2389.52</td><td>52.22</td><td>74.00</td><td>-21.78</td><td>50.68</td><td>30.44</td><td>4.80</td><td>33.70</td><td>100</td><td>33</td><td>PEAK</td></tr></table>						Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor			MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	2389.52	52.22	74.00	-21.78	50.68	30.44	4.80	33.70	100	33	PEAK	Level (dBuV/m) Date: 2024-12-24 130 113.8 97.5 81.3 65.0 48.8 32.5 16.3 0 1000 1400 1800 2200 2600 3000 Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>2422.00</td><td>90.75</td><td>-----</td><td>-----</td><td>89.12</td><td>30.45</td><td>4.83</td><td>33.65</td><td>100</td><td>33</td><td>PEAK</td></tr></table>						Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor			MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	2422.00	90.75	-----	-----	89.12	30.45	4.83	33.65	100	33	PEAK
		Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																	
Freq	Level	Line	Margin	Level	Factor	Loss	Factor																																																																																			
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																																																																	
1	2389.52	52.22	74.00	-21.78	50.68	30.44	4.80	33.70	100	33	PEAK																																																																															
	Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																		
Freq	Level	Line	Margin	Level	Factor	Loss	Factor																																																																																			
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																																																																	
1	2422.00	90.75	-----	-----	89.12	30.45	4.83	33.65	100	33	PEAK																																																																															
Avg	Level (dBuV/m) Date: 2024-12-24 130 113.8 97.5 81.3 65.0 48.8 32.5 16.3 0 2310 2332.4 2354.8 2377.2 2399.6 2422 Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>2388.74</td><td>38.41</td><td>54.00</td><td>-15.59</td><td>36.90</td><td>30.43</td><td>4.79</td><td>33.71</td><td>100</td><td>33</td><td>AVERAGE</td></tr></table>						Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor			MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	2388.74	38.41	54.00	-15.59	36.90	30.43	4.79	33.71	100	33	AVERAGE	Level (dBuV/m) Date: 2024-12-24 130 113.8 97.5 81.3 65.0 48.8 32.5 16.3 0 1000 1400 1800 2200 2600 3000 Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>2422.00</td><td>75.19</td><td>-----</td><td>-----</td><td>73.53</td><td>30.46</td><td>4.84</td><td>33.64</td><td>100</td><td>33</td><td>AVERAGE</td></tr></table>						Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor			MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	2422.00	75.19	-----	-----	73.53	30.46	4.84	33.64	100	33	AVERAGE
		Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																	
Freq	Level	Line	Margin	Level	Factor	Loss	Factor																																																																																			
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																																																																	
1	2388.74	38.41	54.00	-15.59	36.90	30.43	4.79	33.71	100	33	AVERAGE																																																																															
	Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																		
Freq	Level	Line	Margin	Level	Factor	Loss	Factor																																																																																			
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																																																																	
1	2422.00	75.19	-----	-----	73.53	30.46	4.84	33.64	100	33	AVERAGE																																																																															



Mode	10																																																	
	Band Edge - R																																																	
	2400-2483.5_802.11n HT40_CH03_2422MHz																																																	
ANT	SISO																																																	
Pol.	Vertical					Fundamental																																												
Peak	Date: 2024-12-24 <table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>2487.83</td><td>48.40</td><td>74.00</td><td>-25.60</td><td>46.50</td><td>30.50</td><td>4.93</td><td>33.53</td><td>100</td><td>33</td><td>PEAK</td></tr></tbody></table>						Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	2487.83	48.40	74.00	-25.60	46.50	30.50	4.93	33.53	100	33	PEAK	Blank				
		Limit	Read	Ant	Cable	Preamp	APos	TPos																																										
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																										
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																									
1	2487.83	48.40	74.00	-25.60	46.50	30.50	4.93	33.53	100	33	PEAK																																							
Avg	Date: 2024-12-24 <table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>2491.89</td><td>38.33</td><td>54.00</td><td>-15.67</td><td>36.42</td><td>30.50</td><td>4.93</td><td>33.52</td><td>100</td><td>33</td><td>AVERAGE</td></tr></tbody></table>						Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	2491.89	38.33	54.00	-15.67	36.42	30.50	4.93	33.52	100	33	AVERAGE	Blank				
		Limit	Read	Ant	Cable	Preamp	APos	TPos																																										
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																										
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																									
1	2491.89	38.33	54.00	-15.67	36.42	30.50	4.93	33.52	100	33	AVERAGE																																							



Mode	11																																																																																										
	Band Edge - L																																																																																										
	2400-2483.5_802.11n HT40_CH09_2452MHz																																																																																										
ANT	SISO																																																																																										
Pol.	Horizontal						Fundamental																																																																																				
Peak	 Level (dBuV/m) Date: 2024-12-24 <table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>2311.70</td><td>49.41</td><td>74.00</td><td>-24.59</td><td>48.15</td><td>30.39</td><td>4.72</td><td>33.85</td><td>300</td><td>290</td><td>PEAK</td></tr></tbody></table>							Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor			MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	2311.70	49.41	74.00	-24.59	48.15	30.39	4.72	33.85	300	290	PEAK	 Level (dBuV/m) Date: 2024-12-24 <table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>2452.00</td><td>102.70</td><td>-----</td><td>-----</td><td>100.90</td><td>30.48</td><td>4.89</td><td>33.57</td><td>300</td><td>290</td><td>PEAK</td></tr></tbody></table>						Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor			MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	2452.00	102.70	-----	-----	100.90	30.48	4.89	33.57	300	290	PEAK
		Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																		
Freq	Level	Line	Margin	Level	Factor	Loss	Factor																																																																																				
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																																																																		
1	2311.70	49.41	74.00	-24.59	48.15	30.39	4.72	33.85	300	290	PEAK																																																																																
	Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																			
Freq	Level	Line	Margin	Level	Factor	Loss	Factor																																																																																				
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																																																																		
1	2452.00	102.70	-----	-----	100.90	30.48	4.89	33.57	300	290	PEAK																																																																																
Avg	 Level (dBuV/m) Date: 2024-12-24 <table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>2386.68</td><td>38.76</td><td>54.00</td><td>-15.24</td><td>37.25</td><td>30.43</td><td>4.79</td><td>33.71</td><td>300</td><td>290</td><td>AVERAGE</td></tr></tbody></table>							Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor			MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	2386.68	38.76	54.00	-15.24	37.25	30.43	4.79	33.71	300	290	AVERAGE	 Level (dBuV/m) Date: 2024-12-24 <table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>2452.00</td><td>93.65</td><td>-----</td><td>-----</td><td>91.87</td><td>30.48</td><td>4.88</td><td>33.58</td><td>300</td><td>290</td><td>AVERAGE</td></tr></tbody></table>						Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor			MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	2452.00	93.65	-----	-----	91.87	30.48	4.88	33.58	300	290	AVERAGE
		Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																		
Freq	Level	Line	Margin	Level	Factor	Loss	Factor																																																																																				
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																																																																		
1	2386.68	38.76	54.00	-15.24	37.25	30.43	4.79	33.71	300	290	AVERAGE																																																																																
	Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																			
Freq	Level	Line	Margin	Level	Factor	Loss	Factor																																																																																				
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																																																																		
1	2452.00	93.65	-----	-----	91.87	30.48	4.88	33.58	300	290	AVERAGE																																																																																



Mode	11																																									
	Band Edge - R																																									
	2400-2483.5_802.11n HT40_CH09_2452MHz																																									
ANT	SISO																																									
Pol.	Horizontal	Fundamental																																								
Peak	Date: 2024-12-24 <table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>2484.78</td><td>66.83</td><td>74.00</td><td>-7.17</td><td>64.95</td><td>30.49</td><td>4.92</td><td>33.53</td><td>300</td><td>290</td><td>PEAK</td></tr></table>		Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor			MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	2484.78	66.83	74.00	-7.17	64.95	30.49	4.92	33.53	300	290	PEAK	Blank
	Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark																																		
Freq	Level	Line	Margin	Level	Factor	Loss	Factor																																			
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																	
1	2484.78	66.83	74.00	-7.17	64.95	30.49	4.92	33.53	300	290	PEAK																															
Avg	Date: 2024-12-24 <table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>2484.74</td><td>49.55</td><td>54.00</td><td>-4.45</td><td>47.67</td><td>30.49</td><td>4.92</td><td>33.53</td><td>300</td><td>290</td><td>AVERAGE</td></tr></table>		Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor			MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	2484.74	49.55	54.00	-4.45	47.67	30.49	4.92	33.53	300	290	AVERAGE	Blank
	Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark																																		
Freq	Level	Line	Margin	Level	Factor	Loss	Factor																																			
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																	
1	2484.74	49.55	54.00	-4.45	47.67	30.49	4.92	33.53	300	290	AVERAGE																															



Mode	11																																																																																										
	Band Edge - L																																																																																										
	2400-2483.5_802.11n HT40_CH09_2452MHz																																																																																										
ANT	SISO																																																																																										
Pol.	Vertical						Fundamental																																																																																				
Peak	Level (dBuV/m) Date: 2024-12-24 130 113.8 97.5 81.3 65.0 48.8 32.5 16.3 0 2310 2338.4 2366.8 2395.2 2423.6 2452 Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>2383.13</td><td>49.31</td><td>74.00</td><td>-24.69</td><td>47.81</td><td>30.43</td><td>4.79</td><td>33.72</td><td>282</td><td>360</td><td>PEAK</td></tr></table>							Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	2383.13	49.31	74.00	-24.69	47.81	30.43	4.79	33.72	282	360	PEAK	Level (dBuV/m) Date: 2024-12-24 130 113.8 97.5 81.3 65.0 48.8 32.5 16.3 0 1000 1400 1800 2200 2600 3000 Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>2452.00</td><td>87.88</td><td>-----</td><td>-----</td><td>86.10</td><td>30.48</td><td>4.88</td><td>33.58</td><td>282</td><td>360</td><td>PEAK_74</td></tr></table>						Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	2452.00	87.88	-----	-----	86.10	30.48	4.88	33.58	282	360	PEAK_74
		Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																			
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																			
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																																																																		
1	2383.13	49.31	74.00	-24.69	47.81	30.43	4.79	33.72	282	360	PEAK																																																																																
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																				
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																			
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																																																																		
1	2452.00	87.88	-----	-----	86.10	30.48	4.88	33.58	282	360	PEAK_74																																																																																
Avg	Level (dBuV/m) Date: 2024-12-24 130 113.8 97.5 81.3 65.0 48.8 32.5 16.3 0 2310 2338.4 2366.8 2395.2 2423.6 2452 Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>2383.56</td><td>37.89</td><td>54.00</td><td>-16.11</td><td>36.39</td><td>30.43</td><td>4.79</td><td>33.72</td><td>282</td><td>360</td><td>AVERAGE</td></tr></table>							Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	2383.56	37.89	54.00	-16.11	36.39	30.43	4.79	33.72	282	360	AVERAGE	Level (dBuV/m) Date: 2024-12-24 130 113.8 97.5 81.3 65.0 48.8 32.5 16.3 0 1000 1400 1800 2200 2600 3000 Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>2452.00</td><td>81.37</td><td>-----</td><td>-----</td><td>79.59</td><td>30.48</td><td>4.88</td><td>33.58</td><td>282</td><td>360</td><td>AVERAGE</td></tr></table>						Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	2452.00	81.37	-----	-----	79.59	30.48	4.88	33.58	282	360	AVERAGE
		Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																			
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																			
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																																																																		
1	2383.56	37.89	54.00	-16.11	36.39	30.43	4.79	33.72	282	360	AVERAGE																																																																																
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																				
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																			
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																																																																		
1	2452.00	81.37	-----	-----	79.59	30.48	4.88	33.58	282	360	AVERAGE																																																																																







Mode	11																															
	Band Edge - R																															
	2400-2483.5_802.11n HT40_CH09_2452MHz																															
ANT	SISO																															
Pol.	Vertical	Fundamental																														
Peak	Date: 2024-12-24 <table><thead><tr><th>Freq</th><th>Level</th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1 2484.83</td><td>58.13</td><td>74.00</td><td>-15.87</td><td>56.25</td><td>30.49</td><td>4.92</td><td>33.53</td><td>282</td><td>360 PEAK</td></tr></tbody></table>	Freq	Level	Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1 2484.83	58.13	74.00	-15.87	56.25	30.49	4.92	33.53	282	360 PEAK	Blank
Freq	Level	Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark																							
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																							
1 2484.83	58.13	74.00	-15.87	56.25	30.49	4.92	33.53	282	360 PEAK																							
Avg	Date: 2024-12-24 <table><thead><tr><th>Freq</th><th>Level</th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1 2484.59</td><td>42.56</td><td>54.00</td><td>-11.44</td><td>40.68</td><td>30.49</td><td>4.92</td><td>33.53</td><td>282</td><td>360 AVERAGE</td></tr></tbody></table>	Freq	Level	Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1 2484.59	42.56	54.00	-11.44	40.68	30.49	4.92	33.53	282	360 AVERAGE	Blank
Freq	Level	Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark																							
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																							
1 2484.59	42.56	54.00	-11.44	40.68	30.49	4.92	33.53	282	360 AVERAGE																							







Mode	12																																																																																																																																																																																																																			
	LF																																																																																																																																																																																																																			
	2400-2483.5_802.11n HT40_CH03_LF_2422MHz																																																																																																																																																																																																																			
ANT	SISO																																																																																																																																																																																																																			
Pol.	Horizontal						Vertical																																																																																																																																																																																																													
QPI/ Peak	Level (dBuV/m) Date: 2025-01-05 FCC CLASS-B -60dB Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>30.97</td><td>24.92</td><td>40.00</td><td>-15.08</td><td>41.36</td><td>17.78</td><td>0.55</td><td>34.77</td><td>--</td><td>--</td><td>Peak</td></tr><tr><td>2</td><td>142.52</td><td>22.81</td><td>43.50</td><td>-20.69</td><td>37.93</td><td>18.35</td><td>1.25</td><td>34.72</td><td>--</td><td>--</td><td>Peak</td></tr><tr><td>3</td><td>349.13</td><td>24.91</td><td>46.00</td><td>-21.09</td><td>37.37</td><td>20.20</td><td>1.94</td><td>34.60</td><td>--</td><td>--</td><td>Peak</td></tr><tr><td>4</td><td>513.06</td><td>26.81</td><td>46.00</td><td>-19.19</td><td>35.35</td><td>23.57</td><td>2.39</td><td>34.50</td><td>--</td><td>--</td><td>Peak</td></tr><tr><td>5</td><td>610.06</td><td>27.79</td><td>46.00</td><td>-18.21</td><td>33.62</td><td>26.12</td><td>2.63</td><td>34.58</td><td>--</td><td>--</td><td>Peak</td></tr><tr><td>6</td><td>745.86</td><td>30.13</td><td>46.00</td><td>-15.87</td><td>34.04</td><td>27.55</td><td>2.94</td><td>34.40</td><td>--</td><td>--</td><td>Peak</td></tr></tbody></table> Level (dBuV/m) Date: 2025-01-05 FCC CLASS-B -60dB Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>33.88</td><td>24.98</td><td>40.00</td><td>-15.02</td><td>40.82</td><td>18.46</td><td>0.57</td><td>34.87</td><td>--</td><td>--</td><td>Peak</td></tr><tr><td>2</td><td>141.55</td><td>25.03</td><td>43.50</td><td>-18.47</td><td>40.23</td><td>18.27</td><td>1.25</td><td>34.72</td><td>--</td><td>--</td><td>Peak</td></tr><tr><td>3</td><td>198.78</td><td>25.84</td><td>43.50</td><td>-17.66</td><td>43.01</td><td>16.05</td><td>1.48</td><td>34.70</td><td>--</td><td>--</td><td>Peak</td></tr><tr><td>4</td><td>409.27</td><td>22.75</td><td>46.00</td><td>-23.25</td><td>33.45</td><td>21.67</td><td>2.13</td><td>34.50</td><td>--</td><td>--</td><td>Peak</td></tr><tr><td>5</td><td>598.42</td><td>27.24</td><td>46.00</td><td>-18.76</td><td>33.20</td><td>26.02</td><td>2.61</td><td>34.59</td><td>--</td><td>--</td><td>Peak</td></tr><tr><td>6</td><td>823.46</td><td>30.78</td><td>46.00</td><td>-15.22</td><td>33.73</td><td>28.29</td><td>3.06</td><td>34.30</td><td>--</td><td>--</td><td>Peak</td></tr></tbody></table>													Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	30.97	24.92	40.00	-15.08	41.36	17.78	0.55	34.77	--	--	Peak	2	142.52	22.81	43.50	-20.69	37.93	18.35	1.25	34.72	--	--	Peak	3	349.13	24.91	46.00	-21.09	37.37	20.20	1.94	34.60	--	--	Peak	4	513.06	26.81	46.00	-19.19	35.35	23.57	2.39	34.50	--	--	Peak	5	610.06	27.79	46.00	-18.21	33.62	26.12	2.63	34.58	--	--	Peak	6	745.86	30.13	46.00	-15.87	34.04	27.55	2.94	34.40	--	--	Peak		Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	33.88	24.98	40.00	-15.02	40.82	18.46	0.57	34.87	--	--	Peak	2	141.55	25.03	43.50	-18.47	40.23	18.27	1.25	34.72	--	--	Peak	3	198.78	25.84	43.50	-17.66	43.01	16.05	1.48	34.70	--	--	Peak	4	409.27	22.75	46.00	-23.25	33.45	21.67	2.13	34.50	--	--	Peak	5	598.42	27.24	46.00	-18.76	33.20	26.02	2.61	34.59	--	--	Peak	6	823.46	30.78	46.00	-15.22	33.73	28.29	3.06	34.30	--	--	Peak
		Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																																																																																																																																											
	Freq	Level	Line	Margin	Level	Factor	Loss	Factor																																																																																																																																																																																																												
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																																																																																																																																											
1	30.97	24.92	40.00	-15.08	41.36	17.78	0.55	34.77	--	--	Peak																																																																																																																																																																																																									
2	142.52	22.81	43.50	-20.69	37.93	18.35	1.25	34.72	--	--	Peak																																																																																																																																																																																																									
3	349.13	24.91	46.00	-21.09	37.37	20.20	1.94	34.60	--	--	Peak																																																																																																																																																																																																									
4	513.06	26.81	46.00	-19.19	35.35	23.57	2.39	34.50	--	--	Peak																																																																																																																																																																																																									
5	610.06	27.79	46.00	-18.21	33.62	26.12	2.63	34.58	--	--	Peak																																																																																																																																																																																																									
6	745.86	30.13	46.00	-15.87	34.04	27.55	2.94	34.40	--	--	Peak																																																																																																																																																																																																									
	Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																																																																																																																																												
Freq	Level	Line	Margin	Level	Factor	Loss	Factor																																																																																																																																																																																																													
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																																																																																																																																											
1	33.88	24.98	40.00	-15.02	40.82	18.46	0.57	34.87	--	--	Peak																																																																																																																																																																																																									
2	141.55	25.03	43.50	-18.47	40.23	18.27	1.25	34.72	--	--	Peak																																																																																																																																																																																																									
3	198.78	25.84	43.50	-17.66	43.01	16.05	1.48	34.70	--	--	Peak																																																																																																																																																																																																									
4	409.27	22.75	46.00	-23.25	33.45	21.67	2.13	34.50	--	--	Peak																																																																																																																																																																																																									
5	598.42	27.24	46.00	-18.76	33.20	26.02	2.61	34.59	--	--	Peak																																																																																																																																																																																																									
6	823.46	30.78	46.00	-15.22	33.73	28.29	3.06	34.30	--	--	Peak																																																																																																																																																																																																									







Mode	13																																																																																							
	Band Edge																																																																																							
	2400-2483.5_802.11g_CH02_2417MHz																																																																																							
ANT	SISO																																																																																							
Pol.	Horizontal						Fundamental																																																																																	
Peak																																																																																								
	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>2389.69</td><td>65.33</td><td>74.00</td><td>-8.67</td><td>63.79</td><td>30.44</td><td>4.80</td><td>33.70</td><td>100</td><td>76 PEAK</td></tr></table>							Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	2389.69	65.33	74.00	-8.67	63.79	30.44	4.80	33.70	100	76 PEAK	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>2417.00</td><td>108.16</td><td>-----</td><td>-----</td><td>106.53</td><td>30.45</td><td>4.83</td><td>33.65</td><td>100</td><td>76 PEAK</td></tr></table>						Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	2417.00	108.16	-----	-----	106.53	30.45	4.83	33.65	100
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																	
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																																																															
1	2389.69	65.33	74.00	-8.67	63.79	30.44	4.80	33.70	100	76 PEAK																																																																														
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																	
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																																																															
1	2417.00	108.16	-----	-----	106.53	30.45	4.83	33.65	100	76 PEAK																																																																														
Avg																																																																																								
	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>2389.82</td><td>49.97</td><td>54.00</td><td>-4.03</td><td>48.43</td><td>30.44</td><td>4.80</td><td>33.70</td><td>100</td><td>76 AVERAGE</td></tr></table>							Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	2389.82	49.97	54.00	-4.03	48.43	30.44	4.80	33.70	100	76 AVERAGE	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>2417.00</td><td>101.60</td><td>-----</td><td>-----</td><td>99.97</td><td>30.45</td><td>4.83</td><td>33.65</td><td>100</td><td>76 AVERAGE</td></tr></table>						Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	2417.00	101.60	-----	-----	99.97	30.45	4.83	33.65	100
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																	
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																																																															
1	2389.82	49.97	54.00	-4.03	48.43	30.44	4.80	33.70	100	76 AVERAGE																																																																														
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																	
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																																																															
1	2417.00	101.60	-----	-----	99.97	30.45	4.83	33.65	100	76 AVERAGE																																																																														







		13																																																																																								
Mode		Band Edge																																																																																								
		2400-2483.5_802.11g_CH02_2417MHz																																																																																								
ANT		SISO																																																																																								
Pol.		Vertical					Fundamental																																																																																			
Peak	 Level (dBuV/m) Date: 2025-01-07 130 113.8 97.5 81.3 65.0 48.8 32.5 16.3 0 2310 2336 2362 2388 2414 2440 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>2389.30</td><td>53.06</td><td>74.00</td><td>-20.94</td><td>51.54</td><td>30.44</td><td>4.79</td><td>33.71</td><td>347</td><td>360</td><td>PEAK</td></tr></tbody></table>						Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor			MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	2389.30	53.06	74.00	-20.94	51.54	30.44	4.79	33.71	347	360	PEAK	 Level (dBuV/m) Date: 2025-01-07 130 113.8 97.5 81.3 65.0 48.8 32.5 16.3 0 1000 1400 1800 2200 2600 3000 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>2417.00</td><td>97.97</td><td>-----</td><td>-----</td><td>96.36</td><td>30.45</td><td>4.82</td><td>33.66</td><td>347</td><td>360</td><td>PEAK_74</td></tr></tbody></table>						Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor			MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	2417.00	97.97	-----	-----	96.36	30.45	4.82	33.66	347	360	PEAK_74
		Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																	
Freq	Level	Line	Margin	Level	Factor	Loss	Factor																																																																																			
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																																																																	
1	2389.30	53.06	74.00	-20.94	51.54	30.44	4.79	33.71	347	360	PEAK																																																																															
	Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																		
Freq	Level	Line	Margin	Level	Factor	Loss	Factor																																																																																			
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																																																																	
1	2417.00	97.97	-----	-----	96.36	30.45	4.82	33.66	347	360	PEAK_74																																																																															
Avg	 Level (dBuV/m) Date: 2025-01-07 130 113.8 97.5 81.3 65.0 48.8 32.5 16.3 0 2310 2336 2362 2388 2414 2440 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>2389.95</td><td>42.14</td><td>54.00</td><td>-11.86</td><td>40.60</td><td>30.44</td><td>4.80</td><td>33.70</td><td>347</td><td>360</td><td>AVERAGE</td></tr></tbody></table>						Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor			MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	2389.95	42.14	54.00	-11.86	40.60	30.44	4.80	33.70	347	360	AVERAGE	 Level (dBuV/m) Date: 2025-01-07 130 113.8 97.5 81.3 65.0 48.8 32.5 16.3 0 1000 1400 1800 2200 2600 3000 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>2417.00</td><td>90.88</td><td>-----</td><td>-----</td><td>89.27</td><td>30.45</td><td>4.82</td><td>33.66</td><td>347</td><td>360</td><td>AVERAGE</td></tr></tbody></table>						Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor			MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	2417.00	90.88	-----	-----	89.27	30.45	4.82	33.66	347	360	AVERAGE
		Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																	
Freq	Level	Line	Margin	Level	Factor	Loss	Factor																																																																																			
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																																																																	
1	2389.95	42.14	54.00	-11.86	40.60	30.44	4.80	33.70	347	360	AVERAGE																																																																															
	Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																		
Freq	Level	Line	Margin	Level	Factor	Loss	Factor																																																																																			
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																																																																	
1	2417.00	90.88	-----	-----	89.27	30.45	4.82	33.66	347	360	AVERAGE																																																																															







Mode	14																																																																																											
	Band Edge																																																																																											
	2400-2483.5_802.11g_CH10_2457MHz																																																																																											
ANT	SISO																																																																																											
Pol.	Horizontal						Fundamental																																																																																					
Peak	Level (dBuV/m) Date: 2025-01-07  PEAK_BE_74 130 113.8 97.5 81.3 65.0 48.8 32.5 16.3 0 24572465.62474.22482.82491.42500 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>2484.31</td><td>62.64</td><td>74.00</td><td>-11.36</td><td>60.76</td><td>30.49</td><td>4.92</td><td>33.53</td><td>300</td><td>75</td><td>PEAK</td></tr></tbody></table>							Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	2484.31	62.64	74.00	-11.36	60.76	30.49	4.92	33.53	300	75	PEAK	Level (dBuV/m) Date: 2025-01-07  PEAK_74 130 113.8 97.5 81.3 65.0 48.8 32.5 16.3 0 100014001800220026003000 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>2457.00</td><td>113.27</td><td>-----</td><td>-----</td><td>111.49</td><td>30.48</td><td>4.88</td><td>33.58</td><td>300</td><td>75</td><td>PEAK</td></tr></tbody></table>							Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	2457.00	113.27	-----	-----	111.49	30.48	4.88	33.58	300	75	PEAK
		Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																				
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																				
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																																																																			
1	2484.31	62.64	74.00	-11.36	60.76	30.49	4.92	33.53	300	75	PEAK																																																																																	
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																					
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																				
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																																																																			
1	2457.00	113.27	-----	-----	111.49	30.48	4.88	33.58	300	75	PEAK																																																																																	
Avg	Level (dBuV/m) Date: 2025-01-07  AVG_BE_54 130 113.8 97.5 81.3 65.0 48.8 32.5 16.3 0 24572465.62474.22482.82491.42500 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>2483.62</td><td>48.68</td><td>54.00</td><td>-5.32</td><td>46.80</td><td>30.49</td><td>4.92</td><td>33.53</td><td>300</td><td>75</td><td>AVERAGE</td></tr></tbody></table>							Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	2483.62	48.68	54.00	-5.32	46.80	30.49	4.92	33.53	300	75	AVERAGE	Level (dBuV/m) Date: 2025-01-07  AVG_54 130 113.8 97.5 81.3 65.0 48.8 32.5 16.3 0 100014001800220026003000 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>2457.00</td><td>100.12</td><td>-----</td><td>-----</td><td>98.36</td><td>30.47</td><td>4.88</td><td>33.59</td><td>300</td><td>75</td><td>AVERAGE</td></tr></tbody></table>							Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	2457.00	100.12	-----	-----	98.36	30.47	4.88	33.59	300	75	AVERAGE
		Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																				
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																				
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																																																																			
1	2483.62	48.68	54.00	-5.32	46.80	30.49	4.92	33.53	300	75	AVERAGE																																																																																	
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																					
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																				
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																																																																			
1	2457.00	100.12	-----	-----	98.36	30.47	4.88	33.59	300	75	AVERAGE																																																																																	



Mode	14																																																																																								
	Band Edge																																																																																								
	2400-2483.5_802.11g_CH10_2457MHz																																																																																								
ANT	SISO																																																																																								
Pol.	Vertical						Fundamental																																																																																		
Peak																																																																																									
	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th></th></tr><tr><td>1</td><td>2484.82</td><td>62.97</td><td>74.00</td><td>-11.03</td><td>61.09</td><td>30.49</td><td>4.92</td><td>33.53</td><td>400</td><td>142</td><td>PEAK</td></tr></table>							Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB		1	2484.82	62.97	74.00	-11.03	61.09	30.49	4.92	33.53	400	142	PEAK	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th></th></tr><tr><td>1</td><td>2457.00</td><td>101.52</td><td>-----</td><td>-----</td><td>99.77</td><td>30.47</td><td>4.87</td><td>33.59</td><td>400</td><td>142</td><td>PEAK</td></tr></table>							Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB		1	2457.00	101.52	-----	-----	99.77	30.47	4.87	33.59	400	142
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																		
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																	
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB																																																																																		
1	2484.82	62.97	74.00	-11.03	61.09	30.49	4.92	33.53	400	142	PEAK																																																																														
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																		
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																	
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB																																																																																		
1	2457.00	101.52	-----	-----	99.77	30.47	4.87	33.59	400	142	PEAK																																																																														
Avg																																																																																									
	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th></th></tr><tr><td>1</td><td>2483.96</td><td>47.53</td><td>54.00</td><td>-6.47</td><td>45.65</td><td>30.49</td><td>4.92</td><td>33.53</td><td>400</td><td>142</td><td>AVERAGE</td></tr></table>							Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB		1	2483.96	47.53	54.00	-6.47	45.65	30.49	4.92	33.53	400	142	AVERAGE	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th></th></tr><tr><td>1</td><td>2457.00</td><td>94.13</td><td>-----</td><td>-----</td><td>92.37</td><td>30.47</td><td>4.88</td><td>33.59</td><td>400</td><td>142</td><td>AVERAGE</td></tr></table>							Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB		1	2457.00	94.13	-----	-----	92.37	30.47	4.88	33.59	400	142
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																		
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																	
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB																																																																																		
1	2483.96	47.53	54.00	-6.47	45.65	30.49	4.92	33.53	400	142	AVERAGE																																																																														
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																		
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																	
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB																																																																																		
1	2457.00	94.13	-----	-----	92.37	30.47	4.88	33.59	400	142	AVERAGE																																																																														



		15																																																																																						
Mode		Band Edge																																																																																						
		2400-2483.5_802.11n HT20_CH2_2417MHz																																																																																						
ANT		SISO																																																																																						
Pol.		Horizontal					Fundamental																																																																																	
Peak	 Level (dBuV/m) Date: 2025-01-07 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>2388.00</td><td>61.90</td><td>74.00</td><td>-12.10</td><td>60.39</td><td>30.43</td><td>4.79</td><td>33.71</td><td>100</td><td>72 PEAK</td></tr></tbody></table>						Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	2388.00	61.90	74.00	-12.10	60.39	30.43	4.79	33.71	100	72 PEAK	 Level (dBuV/m) Date: 2025-01-07 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>2417.00</td><td>107.12</td><td>-----</td><td>-----</td><td>105.49</td><td>30.45</td><td>4.83</td><td>33.65</td><td>100</td><td>72 PEAK</td></tr></tbody></table>						Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	2417.00	107.12	-----	-----	105.49	30.45	4.83	33.65	100	72 PEAK
		Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																															
Freq	Level	Line	Margin	Level	Factor	Loss	Factor																																																																																	
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																															
1	2388.00	61.90	74.00	-12.10	60.39	30.43	4.79	33.71	100	72 PEAK																																																																														
	Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																
Freq	Level	Line	Margin	Level	Factor	Loss	Factor																																																																																	
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																															
1	2417.00	107.12	-----	-----	105.49	30.45	4.83	33.65	100	72 PEAK																																																																														
Avg	 Level (dBuV/m) Date: 2025-01-07 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>2388.78</td><td>48.26</td><td>54.00</td><td>-5.74</td><td>46.75</td><td>30.43</td><td>4.79</td><td>33.71</td><td>100</td><td>72 AVERAGE</td></tr></tbody></table>						Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	2388.78	48.26	54.00	-5.74	46.75	30.43	4.79	33.71	100	72 AVERAGE	 Level (dBuV/m) Date: 2025-01-07 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>2417.00</td><td>99.74</td><td>-----</td><td>-----</td><td>98.11</td><td>30.45</td><td>4.83</td><td>33.65</td><td>100</td><td>72 AVERAGE</td></tr></tbody></table>						Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	2417.00	99.74	-----	-----	98.11	30.45	4.83	33.65	100	72 AVERAGE
		Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																															
Freq	Level	Line	Margin	Level	Factor	Loss	Factor																																																																																	
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																															
1	2388.78	48.26	54.00	-5.74	46.75	30.43	4.79	33.71	100	72 AVERAGE																																																																														
	Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																
Freq	Level	Line	Margin	Level	Factor	Loss	Factor																																																																																	
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																															
1	2417.00	99.74	-----	-----	98.11	30.45	4.83	33.65	100	72 AVERAGE																																																																														







Mode	15																																																																															
	Band Edge																																																																															
	2400-2483.5_802.11n HT20_CH2_2417MHz																																																																															
ANT	SISO																																																																															
Pol.	Vertical	Fundamental																																																																														
Peak	Level (dBuV/m) Date: 2025-01-07 Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>2383.45</td><td>53.42</td><td>74.00</td><td>-20.58</td><td>51.92</td><td>30.43</td><td>4.79</td><td>33.72</td><td>241</td><td>0° PEAK</td></tr></table>		Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor			MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	2383.45	53.42	74.00	-20.58	51.92	30.43	4.79	33.72	241	0° PEAK	Level (dBuV/m) Date: 2025-01-07 Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>2417.00</td><td>94.29</td><td>-----</td><td>-----</td><td>92.68</td><td>30.45</td><td>4.82</td><td>33.66</td><td>241</td><td>0° PEAK</td></tr></table>		Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor			MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	2417.00	94.29	-----	-----	92.68	30.45	4.82	33.66	241	0° PEAK
		Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																							
Freq	Level	Line	Margin	Level	Factor	Loss	Factor																																																																									
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																																																							
1	2383.45	53.42	74.00	-20.58	51.92	30.43	4.79	33.72	241	0° PEAK																																																																						
	Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																								
Freq	Level	Line	Margin	Level	Factor	Loss	Factor																																																																									
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																																																							
1	2417.00	94.29	-----	-----	92.68	30.45	4.82	33.66	241	0° PEAK																																																																						
Avg	Level (dBuV/m) Date: 2025-01-07 Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>2389.56</td><td>40.57</td><td>54.00</td><td>-13.43</td><td>39.03</td><td>30.44</td><td>4.80</td><td>33.70</td><td>241</td><td>0° AVERAGE</td></tr></table>		Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor			MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	2389.56	40.57	54.00	-13.43	39.03	30.44	4.80	33.70	241	0° AVERAGE	Level (dBuV/m) Date: 2025-01-07 Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>2417.00</td><td>87.52</td><td>-----</td><td>-----</td><td>85.91</td><td>30.45</td><td>4.82</td><td>33.66</td><td>241</td><td>0° AVERAGE</td></tr></table>		Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor			MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	2417.00	87.52	-----	-----	85.91	30.45	4.82	33.66	241	0° AVERAGE
	Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																								
Freq	Level	Line	Margin	Level	Factor	Loss	Factor																																																																									
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																																																							
1	2389.56	40.57	54.00	-13.43	39.03	30.44	4.80	33.70	241	0° AVERAGE																																																																						
	Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																								
Freq	Level	Line	Margin	Level	Factor	Loss	Factor																																																																									
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																																																							
1	2417.00	87.52	-----	-----	85.91	30.45	4.82	33.66	241	0° AVERAGE																																																																						



Mode	16																																																																															
	Band Edge																																																																															
	2400-2483.5_802.11n HT20_CH10_2457MHz																																																																															
ANT	SISO																																																																															
Pol.	Horizontal	Fundamental																																																																														
Peak	Level (dBuV/m) Date: 2025-01-07 113.8 97.5 81.3 65.0 48.8 32.5 16.3 0 2457 2465.6 2474.2 2482.8 2491.4 2500 Frequency (MHz) PEAK_BE_74 <table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>2483.66</td><td>65.74</td><td>74.00</td><td>-8.26</td><td>63.86</td><td>30.49</td><td>4.92</td><td>33.53</td><td>166</td><td>79 PEAK</td></tr></tbody></table>		Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	2483.66	65.74	74.00	-8.26	63.86	30.49	4.92	33.53	166	79 PEAK	Level (dBuV/m) Date: 2025-01-07 113.8 97.5 81.3 65.0 48.8 32.5 16.3 0 1000 1400 1800 2200 2600 3000 Frequency (MHz) PEAK_74 <table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>2457.00</td><td>107.74</td><td>-----</td><td>-----</td><td>105.98</td><td>30.47</td><td>4.88</td><td>33.59</td><td>166</td><td>79 PEAK</td></tr></tbody></table>		Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	2457.00	107.74	-----	-----	105.98	30.47	4.88	33.59	166	79 PEAK
		Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																								
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																								
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																																																							
1	2483.66	65.74	74.00	-8.26	63.86	30.49	4.92	33.53	166	79 PEAK																																																																						
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																									
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																								
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																																																							
1	2457.00	107.74	-----	-----	105.98	30.47	4.88	33.59	166	79 PEAK																																																																						
Avg	Level (dBuV/m) Date: 2025-01-07 113.8 97.5 81.3 65.0 48.8 32.5 16.3 0 2457 2465.6 2474.2 2482.8 2491.4 2500 Frequency (MHz) AVG_BE_54 <table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>2483.83</td><td>48.46</td><td>54.00</td><td>-5.54</td><td>46.58</td><td>30.49</td><td>4.92</td><td>33.53</td><td>166</td><td>79 AVERAGE</td></tr></tbody></table>		Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	2483.83	48.46	54.00	-5.54	46.58	30.49	4.92	33.53	166	79 AVERAGE	Level (dBuV/m) Date: 2025-01-07 113.8 97.5 81.3 65.0 48.8 32.5 16.3 0 1000 1400 1800 2200 2600 3000 Frequency (MHz) AVG_54 <table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>2457.00</td><td>100.00</td><td>-----</td><td>-----</td><td>98.22</td><td>30.48</td><td>4.88</td><td>33.58</td><td>166</td><td>79 AVERAGE</td></tr></tbody></table>		Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	2457.00	100.00	-----	-----	98.22	30.48	4.88	33.58	166	79 AVERAGE
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																									
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																								
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																																																							
1	2483.83	48.46	54.00	-5.54	46.58	30.49	4.92	33.53	166	79 AVERAGE																																																																						
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																									
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																								
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																																																							
1	2457.00	100.00	-----	-----	98.22	30.48	4.88	33.58	166	79 AVERAGE																																																																						



		16																																																																																								
Mode		Band Edge																																																																																								
		2400-2483.5_802.11n HT20_CH10_2457MHz																																																																																								
ANT		SISO																																																																																								
Pol.		Vertical					Fundamental																																																																																			
Peak	Level (dBuV/m) Date: 2025-01-07  PEAK_BE_74 113.8 97.5 81.3 65.0 48.8 32.5 16.3 0 2457 2465.6 2474.2 2482.8 2491.4 2500 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>2484.00</td><td>61.13</td><td>74.00</td><td>-12.87</td><td>59.25</td><td>30.49</td><td>4.92</td><td>33.53</td><td>330</td><td>360</td><td>PEAK</td></tr></tbody></table> Level (dBuV/m) Date: 2025-01-07  PEAK_74 113.8 97.5 81.3 65.0 48.8 32.5 16.3 0 1000 1400 1800 2200 2600 3000 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>2457.00</td><td>101.66</td><td>-----</td><td>-----</td><td>99.88</td><td>30.48</td><td>4.88</td><td>33.58</td><td>330</td><td>360</td><td>PEAK</td></tr></tbody></table>											Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	2484.00	61.13	74.00	-12.87	59.25	30.49	4.92	33.53	330	360	PEAK		Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	2457.00	101.66	-----	-----	99.88	30.48	4.88	33.58	330	360	PEAK
		Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																		
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																		
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																																																																	
1	2484.00	61.13	74.00	-12.87	59.25	30.49	4.92	33.53	330	360	PEAK																																																																															
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																			
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																		
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																																																																	
1	2457.00	101.66	-----	-----	99.88	30.48	4.88	33.58	330	360	PEAK																																																																															
Avg	Level (dBuV/m) Date: 2025-01-07  AVG_BE_54 113.8 97.5 81.3 65.0 48.8 32.5 16.3 0 2457 2465.6 2474.2 2482.8 2491.4 2500 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>2483.66</td><td>45.01</td><td>54.00</td><td>-8.99</td><td>43.13</td><td>30.49</td><td>4.92</td><td>33.53</td><td>330</td><td>360</td><td>AVERAGE</td></tr></tbody></table> Level (dBuV/m) Date: 2025-01-07  AVG_54 113.8 97.5 81.3 65.0 48.8 32.5 16.3 0 1000 1400 1800 2200 2600 3000 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>2457.00</td><td>94.34</td><td>-----</td><td>-----</td><td>92.56</td><td>30.48</td><td>4.88</td><td>33.58</td><td>330</td><td>360</td><td>AVERAGE</td></tr></tbody></table>											Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	2483.66	45.01	54.00	-8.99	43.13	30.49	4.92	33.53	330	360	AVERAGE		Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	2457.00	94.34	-----	-----	92.56	30.48	4.88	33.58	330	360	AVERAGE
		Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																		
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																		
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																																																																	
1	2483.66	45.01	54.00	-8.99	43.13	30.49	4.92	33.53	330	360	AVERAGE																																																																															
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																			
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																		
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																																																																	
1	2457.00	94.34	-----	-----	92.56	30.48	4.88	33.58	330	360	AVERAGE																																																																															



Mode	17																																																																																								
	Band Edge - L																																																																																								
	2400-2483.5_802.11n HT40_CH06_2437MHz																																																																																								
ANT	SISO																																																																																								
Pol.	Horizontal						Fundamental																																																																																		
Peak	Level (dBuV/m) Date: 2025-01-08 Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>2389.12</td><td>67.16</td><td>74.00</td><td>-6.84</td><td>65.65</td><td>30.43</td><td>4.79</td><td>33.71</td><td>100</td><td>77 PEAK</td></tr></table>							Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	2389.12	67.16	74.00	-6.84	65.65	30.43	4.79	33.71	100	77 PEAK	Level (dBuV/m) Date: 2025-01-08 Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>2437.00</td><td>102.29</td><td>-----</td><td>-----</td><td>100.59</td><td>30.46</td><td>4.86</td><td>33.62</td><td>100</td><td>77 PEAK</td></tr></table>						Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	2437.00	102.29	-----	-----	100.59	30.46	4.86	33.62	100	77 PEAK
		Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																	
	Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																																																																
1	2389.12	67.16	74.00	-6.84	65.65	30.43	4.79	33.71	100	77 PEAK																																																																															
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																		
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																	
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																																																																
1	2437.00	102.29	-----	-----	100.59	30.46	4.86	33.62	100	77 PEAK																																																																															
Avg	Level (dBuV/m) Date: 2025-01-08 Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>2389.88</td><td>50.31</td><td>54.00</td><td>-3.69</td><td>48.77</td><td>30.44</td><td>4.80</td><td>33.70</td><td>100</td><td>77 AVERAGE</td></tr></table>							Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	2389.88	50.31	54.00	-3.69	48.77	30.44	4.80	33.70	100	77 AVERAGE	Level (dBuV/m) Date: 2025-01-08 Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>2437.00</td><td>93.78</td><td>-----</td><td>-----</td><td>92.04</td><td>30.47</td><td>4.87</td><td>33.60</td><td>100</td><td>77 AVERAGE</td></tr></table>						Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	2437.00	93.78	-----	-----	92.04	30.47	4.87	33.60	100	77 AVERAGE
		Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																	
	Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																																																																
1	2389.88	50.31	54.00	-3.69	48.77	30.44	4.80	33.70	100	77 AVERAGE																																																																															
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																		
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																	
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																																																																
1	2437.00	93.78	-----	-----	92.04	30.47	4.87	33.60	100	77 AVERAGE																																																																															




Mode	17																																																																																											
	Band Edge - L																																																																																											
	2400-2483.5_802.11n HT40_CH06_2437MHz																																																																																											
ANT	SISO																																																																																											
Pol.	Vertical						Fundamental																																																																																					
Peak	Level (dBuV/m) Date: 2025-01-08 130 113.8 97.5 81.3 65.0 48.8 32.5 16.3 0 2310 2335.4 2360.8 2386.2 2411.6 2437 Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>2389.76</td><td>57.86</td><td>74.00</td><td>-16.14</td><td>56.32</td><td>30.44</td><td>4.80</td><td>33.70</td><td>359</td><td>360</td><td>PEAK</td></tr></table>							Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor			MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	2389.76	57.86	74.00	-16.14	56.32	30.44	4.80	33.70	359	360	PEAK	Level (dBuV/m) Date: 2025-01-08 130 113.8 97.5 81.3 65.0 48.8 32.5 16.3 0 1000 1400 1800 2200 2600 3000 Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>2437.00</td><td>92.49</td><td>-----</td><td>-----</td><td>90.76</td><td>30.47</td><td>4.87</td><td>33.61</td><td>359</td><td>360</td><td>PEAK</td></tr></table>							Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor			MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	2437.00	92.49	-----	-----	90.76	30.47	4.87	33.61	359	360	PEAK
		Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																			
Freq	Level	Line	Margin	Level	Factor	Loss	Factor																																																																																					
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																																																																			
1	2389.76	57.86	74.00	-16.14	56.32	30.44	4.80	33.70	359	360	PEAK																																																																																	
	Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																				
Freq	Level	Line	Margin	Level	Factor	Loss	Factor																																																																																					
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																																																																			
1	2437.00	92.49	-----	-----	90.76	30.47	4.87	33.61	359	360	PEAK																																																																																	
Avg	Level (dBuV/m) Date: 2025-01-08 130 113.8 97.5 81.3 65.0 48.8 32.5 16.3 0 2310 2335.4 2360.8 2386.2 2411.6 2437 Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>2389.88</td><td>44.46</td><td>54.00</td><td>-9.54</td><td>42.92</td><td>30.44</td><td>4.80</td><td>33.70</td><td>359</td><td>360</td><td>AVERAGE</td></tr></table>							Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor			MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	2389.88	44.46	54.00	-9.54	42.92	30.44	4.80	33.70	359	360	AVERAGE	Level (dBuV/m) Date: 2025-01-08 130 113.8 97.5 81.3 65.0 48.8 32.5 16.3 0 1000 1400 1800 2200 2600 3000 Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>2437.00</td><td>84.69</td><td>-----</td><td>-----</td><td>82.97</td><td>30.47</td><td>4.86</td><td>33.61</td><td>359</td><td>360</td><td>AVERAGE</td></tr></table>							Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor			MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	2437.00	84.69	-----	-----	82.97	30.47	4.86	33.61	359	360	AVERAGE
		Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																			
Freq	Level	Line	Margin	Level	Factor	Loss	Factor																																																																																					
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																																																																			
1	2389.88	44.46	54.00	-9.54	42.92	30.44	4.80	33.70	359	360	AVERAGE																																																																																	
	Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																				
Freq	Level	Line	Margin	Level	Factor	Loss	Factor																																																																																					
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																																																																			
1	2437.00	84.69	-----	-----	82.97	30.47	4.86	33.61	359	360	AVERAGE																																																																																	


Appendix D. Duty Cycle Plots

Band	Duty Cycle(%)	T(ms)	1/T(kHz)	VBW Setting
802.11b	100	-	-	10Hz
802.11g	100	-	-	10Hz
802.11n HT20	100	-	-	10Hz
802.11n HT40	99.63	-	-	10Hz


802.11b



802.11g



802.11n HT20



802.11n HT40

