



Appendix E

RF Test Data for 5.8GWIFI (Conducted Measurement)

Product Name: All in one pc

Test Model: XPS24M

Environmental Conditions

Temperature:	23.8° C
Relative Humidity:	52.1%
ATM Pressure:	100.0 kPa
Test Engineer:	Joker Hu
Supervised by:	Nick Peng



Shenzhen LCS Compliance Testing Laboratory Ltd.
Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China
Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com
Scan code to check authenticity



E.1 -6dB Bandwidth

Condition	Mode	Frequency (MHz)	Antenna	-6 dB Bandwidth (MHz)	Limit -6 dB Bandwidth (MHz)	Verdict
NVNT	a	5745	Ant0	14.841	≥ 0.5	Pass
NVNT	a	5785	Ant0	15.527	≥ 0.5	Pass
NVNT	a	5825	Ant0	15.471	≥ 0.5	Pass
NVNT	n20	5745	Ant0	13.825	≥ 0.5	Pass
NVNT	n20	5785	Ant0	14.385	≥ 0.5	Pass
NVNT	n20	5825	Ant0	15.005	≥ 0.5	Pass
NVNT	n40	5755	Ant0	35.078	≥ 0.5	Pass
NVNT	n40	5795	Ant0	34.965	≥ 0.5	Pass
NVNT	ac20	5745	Ant0	15.055	≥ 0.5	Pass
NVNT	ac20	5785	Ant0	15.03	≥ 0.5	Pass
NVNT	ac20	5825	Ant0	15.897	≥ 0.5	Pass
NVNT	ac40	5755	Ant0	35.011	≥ 0.5	Pass
NVNT	ac40	5795	Ant0	35.004	≥ 0.5	Pass
NVNT	ac80	5775	Ant0	75.055	≥ 0.5	Pass




Shenzhen LCS Compliance Testing Laboratory Ltd.
Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China
Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com
Scan code to check authenticity




Test Graphs

-6dB Bandwidth NVNT a 5745MHz Ant0



-6dB Bandwidth NVNT a 5785MHz Ant0



Shenzhen LCS Compliance Testing Laboratory Ltd.


Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com


Scan code to check authenticity



-6dB Bandwidth NVNT a 5825MHz Ant0



-6dB Bandwidth NVNT n20 5745MHz Ant0



Shenzhen LCS Compliance Testing Laboratory Ltd.


Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com


Scan code to check authenticity



-6dB Bandwidth NVNT n20 5785MHz Ant0




-6dB Bandwidth NVNT n20 5825MHz Ant0






-6dB Bandwidth NVNT n40 5755MHz Ant0



-6dB Bandwidth NVNT n40 5795MHz Ant0



Shenzhen LCS Compliance Testing Laboratory Ltd.


Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com


Scan code to check authenticity



-6dB Bandwidth NVNT ac20 5745MHz Ant0



-6dB Bandwidth NVNT ac20 5785MHz Ant0



Shenzhen LCS Compliance Testing Laboratory Ltd.


Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com


Scan code to check authenticity



-6dB Bandwidth NVNT ac20 5825MHz Ant0



-6dB Bandwidth NVNT ac40 5755MHz Ant0



Shenzhen LCS Compliance Testing Laboratory Ltd.


Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com


Scan code to check authenticity



-6dB Bandwidth NVNT ac40 5795MHz Ant0



-6dB Bandwidth NVNT ac80 5775MHz Ant0





Condition	Mode	Frequency (MHz)	Antenna	-6 dB Bandwidth (MHz)	Limit -6 dB Bandwidth (MHz)	Verdict
NVNT	a	5745	Ant1	14.187	≥ 0.5	Pass
NVNT	a	5785	Ant1	15.414	≥ 0.5	Pass
NVNT	a	5825	Ant1	14.644	≥ 0.5	Pass
NVNT	n20	5745	Ant1	15.047	≥ 0.5	Pass
NVNT	n20	5785	Ant1	13.435	≥ 0.5	Pass
NVNT	n20	5825	Ant1	15.03	≥ 0.5	Pass
NVNT	n40	5755	Ant1	35.062	≥ 0.5	Pass
NVNT	n40	5795	Ant1	33.87	≥ 0.5	Pass
NVNT	ac20	5745	Ant1	13.796	≥ 0.5	Pass
NVNT	ac20	5785	Ant1	15.021	≥ 0.5	Pass
NVNT	ac20	5825	Ant1	14.202	≥ 0.5	Pass
NVNT	ac40	5755	Ant1	33.868	≥ 0.5	Pass
NVNT	ac40	5795	Ant1	35.038	≥ 0.5	Pass
NVNT	ac80	5775	Ant1	75.088	≥ 0.5	Pass




Shenzhen LCS Compliance Testing Laboratory Ltd.
Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China
Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com
Scan code to check authenticity




Test Graphs

-6dB Bandwidth NVNT a 5745MHz Ant1



-6dB Bandwidth NVNT a 5785MHz Ant1



Shenzhen LCS Compliance Testing Laboratory Ltd.


Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com


Scan code to check authenticity



-6dB Bandwidth NVNT a 5825MHz Ant1



-6dB Bandwidth NVNT n20 5745MHz Ant1



Shenzhen LCS Compliance Testing Laboratory Ltd.


Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com


Scan code to check authenticity



-6dB Bandwidth NVNT n20 5785MHz Ant1



-6dB Bandwidth NVNT n20 5825MHz Ant1



Shenzhen LCS Compliance Testing Laboratory Ltd.


Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com


Scan code to check authenticity



-6dB Bandwidth NVNT n40 5755MHz Ant1



-6dB Bandwidth NVNT n40 5795MHz Ant1



Shenzhen LCS Compliance Testing Laboratory Ltd.


Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com


Scan code to check authenticity



-6dB Bandwidth NVNT ac20 5745MHz Ant1



-6dB Bandwidth NVNT ac20 5785MHz Ant1



Shenzhen LCS Compliance Testing Laboratory Ltd.


Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com


Scan code to check authenticity



-6dB Bandwidth NVNT ac20 5825MHz Ant1




-6dB Bandwidth NVNT ac40 5755MHz Ant1






-6dB Bandwidth NVNT ac40 5795MHz Ant1



-6dB Bandwidth NVNT ac80 5775MHz Ant1



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



E.2 Maximum Conducted Output Power

Condition	Mode	Frequency (MHz)	Antenna	Conducted Power (dBm)	Duty Factor (dB)	Total Power (dBm)	Limit (dBm)	Verdict
NVNT	a	5745	Ant0	12.56	0.13	12.69	30	Pass
NVNT	a	5785	Ant0	12.78	0.13	12.91	30	Pass
NVNT	a	5825	Ant0	12.48	0.13	12.61	30	Pass
NVNT	n20	5745	Ant0	12.5	0.14	12.64	30	Pass
NVNT	n20	5785	Ant0	12.49	0.14	12.63	30	Pass
NVNT	n20	5825	Ant0	12.3	0.14	12.44	30	Pass
NVNT	n40	5755	Ant0	11.23	0.29	11.52	30	Pass
NVNT	n40	5795	Ant0	11.26	0.29	11.55	30	Pass
NVNT	ac20	5745	Ant0	12.54	0.14	12.68	30	Pass
NVNT	ac20	5785	Ant0	12.46	0.14	12.6	30	Pass
NVNT	ac20	5825	Ant0	12.81	0.14	12.95	30	Pass
NVNT	ac40	5755	Ant0	11.21	0.28	11.49	30	Pass
NVNT	ac40	5795	Ant0	10.96	0.28	11.24	30	Pass
NVNT	ac80	5775	Ant0	10.61	0.55	11.16	30	Pass

Condition	Mode	Frequency (MHz)	Antenna	Conducted Power (dBm)	Duty Factor (dB)	Total Power (dBm)	Limit (dBm)	Verdict
NVNT	a	5745	Ant1	10.65	0.13	10.78	30	Pass
NVNT	a	5785	Ant1	10.7	0.13	10.83	30	Pass
NVNT	a	5825	Ant1	10.91	0.13	11.04	30	Pass
NVNT	n20	5745	Ant1	10.53	0.14	10.67	30	Pass
NVNT	n20	5785	Ant1	10.65	0.15	10.8	30	Pass
NVNT	n20	5825	Ant1	10.66	0.14	10.8	30	Pass
NVNT	n40	5755	Ant1	10.17	0.29	10.46	30	Pass
NVNT	n40	5795	Ant1	10.3	0.28	10.58	30	Pass
NVNT	ac20	5745	Ant1	10.43	0.14	10.57	30	Pass
NVNT	ac20	5785	Ant1	10.55	0.14	10.69	30	Pass
NVNT	ac20	5825	Ant1	10.9	0.14	11.04	30	Pass
NVNT	ac40	5755	Ant1	10.15	0.28	10.43	30	Pass
NVNT	ac40	5795	Ant1	10.37	0.28	10.65	30	Pass
NVNT	ac80	5775	Ant1	9.72	0.55	10.27	30	Pass





MIMO

Condition	Mode	Frequency (MHz)	Total Power (dBm)			Limit (dBm)	Verdict
			Ant0	Ant1	Ant0+Ant1		
NVNT	n20	5745	12.64	10.67	14.78	30	Pass
NVNT	n20	5785	12.63	10.8	14.82	30	Pass
NVNT	n20	5825	12.44	10.8	14.71	30	Pass
NVNT	n40	5755	11.52	10.46	14.03	30	Pass
NVNT	n40	5795	11.55	10.58	14.10	30	Pass
NVNT	ac20	5745	12.68	10.57	14.76	30	Pass
NVNT	ac20	5785	12.6	10.69	14.76	30	Pass
NVNT	ac20	5825	12.95	11.04	15.11	30	Pass
NVNT	ac40	5755	11.49	10.43	14.00	30	Pass
NVNT	ac40	5795	11.24	10.65	13.97	30	Pass
NVNT	ac80	5775	11.16	10.27	13.75	30	Pass



Shenzhen LCS Compliance Testing Laboratory Ltd.
Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China
Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com
Scan code to check authenticity



E.3 Maximum Power Spectral Density Level

Condition	Mode	Frequency (MHz)	Antenna	Conducted PSD (dBm/510KHz)	Duty Factor (dB)	Total PSD (dBm/510KHz)	Limit (dBm/510KHz)	Verdict
NVNT	a	5745	Ant0	0.28	0.13	0.41	30	Pass
NVNT	a	5785	Ant0	0.31	0.13	0.44	30	Pass
NVNT	a	5825	Ant0	-0.12	0.13	0.01	30	Pass
NVNT	n20	5745	Ant0	0.1	0.14	0.24	30	Pass
NVNT	n20	5785	Ant0	-0.22	0.14	-0.08	30	Pass
NVNT	n20	5825	Ant0	-0.45	0.14	-0.31	30	Pass
NVNT	n40	5755	Ant0	-4.5	0.29	-4.21	30	Pass
NVNT	n40	5795	Ant0	-4.35	0.29	-4.06	30	Pass
NVNT	ac20	5745	Ant0	-0.18	0.14	-0.04	30	Pass
NVNT	ac20	5785	Ant0	-0.41	0.14	-0.27	30	Pass
NVNT	ac20	5825	Ant0	0.2	0.14	0.34	30	Pass
NVNT	ac40	5755	Ant0	-4.52	0.28	-4.24	30	Pass
NVNT	ac40	5795	Ant0	-4.66	0.28	-4.38	30	Pass
NVNT	ac80	5775	Ant0	-7.78	0.55	-7.23	30	Pass

Condition	Mode	Frequency (MHz)	Antenna	Conducted PSD (dBm/510KHz)	Duty Factor (dB)	Total PSD (dBm/510KHz)	Limit (dBm/510KHz)	Verdict
NVNT	a	5745	Ant1	-1.76	0.13	-1.63	30	Pass
NVNT	a	5785	Ant1	-1.74	0.13	-1.61	30	Pass
NVNT	a	5825	Ant1	-1.49	0.13	-1.36	30	Pass
NVNT	n20	5745	Ant1	-2.13	0.14	-1.99	30	Pass
NVNT	n20	5785	Ant1	-1.72	0.15	-1.57	30	Pass
NVNT	n20	5825	Ant1	-1.83	0.14	-1.69	30	Pass
NVNT	n40	5755	Ant1	-5.63	0.29	-5.34	30	Pass
NVNT	n40	5795	Ant1	-5.51	0.28	-5.23	30	Pass
NVNT	ac20	5745	Ant1	-2.13	0.14	-1.99	30	Pass
NVNT	ac20	5785	Ant1	-2.11	0.14	-1.97	30	Pass
NVNT	ac20	5825	Ant1	-1.88	0.14	-1.74	30	Pass
NVNT	ac40	5755	Ant1	-5.6	0.28	-5.32	30	Pass
NVNT	ac40	5795	Ant1	-5.37	0.28	-5.09	30	Pass
NVNT	ac80	5775	Ant1	-8.8	0.55	-8.25	30	Pass





MIMO

Condition	Mode	Frequency (MHz)	Total PSD (dBm/510KHz)			Limit (dBm/510KHz)	Verdict
			Ant0	Ant1	Ant0+Ant1		
NVNT	n20	5745	0.24	-1.99	2.28	30	Pass
NVNT	n20	5785	-0.08	-1.57	2.25	30	Pass
NVNT	n20	5825	-0.31	-1.69	2.06	30	Pass
NVNT	n40	5755	-4.21	-5.34	-1.73	30	Pass
NVNT	n40	5795	-4.06	-5.23	-1.60	30	Pass
NVNT	ac20	5745	-0.04	-1.99	2.10	30	Pass
NVNT	ac20	5785	-0.27	-1.97	1.97	30	Pass
NVNT	ac20	5825	0.34	-1.74	2.43	30	Pass
NVNT	ac40	5755	-4.24	-5.32	-1.74	30	Pass
NVNT	ac40	5795	-4.38	-5.09	-1.71	30	Pass
NVNT	ac80	5775	-7.23	-8.25	-4.70	30	Pass




Shenzhen LCS Compliance Testing Laboratory Ltd.
Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China
Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com
Scan code to check authenticity




Test Graphs

PSD NVNT a 5745MHz Ant0




PSD NVNT a 5785MHz Ant0










PSD NVNT a 5825MHz Ant0







PSD NVNT n20 5745MHz Ant0



















Test Graphs

PSD NVNT a 5745MHz Ant1




PSD NVNT a 5785MHz Ant1










PSD NVNT a 5825MHz Ant1



PSD NVNT n20 5745MHz Ant1













PSD NVNT ac20 5745MHz Ant1




PSD NVNT ac20 5785MHz Ant1








PSD NVNT ac40 5795MHz Ant1



PSD NVNT ac80 5775MHz Ant1



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



E.4 Restrict Band

Condition	Mode	Frequency (MHz)	Spur Freq (MHz)	Power (dBm)	Gain (dBi)	EIRP Power (dBm)	Detector	Limit (dBm)	Verdict
NVNT	a Ant0	5745	5650	-48.06	2.56	-45.5	Peak	-27	Pass
NVNT	a Ant0	5745	5650	-55.7	2.56	-53.14	Average	-27	Pass
NVNT	a Ant0	5745	5700	-43.76	2.56	-41.2	Peak	10	Pass
NVNT	a Ant0	5745	5700	-52.53	2.56	-49.97	Average	10	Pass
NVNT	a Ant0	5745	5720	-31.2	2.56	-28.64	Peak	15.6	Pass
NVNT	a Ant0	5745	5720	-43.25	2.56	-40.69	Average	15.6	Pass
NVNT	a Ant0	5745	5725	-27.93	2.56	-25.37	Peak	27	Pass
NVNT	a Ant0	5745	5725	-38.76	2.56	-36.2	Average	27	Pass
NVNT	a Ant0	5825	5850	-34.65	2.56	-32.09	Peak	27	Pass
NVNT	a Ant0	5825	5850	-46.75	2.56	-44.19	Average	27	Pass
NVNT	a Ant0	5825	5855	-42.13	2.56	-39.57	Peak	15.6	Pass
NVNT	a Ant0	5825	5855	-49.62	2.56	-47.06	Average	15.6	Pass
NVNT	a Ant0	5825	5875	-46.35	2.56	-43.79	Peak	10	Pass
NVNT	a Ant0	5825	5875	-53.59	2.56	-51.03	Average	10	Pass
NVNT	a Ant0	5825	5925	-47.11	2.56	-44.55	Peak	-27	Pass
NVNT	a Ant0	5825	5925	-54.95	2.56	-52.39	Average	-27	Pass
NVNT	n20 MIMO	5745	5650	-49.49	5.57	-43.92	Peak	-27	Pass
NVNT	n20 MIMO	5745	5650	-55.6	5.57	-50.03	Average	-27	Pass
NVNT	n20 MIMO	5745	5700	-44.95	5.57	-39.38	Peak	10	Pass
NVNT	n20 MIMO	5745	5700	-52.94	5.57	-47.37	Average	10	Pass
NVNT	n20 MIMO	5745	5720	-35.28	5.57	-29.71	Peak	15.6	Pass
NVNT	n20 MIMO	5745	5720	-44.44	5.57	-38.87	Average	15.6	Pass
NVNT	n20 MIMO	5745	5725	-32.61	5.57	-27.04	Peak	27	Pass
NVNT	n20 MIMO	5745	5725	-40.94	5.57	-35.37	Average	27	Pass
NVNT	n20 MIMO	5825	5850	-36.61	5.57	-31.04	Peak	27	Pass
NVNT	n20 MIMO	5825	5850	-47.41	5.57	-41.84	Average	27	Pass
NVNT	n20 MIMO	5825	5855	-37.91	5.57	-32.34	Peak	15.6	Pass
NVNT	n20 MIMO	5825	5855	-49.82	5.57	-44.25	Average	15.6	Pass
NVNT	n20 MIMO	5825	5875	-45.51	5.57	-39.94	Peak	10	Pass
NVNT	n20 MIMO	5825	5875	-53.6	5.57	-48.03	Average	10	Pass
NVNT	n20 MIMO	5825	5925	-46.87	5.57	-41.3	Peak	-27	Pass
NVNT	n20 MIMO	5825	5925	-54.88	5.57	-49.31	Average	-27	Pass
NVNT	n40 MIMO	5755	5650	-48.47	5.57	-42.9	Peak	-27	Pass
NVNT	n40 MIMO	5755	5650	-55.39	5.57	-49.82	Average	-27	Pass
NVNT	n40 MIMO	5755	5700	-41.6	5.57	-36.03	Peak	10	Pass
NVNT	n40 MIMO	5755	5700	-47.53	5.57	-41.96	Average	10	Pass
NVNT	n40 MIMO	5755	5720	-27.73	5.57	-22.16	Peak	15.6	Pass



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



NVNT	n40 MIMO	5755	5720	-37.73	5.57	-32.16	Average	15.6	Pass
NVNT	n40 MIMO	5755	5725	-24.79	5.57	-19.22	Peak	27	Pass
NVNT	n40 MIMO	5755	5725	-35.31	5.57	-29.74	Average	27	Pass
NVNT	n40 MIMO	5795	5850	-35.15	5.57	-29.58	Peak	27	Pass
NVNT	n40 MIMO	5795	5850	-44.38	5.57	-38.81	Average	27	Pass
NVNT	n40 MIMO	5795	5855	-38.61	5.57	-33.04	Peak	15.6	Pass
NVNT	n40 MIMO	5795	5855	-45.96	5.57	-40.39	Average	15.6	Pass
NVNT	n40 MIMO	5795	5875	-42.17	5.57	-36.6	Peak	10	Pass
NVNT	n40 MIMO	5795	5875	-50.82	5.57	-45.25	Average	10	Pass
NVNT	n40 MIMO	5795	5925	-48.57	5.57	-43	Peak	-27	Pass
NVNT	n40 MIMO	5795	5925	-55.02	5.57	-49.45	Average	-27	Pass
NVNT	ac20 MIMO	5745	5650	-49.2	5.57	-43.63	Peak	-27	Pass
NVNT	ac20 MIMO	5745	5650	-55.77	5.57	-50.2	Average	-27	Pass
NVNT	ac20 MIMO	5745	5700	-45.77	5.57	-40.2	Peak	10	Pass
NVNT	ac20 MIMO	5745	5700	-53.43	5.57	-47.86	Average	10	Pass
NVNT	ac20 MIMO	5745	5720	-33.42	5.57	-27.85	Peak	15.6	Pass
NVNT	ac20 MIMO	5745	5720	-46.52	5.57	-40.95	Average	15.6	Pass
NVNT	ac20 MIMO	5745	5725	-32.48	5.57	-26.91	Peak	27	Pass
NVNT	ac20 MIMO	5745	5725	-42.52	5.57	-36.95	Average	27	Pass
NVNT	ac20 MIMO	5825	5850	-29.03	5.57	-23.46	Peak	27	Pass
NVNT	ac20 MIMO	5825	5850	-37.38	5.57	-31.81	Average	27	Pass
NVNT	ac20 MIMO	5825	5855	-31.51	5.57	-25.94	Peak	15.6	Pass
NVNT	ac20 MIMO	5825	5855	-40.78	5.57	-35.21	Average	15.6	Pass
NVNT	ac20 MIMO	5825	5875	-40.42	5.57	-34.85	Peak	10	Pass
NVNT	ac20 MIMO	5825	5875	-50.22	5.57	-44.65	Average	10	Pass
NVNT	ac20 MIMO	5825	5925	-48.37	5.57	-42.8	Peak	-27	Pass
NVNT	ac20 MIMO	5825	5925	-54.69	5.57	-49.12	Average	-27	Pass
NVNT	ac40 MIMO	5755	5650	-45.42	5.57	-39.85	Peak	-27	Pass
NVNT	ac40 MIMO	5755	5650	-55.11	5.57	-49.54	Average	-27	Pass
NVNT	ac40 MIMO	5755	5700	-37.57	5.57	-32	Peak	10	Pass
NVNT	ac40 MIMO	5755	5700	-46.46	5.57	-40.89	Average	10	Pass
NVNT	ac40 MIMO	5755	5720	-25.43	5.57	-19.86	Peak	15.6	Pass
NVNT	ac40 MIMO	5755	5720	-36.73	5.57	-31.16	Average	15.6	Pass
NVNT	ac40 MIMO	5755	5725	-23.98	5.57	-18.41	Peak	27	Pass
NVNT	ac40 MIMO	5755	5725	-35.25	5.57	-29.68	Average	27	Pass
NVNT	ac40 MIMO	5795	5850	-34.73	5.57	-29.16	Peak	27	Pass
NVNT	ac40 MIMO	5795	5850	-45.03	5.57	-39.46	Average	27	Pass
NVNT	ac40 MIMO	5795	5855	-37.08	5.57	-31.51	Peak	15.6	Pass
NVNT	ac40 MIMO	5795	5855	-46.64	5.57	-41.07	Average	15.6	Pass
NVNT	ac40 MIMO	5795	5875	-41.85	5.57	-36.28	Peak	10	Pass
NVNT	ac40 MIMO	5795	5875	-51.18	5.57	-45.61	Average	10	Pass





NVNT	ac40 MIMO	5795	5925	-49.39	5.57	-43.82	Peak	-27	Pass
NVNT	ac40 MIMO	5795	5925	-54.94	5.57	-49.37	Average	-27	Pass
NVNT	ac80 MIMO	5775	5650	-41.74	5.57	-36.17	Peak	-27	Pass
NVNT	ac80 MIMO	5775	5650	-49.36	5.57	-43.79	Average	-27	Pass
NVNT	ac80 MIMO	5775	5700	-34.45	5.57	-28.88	Peak	10	Pass
NVNT	ac80 MIMO	5775	5700	-41.29	5.57	-35.72	Average	10	Pass
NVNT	ac80 MIMO	5775	5720	-26.17	5.57	-20.6	Peak	15.6	Pass
NVNT	ac80 MIMO	5775	5720	-37.87	5.57	-32.3	Average	15.6	Pass
NVNT	ac80 MIMO	5775	5725	-28.87	5.57	-23.3	Peak	27	Pass
NVNT	ac80 MIMO	5775	5725	-37.61	5.57	-32.04	Average	27	Pass
NVNT	ac80 MIMO	5775	5850	-28.49	5.57	-22.92	Peak	27	Pass
NVNT	ac80 MIMO	5775	5850	-35.79	5.57	-30.22	Average	27	Pass
NVNT	ac80 MIMO	5775	5855	-28.73	5.57	-23.16	Peak	15.6	Pass
NVNT	ac80 MIMO	5775	5855	-36.86	5.57	-31.29	Average	15.6	Pass
NVNT	ac80 MIMO	5775	5875	-32.72	5.57	-27.15	Peak	10	Pass
NVNT	ac80 MIMO	5775	5875	-39.65	5.57	-34.08	Average	10	Pass
NVNT	ac80 MIMO	5775	5925	-38.61	5.57	-33.04	Peak	-27	Pass
NVNT	ac80 MIMO	5775	5925	-47.84	5.57	-42.27	Average	-27	Pass

Note: 802.11a mode, only show the worst set of antenna data.




Shenzhen LCS Compliance Testing Laboratory Ltd.
Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China
Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com
Scan code to check authenticity




Test Graphs

Restrict Band NVNT a 5745MHz Ant0 Peak




Restrict Band NVNT a 5745MHz Ant0 Average






Restrict Band NVNT a 5825MHz Ant0 Peak




Restrict Band NVNT a 5825MHz Ant0 Average






Restrict Band NVNT n20 5745MHz MIMO Peak



Restrict Band NVNT n20 5745MHz MIMO Average



Shenzhen LCS Compliance Testing Laboratory Ltd.


Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com


Scan code to check authenticity



Restrict Band NVNT n20 5825MHz MIMO Peak




Restrict Band NVNT n20 5825MHz MIMO Average






Restrict Band NVNT n40 5755MHz MIMO Peak



Restrict Band NVNT n40 5755MHz MIMO Average



Shenzhen LCS Compliance Testing Laboratory Ltd.


Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com


Scan code to check authenticity



Restrict Band NVNT n40 5795MHz MIMO Peak



Restrict Band NVNT n40 5795MHz MIMO Average



Shenzhen LCS Compliance Testing Laboratory Ltd.


Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com


Scan code to check authenticity



Restrict Band NVNT ac20 5745MHz MIMO Peak




Restrict Band NVNT ac20 5745MHz MIMO Average






Restrict Band NVNT ac20 5825MHz MIMO Peak



Restrict Band NVNT ac20 5825MHz MIMO Average



Shenzhen LCS Compliance Testing Laboratory Ltd.


Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com


Scan code to check authenticity



Restrict Band NVNT ac40 5755MHz MIMO Peak




Restrict Band NVNT ac40 5755MHz MIMO Average






Restrict Band NVNT ac40 5795MHz MIMO Peak




Restrict Band NVNT ac40 5795MHz MIMO Average






Restrict Band NVNT ac80 5775MHz MIMO Peak




Restrict Band NVNT ac80 5775MHz MIMO Average






Restrict Band NVNT ac80 5775MHz MIMO Peak



Restrict Band NVNT ac80 5775MHz MIMO Average





E.5 Frequency Stability

Condition	Mode	Frequency (MHz)	Antenna	Measured Frequency (MHz)	Frequency Error (Hz)	Deviation (ppm)	Limit (ppm)	Verdict
NVNT	ac20	5745	Ant0	5744.98	-20000	-3.48	25	Pass
NVNT	ac20	5785	Ant0	5784.98	-20000	-3.46	25	Pass
NVNT	ac20	5825	Ant0	5825	0	0	25	Pass
NVNT	ac40	5755	Ant0	5755	0	0	25	Pass
NVNT	ac40	5795	Ant0	5795.04	40000	6.9	25	Pass
NVNT	ac80	5775	Ant0	5775.08	80000	13.85	25	Pass




Shenzhen LCS Compliance Testing Laboratory Ltd.
Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China
Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com
Scan code to check authenticity




Test Graphs

Freq. Stability NVNT ac20 5745MHz Ant0




Freq. Stability NVNT ac20 5785MHz Ant0






Freq. Stability NVNT ac20 5825MHz Ant0




Freq. Stability NVNT ac40 5755MHz Ant0






Freq. Stability NVNT ac40 5795MHz Ant0



Freq. Stability NVNT ac80 5775MHz Ant0





Condition	Mode	Frequency (MHz)	Antenna	Measured Frequency (MHz)	Frequency Error (Hz)	Deviation (ppm)	Limit (ppm)	Verdict
NVNT	ac20	5745	Ant1	5744.98	-20000	-3.48	25	Pass
NVNT	ac20	5785	Ant1	5784.98	-20000	-3.46	25	Pass
NVNT	ac20	5825	Ant1	5824.98	-20000	-3.43	25	Pass
NVNT	ac40	5755	Ant1	5754.96	-40000	-6.95	25	Pass
NVNT	ac40	5795	Ant1	5795	0	0	25	Pass
NVNT	ac80	5775	Ant1	5775.08	80000	13.85	25	Pass




Shenzhen LCS Compliance Testing Laboratory Ltd.
Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen,
518000, China
Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com
Scan code to check authenticity




Test Graphs

Freq. Stability NVNT ac20 5745MHz Ant1




Freq. Stability NVNT ac20 5785MHz Ant1






Freq. Stability NVNT ac20 5825MHz Ant1



Freq. Stability NVNT ac40 5755MHz Ant1



Shenzhen LCS Compliance Testing Laboratory Ltd.


Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com


Scan code to check authenticity



Freq. Stability NVNT ac40 5795MHz Ant1



Freq. Stability NVNT ac80 5775MHz Ant1





E.6 Duty Cycle


Condition	Mode	Frequency (MHz)	Antenna	Duty Cycle (%)	Correction Factor (dB)	1/T (kHz)
NVNT	a	5745	Ant0	96.94	0.13	0.72
NVNT	a	5785	Ant0	96.94	0.13	0.72
NVNT	a	5825	Ant0	96.94	0.13	0.72
NVNT	n20	5745	Ant0	96.73	0.14	0.77
NVNT	n20	5785	Ant0	96.73	0.14	0.77
NVNT	n20	5825	Ant0	96.73	0.14	0.77
NVNT	n40	5755	Ant0	93.53	0.29	1.57
NVNT	n40	5795	Ant0	93.53	0.29	1.57
NVNT	ac20	5745	Ant0	96.76	0.14	0.76
NVNT	ac20	5785	Ant0	96.76	0.14	0.76
NVNT	ac20	5825	Ant0	96.76	0.14	0.76
NVNT	ac40	5755	Ant0	93.68	0.28	1.53
NVNT	ac40	5795	Ant0	93.68	0.28	1.53
NVNT	ac80	5775	Ant0	88.08	0.55	3.08






Test Graphs

Duty Cycle NVNT a 5745MHz Ant0



Duty Cycle NVNT a 5785MHz Ant0



Shenzhen LCS Compliance Testing Laboratory Ltd.


Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com


Scan code to check authenticity



Duty Cycle NVNT a 5825MHz Ant0




Duty Cycle NVNT n20 5745MHz Ant0






Duty Cycle NVNT n20 5785MHz Ant0



Duty Cycle NVNT n20 5825MHz Ant0



Shenzhen LCS Compliance Testing Laboratory Ltd.


Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com


Scan code to check authenticity



Duty Cycle NVNT n40 5755MHz Ant0




Duty Cycle NVNT n40 5795MHz Ant0






Duty Cycle NVNT ac20 5745MHz Ant0



Duty Cycle NVNT ac20 5785MHz Ant0



Shenzhen LCS Compliance Testing Laboratory Ltd.


Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com


Scan code to check authenticity



Duty Cycle NVNT ac20 5825MHz Ant0




Duty Cycle NVNT ac40 5755MHz Ant0






Duty Cycle NVNT ac40 5795MHz Ant0



Duty Cycle NVNT ac80 5775MHz Ant0






Condition	Mode	Frequency (MHz)	Antenna	Duty Cycle (%)	Correction Factor (dB)	1/T (kHz)
NVNT	a	5745	Ant1	96.94	0.13	0.72
NVNT	a	5785	Ant1	96.94	0.13	0.72
NVNT	a	5825	Ant1	96.94	0.13	0.72
NVNT	n20	5745	Ant1	96.73	0.14	0.77
NVNT	n20	5785	Ant1	96.65	0.15	0.77
NVNT	n20	5825	Ant1	96.73	0.14	0.77
NVNT	n40	5755	Ant1	93.64	0.29	1.54
NVNT	n40	5795	Ant1	93.79	0.28	1.54
NVNT	ac20	5745	Ant1	96.76	0.14	0.76
NVNT	ac20	5785	Ant1	96.76	0.14	0.76
NVNT	ac20	5825	Ant1	96.76	0.14	0.76
NVNT	ac40	5755	Ant1	93.68	0.28	1.53
NVNT	ac40	5795	Ant1	93.68	0.28	1.53
NVNT	ac80	5775	Ant1	88.08	0.55	3.08






Test Graphs

Duty Cycle NVNT a 5745MHz Ant1



Duty Cycle NVNT a 5785MHz Ant1



Shenzhen LCS Compliance Testing Laboratory Ltd.


Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com


Scan code to check authenticity



Duty Cycle NVNT a 5825MHz Ant1




Duty Cycle NVNT n20 5745MHz Ant1






Duty Cycle NVNT n20 5785MHz Ant1




Duty Cycle NVNT n20 5825MHz Ant1






Duty Cycle NVNT n40 5755MHz Ant1




Duty Cycle NVNT n40 5795MHz Ant1






Duty Cycle NVNT ac20 5745MHz Ant1




Duty Cycle NVNT ac20 5785MHz Ant1






Duty Cycle NVNT ac20 5825MHz Ant1




Duty Cycle NVNT ac40 5755MHz Ant1






Duty Cycle NVNT ac40 5795MHz Ant1



Duty Cycle NVNT ac80 5775MHz Ant1



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity