



Wireless Remote Control RC200

Technical Specifications:

Antenna Type	PCB Antenna
Modulation	OOK
Working voltage	12V 23A battery
Working current	≤15mA
Range	60-120m (200-400 ft) ^①
Encoding type	Fixed code(ht640)
Frequency	418MHz
Button	3 (Up, Stop, Down)
Dimension	90mm x 40mm x 15mm
Color	White
Temperature	-20° to 72°C
Material	PC
Other	Holder(optional)
Certificate	Design under CE, FCC directive ^③

- ① Transmitting distance is measured LOS (line of sight) with little radio interference in open air, actual distance may vary greatly depending on the installation and operating environment.
- ② Our products meet CE and FCC requirement, parts of them didn't show on certification.

Applications

remote engine starter	wireless parking sensor garage door
Anti-theft alarm	electric roller shutter doors windows
security system	retractable doors
personal alarm	remote pull gates
home security system	sliding door controller, electric curtains
home electric control	electric door
burglar alarm	wireless doorbell
home appliance control	etc

FCC Warning

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions:(1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

Any Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions,



may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

The device has been evaluated to meet general RF exposure requirement. The device can be used in portable exposure condition without restriction.