




Specification

Specification

Speaker: 660mm
Impedance: 32±15%Ω
Sensitivity: 111±3dB
Frequency response: 20Hz to 20kHz
Microphone: Q6, Qx5, Qmx
Microphone sensitivity: -42±3dB
Wireless distance: 10m
Plug: BT+3.5mm Audio cable
Recharge battery: 1050mAh
Charging time: about 3H
Charging method: (Type-C)/USB 5V
Low latency: 29MS
Size: 92*105*206mm
Weight: 341g
Connectivity Play: 2.4G: 35M/No back
backtrack 11M/backtrack backtracks



Removable magnetic

Operation Guide

Wired mode (3.5mm Audio cable)

1) Plug and play. Connecting the headphone to a music player with the provided dual 3.5mm audio cable, the headphone can be used as wired headphone without starting.

2) In this mode, you can't use any function of the headphone, including pause/playback, volume adjustment, microphone and so on.

2.4G mode

1. **Operating instructions**
 - 1) Connect the receiver to PC/S4 or other devices, the indicator lights up and flashes.
 - 2) Press the power button to turn on the headset, the headset power indicator blue light is always on for 10 seconds (Headset power indicator flashes red/green alternately while waiting to connect after the connection is successful, the headset indicator blinks green once every 2 seconds.)
 - 3) Toggle the toggle switch up and down to adjust the volume level, toggle up and down for 1.5 seconds to turn on and down for 1.5 seconds to turn off.
 - 4) The microphone is on by default. To turn the microphone off, press the microphone key once (a beep sound and the microphone indicator will turn off). To turn the microphone on, press the microphone key again (a beep will sound and the microphone indicator will turn red) (See 2.4G UI below for specific operations)

	Subnet/segment	Function	Operation	Mask
Power switch	ON/OFF	ON	Power supply ON	Power supply ON
		ON	Power supply ON	Power supply ON
		ON	Power supply ON	Power supply ON
		ON	Power supply ON	Power supply ON
24 G 10	ST	ST	ST	ST
		ST	ST	ST
		ST	ST	ST
		ST	ST	ST
Light button	Light button	Light button	Light button	Light button
		Light button	Light button	Light button
		Light button	Light button	Light button
		Light button	Light button	Light button
Toggle Switch	Toggle Switch	Toggle Switch	Toggle Switch	Toggle Switch
		Toggle Switch	Toggle Switch	Toggle Switch
		Toggle Switch	Toggle Switch	Toggle Switch
		Toggle Switch	Toggle Switch	Toggle Switch

Buttons/Function, Light	Function indicator	Operation	Mark
Micro-USB	Micro-usb	Short click	Recharge on when phone indicator light of when plugged into power source
TYPE-C	Charging	Plug the USB-A type-C charging cable into the Type-C charging jack on the light or headset to charge	Brightest light
2.4G USB	Finished charging	Unplug the USB-A to Type-C charging cable	The indicator light is green
Patterns of brightness		When the voltage is lower than 2.5V, give a low power warning and turn off the headsetphone light can be turned on manually. The voice light can be turned every 5 minutes. The power indicator changes from blue and green to red and blink every two seconds. When the voltage is lower than 1.5V, the headsetphone automatically shut down. The earphone will automatically shut down after 5 minutes without connecting to any device.	The power indicator is green when blue or green and blink every 2 seconds The power indicator is red for 1 second

3) Turn on the headphone, double click the power switch to Wireless mode, and you can hear the voice prompt "Wireless mode". When the headphone enter the pairing mode, the headphone power indicator flashes red and blue alternately;

Key function

Answer an incoming call
Double click the MIC button to answer the incoming call.
Tip: As some mobile phones answer calls through their own receivers by default, please refer to your mobile phone instructions and set them on your mobile phone.

End current call
Double click the MIC button to end the current call.


Refuse to answer the phone
When there is an incoming call, press the MIC button for 1.5 seconds

Three-way call answered call
Triple-tap the MIC button to hold the current call, answer a new call, and triple-tap again to rotate between the two calls.

Play music:

- 1) Play/Pause: short press the toggle switch.
- 2) Volume+: Toggle the toggle up a bit
- 3) Volume-: Toggle the lever down a bit
- 4) Previous song: Toggle up for 1.5 seconds.
- 5) Next song: Toggle down for 1.5 seconds. (See the Wireless UI below for details.)

GEHA

[illegible]

	Buttons/Function keys	Function indication	Operation	Mask
Microcrist		Microcrist	Short click	
		Answer/braking signal	Double click	
		Deactivate a call	Long pulse 1 s	Red light on when open, yellow if call when closed (blue light)
Type-C		Three-way call answered call	Press three times	
		Charging	Flashes the USB-A Type-C charging cable in the Type-C charging cable (the USB-C charging cable is the indicator to charge)	Bright red light
		Finished charging	Carry the USB-A Type-C charging cable (Carrying the USB-A Type-C charging cable is the indicator when charging)	The indicator light is green
Wireless UI			When the voltage is lower than 3.2V, (plus 3 low power warning and 3 red headlights) the low voltage can be learned automatically. The warning signal will continue every 5 minutes. The power indicator will continue to flash red and blue light every two seconds. When the voltage is lower than 3.0V, the warning automatically stops (when)	
Patterns of intelligence			The response will automatically stop when after 3 minutes without connecting to any device.	The power indicator will turn on for 10 seconds and will auto shut down if no power is received

Warnings

2) Please follow the instruction to operate

3) Please charge the headphone with input power below 3.3V, in order to protect the battery;

4) Please store or use the headphone in a normal temperature environment.

5) Please keep the headphone from heat source, such as radiators, hot air regulators, stoves, or other heat-generating instruments. As it is not anti-high temperature.

5) Don't jam the ports of the headphone, such as charger port, LED port and microphone etc...

6) In order to protect your hearing and extend the headphone service life, it is not recommended to adjust the volume to the maximum level for a long time.

7) Whatever reasons damage the headphone, please believe free to contact our after-sales staff in time rather than repair by yourself. Otherwise, you will accept without after-sales service.

FCC STATEMENT



Any Changes expressly or modifications not approved by the party responsible for compliance could void the user's authority to operate the equipment.

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions:

(1) This device may not cause harmful interference, and

(2) this device must accept any interference received, including interference that may cause undesired operation.

Note: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio-frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

FCC Radiation Exposure Statement

This equipment complies with FCC radiation exposure limits set forth for an uncontrolled environment. This transmitter must not be collocated or operating in conjunction with any other antenna or transmitter.

IC STATEMENT

Any changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

This device complies with Innovation, Science and Economic Development Canada licence-exempt RSS standard (s). Operation is subject to the following two conditions:

- (1) this device may not cause interference,
- (2) the device must accept any interference including interference that may cause undesired operation of the device.

Tous les changements ou modifications non expressément approuvés par le responsable de la conformité pourraient annuler l'autorité de l'utilisateur à exploiter l'équipement.

L'exploitation est autorisée sous les deux conditions suivantes:

- (1) l'appareil ne doit pas produire de brouillage, et
- (2) l'appareil doit accepter tout brouillage radioélectrique subi, qu'il ne braille pas susceptible d'en compromettre le fonctionnement.

ISED Radiation Exposure Statement

This equipment complies with FCC RF radiation exposure limits set forth for an uncontrolled environment. This transmitter must not be co-located or operating in conjunction with any other antenna or transmitter.

Get appareil est

Cet appareil est

conforme aux limites d'exposition de rayonnement RF (SEEC) établies pour un environnement non contrôlé. Cet émetteur ne doit pas être co-implanté ou fonctionner en conjonction avec toute autre antenne ou transmetteur.