



Meeting Room Tablet

Meeting room tablets are the perfect way for your organization to extend its digital signage to meeting areas.

- Show schedules from your own calendar app
- Make space reservations at the room sign
- See room status instantly with availability lights
- Easily recess or surface mount out of the box
- Use PoE+ via network switch

Easily create, import and schedule a wide range of calendar schedules, so meeting participants don't miss important updates.



Ultra-slim body




Full colour LED strip



Easy Installation



RFID&NFC



POE power supply



Dual-band Wi-Fi 802.11ac



Face Recognition



High Resolution



High-performance cpu



10-point touchscreen



Application compatibility



Customization

Specifications	
Diagonal Size	11.6"
Operating System	Android 11
Processor	RK3568
Memory	Standard: 2G; Value: 4G
Storage	Standard: 16G; Value: 32G
Resolution	Standard: 1280×800; Value:1920*1080
Aspect Ratio	16:9
Brightness	LCD Panel: 300 nits
Response Time	< 25 ms
Touch Technology	10-point capacitive touch
Speakers	1W、8Ω
LED	256 RGB stripe
Wi-Fi	WiFi IEEE Support 802/b/g/n
Bluetooth	Bluetooth 5.2
Camera	Standard: No Camera; Value: Front Camera: 2MPX
RFID/NFC	RFID/NFC, ISO/IEC 14443 A/MIFARE
I/O Ports	RJ45, POE, Wifi, USB-C
Housing	Aluminium (Plastic optional)
Dimensions (L x W x H)	281*171*20 (mm)
Net weight	0.89kg
Viewing Angle	Horizontal: ±80° total / Vertical: ±80° total
Waterproof front panel	IP65
Working Temperature	0°C~50°C
Anti-fingerprint coating	Support
Installation	Vesa 100mm (with bracket)
Warranty	1 year
Security Updates	Complimentary security updates provided for 3 months
Regulatory Approvals	CE 、 CCC、 FCC

Learn more about at www.icomi.cn.

Note: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- * —Reorient or relocate the receiving antenna.
- * —Increase the separation between the equipment and receiver.
- * —Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- * —Consult the dealer or an experienced radio/TV technician for help.

Tel: +86 21 52556826

Email: marketing@icomi.cn

Address: 6F, 1# BLD, Tiandi tech square, No.958 Zhenbei Rd, Putuo, Shanghai China



FCC STATEMENT

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:

- (1) This device may not cause harmful interference, and
- (2) This device must accept any interference received, including interference that may cause undesired operation.

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. The limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following.

measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/ TV technician for help.

Operations in the 5.15-5.35GHz band are restricted to indoor usage only.

FCC Radiation Exposure Statement:

This equipment complies with FCC radiation exposure limits set forth for an uncontrolled environment. In order to avoid the possibility of exceeding the FCC radio frequency exposure limits, Human proximity to the antenna shall not be less than 20cm(8 inches)during normal operation.