

Appendix Test Data for SRD (Conducted Measurement)

Product Name: Wireless Mechanical Keyboard

Trade Mark: Keychron

Test Model: K10HE

FCC ID: 2BGKB-K10HE

Environmental Conditions

Temperature:	23.5℃
Relative Humidity:	58%
ATM Pressure:	100.0 kPa
Test Engineer:	Allen Lai
Supervised by:	Max Zhang
NOTE	N/A


Appendix A: DTS Bandwidth


Test Result

Test Mode	Antenna	Frequency [MHz]	DTS BW [MHz]	FL [MHz]	FH [MHz]	Limit [MHz]	Verdict
SRD	Ant1	2402	1.332	2401.356	2402.688	0.5	PASS
SRD	Ant1	2440	1.412	2439.300	2440.712	0.5	PASS
SRD	Ant1	2480	1.304	2479.384	2480.688	0.5	PASS

Note: offset(dB) = cable loss(dB) + attenuator factor(dB)

Test Graphs





SRD-Ant1-2480-PASS

Appendix B: Occupied Channel Bandwidth


Test Result

Test Mode	Antenna	Frequency [MHz]	OCB [MHz]	FL [MHz]	FH [MHz]	Limit [MHz]	Verdict
SRD	Ant1	2402	2.0663	2400.9793	2403.0456	---	---
SRD	Ant1	2440	2.0527	2438.9626	2441.0153	---	---
SRD	Ant1	2480	2.0172	2478.9852	2481.0024	---	---

Note: offset(dB) = cable loss(dB) + attenuator factor(dB)

Test Graphs






Appendix C: Maximum peak conducted output power


Test Result Peak

Test Mode	Antenna	Frequency [MHz]	Conducted Peak Power [dBm]	Conducted Limit [dBm]	Verdict
SRD	Ant1	2402	-0.19	≤30	PASS
SRD	Ant1	2440	0.65	≤30	PASS
SRD	Ant1	2480	0.72	≤30	PASS

Note: offset(dB) = cable loss(dB) + attenuator factor(dB)

Test Graphs Peak






Appendix D: Maximum peak power spectral density


Test Result

Test Mode	Antenna	Frequency [MHz]	Result [dBm/3kHz]	Limit [dBm/3kHz]	Verdict
SRD	Ant1	2402	-13.15	≤8.00	PASS
SRD	Ant1	2440	-12.12	≤8.00	PASS
SRD	Ant1	2480	-12.36	≤8.00	PASS

Note: offset(dB) = cable loss(dB) + attenuator factor(dB)

Test Graphs






Appendix E: Band edge measurements

Test Result

Test Mode	Antenna	Ch. Name	Frequency [MHz]	Ref. Level [dBm]	Result [dBm]	Limit [dBm]	Verdict
SRD	Ant1	Low	2402	-2.84	-35.76	≤ -22.84	PASS
SRD	Ant1	High	2480	-2.28	-48.82	≤ -22.28	PASS

Note: offset(dB) = cable loss(dB) + attenuator factor(dB)

Test Graphs



Appendix F: Conducted Spurious Emission


Test Result

Test Mode	Antenna	Frequency [MHz]	Freq. Range [MHz]	Ref. Level [dBm]	Result [dBm]	Limit [dBm]	Verdict
SRD	Ant1	2402	0~Reference	-3.23	-3.23	---	PASS
SRD	Ant1	2402	30~1000	-3.23	-61.81	≤ -23.23	PASS
SRD	Ant1	2402	1000~26500	-3.23	-45.56	≤ -23.23	PASS
SRD	Ant1	2440	0~Reference	-1.31	-1.31	---	PASS
SRD	Ant1	2440	30~1000	-1.31	-62.38	≤ -21.31	PASS
SRD	Ant1	2440	1000~26500	-1.31	-45.24	≤ -21.31	PASS
SRD	Ant1	2480	0~Reference	-1.86	-1.86	---	PASS
SRD	Ant1	2480	30~1000	-1.86	-63.2	≤ -21.86	PASS
SRD	Ant1	2480	1000~26500	-1.86	-45.96	≤ -21.86	PASS

Note: offset(dB) in Reference test plots = cable loss(dB) + attenuator factor(dB); For spurious emissions plots from 30MHz to 26.5GHz, the cable loss and attenuator factors have been set in the 'Input Correction' of the Spectrum Analyzer during the test.

Test Graphs








SRD-Ant1-2402-1000~26500-PASS



SRD-Ant1-2440-0~Reference-PASS







Appendix G: Duty Cycle


Test Result

Test Mode	Antenna	Frequency [MHz]	ON Time [ms]	Period [ms]	Duty Cycle [%]	Duty Cycle Factor [dB]
SRD	Ant1	2402	19.00	19.00	100.00	0.00
SRD	Ant1	2440	19.00	19.00	100.00	0.00
SRD	Ant1	2480	19.00	19.00	100.00	0.00

Note: offset(dB) = cable loss(dB) + attenuator factor(dB)

Test Graphs





NTNV-SRD-Ant1-2480