














 <p>产品规格 型号:HTC NE56 蓝牙 范围:≈10m 版本:6.0 喇叭 直径:11mm 阻抗:16Ω 耳机功率 输入:5V=40mA 电池容量:40mAh 使用时间:≈5小时 充电时间:≈1.5小时 充电仓功率 输入:5V=250mA 输出:5V=80mA 电池容量:250mAh 充电时间:≈1小时 充电仓充满电时,能给耳机充电约2次 快速入门指南 使用前请阅读使用说明书 HTC NE56</p>	<p>物品清单</p>  <p>充电仓 2耳机 快速入门指南 USB-C充电线</p>	<p>部件</p>  <p>Earphone LED Touchpad Charging contacts Earphone speaker Charging case LED USB Type-C port</p>	<p>取出耳机并配对</p>  <p>如果这是第一次使用耳机,请将两个耳机从充电仓中取出,其中一个耳机的LED灯将会交替闪烁白灯和青灯,表示它们处于配对模式。 注: •如果耳机未与任何设备配对,打开后会自动进入配对模式。 •配对成功后,您会听到提示音。 •如果耳机之前已配对,打开后会自动重新连接。连接时您会听到提示音。</p>	<p>如何佩戴耳机</p>  <p>1 6 7 8 9</p>	 <p>2 3 4</p>																									
<p>开机和关机</p>  <p>开机 自动开机:将耳机从充电仓中取出,耳机开机。 手动开机:长按5秒,耳机开机。 关机 自动关机:耳机放入充电仓中,耳机关机。 手动关机:长按5秒,耳机关机。 注:当耳机开机后,3分钟后与蓝牙设备配对,便会自动开机;当配对的蓝牙设备发出信号有效连接距离,且未重新连接,3分钟后,耳机自动关机。</p>	<p>连接到蓝牙设备</p>  <p>在您的设备上,打开蓝牙并选择连接到“HTC NE56”。</p>	<p>基本操作</p>  <p>开/关机 通话模式 音乐模式 指示灯显示 功能操作 注:当耳机使用时,按住任一耳机2秒,均可激活语音助手 游戏模式与音乐模式切换:按住右耳机2秒切换 注:当耳机设置认为音乐模式 注:当耳机音量较大的是游戏模式 指示灯显示 双耳从充电仓取出后会自动开机配对,耳机未与蓝牙设备连接或从蓝牙设备取消连接状态时,分别对左耳机和右耳机连续五次多功能键,提示音“嘟”声后,耳机自动关机后将双耳机放回充电仓,并将双耳机取出,双耳机会自动配对,完成后即可连接蓝牙设备使用。 适用于以下情况: A:双耳无法配对时,短按音键,双配对时。 B:使用单耳机分别连接不同蓝牙设备时。 C:消除连接的所有蓝牙设备时。 特别提示: 当单耳机出现无声,或者无法配对时,请按以上恢复重置操作。</p>	<p>如何清除蓝牙配对历史记录</p>  <p>14 15</p>	<p>产品中有害物质名称及含量</p> <table border="1"> <tr> <th colspan="6">产品中有害物质的名称及含量</th> </tr> <tr> <th>部件名称</th> <th>铅(Pb)</th> <th>汞(Hg)</th> <th>镉(Cd)</th> <th>六价铬(Cr6+)</th> <th>多溴联苯(PBB)</th> </tr> <tr> <td>印刷电路组件</td> <td>○</td> <td>○</td> <td>○</td> <td>○</td> <td>○</td> </tr> <tr> <td>外壳等小结构件</td> <td>○</td> <td>○</td> <td>○</td> <td>○</td> <td>○</td> </tr> </table> <p>本表格依据SJ/T 11364的规定编制。 ○:表示该有害物质在该部件所有均质材料中的含量均在GB/T 26572规定的限量要求以下。 ×:表示该有害物质至少在该部件的某一均质材料中的含量超出GB/T 26572规定的限量要求。 表单标记“×”的部件,皆因全球技术发展水平限制而无法实现有害物质的替代。</p> <p>重要安全说明</p> <p>在使用本产品之前,请仔细阅读本说明书中的所有安全说明。</p> <p>常规安全说明</p> <p>小心使用本产品,并将其存放在没有极端温度、高温高压和潮湿的清洁环境中。确保产品存放在不易弯曲或挤压的地方。 维修和更换只能由授权的售后服务人员进行。 请勿自行拆卸或更换产品的任何部件,以防受伤或损坏设备。 对产品的任何未经授权的修改都将使保修无效。 • 仅在允许蓝牙使用的环境内使用本产品。</p> <p>个人安全说明</p> <p>• 如果产品有明显缺陷或出现膨胀或温度过高等异常,请勿使用。 • 执行需要全神贯注的高风险任务时,请勿使用本产品。 • 为了保护您的听力,请勿长时间高音量收听。 • 请将产品及其包装放在儿童和宠物接触不到的地方,以防发生吞咽和窒息等事故。</p> <p>电池安全说明</p> <p>该产品内含可充电电池,请阅读以下说明,确保安全使用和处置。 • 请勿将产品长时间暴露在热源中,如明火或阳光直射。 • 将产品存放在环境温度为0°C至35°C(32°F至95°F)的环境中。 • 请勿在潮湿、灰尘、烟雾、高温、高压或高湿度的环境中使用或存放产品。 • 保持产品干燥,远离液体或湿气。 • 请勿使产品接触FCC或CCC认证,输出电压为DC 5V/1A的充电器。 • 充电时不要使用产品。 • 产品充电时间不要超过8小时。 • 按照当地的废物管理规定负责任地处理产品。</p>	产品中有害物质的名称及含量						部件名称	铅(Pb)	汞(Hg)	镉(Cd)	六价铬(Cr6+)	多溴联苯(PBB)	印刷电路组件	○	○	○	○	○	外壳等小结构件	○	○	○	○	○	<p>售后电话:4009933981</p> <p>法律声明</p> <p>商标和许可: HTC和HTC标志为HTC公司的商标。 授权给深圳南士兰沃德科技有限公司使用。 2025版权©归深圳市南士兰沃德科技有限公司。 本文件仅供参考,不构成任何形式的保证,本公司保留所有权利。</p>	
产品中有害物质的名称及含量																														
部件名称	铅(Pb)	汞(Hg)	镉(Cd)	六价铬(Cr6+)	多溴联苯(PBB)																									
印刷电路组件	○	○	○	○	○																									
外壳等小结构件	○	○	○	○	○																									

 <p>Quick Start Guide HTC NE56</p>	<p>Product Specifications Model: HTC NE56</p> <p>Bluetooth Range: ≈10 m Version: 6.0</p> <p>Speaker Diameter: 11 mm Impedance: 16 Ω</p> <p>Earphone power Input: 5V=40 mA Battery capacity: 40 mAh Battery life: ≈ 5 hrs Charging time: ≈ 1.5 hrs</p> <p>Charging case power Input: 5V=250 mA Output: 5V=80 mA Battery capacity: 250 mAh Charging time: ≈ 1 hrs Earphone recharges: 2 charges (when case is fully charged)</p>	<p>What's in the box</p>  <p>Charging case 2 Earphones Quick Start Guide USB-C cable</p>	<p>Components</p>  <p>Earphone LED Touchpad Charging contacts Earphone speaker Charging case LED USB Type-C port</p>	<p>Take out and pair the earphones</p>  <p>If you're using the earphones for the first time, remove both from the charging case. The LED on one earphone will blink white and cyan alternately, indicating that they are in pairing mode.</p> <p>Note: • If the earphones have not been paired with each other, they will automatically enter pairing mode when turned on. You'll hear two beeps when pairing is successful. • If the earphones have been paired before, they will automatically reconnect to each other when turned on. You'll hear a beep when they connect.</p>	<p>How to put on the earphones</p>  <p>1 6 7 8 9</p>	 <p>3 4</p>																
<p>Basic operations</p>  <p>Power on/off Phone mode Music mode Indicator LEDs Reset earphones</p> <p>10 11</p>	<p>Key functions</p> <ul style="list-style-type: none"> Play/Pause: Tap either earphone once. Volume up: Tap the right earphone twice. Volume down: Tap the left earphone twice. Play next track: Tap the left earphone three times. Play previous track: Tap the right earphone three times. Answer/End call: Tap either earphone once. Reject call: Press and hold the left earphone for two seconds. Activate voice assistant: Press and hold the left earphone for two seconds. Note: When using a single earphone only, press and hold the active earphone for two seconds. Switch between Game and Music modes: Music mode is the default mode. Press and hold the right earphone for two seconds to switch between modes. (The louder notification sound indicates Game mode.) Note: Mode switching is disabled when you're using a single earphone only. <p>Indicator LEDs</p> <table border="1"> <tr> <th>Earphone LED</th> <th>Status</th> </tr> <tr> <td>Blinking white and cyan</td> <td>Both earphones: Powered on Single earphone: Unpaired</td> </tr> <tr> <td>Solid white</td> <td>Earphone charging</td> </tr> <tr> <td>Off</td> <td>Paired or fully charged</td> </tr> <tr> <td>Charging case LED</td> <td>Status</td> </tr> <tr> <td>Solid cyan</td> <td>Earphone charging</td> </tr> <tr> <td>Blinking cyan</td> <td>Case charging</td> </tr> <tr> <td>Solid cyan</td> <td>Case fully charged</td> </tr> </table> <p>12 13</p>	Earphone LED	Status	Blinking white and cyan	Both earphones: Powered on Single earphone: Unpaired	Solid white	Earphone charging	Off	Paired or fully charged	Charging case LED	Status	Solid cyan	Earphone charging	Blinking cyan	Case charging	Solid cyan	Case fully charged	<p>How to reset the earphones</p> <p>If the earphones fail to pair or reconnect to each other, reset them by tapping both earphones five times simultaneously.</p> <p>Note: Resetting the earphones will clear the Bluetooth pairing history.</p>  <p>14 15</p>	<p>Important Safety Instructions</p> <p>Carefully read all the safety instructions in this document before using the product.</p> <p>General safety instructions</p> <ul style="list-style-type: none"> Use the product with care and store it in a clean environment that is free from extreme temperature, pressure, and humidity. Make sure that the product is stored in a location where it cannot be bent or squeezed. Repairs and replacements should only be performed by authorized after-sales service staff. Do not attempt to disassemble or replace any part of the product yourself to prevent injury or damage to the device. Any unauthorized modification to the product voids the warranty. Only use the product in environments where Bluetooth transmission is permitted. <p>Personal safety instructions</p> <ul style="list-style-type: none"> Do not use the product if it is obviously defective or exhibits abnormalities such as bulging or excessive heating. Do not use the product when performing high-risk tasks that require your full attention. For your hearing protection, do not listen at high volume for long periods. Keep the product and its packaging out of reach of children and pets to prevent accidents such as swallowing and choking. 	<p>Battery safety instructions</p> <p>The product has a built-in rechargeable battery. Read the following instructions to ensure safe use and disposal.</p> <ul style="list-style-type: none"> Keep the product away from prolonged exposure to heat sources such as open fires or direct sunlight. Only store the product in environments with ambient temperatures of 0°C to 35°C (32°F to 95°F). Do not use or store the product in dust-prone, smoke-prone, high-temperature, high-pressure, or highly humid environments. Keep the product dry and away from liquids or moisture. Only use an FCC or CCC-certified charger with an output voltage of 5V/1A DC. Do not use the product while charging. Do not leave the product charging for longer than eight hours. Dispose of the product responsibly according to your local waste management guidelines. <p>FCC ID: 2BHJR-NE56</p> <p>FCC Caution: This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.</p> <p>Any changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.</p> <p>Note: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:</p> <ul style="list-style-type: none"> Reorient or relocate the receiving antenna. Increase the separation between the equipment and receiver. Connect the equipment into an outlet on a circuit different from that to which the receiver is connected. 	<p>US REP</p> <p>Company name: MIRAMONT SOLUTIONS LLC Company address: 19 GEORGETOWN, IRVINE, CA 92612 United States FCC ID: 0036131369 Agent name: Wenyi Wang Title: CEO Email: wenyiwang@miramontsolutions.com Phone: 951 401 3633</p> <p>Customer Service Email: service@yhemt.net</p> <p>Legal notice</p> <p>Trademarks and permissions:</p> <p>HTC and the HTC logo are trademarks of HTC Corporation and used under license by Shenzhen Brands World Technology Co., Ltd. Copyright © 2025 Shenzhen Brands World Technology Co., Ltd. All rights reserved.</p> <p>THIS DOCUMENT IS FOR INFORMATION PURPOSES ONLY AND DOES NOT CONSTITUTE ANY KIND OF WARRANTY.</p>	
Earphone LED	Status																					
Blinking white and cyan	Both earphones: Powered on Single earphone: Unpaired																					
Solid white	Earphone charging																					
Off	Paired or fully charged																					
Charging case LED	Status																					
Solid cyan	Earphone charging																					
Blinking cyan	Case charging																					
Solid cyan	Case fully charged																					