Professional Digital Sound Card

User Guide

One-stop Mixer Console

For Streaming and Podcast On Computer & Mobile Devices

NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment. This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions:
(1) this device may not cause harmful interference, and
(2) this device must accept any interference received, including interference that may cause undesired operation.

Product Overview

The GAM mixer is a professional-level all-in-one sound card, mixer, and live streaming audio device. It is designed for podcasting, live streaming, and gaming, and is an entertainment sound mixer, so its audio quality is not as professional as professional audio mixer, audio interface, or dj mixer.

It features a compact structure, full-color LED screen, 3 large rotary adjustment knobs with RGB lighting effect, 9 commonly-used voice adjustment modes, and 29 keys, Easy to adjust. It supports multiple types of audio inputs such as Type-C/USB, wireless connection, 3.5mm for the running and sound effects, no delay software, no sound card driver, plug and play process, no need long-time learning curve, and has powerful and abundant range of audio and effects effects.

The GAM1 features 10 audio jacks, provides enough channels to accommodate your main home devices, 2 Mics in XLR/3.5mm, 4 TRS, 2 XLR, mic, microphone jacks, allow you use your different type microphone, and a 3.5mm TRRS jack for headphone microphone mixer and make a video meeting. Moreover, the four mic/USB jack are two 3.5mm TRRS jacks to output your computers, tablets, smartphones and more. It is compatible with iOS, Android, Windows, etc system, no need learning about the connection.

Rear Panel



1, 48V XLR Mic:
48V condenser microphone input port. *48V phantom power for condenser mic through the 48V key*, **the input volume is controlled by " Total Mic Volume" knob.**

2, Musical instrument:
6.35mm port, Connect 6.35mm musical instrument devices, **Controlled by " Musical instrument" knob.**
Tips: The 6.35mm dynamic mic can input audio through this port, but effects such as reverb, EQ, voice changing, etc. can not have an effect on this channel.

3, Stereo mic microphone:
6.35mm dynamic mic input port, controlled by "Total Mic Volume" knob.

4, Microphone:
3.5mm TRS mic port, Connect a (MLX to 3.5mm) condenser microphone. **Controlled by " Total Mic Volume" knob.**

5, Headphone/speaker:
Two 3.5mm ports used for monitoring all sound resources of the mixer in real time. Supports THS/TRRS headphones. **Controlled by " Monitoring" knob.**

6, Headset:
3.5mm TRRS port, Connect a headphone mic, used for inputs input via headset, and also can output some monitor allsound sources on it. **The monitoring volume is controlled by " Monitoring" knobs. The input volume is controlled by " Total Mic Volume" knob.**

7, Accompaniment:
3.5mm music resources input port. Connect an external audio source or devices to the mixer via a 3.5mm audio cable, to access the background music during streaming or recording. Can be connected to the smartphone 3.5mm jack, PC, smartphone jack, **the input volume is controlled by " Accompaniment " knob.**

8, Live Streaming:
Two 3.5mm TRRS analog output ports; By the port, the mixed audio can be output to the smartphone, tablet or other devices through a 3.5mm TRRS cable, so that you can hear the mixed audio from the mixer, then do live streaming podcast, or recording on smartphone or tablet.
When you chat with followers, fans and other streamers, the voice of other party can be input through this port. However, the volume of other party depends on the output volume of the other party, the mixer can not control / record the audio.

9, OTG:
USB-C port. Data interface port, can be used for audio data communications with computer and mobile devices; for audio signal this audio can be connected to PC mobile devices for recording or streaming podcast.
The input volume is controlled by " Accompaniment " knob, The output volume is controlled by " Recording" knob.
Tips: Adjusting accompaniment volume inputted through the USB-C port (from mobile phones and PC) requires enabling Loopback function/Power-keep.

10, Charging/PC Live:
Data interface & charging port. can be used for audio data communications with computer and mobile devices for audio signal live audio,
The input volume is controlled by " Accompaniment " knob, The output volume is controlled by " Recording" knob.

Top Panel