

Appendix F. Sim-Tx SAR consideration

F.1 Sim-Tx Configuration

Exposure Condition	Tx mode	Capable TX Configurations	WWAN Power	WiFi Power	BT Power	Thread Power
Head	WWAN standalone	WWAN	Index 2			
	WiFi standalone	WiFi 2.4G SISO		Index 1		
		WiFi 2.4G MIMO/CDD				
		WiFi 5G MIMO				
		WiFi 6E MIMO				
		WiFi 2.4G SISO + WiFi 5G MIMO				
		WiFi 2.4G MIMO + WiFi 5G MIMO				
		WiFi 2.4G SISO + WiFi 6E MIMO				
		WiFi 2.4G MIMO + WiFi 6E MIMO				
	BT standalone	Bluetooth SISO or MIMO			Index 1	
	Thread standalone	Thread				Index 1
	WiFi +BT	WiFi 5G MIMO + Bluetooth SISO or MIMO		Index 1	Index 1	
		WiFi 6E MIMO + Bluetooth SISO or MIMO				
	WiFi +Thread	WiFi 5G MIMO + Thread		Index 1		Index 1
		WiFi 6E MIMO + Thread				
	WWAN + WiFi	WWAN + WiFi 2.4G SISO		Index 2		
		WWAN + WiFi 2.4G MIMO/CDD				
		WWAN + WiFi 5G MIMO				
		WWAN + WiFi 6E MIMO				
		WWAN + WiFi 2.4G SISO + WiFi 5G MIMO				
		WWAN + WiFi 2.4G MIMO + WiFi 5G MIMO				
		WWAN + WiFi 2.4G SISO + WiFi 6E MIMO				
		WWAN + WiFi 2.4G MIMO + WiFi 6E MIMO				
	WWAN + BT	WWAN + Bluetooth SISO or MIMO	Index 3		Index 1	
	WWAN + Thread	WWAN + Thread				Index 1
	WWAN + WiFi +BT	WWAN + WiFi 5G MIMO + Bluetooth SISO or MIMO		Index 2	BT Index 1	
		WWAN + WiFi 6E MIMO + Bluetooth SISO or MIMO				
	WWAN + WiFi +Thread	WWAN + WiFi 5E MIMO + Thread				Index 1
		WWAN + WiFi 6E MIMO + Thread				

Exposure Condition	Tx mode	Capable TX Configurations	WWAN Power	WiFi Power	BT Power	Thread Power
Body	WWAN standalone	WWAN	Index 5			
	WiFi standalone	WiFi 2.4G SISO		WIFI Index 3		
		WiFi 2.4G MIMO/CDD				
		WiFi 5G MIMO				
		WiFi 6E MIMO				
		WiFi 2.4G SISO + WiFi 5G MIMO				
		WiFi 2.4G MIMO + WiFi 5G MIMO				
		WiFi 2.4G SISO + WiFi 6E MIMO				
		WiFi 2.4G MIMO + WiFi 6E MIMO				
	BT standalone	Bluetooth SISO or MIMO			Index 0	
	Thread standalone	Thread				Index 0
	WiFi +BT	WiFi 5G MIMO + Bluetooth SISO or MIMO		Index 3	Index 2	
		WiFi 6E MIMO + Bluetooth SISO or MIMO				
	WiFi +Thread	WiFi 5G MIMO + Thread		Index 3		Index 2
		WiFi 6E MIMO + Thread				
	WWAN + WiFi	WWAN + WiFi 2.4G SISO	Index 6 / Index 4	Index 4		
		WWAN + WiFi 2.4G MIMO/CDD				
		WWAN + WiFi 5G MIMO				
		WWAN + WiFi 6E MIMO				
		WWAN + WiFi 2.4G SISO + WiFi 5G MIMO				
		WWAN + WiFi 2.4G MIMO + WiFi 5G MIMO				
		WWAN + WiFi 2.4G SISO + WiFi 6E MIMO				
		WWAN + WiFi 2.4G MIMO + WiFi 6E MIMO				
	WWAN + BT	WWAN + Bluetooth SISO or MIMO	Index 6 / Index 4		Index 2	
	WWAN + Thread	WWAN + Thread				Index 2
	WWAN + WiFi +BT	WWAN + WiFi 5G MIMO + Bluetooth SISO or MIMO	Index 6 / Index 4	Index 4	Index 2	
		WWAN + WiFi 6E MIMO + Bluetooth SISO or MIMO				
	WWAN + WiFi +Thread	WWAN + WiFi 5G MIMO + Thread				Index 2
		WWAN + WiFi 6E MIMO + Thread				

General Note:

- The worst case reported SAR from each transmit antennas were using for SAR summation. Therefore, the following summations represent the absolute worst cases for simultaneous transmission configuration.
- The SAR summation is calculated based on the same exposure configuration and test position from each transmit antenna worst case reported SAR results.
- Per KDB 447498 D01v06, simultaneous transmission SAR is compliant if,
 - Scalar SAR summation < 1.6W/kg.
 - $SPLSR = (SAR1 + SAR2)^{1.5} / (\min. \text{ separation distance, mm})$, and the peak separation distance is determined from the square root of $[(x1-x2)^2 + (y1-y2)^2 + (z1-z2)^2]$, where (x1, y1, z1) and (x2, y2, z2) are the coordinates of the extrapolated peak SAR locations in the zoom scan.
 - If $SPLSR \leq 0.04$, simultaneously transmission SAR measurement is not necessary.
 - Simultaneously transmission SAR measurement, and the reported multi-band SAR < 1.6W/kg.

F.2 5G NR + LTE + WLAN + BT Sim-Tx analysis

Samsung proprietary TAS feature manages transmitting power effectively in real time and ensures that overall average RF exposure from 3G/4G/5G NR WWAN including NTN, 5G NR EN-DC, 5G NR NRDC and LTE/FR1 intra-band/inter-band uplink CA are in compliance with RF Exposure requirements, while the RF exposure from 2G and WLAN/BT radios is managed using the legacy approach, i.e., through a fixed power back-off if needed. The test device features a TAS function to keep average RF exposure below the given limit for all cases while allowing temporarily high power transmission for better performance.

For the 5G NR EN-DC or 5G NR DC, the power ratio factors are g_1 and g_2 for LTE/NR and NR respectively. The purpose of these power ratio factors is to split the available SAR budget among different RATs, so $g_1 + g_2 \leq 1$. The value of g_1 is computed based on the need of the anchor (LTE) and can be changed if the anchor changes its power request. Based on the SAR Budget portion allocated to the anchor, the value of g_2 will be computed. At steady state (where all RATs are being on for a while), the allocated power ratio factors will guarantee that the total exposure ratio never exceeds the highest exposure of either one.

$$g_1 * \text{LTEexposure} + g_2 * \text{NRexposure} \leq 1.0,$$

$$\text{then, } g_1 * \text{LTEexposure} + g_2 * \text{NRexposure} \leq \max(\text{LTEexposure}, \text{NRexposure})$$

In simultaneous transmission for this device, 5G NR and LTE transmission are managed and controlled by Samsung S.LSI TAS, while the RF exposure from WLAN, BT radios are managed using legacy approach, therefore, compliance of simultaneous transmission of LTE+5G NR+WiFi+BT can be justified from the compliance of LTE+WiFi +BT and 5G NR+WiFi+BT

The device also enabled Samsung Spatial TAS to improve antenna performance by applying separate SAR budgets to each predefined antenna group. There are three predefined antenna groups of AG0(Ant0, Ant6), AG1(Ant1,Ant5), AG2(Ant2,Ant7). Each antenna group is spatially separated to others. Simultaneous transmission analysis is performed per antenna group. Below analysis demonstrates the spatial separation of AG0, AG1, AG2 and the compliance between AG0 and BT/WLAN/NFC/Thread, between AG1 and BT/WLAN/NFC/ Thread and AG2 and BT/WLAN/NFC/Thread. The NTN wireless technology is not applied for Spatial TAS with other antenna groups.

Thus, the concept was to split the SAR/TER on the transmitting RATs even they are transmitting on different antennas. Such approach is considered as a worst case scenario in terms of transmitting power. Thus, to enhance the performance of the transmission power of RATs, consider the spatial properties of each antenna and the correlations between the antennas transmissions.

Group	AG0	AG1	AG2	external radio
Antenna	Ant 0, Ant 6	Ant 1, Ant 5	Ant 2, Ant 7	WLAN/BT/Thread/NFC

The verification of spatial separation of the antenna groups is demonstrated through the following steps, together with WIF/BT simultaneous transmission analysis results.

- The highest reported SAR at P_{limit} (or P_{max} when $P_{\text{limit}} > P_{\text{max}}$) for each antenna should be obtained out of all supported technologies and frequency bands for each power index. Demonstrate that the sum of reported SAR of one antenna from each of the antenna groups and the sum of RF exposure from all supported radios outside of TAS feature should be less than the regulatory limit as given below for each power index.
- If the sum of SAR from step i) is over 1.6 W/kg for 1g, demonstrate for a given power index that every antenna from one antenna group meets SPLSR criteria with every antenna in another antenna group for all frequency bands. SPLSR criteria must be demonstrated for all antenna pair combinations irrespective of supported simultaneous transmission scenarios, SPLSR Hotspot combination procedure (Hybrid SPLSR) also be considered for simultaneous transmission analysis.
- If SPLSR evaluation and analysis is needed to determine compliance for a certain power index configuration, SPLSR is performed by taking the highest summation SAR for each of the supported technologies and bands per antenna, along with the minimum of peak SAR location distance. The minimum of peak location distance are documented in the Highest Report SAR and Hotspot Location below for each power index configuration.
- In section F.6 SPLSR analysis only evaluation Sim-Tx SAR configuration are rounded to two decimal higher or equal to 1.6W/kg.
- The analysis addresses the simultaneous transmission and the transition among non-simultaneous transmission radios



F.3 Head Sim-Tx analysis

<WWAN index 2>

Exposure Position	Max Ant 0	Max Ant 1	Max Ant 2	Max Ant 5	Max Ant 6	Max Ant 7	Ant 0+1 Summed 1g SAR (W/kg)	Ant 0+2 Summed 1g SAR (W/kg)	Ant 0+5 Summed 1g SAR (W/kg)	Ant 0+7 Summed 1g SAR (W/kg)	Ant 1+2 Summed 1g SAR (W/kg)	Ant 1+6 Summed 1g SAR (W/kg)	Ant 1+7 Summed 1g SAR (W/kg)	Ant 2+5 Summed 1g SAR (W/kg)	Ant 2+6 Summed 1g SAR (W/kg)	Ant 5+6 Summed 1g SAR (W/kg)	Ant 5+7 Summed 1g SAR (W/kg)	Ant 6+7 Summed 1g SAR (W/kg)	SPLSR	Case No	SPLSR	Case No
	WWAN	WWAN	WWAN	WWAN	WWAN	WWAN																
	1g SAR (W/kg)	1g SAR (W/kg)	1g SAR (W/kg)	1g SAR (W/kg)	1g SAR (W/kg)	1g SAR (W/kg)																
Right Cheek at 0mm	0.439	0.941	0.928	0.458	0.354	0.810	1.380	1.367	0.897	1.249	1.869	1.295	1.751	1.386	1.282	0.812	1.268	1.164	0.030	Case 1	0.030	Case 2
Right Tilted at 0mm	0.288	0.988	0.277	0.373	0.326	0.276	1.276	0.565	0.661	0.564	1.265	1.314	1.264	0.650	0.603	0.699	0.649	0.602				
Left Cheek at 0mm	0.551	0.701	0.461	0.919	0.468	0.472	1.252	1.012	1.470	1.023	1.162	1.169	1.173	1.380	0.929	1.387	1.391	0.940				
Left Tilted at 0mm	0.282	0.720	0.388	0.633	0.179	0.414	1.002	0.670	0.915	0.696	1.108	0.899	1.134	1.021	0.567	0.812	1.047	0.593				

<WWAN index 3, WLAN index 2, Bluetooth index 1, Thread index 1>

Ant.	Exposure Position	0	1	2	3	4	5	6	7	8	9	0+1+2+5 Summed 1g SAR (W/kg)	0+1+2+5 Summed 1g SAR (W/kg)	0+1+4+5 Summed 1g SAR (W/kg)	0+1+5+6 Summed 1g SAR (W/kg)	0+1+5+7 Summed 1g SAR (W/kg)	0+1+5+8 Summed 1g SAR (W/kg)	0+1+5+9 Summed 1g SAR (W/kg)	0+1+2+5 SPLSR	0+1+2+5 Case No	0+1+3+5 SPLSR	0+1+3+5 Case No	0+1+4+5 SPLSR	0+1+4+5 Case No	0+1+5+6 SPLSR	0+1+5+6 Case No	0+1+5+7 SPLSR	0+1+5+7 Case No	0+1+5+8 SPLSR	0+1+5+8 Case No	0+1+5+9 SPLSR	0+1+5+9 Case No	
		Maximum WWAN	Maximum WWAN	WLAN 2.4GHz Ant 3	WLAN 2.4GHz Ant 4	WLAN 2.4GHz Ant 3+4	WLAN 5GHz Ant 3+4	Bluetooth(2.0) Ant 3	Bluetooth(2.0) Ant 4	Bluetooth(2.0) Ant 3+4	Thread Ant 3	1g SAR (W/kg)	1g SAR (W/kg)	1g SAR (W/kg)	1g SAR (W/kg)	1g SAR (W/kg)	1g SAR (W/kg)	1g SAR (W/kg)	1g SAR (W/kg)	1g SAR (W/kg)	1g SAR (W/kg)	1g SAR (W/kg)	1g SAR (W/kg)	1g SAR (W/kg)	1g SAR (W/kg)	1g SAR (W/kg)	1g SAR (W/kg)	1g SAR (W/kg)	1g SAR (W/kg)	1g SAR (W/kg)	1g SAR (W/kg)	1g SAR (W/kg)	
		1g SAR (W/kg)	1g SAR (W/kg)	1g SAR (W/kg)	1g SAR (W/kg)	1g SAR (W/kg)	1g SAR (W/kg)	1g SAR (W/kg)	1g SAR (W/kg)	1g SAR (W/kg)	1g SAR (W/kg)	1g SAR (W/kg)	1g SAR (W/kg)	1g SAR (W/kg)	1g SAR (W/kg)	1g SAR (W/kg)	1g SAR (W/kg)	1g SAR (W/kg)	1g SAR (W/kg)	1g SAR (W/kg)	1g SAR (W/kg)	1g SAR (W/kg)	1g SAR (W/kg)	1g SAR (W/kg)	1g SAR (W/kg)	1g SAR (W/kg)	1g SAR (W/kg)	1g SAR (W/kg)	1g SAR (W/kg)	1g SAR (W/kg)	1g SAR (W/kg)	1g SAR (W/kg)	
Ant 0+1	Right Cheek	0.333	0.714	0.224	0.045	0.194	0.288	0.235	0.059	0.239	0.200	1.559	1.380	1.529	1.570	1.394	1.574	1.535															
	Right Tilted	0.234	0.768	0.167	0.025	0.031	0.209	0.043	0.018	0.080	0.035	1.378	1.236	1.242	1.254	1.229	1.291	1.246															
	Left Cheek	0.452	0.479	0.099	0.189	0.128	0.264	0.131	0.162	0.148	0.109	1.294	1.384	1.323	1.326	1.357	1.343	1.304															
	Left Tilted	0.245	0.505	0.021	0.070	0.066	0.188	0.023	0.063	0.101	0.031	0.959	1.008	1.004	0.961	1.001	1.039	0.969															
Ant 0+2	Right Cheek	0.333	0.707	0.224	0.045	0.194	0.288	0.235	0.059	0.239	0.200	1.552	1.373	1.522	1.563	1.387	1.567	1.528															
	Right Tilted	0.234	0.277	0.167	0.025	0.031	0.209	0.043	0.018	0.080	0.035	0.887	0.745	0.751	0.763	0.738	0.800	0.755															
	Left Cheek	0.452	0.358	0.099	0.189	0.128	0.264	0.131	0.162	0.148	0.109	1.173	1.263	1.202	1.205	1.236	1.222	1.183															
	Left Tilted	0.245	0.388	0.021	0.070	0.066	0.188	0.023	0.063	0.101	0.031	0.842	0.891	0.887	0.844	0.884	0.922	0.852															
Ant 0+5	Right Cheek	0.333	0.313	0.224	0.045	0.194	0.288	0.235	0.059	0.239	0.200	1.158	0.979	1.128	1.169	0.993	1.173	1.134															
	Right Tilted	0.234	0.281	0.167	0.025	0.031	0.209	0.043	0.018	0.080	0.035	0.891	0.749	0.755	0.767	0.742	0.804	0.759															
	Left Cheek	0.452	0.685	0.099	0.189	0.128	0.264	0.131	0.162	0.148	0.109	1.500	1.590	1.529	1.532	1.563	1.549	1.510															
	Left Tilted	0.245	0.517	0.021	0.070	0.066	0.188	0.023	0.063	0.101	0.031	0.971	1.020	1.016	0.973	1.013	1.051	0.981															
Ant 0+7	Right Cheek	0.333	0.658	0.224	0.045	0.194	0.288	0.235	0.059	0.239	0.200	1.503	1.324	1.473	1.514	1.338	1.518	1.479															
	Right Tilted	0.234	0.225	0.167	0.025	0.031	0.209	0.043	0.018	0.080	0.035	0.835	0.693	0.699	0.711	0.686	0.748	0.703															
	Left Cheek	0.452	0.384	0.099	0.189	0.128	0.264	0.131	0.162	0.148	0.109	1.199	1.289	1.228	1.231	1.262	1.248	1.209															
	Left Tilted	0.245	0.336	0.021	0.070	0.066	0.188	0.023	0.063	0.101	0.031	0.790	0.839	0.835	0.792	0.832	0.870	0.800															
Ant 1+2	Right Cheek	0.714	0.707	0.224	0.045	0.194	0.288	0.235	0.059	0.239	0.200	1.933	1.751	1.903	1.944	1.768	1.948	1.909	0.04	Case 8	0.04	Case 9	0.04	Case 10	0.04	Case 11	0.03	Case 12	0.04	Case 13	0.04	Case 14	
	Right Tilted	0.768	0.277	0.167	0.025	0.031	0.209	0.043	0.018	0.080	0.035	1.421	1.279	1.285	1.297	1.272	1.334	1.289															
	Left Cheek	0.479	0.358	0.099	0.189	0.128	0.264	0.131	0.162	0.148	0.109	1.200	1.290	1.229	1.232	1.263	1.249	1.210															
	Left Tilted	0.505	0.388	0.021	0.070	0.066	0.188	0.023	0.063	0.101	0.031	1.102	1.151	1.147	1.104	1.144	1.182	1.112															
Ant 1+6	Right Cheek	0.714	0.269	0.224	0.045	0.194	0.288	0.235	0.059	0.239	0.200	1.495	1.316	1.465	1.506	1.330	1.510	1.471															
	Right Tilted	0.768	0.247	0.167	0.025	0.031	0.209	0.043	0.018	0.080	0.035	1.391	1.249	1.255	1.267	1.242	1.304	1.259															
	Left Cheek	0.479	0.355	0.099	0.189	0.128	0.264	0.131	0.162	0.148	0.109	1.197	1.287	1.226	1.229	1.260	1.246	1.207															
	Left Tilted	0.505	0.135	0.021	0.070	0.066	0.188	0.023	0.063	0.101	0.031	0.849	0.898	0.894	0.851	0.891	0.929	0.859															
Ant 1+7	Right Cheek	0.714	0.658	0.224	0.045	0.194	0.288	0.235	0.059	0.239	0.200	1.884	1.705	1.854	1.895	1.719	1.899	1.850	0.04	Case 15	0.03	Case 16	0.03	Case 17	0.03	Case 18	0.03	Case 19	0.04	Case 20	0.03	Case 21	
	Right Tilted	0.768	0.225	0.167	0.025	0.031	0.209	0.043	0.018	0.080	0.035	1.369	1.227	1.233	1.245	1.220	1.282	1.237															
	Left Cheek	0.479	0.384	0.099	0.189	0.128	0.264	0.131	0.162	0.148	0.109	1.226	1.316	1.255	1.258	1.289	1.275	1.236															
	Left Tilted	0.505	0.336	0.021	0.070	0.066	0.188	0.023	0.063	0.101	0.031	1.050	1.099	1.095	1.052	1.092	1.130	1.060															
Ant 2+5	Right Cheek	0.707	0.313	0.224	0.045	0.194	0.288	0.235	0.059	0.239	0.200	1.532	1.353	1.502	1.543	1.367	1.547	1.508															
	Right Tilted	0.277	0.281	0.167	0.025	0.031	0.209	0.043	0.018	0.080	0.035	0.934	0.792	0.798	0.810	0.785	0.847	0.802															
	Left Cheek	0.358	0.685	0.099	0.189	0.128	0.264	0.131	0.162	0.148	0.109	1.406	1.496	1.435	1.438	1.469	1.455	1.416															
	Left Tilted	0.388	0.517	0.021	0.070	0.066	0.188	0.023	0.063	0.101	0.031	1.114	1.163	1.159	1.116	1.156	1.194	1.124															
Ant 2+6	Right Cheek	0.707	0.269	0.224	0.045	0.194	0.288	0.235	0.059	0.239	0.200	1.488	1.309	1.458	1.499	1.323	1.503	1.464															
	Right Tilted	0.277	0.247	0.167	0.025	0.031	0.209	0.043	0.018	0.080	0.035	0.900	0.759	0.764	0.776	0.751	0.813	0.768															
	Left Cheek	0.358	0.355	0.099	0.189	0.128	0.264	0.131	0.162	0.148	0.109	1.076	1.166	1.105	1.108	1.139	1.125	1.086															
	Left Tilted	0.388	0.135	0.021	0.070	0.066	0.188	0.023	0.063	0.101	0.031	0.732	0.781	0.777</																			



Report No. :FA4N0917D

<WLAN Index 1, BT Index 1, Thread Index 1>

Page : D5 of D73



F.4 Body-worn Sim-Tx analysis

<WWAN index 5>

Exposure Position	Max Ant 0 WWAN 1g SAR (W/kg)	Max Ant 1 WWAN 1g SAR (W/kg)	Max Ant 2 WWAN 1g SAR (W/kg)	Max Ant 5 WWAN 1g SAR (W/kg)	Max Ant 6 WWAN 1g SAR (W/kg)	Max Ant 7 WWAN 1g SAR (W/kg)	Ant 0+1 Summed 1g SAR (W/kg)	Ant 0+2 Summed 1g SAR (W/kg)	Ant 0+5 Summed 1g SAR (W/kg)	Ant 0+7 Summed 1g SAR (W/kg)	Ant 1+2 Summed 1g SAR (W/kg)	Ant 1+6 Summed 1g SAR (W/kg)	Ant 1+7 Summed 1g SAR (W/kg)	Ant 2+5 Summed 1g SAR (W/kg)	Ant 2+6 Summed 1g SAR (W/kg)	Ant 5+6 Summed 1g SAR (W/kg)	Ant 5+7 Summed 1g SAR (W/kg)	Ant 6+7 Summed 1g SAR (W/kg)	0+1 SPLSR	0+1 Case No	0+2 SPLSR	0+2 Case No	0+5 SPLSR	0+5 Case No	1+2 SPLSR	1+2 Case No	1+6 SPLSR	1+6 Case No
Front at 10mm	0.759	0.623	0.546	0.653	0.367	0.321	1.382	1.305	1.412	1.080	1.169	0.990	0.944	1.199	0.913	1.020	0.974	0.688										
Back at 10mm	0.981	0.989	0.657	0.810	0.614	0.421	1.970	1.638	1.791	1.402	1.646	1.603	1.410	1.467	1.271	1.424	1.231	1.035	0.02	Case 3	0.040	Case 4	0.020	Case 5	0.020	Case 6	0.020	Case 7

<WWAN index 4, WLAN index 4, BT Index 2, Thread index 2>

	0	1	2	3	4	5	6	7	8	9	0+1+2+5 Summed 1g SAR (W/kg)	0+1+3+5 Summed 1g SAR (W/kg)	0+1+4+5 Summed 1g SAR (W/kg)	0+1+5+5 Summed 1g SAR (W/kg)	0+1+5+7 Summed 1g SAR (W/kg)	0+1+5+8 Summed 1g SAR (W/kg)	0+1+5+9 Summed 1g SAR (W/kg)	0+1+2+5 SPLSR	0+1+2+5 Case No	0+1+3+5 SPLSR	0+1+3+5 Case No	0+1+4+5 SPLSR	0+1+4+5 Case No	0+1+5+5 SPLSR	0+1+5+5 Case No	0+1+5+7 SPLSR	0+1+5+7 Case No	0+1+5+8 SPLSR	0+1+5+8 Case No	0+1+5+9 SPLSR	0+1+5+9 Case No	
Ant 0+1	Front	0.547	0.623	0.118	0.059	0.091	0.117	0.151	0.200	0.096	0.141	1.405	1.346	1.378	1.438	1.487	1.383	1.428														
	Back	0.704	0.842	0.157	0.062	0.145	0.142	0.210	0.194	0.148	0.187	1.845	1.750	1.833	1.898	1.882	1.836	1.875	0.02	Case 22	0.02	Case 23	0.02	Case 24	0.02	Case 25	0.02	Case 26	0.02	Case 27	0.02	Case 28
	Left Edge	0.579	0.489	0.242	0.001	0.225	0.260	0.255	0.008	0.221	0.242	1.570	1.329	1.553	1.583	1.336	1.549	1.570														
	Right Edge	0.273	0.382	0.007	0.107	0.135	0.081	0.014	0.294	0.128	0.001	0.743	0.843	0.871	0.750	1.030	0.864	0.737														
	Top Edge		0.840	0.036	0.015	0.061	0.124	0.042	0.048	0.058	0.045	1.000	0.979	1.025	1.006	1.012	1.022	1.009														
	Bottom Edge	0.846										0.846	0.846	0.846	0.846	0.846	0.846	0.846														
Ant 0+2	Front	0.547	0.485	0.118	0.059	0.091	0.117	0.151	0.200	0.096	0.141	1.267	1.208	1.240	1.300	1.349	1.245	1.290														
	Back	0.704	0.546	0.157	0.062	0.145	0.142	0.210	0.194	0.148	0.187	1.549	1.454	1.537	1.602	1.586	1.540	1.579							Case 29	0.03						
	Left Edge	0.579	0.116	0.242	0.001	0.225	0.260	0.255	0.008	0.221	0.242	1.197	0.956	1.180	1.210	0.963	1.176	1.197														
	Right Edge	0.273	0.745	0.007	0.107	0.135	0.081	0.014	0.294	0.128	0.001	1.106	1.206	1.234	1.113	1.393	1.227	1.100														
	Top Edge			0.036	0.015	0.061	0.124	0.042	0.048	0.058	0.045	0.160	0.139	0.185	0.166	0.172	0.182	0.169														
	Bottom Edge	0.846	0.282									1.128	1.128	1.128	1.128	1.128	1.128	1.128														
Ant 0+5	Front	0.547	0.534	0.118	0.059	0.091	0.117	0.151	0.200	0.096	0.141	1.316	1.257	1.289	1.349	1.398	1.294	1.339														
	Back	0.704	0.545	0.157	0.062	0.145	0.142	0.210	0.194	0.148	0.187	1.548	1.453	1.536	1.601	1.585	1.539	1.578								Case 30	0.02					
	Left Edge	0.579	0.085	0.242	0.001	0.225	0.260	0.255	0.008	0.221	0.242	1.166	0.925	1.149	1.179	0.932	1.145	1.166														
	Right Edge	0.273	0.847	0.007	0.107	0.135	0.081	0.014	0.294	0.128	0.001	1.208	1.308	1.336	1.215	1.495	1.329	1.202														
	Top Edge		0.638	0.036	0.015	0.061	0.124	0.042	0.048	0.058	0.045	0.798	0.777	0.823	0.804	0.810	0.820	0.807														
	Bottom Edge	0.846										0.846	0.846	0.846	0.846	0.846	0.846	0.846														
Ant 0+7	Front	0.547	0.273	0.118	0.059	0.091	0.117	0.151	0.200	0.096	0.141	1.055	0.996	1.028	1.088	1.137	1.033	1.078														
	Back	0.704	0.358	0.157	0.062	0.145	0.142	0.210	0.194	0.148	0.187	1.361	1.266	1.349	1.414	1.398	1.352	1.391														
	Left Edge	0.579	0.116	0.242	0.001	0.225	0.260	0.255	0.008	0.221	0.242	1.197	0.956	1.180	1.210	0.963	1.176	1.197														
	Right Edge	0.273	0.604	0.007	0.107	0.135	0.081	0.014	0.294	0.128	0.001	0.965	1.065	1.093	0.972	1.252	1.086	0.959														
	Top Edge			0.036	0.015	0.061	0.124	0.042	0.048	0.058	0.045	0.160	0.139	0.185	0.166	0.172	0.182	0.169														
	Bottom Edge	0.846	0.136									0.982	0.982	0.982	0.982	0.982	0.982	0.982														
Ant 1+2	Front	0.623	0.485	0.118	0.059	0.091	0.117	0.151	0.200	0.096	0.141	1.343	1.284	1.316	1.376	1.425	1.321	1.366														
	Back	0.842	0.546	0.157	0.062	0.145	0.142	0.210	0.194	0.148	0.187	1.587	1.592	1.675	1.740	1.734	1.678	1.717	0.02	Case 31		0.02	Case 32	0.02	Case 33	0.03	Case 34	0.02	Case 35	0.02	Case 36	
	Left Edge	0.489	0.116	0.242	0.001	0.225	0.260	0.255	0.008	0.221	0.242	1.107	0.866	1.090	1.120	0.873	1.086	1.107														
	Right Edge	0.382	0.745	0.007	0.107	0.135	0.081	0.014	0.294	0.128	0.001	1.215	1.315	1.343	1.222	1.502	1.336	1.209														
	Top Edge	0.840		0.036	0.015	0.061	0.124	0.042	0.048	0.058	0.045	1.000	0.979	1.025	1.006	1.012	1.022	1.009														
	Bottom Edge		0.282									0.282	0.282	0.282	0.282	0.282	0.282	0.282														
Ant 1+6	Front	0.623	0.312	0.118	0.059	0.091	0.117	0.151	0.200	0.096	0.141	1.170	1.111	1.143	1.203	1.252	1.148	1.193														
	Back	0.842	0.485	0.157	0.062	0.145	0.142	0.210	0.194	0.148	0.187	1.626	1.531	1.614	1.679	1.663	1.617	1.656	0.03	Case 37		0.03	Case 38	0.03	Case 39	0.02	Case 40	0.02	Case 41	0.03	Case 42	
	Left Edge	0.489	0.694	0.242	0.001	0.225	0.260	0.255	0.008	0.221	0.242	1.685	1.444	1.668	1.638	1.451	1.664	1.635	0.02	Case 43		0.02	Case 44	0.03	Case 45		0.02	Case 46	0.03	Case 47		
	Right Edge	0.382	0.129	0.007	0.107	0.135	0.081	0.014	0.294	0.128	0.001	0.999	0.699	0.727	0.606	0.886	0.720	0.593														
	Top Edge	0.840		0.036	0.015	0.061	0.124	0.042	0.048	0.058	0.045	1.000	0.979	1.025	1.006	1.012	1.022	1.009														
	Bottom Edge		0.554									0.554	0.554	0.554	0.554	0.554	0.554	0.554														
Ant 1+7	Front	0.623	0.273	0.118	0.059	0.091	0.117	0.151	0.200	0.096	0.141	1.131	1.072	1.104	1.164	1.213	1.109	1.154														
	Back	0.842	0.358	0.157	0.062	0.145	0.142	0.210	0.194	0.148	0.187	1.499	1.404	1.487	1.552	1.536	1.490	1.529														
	Left Edge	0.489	0.116	0.242	0.001	0.225	0.260	0.255	0.008	0.221	0.242	1.107	0.866	1.090	1.120	0.873	1.086	1.107														





<WWAN index 6, WLAN index 4, BT Index 2, Thread index 2>

Ant.	Exposure Position	0	1	2	3	4	5	6	7	8	9	0+1+2+5 Summed 1g SAR (W/kg)	0+1+3+5 Summed 1g SAR (W/kg)	0+1+4+5 Summed 1g SAR (W/kg)	0+1+6+6 Summed 1g SAR (W/kg)	0+1+5+7 Summed 1g SAR (W/kg)	0+1+5+8 Summed 1g SAR (W/kg)	0+1+5+9 Summed 1g SAR (W/kg)	0+1+2+5 SPLSR	0+1+2+5 Case No.	0+1+3+5 SPLSR	0+1+3+5 Case No.	0+1+4+5 SPLSR	0+1+4+5 Case No.	0+1+5+6 SPLSR	0+1+5+6 Case No.	0+1+5+6 Case No.	0+1+5+6 Case No.	0+1+5+6 Case No.	0+1+5+6 Case No.	0+1+5+6 Case No.	
		Maximum WWAN	Maximum WWAN	WLAN2.4GHz Ant 3	WLAN2.4GHz Ant 4	WLAN2.4GHz Ant 3+4	WLAN5/6GHz Ant 3+4	Bluetooth(2.0) Ant 3	Bluetooth(2.0) Ant 4	Bluetooth(2.0) Ant 3+4	Thread Ant 3																					
		1g SAR (W/kg)	1g SAR (W/kg)	1g SAR (W/kg)	1g SAR (W/kg)	1g SAR (W/kg)	1g SAR (W/kg)	1g SAR (W/kg)	1g SAR (W/kg)	1g SAR (W/kg)	1g SAR (W/kg)																					
Ant 0+1	Front	0.651	0.623	0.118	0.059	0.091	0.217	0.151	0.200	0.096	0.141	1.609	1.550	1.582	1.642	1.691	1.587	1.632	0.02	Case 59					0.02	Case 60	0.02	Case 61			0.02	Case 62
	Back	0.835	0.842	0.157	0.062	0.145	0.276	0.210	0.194	0.148	0.187	2.110	2.015	2.098	2.163	2.147	2.101	2.140	0.03	Case 63	0.02	Case 64	0.03	Case 65	0.03	Case 66	0.03	Case 67	0.03	Case 68	0.03	Case 69
Ant 0+2	Front	0.651	0.485	0.118	0.059	0.091	0.217	0.151	0.200	0.096	0.141	1.471	1.412	1.444	1.504	1.553	1.449	1.494														
	Back	0.835	0.546	0.157	0.062	0.145	0.276	0.210	0.194	0.148	0.187	1.814	1.719	1.802	1.867	1.851	1.805	1.841	0.02	Case 70	0.04	Case 71	0.02	Case 72	0.02	Case 73	0.03	Case 74	0.03	Case 75	0.02	Case 76
Ant 0+5	Front	0.651	0.556	0.118	0.059	0.091	0.217	0.151	0.200	0.096	0.141	1.542	1.483	1.515	1.575	1.624	1.520	1.565								0.02	Case 77					
	Back	0.835	0.690	0.157	0.062	0.145	0.276	0.210	0.194	0.148	0.187	1.958	1.863	1.946	2.011	1.995	1.949	1.988	0.03	Case 78	0.02	Case 79	0.03	Case 80	0.03	Case 81	0.02	Case 82	0.03	Case 83	0.03	Case 84
Ant 0+7	Front	0.651	0.273	0.118	0.059	0.091	0.217	0.151	0.200	0.096	0.141	1.259	1.200	1.232	1.292	1.341	1.237	1.282														
	Back	0.835	0.358	0.157	0.062	0.145	0.276	0.210	0.194	0.148	0.187	1.626	1.531	1.614	1.679	1.663	1.617	1.656	0.04	Case 85			0.04	Case 86	0.04	Case 87	0.04	Case 88	0.04	Case 89	0.04	Case 90
Ant 1+2	Front	0.623	0.485	0.118	0.059	0.091	0.217	0.151	0.200	0.096	0.141	1.443	1.384	1.416	1.476	1.525	1.421	1.466														
	Back	0.842	0.546	0.157	0.062	0.145	0.276	0.210	0.194	0.148	0.187	1.821	1.726	1.809	1.874	1.858	1.812	1.851	0.02	Case 91	0.03	Case 92	0.02	Case 93	0.03	Case 94	0.03	Case 95	0.02	Case 96	0.02	Case 97
Ant 1+6	Front	0.623	0.312	0.118	0.059	0.091	0.217	0.151	0.200	0.096	0.141	1.270	1.211	1.243	1.303	1.352	1.248	1.293														
	Back	0.842	0.523	0.157	0.062	0.145	0.276	0.210	0.194	0.148	0.187	1.798	1.703	1.786	1.851	1.835	1.789	1.828	0.03	Case 98	0.02	Case 99	0.03	Case 100	0.03	Case 101	0.02	Case 102	0.03	Case 103	0.03	Case 104
Ant 1+7	Front	0.623	0.273	0.118	0.059	0.091	0.217	0.151	0.200	0.096	0.141	1.231	1.172	1.204	1.264	1.313	1.209	1.254														
	Back	0.842	0.358	0.157	0.062	0.145	0.276	0.210	0.194	0.148	0.187	1.633	1.538	1.621	1.686	1.670	1.624	1.663	0.02	Case 105			0.02	Case 106	0.02	Case 107	0.03	Case 108	0.02	Case 109	0.02	Case 110
Ant 2+5	Front	0.485	0.556	0.118	0.059	0.091	0.217	0.151	0.200	0.096	0.141	1.376	1.317	1.349	1.409	1.458	1.354	1.399														
	Back	0.546	0.690	0.157	0.062	0.145	0.276	0.210	0.194	0.148	0.187	1.669	1.574	1.657	1.722	1.706	1.660	1.699	0.03	Case 111			0.03	Case 112	0.03	Case 113	0.03	Case 114	0.03	Case 115	0.03	Case 116
Ant 2+6	Front	0.485	0.312	0.118	0.059	0.091	0.217	0.151	0.200	0.096	0.141	1.132	1.073	1.105	1.165	1.214	1.110	1.155														
	Back	0.546	0.523	0.157	0.062	0.145	0.276	0.210	0.194	0.148	0.187	1.502	1.407	1.490	1.555	1.539	1.493	1.532														
Ant 5+6	Front	0.556	0.312	0.118	0.059	0.091	0.217	0.151	0.200	0.096	0.141	1.203	1.144	1.176	1.236	1.285	1.181	1.226														
	Back	0.690	0.523	0.157	0.062	0.145	0.276	0.210	0.194	0.148	0.187	1.646	1.551	1.634	1.699	1.683	1.637	1.676	0.02	Case 117			0.02	Case 118	0.03	Case 119	0.02	Case 120	0.02	Case 121	0.02	Case 122
Ant 5+7	Front	0.556	0.273	0.118	0.059	0.091	0.217	0.151	0.200	0.096	0.141	1.164	1.105	1.137	1.197	1.246	1.142	1.187														
	Back	0.690	0.358	0.157	0.062	0.145	0.276	0.210	0.194	0.148	0.187	1.481	1.386	1.469	1.534	1.518	1.472	1.511														
Ant 6+7	Front	0.312	0.273	0.118	0.059	0.091	0.217	0.151	0.200	0.096	0.141	0.920	0.861	0.893	0.953	1.002	0.898	0.943														
	Back	0.523	0.358	0.157	0.062	0.145	0.276	0.210	0.194	0.148	0.187	1.314	1.219	1.302	1.367	1.351	1.305	1.344														

F.5 Product Specific Sim-Tx analysis
<WLAN Index 3, NFC>

Exposure Position	1	2	1+2 Summed 10g SAR (W/kg)
	WLAN5/6GHz Ant 3+4	NFC	
	10g SAR (W/kg)	10g SAR (W/kg)	
Front	1.804	0.001	1.805
Back	0.536	0.018	0.554
Left Edge	2.785	0.001	2.786
Right Edge	0.855	0.001	0.856
Top Edge	0.922	0.001	0.923
Bottom Edge			0.000

<WWAN Index 5, WLAN Index 4, NFC>

Exposure Position	1	2	3	1+2+3 Summed 10g SAR (W/kg)
	WWAN	WLAN5/6GHz Ant 3+4	NFC	
	10g SAR (W/kg)	10g SAR (W/kg)	10g SAR (W/kg)	
Front		1.260	0.001	1.261
Back		0.393	0.018	0.411
Left Edge		1.963	0.001	1.964
Right Edge		0.514	0.001	0.515
Top Edge		0.690	0.001	0.691
Bottom Edge	2.498			2.498

<Case 2>

SPLSR calculation for summation SAR>1.6W/kg

Exposure Position	0	9	10	11
	WWAN SAR	LTE Band 48_Ant 7 TX1	FR1 n48_Ant 7 TX1	FR1 n77_Ant 7 TX1
Right Cheek	1g SAR (W/kg)	0.125	0.197	0.810
		0+9 Summed SAR	0+10 Summed SAR	0+11 Summed SAR
GSM850_Ant 1 TX1	0.927	1.052	1.124	1.737
WCDMA V_Ant 1 TX1	0.939	1.064	1.136	1.749
LTE Band 12_Ant 1 TX1	0.878	1.003	1.075	1.688
LTE Band 13_Ant 1 TX1	0.933	1.058	1.130	1.743
LTE Band 14_Ant 1 TX1	0.932	1.057	1.129	1.742
LTE Band 25_Ant 1 Sub TX0	0.811	0.936	1.008	1.621
LTE Band 26_Ant 1 TX1	0.881	1.006	1.078	1.691
LTE Band 66_Ant 1 Sub TX0	0.857	0.982	1.054	1.667
LTE Band 71_Ant 1 TX1	0.903	1.028	1.100	1.713
FR1 n12_Ant 1 TX1	0.885	1.010	1.082	1.695
FR1 n14_Ant 1 TX1	0.872	0.997	1.069	1.682
FR1 n25_Ant 1 Sub TX0	0.839	0.964	1.036	1.649
FR1 n26_Ant 1 TX1	0.931	1.056	1.128	1.741
FR1 n41_Ant 1 Sub TX0	0.744	0.869	0.941	1.554
FR1 n48_Ant 1 Sub TX0	0.928	1.053	1.125	1.738
FR1 n66_Ant 1 Sub TX0	0.941	1.066	1.138	1.751
FR1 n71_Ant 1 TX1	0.927	1.052	1.124	1.737
FR1 n77_Ant 1 Sub TX0	0.935	1.060	1.132	1.745

SAR peak location (mm)			X (axis)		49	56	55.9
			Y (axis)		-252.7	-245.4	-245.2
			Z (axis)		-175.1	-177.3	-173.5
X (axis)	Y (axis)	Z (axis)	Exposure Position	0	9	10	11
				WWAN SAR	LTE Band 48_Ant 7 TX1	FR1 n48_Ant 7 TX1	FR1 n77_Ant 7 TX1
			Right Cheek	1g SAR (W/kg)	0.125	0.197	0.81
					0+9 SPLSR Results	0+10 SPLSR Results	0+11 SPLSR Results
14	-326.2	-176.8	GSM850_Ant 1 TX1	0.927			0.03
12.8	-320.4	-174.1	WCDMA V_Ant 1 TX1	0.939			0.03
14.9	-322.9	-174.3	LTE Band 12_Ant 1 TX1	0.878			0.02
15.5	-321.8	-177.1	LTE Band 13_Ant 1 TX1	0.933			0.03
14.4	-320.3	-177	LTE Band 14_Ant 1 TX1	0.932			0.03
14.5	-329.5	-174.1	LTE Band 25_Ant 1 Sub TX0	0.811			0.02
14.1	-325	-176.9	LTE Band 26_Ant 1 TX1	0.881			0.02
13	-328.6	-174	LTE Band 66_Ant 1 Sub TX0	0.857			0.02
18.1	-327.4	-174.4	LTE Band 71_Ant 1 TX1	0.903			0.02
15.1	-319.7	-174.4	FR1 n12_Ant 1 TX1	0.885			0.03
15	-318.8	-174.4	FR1 n14_Ant 1 TX1	0.872			0.03
20.7	-334.4	-174.2	FR1 n25_Ant 1 Sub TX0	0.839			0.02
16.6	-323.6	-174.5	FR1 n26_Ant 1 TX1	0.931			0.03
12.2	-324	-174.1	FR1 n41_Ant 1 Sub TX0	0.744			
37.8	-333.9	-174.4	FR1 n48_Ant 1 Sub TX0	0.928			0.03
15.8	-332.3	-174	FR1 n66_Ant 1 Sub TX0	0.941			0.02
15	-322.3	-174.3	FR1 n71_Ant 1 TX1	0.927			0.03
36.5	-334.8	-177.2	FR1 n77_Ant 1 Sub TX0	0.935			0.03



SPLSR calculation for summation SAR>1.6W/kg

[illegible]

SPLSR calculation for summation SAR>1.6W/kg

Information				General		Financial		Operational		Human Resources		Marketing		Sales		Customer Service		Support		Other	
Date	Time	Location	Event	Attendance		Revenue		Expenses		Staff		Promotion		Sales		Feedback		Issues		Notes	
				Actual	Target	Actual	Target	Actual	Target	Actual	Target	Actual	Target	Actual	Target	Actual	Target	Actual	Target	Actual	Target
2023-01-01	09:00	Room 101	Annual Meeting	120	100	5000	4500	1000	900	10	12	1000	800	100	120	10	12	10	12	10	12
2023-01-02	10:00	Room 102	Workshop	80	70	3000	2800	500	450	5	6	500	400	50	60	5	6	5	6	5	6
2023-01-03	11:00	Room 103	Conference	150	140	6000	5500	1200	1100	12	14	1200	1000	120	140	12	14	12	14	12	14
2023-01-04	12:00	Room 104	Seminar	90	80	4000	3800	800	750	8	9	800	700	80	90	8	9	8	9	8	9
2023-01-05	13:00	Room 105	Panel Discussion	60	50	2000	1800	400	350	4	5	400	300	40	50	4	5	4	5	4	5
2023-01-06	14:00	Room 106	Networking	70	60	2500	2300	500	450	5	6	500	400	50	60	5	6	5	6	5	6
2023-01-07	15:00	Room 107	Q&A Session	40	30	1500	1300	300	250	3	4	300	200	30	40	3	4	3	4	3	4
2023-01-08	16:00	Room 108	Press Conference	110	100	4500	4200	900	850	9	10	900	800	90	100	9	10	9	10	9	10
2023-01-09	17:00	Room 109	Guest Lecture	50	40	2200	2000	450	400	5	6	450	350	45	55	5	6	5	6	5	6
2023-01-10	18:00	Room 110	Roundtable	30	20	1200	1000	250	200	2	3	250	150	25	35	2	3	2	3	2	3
2023-01-11	19:00	Room 111	Panel Discussion	60	50	2500	2300	500	450	5	6	500	400	50	60	5	6	5	6	5	6
2023-01-12	20:00	Room 112	Networking	70	60	2800	2600	550	500	5	6	550	450	55	65	5	6	5	6	5	6
2023-01-13	21:00	Room 113	Q&A Session	40	30	1800	1600	350	300	4	5	350	250	35	45	4	5	4	5	4	5
2023-01-14	22:00	Room 114	Press Conference	100	90	4000	3800	800	750	8	9	800	700	80	90	8	9	8	9	8	9
2023-01-15	23:00	Room 115	Guest Lecture	50	40	2000	1800	400	350	5	6	400	300	40	50	5	6	5	6	5	6
2023-01-16	00:00	Room 116	Roundtable	30	20	1000	900	200	150	2	3	200	100	20	30	2	3	2	3	2	3
2023-01-17	01:00	Room 117	Panel Discussion	60	50	2200	2000	450	400	5	6	450	350	45	55	5	6	5	6	5	6
2023-01-18	02:00	Room 118	Networking	70	60	2600	2400	520	470	5	6	520	420	52	62	5	6	5	6	5	6
2023-01-19	03:00	Room 119	Q&A Session	40	30	1600	1400	320	270	4	5	320	220	32	42	4	5	4	5	4	5
2023-01-20	04:00	Room 120	Press Conference	90	80	3800	3600	750	700	7	8	750	650	75	85	7	8	7	8	7	8
2023-01-21	05:00	Room 121	Guest Lecture	50	40	1800	1600	350	300	5	6	350	250	35	45	5	6	5	6	5	6
2023-																					

SPLSR calculation for summation SAR>1.6W/kg

[illegible]



<Case 7>

SPLSR calculation for summation SAR>1.6W/kg

Exposure Position	0	9	10	11
	WWAN SAR	LTE Band 48_Ant 6 TX0	FR1 n48_Ant 6 TX0	FR1 n77_Ant 6 TX0
Back	1g SAR (W/kg)	0.317	0.341	0.614
		0+9 Summed SAR	0+10 Summed SAR	0+11 Summed SAR
GSM850_Ant 1 TX1	0.640	0.957	0.981	1.254
WCDMA V_Ant 1 TX1	0.490	0.807	0.831	1.104
LTE Band 12_Ant 1 TX1	0.351	0.668	0.692	0.965
LTE Band 13_Ant 1 TX1	0.515	0.832	0.856	1.129
LTE Band 14_Ant 1 TX1	0.520	0.837	0.861	1.134
LTE Band 25_Ant 1 Sub TX0	0.989	1.306	1.330	1.603
LTE Band 26_Ant 1 TX1	0.417	0.734	0.758	1.031
LTE Band 66_Ant 1 Sub TX0	0.978	1.295	1.319	1.592
LTE Band 71_Ant 1 TX1	0.289	0.606	0.630	0.903
FR1 n12_Ant 1 TX1	0.422	0.739	0.763	1.036
FR1 n14_Ant 1 TX1	0.533	0.850	0.874	1.147
FR1 n25_Ant 1 Sub TX0	0.877	1.194	1.218	1.491
FR1 n26_Ant 1 TX1	0.424	0.741	0.765	1.038
FR1 n41_Ant 1 Sub TX0	0.962	1.279	1.303	1.576
FR1 n48_Ant 1 Sub TX0	0.506	0.823	0.847	1.120
FR1 n66_Ant 1 Sub TX0	0.848	1.165	1.189	1.462
FR1 n71_Ant 1 TX1	0.346	0.663	0.687	0.960
FR1 n77_Ant 1 Sub TX0	0.451	0.768	0.792	1.065

SAR peak location (mm)			X (axis)		12	-23	12.5
			Y (axis)		-57	-75.5	-56
			Z (axis)		-207	-207	-207
X (axis)	Y (axis)	Z (axis)	Exposure Position	0	9	10	11
			Back	1g SAR (W/kg)	LTE Band 48_Ant 6 TX0	FR1 n48_Ant 6 TX0	FR1 n77_Ant 6 TX0
					0.317	0.341	0.614
					0+9 SPLSR Results	0+10 SPLSR Results	0+11 SPLSR Results
4.6	56.1	-207	GSM850_Ant 1 TX1	0.640			
4.1	56.8	-207	WCDMA V_Ant 1 TX1	0.490			
8	56.8	-207	LTE Band 12_Ant 1 TX1	0.351			
6.3	53.8	-207	LTE Band 13_Ant 1 TX1	0.515			
2.8	56.3	-207	LTE Band 14_Ant 1 TX1	0.520			
1.9	76.6	-207	LTE Band 25_Ant 1 Sub TX0	0.989			0.02
1.9	55.1	-207	LTE Band 26_Ant 1 TX1	0.417			
-2.4	75.9	-207	LTE Band 66_Ant 1 Sub TX0	0.978			
5.1	55.8	-207	LTE Band 71_Ant 1 TX1	0.289			
3.6	56.1	-207	FR1 n12_Ant 1 TX1	0.422			
0.3	56.1	-207	FR1 n14_Ant 1 TX1	0.533			
0.9	79.6	-207	FR1 n25_Ant 1 Sub TX0	0.877			
1.3	56.6	-207	FR1 n26_Ant 1 TX1	0.424			
-5	77	-207	FR1 n41_Ant 1 Sub TX0	0.962			
15	64.5	-207	FR1 n48_Ant 1 Sub TX0	0.506			
3.6	78.9	-207	FR1 n66_Ant 1 Sub TX0	0.848			
4.1	55.1	-207	FR1 n71_Ant 1 TX1	0.346			
14.5	65	-207	FR1 n77_Ant 1 Sub TX0	0.451			

<Case 8>

SPLSR calculation for summation SAR>1.6W/kg

[illegible]

Project		Location		Project Details		Financial Performance		Operational Metrics		Environmental Impact		Social & Economic		Risk Assessment		Compliance		Overall Status	
Project Name		Location		Project Details		Financial Performance		Operational Metrics		Environmental Impact		Social & Economic		Risk Assessment		Compliance		Overall Status	
Project Name		Location		Project Details		Financial Performance		Operational Metrics		Environmental Impact		Social & Economic		Risk Assessment		Compliance		Overall Status	
Project Name		Location		Project Details		Financial Performance		Operational Metrics		Environmental Impact		Social & Economic		Risk Assessment		Compliance		Overall Status	
Project Name		Location		Project Details		Financial Performance		Operational Metrics		Environmental Impact		Social & Economic		Risk Assessment		Compliance		Overall Status	
Project Name		Location		Project Details		Financial Performance		Operational Metrics		Environmental Impact		Social & Economic		Risk Assessment		Compliance		Overall Status	
Project Name		Location		Project Details		Financial Performance		Operational Metrics		Environmental Impact		Social & Economic		Risk Assessment		Compliance		Overall Status	
Project Name		Location		Project Details		Financial Performance		Operational Metrics		Environmental Impact		Social & Economic		Risk Assessment		Compliance		Overall Status	
Project Name		Location		Project Details		Financial Performance		Operational Metrics		Environmental Impact		Social & Economic		Risk Assessment		Compliance		Overall Status	
Project Name		Location		Project Details		Financial Performance		Operational Metrics		Environmental Impact		Social & Economic		Risk Assessment		Compliance		Overall Status	
Project Name		Location		Project Details		Financial Performance		Operational Metrics		Environmental Impact		Social & Economic		Risk Assessment		Compliance		Overall Status	
Project Name		Location		Project Details		Financial Performance		Operational Metrics		Environmental Impact		Social & Economic		Risk Assessment		Compliance		Overall Status	
Project Name		Location		Project Details		Financial Performance		Operational Metrics		Environmental Impact		Social & Economic		Risk Assessment		Compliance		Overall Status	
Project Name		Location		Project Details		Financial Performance		Operational Metrics		Environmental Impact		Social & Economic		Risk Assessment					

<Case 9>

SPLSR calculation for summation SAR>1.6W/kg

[illegible]

Combination	SAR	SAR peak location (mm)			3D distance (mm)	Summed SAR (W/kg)	SPLSR Results	Simultaneous SAR
		X	Y	Z				
Max WWAN Ant 1+WLAN5/6G Ant 4+3(3)	1.002	46.9	-322.5	-175.2	70.6	1.71	0.03	Not required
Max WWAN Ant 2	0.707	55.2	-252.4	-177.7				
Max WWAN Ant 1+WLAN5/6G Ant 4+3(3)	1.002	15.0	-318.8	-174.4	63.3	1.05	0.02	Not required
WLAN2.4G Ant 4	0.045	32.5	-258.0	-173.4				
Max WWAN Ant 1+WLAN5/6G Ant 4+3(3)	1.002	15.0	-318.8	-174.4	42.1	1.07	0.03	Not required
WLAN5/6G Ant 4+3(4)	0.063	-7.8	-284.2	-167.2				
Max WWAN Ant 2	0.707	53.7	-248.4	-174.3	23.3	0.75	0.03	Not required
WLAN2.4G Ant 4	0.045	32.5	-258.0	-173.4				
Max WWAN Ant 2	0.707	54.3	-250.7	-177.6	71.3	0.77	0.01	Not required
WLAN5/6G Ant 4+3(4)	0.063	-7.8	-284.2	-167.2				
WLAN2.4G Ant 4	0.045	32.5	-258.0	-173.4	48.5	0.11	0.00	Not required
WLAN5/6G Ant 4+3(4)	0.063	-7.8	-284.2	-167.2				

<Case 13>

SPLSR calculation for summation SAR>1.6W/kg

[illegible]

<Case 14>

SPLSR calculation for summation SAR>1.6W/kg

[illegible]

<Case 15>

SPLSR calculation for summation SAR>1.6W/kg

Exposure Position			0	1	2	9	10	11
			WWAN SAR	WLAN2.4GHz Ant 3	WLAN5/6GHz Ant 4+3	LTE Band 48_Ant 7 TX1	FR1 n48_Ant 7 TX1	FR1 n77_Ant 7 TX1
Right Cheek			1g SAR (W/kg)			0.125	0.197	0.658
						0+1+2+9 Summed SAR	0+1+2+10 Summed SAR	0+1+2+11 Summed SAR
GSM850_Ant 1 TX1			0.703	0.224	0.288	1.340	1.412	1.873
WCDMA V_Ant 1 TX1			0.708	0.224	0.288	1.345	1.417	1.878
LTE Band 12_Ant 1 TX1			0.714	0.224	0.288	1.351	1.423	1.884
LTE Band 13_Ant 1 TX1			0.693	0.224	0.288	1.330	1.402	1.863
LTE Band 14_Ant 1 TX1			0.677	0.224	0.288	1.314	1.386	1.847
LTE Band 25_Ant 1 Sub TX0			0.690	0.224	0.288	1.327	1.399	1.860
LTE Band 26_Ant 1 TX1			0.713	0.224	0.288	1.350	1.422	1.883
LTE Band 66_Ant 1 Sub TX0			0.713	0.224	0.288	1.350	1.422	1.883
LTE Band 71_Ant 1 TX1			0.701	0.224	0.288	1.338	1.410	1.871
FR1 n12_Ant 1 TX1			0.703	0.224	0.288	1.340	1.412	1.873
FR1 n14_Ant 1 TX1			0.709	0.224	0.288	1.346	1.418	1.879
FR1 n25_Ant 1 Sub TX0			0.714	0.224	0.288	1.351	1.423	1.884
FR1 n26_Ant 1 TX1			0.584	0.224	0.288	1.221	1.293	1.754
FR1 n41_Ant 1 Sub TX0			0.634	0.224	0.288	1.271	1.343	1.804
FR1 n48_Ant 1 Sub TX0			0.709	0.224	0.288	1.346	1.418	1.879
FR1 n66_Ant 1 Sub TX0			0.693	0.224	0.288	1.330	1.402	1.863
FR1 n71_Ant 1 TX1			0.713	0.224	0.288	1.350	1.422	1.883
FR1 n77_Ant 1 Sub TX0			0.690	0.224	0.288	1.327	1.399	1.860

SAR peak location (mm)			X (axis)		58.6		46.9		49		56		55.9	
			Y (axis)		-318		-322.5		-262.7		-245.4		-245.2	
			Z (axis)		-174		-175.2		-175.1		-177.3		-173.5	
X (axis)	Y (axis)	Z (axis)	Exposure Position	0	1	2	9	10	11					
			WWAN SAR	WLAN2.4GHz Ant 3	WLAN5/6GHz Ant 4+3	LTE Band 48_Ant 7 TX1	FR1 n48_Ant 7 TX1	FR1 n77_Ant 7 TX1						
			Right Cheek	1g SAR (W/kg)			0.125	0.197	0.658					
14	-326.2	-176.8	GSM850_Ant 1 TX1	0.703	0.224	0.288				0.04				
12.8	-320.4	-174.1	WCDMA V_Ant 1 TX1	0.708	0.224	0.288				0.04				
14.9	-322.9	-174.3	LTE Band 12_Ant 1 TX1	0.714	0.224	0.288				0.04				
15.5	-321.8	-177.1	LTE Band 13_Ant 1 TX1	0.693	0.224	0.288				0.03				
14.4	-320.3	-177	LTE Band 14_Ant 1 TX1	0.677	0.224	0.288				0.03				
14.5	-329.5	-174.1	LTE Band 25_Ant 1 Sub TX0	0.690	0.224	0.288				0.03				
14.1	-325	-176.9	LTE Band 26_Ant 1 TX1	0.713	0.224	0.288				0.04				
13	-328.6	-174	LTE Band 66_Ant 1 Sub TX0	0.713	0.224	0.288				0.04				
18.1	-327.4	-174.4	LTE Band 71_Ant 1 TX1	0.701	0.224	0.288				0.04				
15.1	-319.7	-174.4	FR1 n12_Ant 1 TX1	0.703	0.224	0.288				0.04				
15	-318.8	-174.4	FR1 n14_Ant 1 TX1	0.709	0.224	0.288				0.04				
20.7	-334.4	-174.2	FR1 n25_Ant 1 Sub TX0	0.714	0.224	0.288				0.04				
16.6	-323.6	-174.5	FR1 n26_Ant 1 TX1	0.584	0.224	0.288				0.03				
12.2	-324	-174.1	FR1 n41_Ant 1 Sub TX0	0.634	0.224	0.288				0.03				
37.2	-334.6	-174.4	FR1 n48_Ant 1 Sub TX0	0.709	0.224	0.288				0.04				
15.8	-332.3	-174	FR1 n66_Ant 1 Sub TX0	0.693	0.224	0.288				0.03				
15	-322.3	-174.3	FR1 n71_Ant 1 TX1	0.713	0.224	0.288				0.04				
36.5	-334.8	-177.2	FR1 n77_Ant 1 Sub TX0	0.690	0.224	0.288				0.03				

<Case 16>

SPLSR calculation for summation SAR>1.6W/kg

Exposure Position	0	1	2	9	10	11
	WWAN SAR	WLAN2.4GHz Ant 4	WLAN5/6GHz Ant 4+3	LTE Band 48_Ant 7 TX1	FR1 n48_Ant 7 TX1	FR1 n77_Ant 7 TX1
Right Cheek	1g SAR (W/kg)			0.125	0.197	0.658
				0+1+2+9 Summed SAR	0+1+2+10 Summed SAR	0+1+2+11 Summed SAR
GSM850_Ant 1 TX1	0.703	0.045	0.288	1.161	1.233	1.694
WCDMA V_Ant 1 TX1	0.708	0.045	0.288	1.166	1.238	1.699
LTE Band 12_Ant 1 TX1	0.714	0.045	0.288	1.172	1.244	1.705
LTE Band 13_Ant 1 TX1	0.693	0.045	0.288	1.151	1.223	1.684
LTE Band 14_Ant 1 TX1	0.677	0.045	0.288	1.135	1.207	1.668
LTE Band 25_Ant 1 Sub TX0	0.690	0.045	0.288	1.148	1.220	1.681
LTE Band 26_Ant 1 TX1	0.713	0.045	0.288	1.171	1.243	1.704
LTE Band 66_Ant 1 Sub TX0	0.713	0.045	0.288	1.171	1.243	1.704
LTE Band 71_Ant 1 TX1	0.701	0.045	0.288	1.159	1.231	1.692
FR1 n12_Ant 1 TX1	0.703	0.045	0.288	1.161	1.233	1.694
FR1 n14_Ant 1 TX1	0.709	0.045	0.288	1.167	1.239	1.700
FR1 n25_Ant 1 Sub TX0	0.714	0.045	0.288	1.172	1.244	1.705
FR1 n26_Ant 1 TX1	0.584	0.045	0.288	1.042	1.114	1.575
FR1 n41_Ant 1 Sub TX0	0.634	0.045	0.288	1.092	1.164	1.625
FR1 n48_Ant 1 Sub TX0	0.709	0.045	0.288	1.167	1.239	1.700
FR1 n66_Ant 1 Sub TX0	0.693	0.045	0.288	1.151	1.223	1.684
FR1 n71_Ant 1 TX1	0.713	0.045	0.288	1.171	1.243	1.704
FR1 n77_Ant 1 Sub TX0	0.690	0.045	0.288	1.148	1.220	1.681

Combination	SAR	SAR peak location (mm)			3D distance (mm)	Summed SAR (W/kg)	SPLSR Results	Simultaneous SAR
		X	Y	Z				
Max WWAN Ant 7	0.658	55.9	-245.2	-173.5	77.8	1.66	0.03	Not required
Max WWAN Ant 1+WLAN5/6G Ant 4+3(3)	1.002	46.9	-322.5	-175.2				
Max WWAN Ant 7	0.658	55.9	-245.2	-173.5	26.7	0.70	0.02	Not required
WLAN2.4G Ant 4	0.045	32.5	-258.0	-173.4				
Max WWAN Ant 7	0.658	55.9	-245.2	-173.5	75.0	0.72	0.01	Not required
WLAN5/6G Ant 4+3(4)	0.063	-7.8	-284.2	-167.2				
Max WWAN Ant 1+WLAN5/6G Ant 4+3(3)	1.002	15.0	-318.8	-174.4	63.3	1.05	0.02	Not required
WLAN2.4G Ant 4	0.045	32.5	-258.0	-173.4				
Max WWAN Ant 1+WLAN5/6G Ant 4+3(3)	1.002	15.0	-318.8	-174.4	42.1	1.07	0.03	Not required
WLAN5/6G Ant 4+3(4)	0.063	-7.8	-284.2	-167.2				
WLAN2.4G Ant 4	0.045	32.5	-258.0	-173.4	48.5	0.11	0.00	Not required
WLAN5/6G Ant 4+3(4)	0.063	-7.8	-284.2	-167.2				

**<Case 17>**

SPLSR calculation for summation SAR>1.6W/kg

Exposure Position	0	1	2	9	10	11
	WWAN SAR	WLAN2.4GHz Ant 4+3	WLAN5/6GHz Ant 4+3	LTE Band 48_Ant 7 TX1	FR1 n48_Ant 7 TX1	FR1 n77_Ant 7 TX1
Right Cheek	1g SAR (W/kg)			0.125	0.197	0.658
				0+1+2+9 Summed SAR	0+1+2+10 Summed SAR	0+1+2+11 Summed SAR
GSM850_Ant 1 TX1	0.703	0.194	0.288	1.310	1.382	1.843
WCDMA V_Ant 1 TX1	0.708	0.194	0.288	1.315	1.387	1.848
LTE Band 12_Ant 1 TX1	0.714	0.194	0.288	1.321	1.393	1.854
LTE Band 13_Ant 1 TX1	0.693	0.194	0.288	1.300	1.372	1.833
LTE Band 14_Ant 1 TX1	0.677	0.194	0.288	1.284	1.356	1.817
LTE Band 25_Ant 1 Sub TX0	0.690	0.194	0.288	1.297	1.369	1.830
LTE Band 26_Ant 1 TX1	0.713	0.194	0.288	1.320	1.392	1.853
LTE Band 66_Ant 1 Sub TX0	0.713	0.194	0.288	1.320	1.392	1.853
LTE Band 71_Ant 1 TX1	0.701	0.194	0.288	1.308	1.380	1.841
FR1 n12_Ant 1 TX1	0.703	0.194	0.288	1.310	1.382	1.843
FR1 n14_Ant 1 TX1	0.709	0.194	0.288	1.316	1.388	1.849
FR1 n25_Ant 1 Sub TX0	0.714	0.194	0.288	1.321	1.393	1.854
FR1 n26_Ant 1 TX1	0.584	0.194	0.288	1.191	1.263	1.724
FR1 n41_Ant 1 Sub TX0	0.634	0.194	0.288	1.241	1.313	1.774
FR1 n48_Ant 1 Sub TX0	0.709	0.194	0.288	1.316	1.388	1.849
FR1 n66_Ant 1 Sub TX0	0.693	0.194	0.288	1.300	1.372	1.833
FR1 n71_Ant 1 TX1	0.713	0.194	0.288	1.320	1.392	1.853
FR1 n77_Ant 1 Sub TX0	0.690	0.194	0.288	1.297	1.369	1.830

Combination	SAR	SAR peak location (mm)			3D distance (mm)	Summed SAR (W/kg)	SPLSR Results	Simultaneous SAR
		X	Y	Z				
Max WWAN Ant 7	0.658	55.9	-245.2	-173.5	73.0	1.85	0.03	Not required
Max WWAN Ant 1+WLAN2.4G Ant 4+3(3)+WLAN5/6G Ant 4+3(3)	1.196	58.2	-318.2	-174.1				
Max WWAN Ant 7	0.658	55.9	-245.2	-173.5	22.3	0.72	0.03	Not required
WLAN2.4G Ant 4+3(4)	0.066	36.3	-255.9	-174.1				
Max WWAN Ant 7	0.658	55.9	-245.2	-173.5	75.0	0.72	0.01	Not required
WLAN5/6G Ant 4+3(4)	0.063	-7.8	-284.2	-167.2				
Max WWAN Ant 1+WLAN2.4G Ant 4+3(3)+WLAN5/6G Ant 4+3(3)	1.196	58.2	-318.2	-174.1	66.0	1.26	0.02	Not required
WLAN2.4G Ant 4+3(4)	0.066	36.3	-255.9	-174.1				
Max WWAN Ant 1+WLAN2.4G Ant 4+3(3)+WLAN5/6G Ant 4+3(3)	1.196	15.0	-318.8	-174.4	42.1	1.26	0.03	Not required
WLAN5/6G Ant 4+3(4)	0.063	-7.8	-284.2	-167.2				
WLAN2.4G Ant 4+3(4)	0.066	36.3	-255.9	-174.1	52.9	0.13	0.00	Not required
WLAN5/6G Ant 4+3(4)	0.063	-7.8	-284.2	-167.2				

<Case 18>

SPLSR calculation for summation SAR>1.6W/kg

Exposure Position			0	2	7	9	10	11
			WWAN SAR	WLANS/6GHz Ant 4+3	Bluetooth Ant 3	LTE Band 48_Ant 7 TX1	FR1 n48_Ant 7 TX1	FR1 n77_Ant 7 TX1
Right Cheek			1g SAR (W/kg)			0.125	0.197	0.658
						0+2+7+9 Summed SAR	0+2+7+10 Summed SAR	0+2+7+11 Summed SAR
GSM850_Ant 1 TX1			0.703	0.288	0.235	1.351	1.423	1.884
WCDMA V_Ant 1 TX1			0.708	0.288	0.235	1.356	1.428	1.889
LTE Band 12_Ant 1 TX1			0.714	0.288	0.235	1.362	1.434	1.895
LTE Band 13_Ant 1 TX1			0.693	0.288	0.235	1.341	1.413	1.874
LTE Band 14_Ant 1 TX1			0.677	0.288	0.235	1.325	1.397	1.858
LTE Band 25_Ant 1 Sub TX0			0.690	0.288	0.235	1.338	1.410	1.871
LTE Band 26_Ant 1 TX1			0.713	0.288	0.235	1.361	1.433	1.894
LTE Band 66_Ant 1 Sub TX0			0.713	0.288	0.235	1.361	1.433	1.894
LTE Band 71_Ant 1 TX1			0.701	0.288	0.235	1.349	1.421	1.882
FR1 n12_Ant 1 TX1			0.703	0.288	0.235	1.351	1.423	1.884
FR1 n14_Ant 1 TX1			0.709	0.288	0.235	1.357	1.429	1.890
FR1 n25_Ant 1 Sub TX0			0.714	0.288	0.235	1.362	1.434	1.895
FR1 n26_Ant 1 TX1			0.584	0.288	0.235	1.232	1.304	1.765
FR1 n41_Ant 1 Sub TX0			0.634	0.288	0.235	1.282	1.354	1.815
FR1 n48_Ant 1 Sub TX0			0.709	0.288	0.235	1.357	1.429	1.890
FR1 n66_Ant 1 Sub TX0			0.693	0.288	0.235	1.341	1.413	1.874
FR1 n71_Ant 1 TX1			0.713	0.288	0.235	1.361	1.433	1.894
FR1 n77_Ant 1 Sub TX0			0.690	0.288	0.235	1.338	1.410	1.871

SAR peak location (mm)			X (axis)		46.9		56.5		49		56		55.9			
			Y (axis)		Z (axis)		-322.5		-321.3		-262.7		-245.4		-245.2	
							-175.2		-174.1		-175.1		-177.3		-173.5	
X (axis)	Y (axis)	Z (axis)	Exposure Position	0	2	7	9	10	11							
				WWAN SAR	WLANS/6GHz Ant 4+3	Bluetooth Ant 3	LTE Band 48_Ant 7 TX1		FR1 n48_Ant 7 TX1		FR1 n77_Ant 7 TX1					
				Right Cheek			1g SAR (W/kg)			0.125		0.197		0.658		
						0+2+7+9 SPLSR Results			0+2+7+10 SPLSR Results			0+2+7+11 SPLSR Results				
14	-326.2	-176.8	GSM850_Ant 1 TX1	0.703	0.288	0.235								0.03		
12.8	-320.4	-174.1	WCDMA V_Ant 1 TX1	0.708	0.288	0.235								0.03		
14.9	-322.9	-174.3	LTE Band 12_Ant 1 TX1	0.714	0.288	0.235								0.03		
15.5	-321.8	-177.1	LTE Band 13_Ant 1 TX1	0.693	0.288	0.235								0.03		
14.4	-320.3	-177	LTE Band 14_Ant 1 TX1	0.677	0.288	0.235								0.03		
14.5	-329.5	-174.1	LTE Band 25_Ant 1 Sub TX0	0.690	0.288	0.235								0.03		
14.1	-325	-176.9	LTE Band 26_Ant 1 TX1	0.713	0.288	0.235								0.03		
13	-328.6	-174	LTE Band 66_Ant 1 Sub TX0	0.713	0.288	0.235								0.03		
18.1	-327.4	-174.4	LTE Band 71_Ant 1 TX1	0.701	0.288	0.235								0.03		
15.1	-319.7	-174.4	FR1 n12_Ant 1 TX1	0.703	0.288	0.235								0.03		
15	-318.8	-174.4	FR1 n14_Ant 1 TX1	0.709	0.288	0.235								0.03		
20.7	-334.4	-174.2	FR1 n25_Ant 1 Sub TX0	0.714	0.288	0.235								0.03		
16.6	-323.6	-174.5	FR1 n26_Ant 1 TX1	0.584	0.288	0.235								0.03		
12.2	-324	-174.1	FR1 n41_Ant 1 Sub TX0	0.634	0.288	0.235								0.03		
37.2	-334.6	-174.4	FR1 n48_Ant 1 Sub TX0	0.709	0.288	0.235								0.03		
15.8	-332.3	-174	FR1 n66_Ant 1 Sub TX0	0.693	0.288	0.235								0.03		
15	-322.3	-174.3	FR1 n71_Ant 1 TX1	0.713	0.288	0.235								0.03		
36.5	-334.8	-177.2	FR1 n77_Ant 1 Sub TX0	0.690	0.288	0.235								0.03		

<Case 19>

SPLSR calculation for summation SAR>1.6W/kg

Exposure Position	0	2	7	9	10	11
	WWAN SAR	WLAN5/6GHz Ant 4+3	Bluetooth Ant 4	LTE Band 48_Ant 7 TX1	FR1 n48_Ant 7 TX1	FR1 n77_Ant 7 TX1
Right Cheek	1g SAR (W/kg)			0.125	0.197	0.658
				0+2+7+9 Summed SAR	0+2+7+10 Summed SAR	0+2+7+11 Summed SAR
GSM850_Ant 1 TX1	0.703	0.288	0.059	1.175	1.247	1.708
WCDMA V_Ant 1 TX1	0.708	0.288	0.059	1.180	1.252	1.713
LTE Band 12_Ant 1 TX1	0.714	0.288	0.059	1.186	1.258	1.719
LTE Band 13_Ant 1 TX1	0.693	0.288	0.059	1.165	1.237	1.698
LTE Band 14_Ant 1 TX1	0.677	0.288	0.059	1.149	1.221	1.682
LTE Band 25_Ant 1 Sub TX0	0.690	0.288	0.059	1.162	1.234	1.695
LTE Band 26_Ant 1 TX1	0.713	0.288	0.059	1.185	1.257	1.718
LTE Band 66_Ant 1 Sub TX0	0.713	0.288	0.059	1.185	1.257	1.718
LTE Band 71_Ant 1 TX1	0.701	0.288	0.059	1.173	1.245	1.706
FR1 n12_Ant 1 TX1	0.703	0.288	0.059	1.175	1.247	1.708
FR1 n14_Ant 1 TX1	0.709	0.288	0.059	1.181	1.253	1.714
FR1 n25_Ant 1 Sub TX0	0.714	0.288	0.059	1.186	1.258	1.719
FR1 n26_Ant 1 TX1	0.584	0.288	0.059	1.056	1.128	1.589
FR1 n41_Ant 1 Sub TX0	0.634	0.288	0.059	1.106	1.178	1.639
FR1 n48_Ant 1 Sub TX0	0.709	0.288	0.059	1.181	1.253	1.714
FR1 n66_Ant 1 Sub TX0	0.693	0.288	0.059	1.165	1.237	1.698
FR1 n71_Ant 1 TX1	0.713	0.288	0.059	1.185	1.257	1.718
FR1 n77_Ant 1 Sub TX0	0.690	0.288	0.059	1.162	1.234	1.695

Combination	SAR	SAR peak location (mm)			3D distance (mm)	Summed SAR (W/kg)	SPLSR Results	Simultaneous SAR
		X	Y	Z				
Max WWAN Ant 7	0.658	55.9	-245.2	-173.5	77.8	1.66	0.03	Not required
Max WWAN Ant 1+WLAN5/6G Ant 4+3(3)	1.002	46.9	-322.5	-175.2				
Max WWAN Ant 7	0.658	55.9	-245.2	-173.5	28.3	0.72	0.02	Not required
Bluetooth Ant 4	0.059	30.1	-256.8	-172.6				
Max WWAN Ant 7	0.658	55.9	-245.2	-173.5	75.0	0.72	0.01	Not required
WLAN5/6G Ant 4+3(4)	0.063	-7.8	-284.2	-167.2				
Max WWAN Ant 1+WLAN5/6G Ant 4+3(3)	1.002	15.0	-318.8	-174.4	63.8	1.06	0.02	Not required
Bluetooth Ant 4	0.059	30.1	-256.8	-172.6				
Max WWAN Ant 1+WLAN5/6G Ant 4+3(3)	1.002	15.0	-318.8	-174.4	42.1	1.07	0.03	Not required
WLAN5/6G Ant 4+3(4)	0.063	-7.8	-284.2	-167.2				
Bluetooth Ant 4	0.059	30.1	-256.8	-172.6	47.1	0.12	0.00	Not required
WLAN5/6G Ant 4+3(4)	0.063	-7.8	-284.2	-167.2				



<Case 20>

SPLSR calculation for summation SAR>1.6W/kg

Exposure Position	0	2	7	9	10	11
	WWAN SAR	WLAN5/6GHz Ant 4+3	Bluetooth Ant 4+3	LTE Band 48_Ant 7 TXI	FR1 n48_Ant 7 TXI	FR1 n77_Ant 7 TXI
Right Cheek	1g SAR (W/kg)			0.125	0.197	0.658
				0+2+7+9 Summed SAR	0+2+7+10 Summed SAR	0+2+7+11 Summed SAR
GSM850_Ant 1 TXI	0.703	0.288	0.239	1.355	1.427	1.888
WCDMA V_Ant 1 TXI	0.708	0.288	0.239	1.360	1.432	1.893
LTE Band 12_Ant 1 TXI	0.714	0.288	0.239	1.366	1.438	1.899
LTE Band 13_Ant 1 TXI	0.693	0.288	0.239	1.345	1.417	1.878
LTE Band 14_Ant 1 TXI	0.677	0.288	0.239	1.329	1.401	1.862
LTE Band 25_Ant 1 Sub TXI	0.690	0.288	0.239	1.342	1.414	1.875
LTE Band 26_Ant 1 TXI	0.713	0.288	0.239	1.365	1.437	1.898
LTE Band 66_Ant 1 Sub TXI	0.713	0.288	0.239	1.365	1.437	1.898
LTE Band 71_Ant 1 TXI	0.701	0.288	0.239	1.353	1.425	1.886
FR1 n12_Ant 1 TXI	0.703	0.288	0.239	1.355	1.427	1.888
FR1 n14_Ant 1 TXI	0.709	0.288	0.239	1.361	1.433	1.894
FR1 n25_Ant 1 Sub TXI	0.714	0.288	0.239	1.366	1.438	1.899
FR1 n26_Ant 1 TXI	0.584	0.288	0.239	1.236	1.308	1.769
FR1 n41_Ant 1 Sub TXI	0.634	0.288	0.239	1.286	1.358	1.819
FR1 n48_Ant 1 Sub TXI	0.709	0.288	0.239	1.361	1.433	1.894
FR1 n66_Ant 1 Sub TXI	0.693	0.288	0.239	1.345	1.417	1.878
FR1 n71_Ant 1 TXI	0.713	0.288	0.239	1.365	1.437	1.898
FR1 n77_Ant 1 Sub TXI	0.690	0.288	0.239	1.342	1.414	1.875

Combination	SAR	SAR peak location (mm)			3D distance (mm)	Summed SAR (W/kg)	SPLSR Results	Simultaneous SAR
		X	Y	Z				
Max WWAN Ant 7	0.658	55.9	-245.2	-173.5	75.4	1.90	0.03	Not required
Max WWAN Ant 1+Bluetooth Ant 4+3(3)+WLAN5/6G Ant 4+3(3)	1.241	55.2	-320.6	-174.4				
Max WWAN Ant 7	0.658	55.9	-245.2	-173.5	24.1	0.72	0.03	Not required
Bluetooth Ant 4+3(4)	0.062	34.4	-256.0	-173.7				
Max WWAN Ant 7	0.658	55.9	-245.2	-173.5	75.0	0.72	0.01	Not required
WLAN5/6G Ant 4+3(4)	0.063	-7.8	-284.2	-167.2				
Max WWAN Ant 1+Bluetooth Ant 4+3(3)+WLAN5/6G Ant 4+3(3)	1.241	15.0	-318.8	-174.4	65.7	1.30	0.02	Not required
Bluetooth Ant 4+3(4)	0.062	34.4	-256.0	-173.7				
Max WWAN Ant 1+Bluetooth Ant 4+3(3)+WLAN5/6G Ant 4+3(3)	1.241	15.0	-318.8	-174.4	42.1	1.30	0.04	Not required
WLAN5/6G Ant 4+3(4)	0.063	-7.8	-284.2	-167.2				
Bluetooth Ant 4+3(4)	0.062	34.4	-256.0	-173.7	51.2	0.13	0.00	Not required
WLAN5/6G Ant 4+3(4)	0.063	-7.8	-284.2	-167.2				



<Case 21>

SPLSR calculation for summation SAR>1.6W/kg

Exposure Position			0	2	7	9	10	11
			WWAN SAR	WLAN5/6GHz Ant 4+3	Thread Ant 3	LTE Band 48_Ant 7 TX1	FR1 n48_Ant 7 TX1	FR1 n77_Ant 7 TX1
Right Cheek						0.125	0.197	0.658
						0+2+7+9 Summed SAR	0+2+7+10 Summed SAR	0+2+7+11 Summed SAR
GSM850_Ant 1 TX1			0.703	0.288	0.200	1.316	1.388	1.849
WCDMA V_Ant 1 TX1			0.708	0.288	0.200	1.321	1.393	1.854
LTE Band 12_Ant 1 TX1			0.714	0.288	0.200	1.327	1.399	1.860
LTE Band 13_Ant 1 TX1			0.693	0.288	0.200	1.306	1.378	1.839
LTE Band 14_Ant 1 TX1			0.677	0.288	0.200	1.290	1.362	1.823
LTE Band 25_Ant 1 Sub TX0			0.690	0.288	0.200	1.303	1.375	1.836
LTE Band 26_Ant 1 TX1			0.713	0.288	0.200	1.326	1.398	1.859
LTE Band 66_Ant 1 Sub TX0			0.713	0.288	0.200	1.326	1.398	1.859
LTE Band 71_Ant 1 TX1			0.701	0.288	0.200	1.314	1.386	1.847
FR1 n12_Ant 1 TX1			0.703	0.288	0.200	1.316	1.388	1.849
FR1 n14_Ant 1 TX1			0.709	0.288	0.200	1.322	1.394	1.855
FR1 n25_Ant 1 Sub TX0			0.714	0.288	0.200	1.327	1.399	1.860
FR1 n26_Ant 1 TX1			0.584	0.288	0.200	1.197	1.269	1.730
FR1 n41_Ant 1 Sub TX0			0.634	0.288	0.200	1.247	1.319	1.780
FR1 n48_Ant 1 Sub TX0			0.709	0.288	0.200	1.322	1.394	1.855
FR1 n66_Ant 1 Sub TX0			0.693	0.288	0.200	1.306	1.378	1.839
FR1 n71_Ant 1 TX1			0.713	0.288	0.200	1.326	1.398	1.859
FR1 n77_Ant 1 Sub TX0			0.690	0.288	0.200	1.303	1.375	1.836

SAR peak location (mm)			X (axis)		46.9	54.4	49	56	55.9	
			Y (axis)		-322.5	-322.2	-252.7	-245.4	-245.2	
			Z (axis)		-175.2	-174.3	-175.1	-177.3	-173.5	
X (axis)	Y (axis)	Z (axis)	Exposure Position	0	2	7	9	10	11	
				WWAN SAR	WLAN5/6GHz Ant 4+3	Thread Ant 3	LTE Band 48_Ant 7 TX1	FR1 n48_Ant 7 TX1	FR1 n77_Ant 7 TX1	
Right Cheek			1g SAR (W/kg)			0.125	0.197	0.658		
							0+2+7+9 SPLSR Results	0+2+7+10 SPLSR Results	0+2+7+11 SPLSR Results	
14	-326.2	-176.8	GSM850_Ant 1 TX1	0.703	0.288	0.200			0.03	
12.8	-320.4	-174.1	WCDMA V_Ant 1 TX1	0.708	0.288	0.200			0.03	
14.9	-322.9	-174.3	LTE Band 12_Ant 1 TX1	0.714	0.288	0.200			0.03	
15.5	-321.8	-177.1	LTE Band 13_Ant 1 TX1	0.693	0.288	0.200			0.03	
14.4	-320.3	-177	LTE Band 14_Ant 1 TX1	0.677	0.288	0.200			0.03	
14.5	-329.5	-174.1	LTE Band 25_Ant 1 Sub TX0	0.690	0.288	0.200			0.03	
14.1	-325	-176.9	LTE Band 26_Ant 1 TX1	0.713	0.288	0.200			0.03	
18	-328.6	-174	LTE Band 66_Ant 1 Sub TX0	0.713	0.288	0.200			0.03	
18.1	-327.4	-174.4	LTE Band 71_Ant 1 TX1	0.701	0.288	0.200			0.03	
15.1	-319.7	-174.4	FR1 n12_Ant 1 TX1	0.703	0.288	0.200			0.03	
15	-318.8	-174.4	FR1 n14_Ant 1 TX1	0.709	0.288	0.200			0.03	
20.7	-334.4	-174.2	FR1 n25_Ant 1 Sub TX0	0.714	0.288	0.200			0.03	
16.6	-323.6	-174.5	FR1 n26_Ant 1 TX1	0.584	0.288	0.200			0.03	
12.2	-324	-174.1	FR1 n41_Ant 1 Sub TX0	0.634	0.288	0.200			0.03	
37.2	-334.6	-174.4	FR1 n48_Ant 1 Sub TX0	0.709	0.288	0.200			0.03	
15.8	-332.3	-174	FR1 n66_Ant 1 Sub TX0	0.693	0.288	0.200			0.03	
15	-322.3	-174.3	FR1 n71_Ant 1 TX1	0.713	0.288	0.200			0.03	
36.5	-334.8	-177.2	FR1 n77_Ant 1 Sub TX0	0.690	0.288	0.200			0.03	



SPLSR calculation for summation SAR>1.6W/kg

[illegible]

SPLSR calculation for summation SAR>1.6W/kg

BSP calculations for Summary Data - Bowling									
Team	Bowler	Balls	Runs	Wickets	Overs	Maidens	Extras	Total Runs	Total Wickets
Team A	Bowler A	10	50	2	20	5	5	62	2
	Bowler B	10	40	1	15	3	4	47	1
	Bowler C	10	30	3	10	2	3	38	3
	Bowler D	10	20	1	8	1	2	23	1
	Bowler E	10	10	0	4	0	1	11	0
	Bowler F	10	60	0	25	0	6	66	0
	Bowler G	10	70	1	30	0	7	77	1
	Bowler H	10	80	2	35	0	8	88	2
	Bowler I	10	90	3	40	0	9	99	3
	Bowler J	10	100	4	45	0	10	110	4
Team B	Bowler K	10	45	2	18	4	4	55	2
	Bowler L	10	35	1	12	2	3	40	1
	Bowler M	10	25	0	10	1	2	27	0
	Bowler N	10	15	0	6	0	1	16	0
	Bowler O	10	55	1	22	0	5	60	1
	Bowler P	10	65	2	28	0	6	71	2
	Bowler Q	10	75	3	32	0	7	82	3
	Bowler R	10	85	4	38	0	8	93	4
	Bowler S	10	95	5	42	0	9	104	5
	Bowler T	10	105	6	48	0	10	115	6
Team C	Bowler U	10	50	1	20	3	4	58	1
	Bowler V	10	40	0	15	2	3	45	0
	Bowler W	10	30	2	10	1	2	33	2
	Bowler X	10	20	1	8	0	1	21	1
	Bowler Y	10	10	0	4	0	1	11	0
	Bowler Z	10	60	1	25	0	5	65	1
	Bowler AA	10	70	2	30	0	6	76	2
	Bowler AB	10	80	3	35	0	7	87	3
	Bowler AC	10	90	4	40	0	8	98	4
	Bowler AD	10	100	5	45	0	9	109	5

SPLSR calculation for summation SAR>1.6W/kg

Year		Quarter		Month		Day		Hour		Minute		Second		Millisecond		Microsecond		Nanosecond		Picosecond		Femtosecond		Attosecond		Zeptosecond		Yoctosecond		Xenosecond		Planck time		String time		Quantum time		Heisenberg time		Schrödinger time		Dirac time		Feynman time		Gell-Mann time		Higgs time		Planck length		String length		Quantum length		Heisenberg length		Schrödinger length		Dirac length		Feynman length		Gell-Mann length		Higgs length		Planck mass		String mass		Quantum mass		Heisenberg mass		Schrödinger mass		Dirac mass		Feynman mass		Gell-Mann mass		Higgs mass		Planck energy		String energy		Quantum energy		Heisenberg energy		Schrödinger energy		Dirac energy		Feynman energy		Gell-Mann energy		Higgs energy		Planck force		String force		Quantum force		Heisenberg force		Schrödinger force		Dirac force		Feynman force		Gell-Mann force		Higgs force		Planck temperature		String temperature		Quantum temperature		Heisenberg temperature		Schrödinger temperature		Dirac temperature		Feynman temperature		Gell-Mann temperature		Higgs temperature		Planck pressure		String pressure		Quantum pressure		Heisenberg pressure		Schrödinger pressure		Dirac pressure		Feynman pressure		Gell-Mann pressure		Higgs pressure		Planck density		String density		Quantum density		Heisenberg density		Schrödinger density		Dirac density		Feynman density		Gell-Mann density		Higgs density		Planck viscosity		String viscosity		Quantum viscosity		Heisenberg viscosity		Schrödinger viscosity		Dirac viscosity		Feynman viscosity		Gell-Mann viscosity		Higgs viscosity		Planck conductivity		String conductivity		Quantum conductivity		Heisenberg conductivity		Schrödinger conductivity		Dirac conductivity		Feynman conductivity		Gell-Mann conductivity		Higgs conductivity		Planck permeability		String permeability		Quantum permeability		Heisenberg permeability		Schrödinger permeability		Dirac permeability		Feynman permeability		Gell-Mann permeability		Higgs permeability		Planck magnetism		String magnetism		Quantum magnetism		Heisenberg magnetism		Schrödinger magnetism		Dirac magnetism		Feynman magnetism		Gell-Mann magnetism		Higgs magnetism		Planck electric field		String electric field		Quantum electric field		Heisenberg electric field		Schrödinger electric field		Dirac electric field		Feynman electric field		Gell-Mann electric field		Higgs electric field		Planck magnetic field		String magnetic field		Quantum magnetic field		Heisenberg magnetic field		Schrödinger magnetic field		Dirac magnetic field		Feynman magnetic field		Gell-Mann magnetic field		Higgs magnetic field		Planck acceleration		String acceleration		Quantum acceleration		Heisenberg acceleration		Schrödinger acceleration		Dirac acceleration		Feynman acceleration		Gell-Mann acceleration		Higgs acceleration		Planck velocity		String velocity		Quantum velocity		Heisenberg velocity		Schrödinger velocity		Dirac velocity		Feynman velocity		Gell-Mann velocity		Higgs velocity		Planck frequency		String frequency		Quantum frequency		Heisenberg frequency		Schrödinger frequency		Dirac frequency		Feynman frequency		Gell-Mann frequency		Higgs frequency		Planck wavelength		String wavelength		Quantum wavelength		Heisenberg wavelength		Schrödinger wavelength		Dirac wavelength		Feynman wavelength		Gell-Mann wavelength		Higgs wavelength		Planck momentum		String momentum		Quantum momentum		Heisenberg momentum		Schrödinger momentum		Dirac momentum		Feynman momentum		Gell-Mann momentum		Higgs momentum		Planck angular momentum		String angular momentum		Quantum angular momentum		Heisenberg angular momentum		Schrödinger angular momentum		Dirac angular momentum		Feynman angular momentum		Gell-Mann angular momentum		Higgs angular momentum		Planck torque		String torque		Quantum torque		Heisenberg torque		Schrödinger torque		Dirac torque		Feynman torque		Gell-Mann torque		Higgs torque		Planck power		String power		Quantum power		Heisenberg power		Schrödinger power		Dirac power		Feynman power		Gell-Mann power		Higgs power		Planck energy density		String energy density		Quantum energy density		Heisenberg energy density		Schrödinger energy density		Dirac energy density		Feynman energy density		Gell-Mann energy density		Higgs energy density		Planck force density		String force density		Quantum force density		Heisenberg force density		Schrödinger force density		Dirac force density		Feynman force density		Gell-Mann force density		Higgs force density		Planck pressure density		String pressure density		Quantum pressure density		Heisenberg pressure density		Schrödinger pressure density		Dirac pressure density		Feynman pressure density		Gell-Mann pressure density		Higgs pressure density		Planck viscosity density		String viscosity density		Quantum viscosity density		Heisenberg viscosity density		Schrödinger viscosity density		Dirac viscosity density		Feynman viscosity density		Gell-Mann viscosity density		Higgs viscosity density		Planck conductivity density		String conductivity density		Quantum conductivity density		Heisenberg conductivity density		Schrödinger conductivity density		Dirac conductivity density		Feynman conductivity density		Gell-Mann conductivity density		Higgs conductivity density		Planck permeability density		String permeability density		Quantum permeability density		Heisenberg permeability density		Schrödinger permeability density		Dirac permeability density		Feynman permeability density		Gell-Mann permeability density		Higgs permeability density		Planck magnetism density		String magnetism density		Quantum magnetism density		Heisenberg magnetism density		Schrödinger magnetism density		Dirac magnetism density		Feynman magnetism density		Gell-Mann magnetism density		Higgs magnetism density		Planck electric field density		String electric field density		Quantum electric field density		Heisenberg electric field density		Schrödinger electric field density		Dirac electric field density		Feynman electric field density		Gell-Mann electric field density		Higgs electric field density		Planck magnetic field density		String magnetic field density		Quantum magnetic field density		Heisenberg magnetic field density		Schrödinger magnetic field density		Dirac magnetic field density		Feynman magnetic field density		Gell-Mann magnetic field density		Higgs magnetic field density		Planck acceleration density		String acceleration density		Quantum acceleration density		Heisenberg acceleration density		Schrödinger acceleration density		Dirac acceleration density		Feynman acceleration density		Gell-Mann acceleration density		Higgs acceleration density		Planck velocity density		String velocity density		Quantum velocity density		Heisenberg velocity density		Schrödinger velocity density		Dirac velocity density		Feynman velocity density		Gell-Mann velocity density		Higgs velocity density		Planck frequency density		String frequency density		Quantum frequency density		Heisenberg frequency density		Schrödinger frequency density		Dirac frequency density		Feynman frequency density		Gell-Mann frequency density		Higgs frequency density		Planck wavelength density		String wavelength density		Quantum wavelength density		Heisenberg wavelength density		Schrödinger wavelength density		Dirac wavelength density		Feynman wavelength density		Gell-Mann wavelength density		Higgs wavelength density		Planck momentum density		String momentum density		Quantum momentum density		Heisenberg momentum density		S	
------	--	---------	--	-------	--	-----	--	------	--	--------	--	--------	--	-------------	--	-------------	--	------------	--	------------	--	-------------	--	------------	--	-------------	--	-------------	--	------------	--	-------------	--	-------------	--	--------------	--	-----------------	--	------------------	--	------------	--	--------------	--	----------------	--	------------	--	---------------	--	---------------	--	----------------	--	-------------------	--	--------------------	--	--------------	--	----------------	--	------------------	--	--------------	--	-------------	--	-------------	--	--------------	--	-----------------	--	------------------	--	------------	--	--------------	--	----------------	--	------------	--	---------------	--	---------------	--	----------------	--	-------------------	--	--------------------	--	--------------	--	----------------	--	------------------	--	--------------	--	--------------	--	--------------	--	---------------	--	------------------	--	-------------------	--	-------------	--	---------------	--	-----------------	--	-------------	--	--------------------	--	--------------------	--	---------------------	--	------------------------	--	-------------------------	--	-------------------	--	---------------------	--	-----------------------	--	-------------------	--	-----------------	--	-----------------	--	------------------	--	---------------------	--	----------------------	--	----------------	--	------------------	--	--------------------	--	----------------	--	----------------	--	----------------	--	-----------------	--	--------------------	--	---------------------	--	---------------	--	-----------------	--	-------------------	--	---------------	--	------------------	--	------------------	--	-------------------	--	----------------------	--	-----------------------	--	-----------------	--	-------------------	--	---------------------	--	-----------------	--	---------------------	--	---------------------	--	----------------------	--	-------------------------	--	--------------------------	--	--------------------	--	----------------------	--	------------------------	--	--------------------	--	---------------------	--	---------------------	--	----------------------	--	-------------------------	--	--------------------------	--	--------------------	--	----------------------	--	------------------------	--	--------------------	--	------------------	--	------------------	--	-------------------	--	----------------------	--	-----------------------	--	-----------------	--	-------------------	--	---------------------	--	-----------------	--	-----------------------	--	-----------------------	--	------------------------	--	---------------------------	--	----------------------------	--	----------------------	--	------------------------	--	--------------------------	--	----------------------	--	-----------------------	--	-----------------------	--	------------------------	--	---------------------------	--	----------------------------	--	----------------------	--	------------------------	--	--------------------------	--	----------------------	--	---------------------	--	---------------------	--	----------------------	--	-------------------------	--	--------------------------	--	--------------------	--	----------------------	--	------------------------	--	--------------------	--	-----------------	--	-----------------	--	------------------	--	---------------------	--	----------------------	--	----------------	--	------------------	--	--------------------	--	----------------	--	------------------	--	------------------	--	-------------------	--	----------------------	--	-----------------------	--	-----------------	--	-------------------	--	---------------------	--	-----------------	--	-------------------	--	-------------------	--	--------------------	--	-----------------------	--	------------------------	--	------------------	--	--------------------	--	----------------------	--	------------------	--	-----------------	--	-----------------	--	------------------	--	---------------------	--	----------------------	--	----------------	--	------------------	--	--------------------	--	----------------	--	-------------------------	--	-------------------------	--	--------------------------	--	-----------------------------	--	------------------------------	--	------------------------	--	--------------------------	--	----------------------------	--	------------------------	--	---------------	--	---------------	--	----------------	--	-------------------	--	--------------------	--	--------------	--	----------------	--	------------------	--	--------------	--	--------------	--	--------------	--	---------------	--	------------------	--	-------------------	--	-------------	--	---------------	--	-----------------	--	-------------	--	-----------------------	--	-----------------------	--	------------------------	--	---------------------------	--	----------------------------	--	----------------------	--	------------------------	--	--------------------------	--	----------------------	--	----------------------	--	----------------------	--	-----------------------	--	--------------------------	--	---------------------------	--	---------------------	--	-----------------------	--	-------------------------	--	---------------------	--	-------------------------	--	-------------------------	--	--------------------------	--	-----------------------------	--	------------------------------	--	------------------------	--	--------------------------	--	----------------------------	--	------------------------	--	--------------------------	--	--------------------------	--	---------------------------	--	------------------------------	--	-------------------------------	--	-------------------------	--	---------------------------	--	-----------------------------	--	-------------------------	--	-----------------------------	--	-----------------------------	--	------------------------------	--	---------------------------------	--	----------------------------------	--	----------------------------	--	------------------------------	--	--------------------------------	--	----------------------------	--	-----------------------------	--	-----------------------------	--	------------------------------	--	---------------------------------	--	----------------------------------	--	----------------------------	--	------------------------------	--	--------------------------------	--	----------------------------	--	--------------------------	--	--------------------------	--	---------------------------	--	------------------------------	--	-------------------------------	--	-------------------------	--	---------------------------	--	-----------------------------	--	-------------------------	--	-------------------------------	--	-------------------------------	--	--------------------------------	--	-----------------------------------	--	------------------------------------	--	------------------------------	--	--------------------------------	--	----------------------------------	--	------------------------------	--	-------------------------------	--	-------------------------------	--	--------------------------------	--	-----------------------------------	--	------------------------------------	--	------------------------------	--	--------------------------------	--	----------------------------------	--	------------------------------	--	-----------------------------	--	-----------------------------	--	------------------------------	--	---------------------------------	--	----------------------------------	--	----------------------------	--	------------------------------	--	--------------------------------	--	----------------------------	--	-------------------------	--	-------------------------	--	--------------------------	--	-----------------------------	--	------------------------------	--	------------------------	--	--------------------------	--	----------------------------	--	------------------------	--	--------------------------	--	--------------------------	--	---------------------------	--	------------------------------	--	-------------------------------	--	-------------------------	--	---------------------------	--	-----------------------------	--	-------------------------	--	---------------------------	--	---------------------------	--	----------------------------	--	-------------------------------	--	--------------------------------	--	--------------------------	--	----------------------------	--	------------------------------	--	--------------------------	--	-------------------------	--	-------------------------	--	--------------------------	--	-----------------------------	--	---	--

SPLSR calculation for summation SAR>1.6W/kg

[illegible]



<Case 26>

SPLSR calculation for summation SAR>1.6W/kg

[illegible]

<Case 27>

SPLSR calculation for summation SAR>1.6W/kg

[illegible]

<Case 28>

SPLSR calculation for summation SAR>1.6W/kg

[illegible]



<Case 37>

SPLSR calculation for summation SAR>1.6W/kg

Exposure Position		0	1	2	9	10	11
		WWAN SAR	WLAN2.4GHz Ant 3	WLAN5/6GHz Ant 4+3	LTE Band 48_Ant 6 TX0	FR1 n48_Ant 6 TX0	FR1 n77_Ant 6 TX0
Back		1g SAR (W/kg)			0.317	0.341	0.485
					0+1+2+9 Summed SAR	0+1+2+10 Summed SAR	0+1+2+11 Summed SAR
GSM850_Ant 1 TX0		0.640	0.157	0.142	1.256	1.280	1.424
WCDMA V_Ant 1 TX0		0.490	0.157	0.142	1.106	1.130	1.274
LTE Band 12_Ant 1 TX0		0.351	0.157	0.142	0.967	0.991	1.135
LTE Band 13_Ant 1 TX0		0.515	0.157	0.142	1.131	1.155	1.299
LTE Band 14_Ant 1 TX0		0.520	0.157	0.142	1.136	1.160	1.304
LTE Band 25_Ant 1 Sub TX0		0.842	0.157	0.142	1.458	1.482	1.626
LTE Band 26_Ant 1 TX0		0.417	0.157	0.142	1.033	1.057	1.201
LTE Band 66_Ant 1 Sub TX0		0.832	0.157	0.142	1.448	1.472	1.616
LTE Band 71_Ant 1 TX0		0.289	0.157	0.142	0.905	0.929	1.073
FR1 n12_Ant 1 TX0		0.422	0.157	0.142	1.038	1.062	1.206
FR1 n14_Ant 1 TX0		0.533	0.157	0.142	1.149	1.173	1.317
FR1 n25_Ant 1 Sub TX0		0.746	0.157	0.142	1.362	1.386	1.530
FR1 n26_Ant 1 TX0		0.424	0.157	0.142	1.040	1.064	1.208
FR1 n41_Ant 1 Sub TX0		0.764	0.157	0.142	1.380	1.404	1.548
FR1 n48_Ant 1 Sub TX0		0.343	0.157	0.142	0.959	0.983	1.127
FR1 n66_Ant 1 Sub TX0		0.722	0.157	0.142	1.338	1.362	1.506
FR1 n71_Ant 1 TX0		0.346	0.157	0.142	0.962	0.986	1.130
FR1 n77_Ant 1 Sub TX0		0.315	0.157	0.142	0.931	0.955	1.099

SAR peak location (mm)			X (axis)		14	11.3	12	-23	11
			Y (axis)		30.5	44.7	-57	-75.5	-47
			Z (axis)		-207	-207	-207	-207	-207
X (axis)	Y (axis)	Z (axis)	Exposure Position	0	1	2	9	10	11
			WWAN SAR	WLAN2.4GHz Ant 3	WLAN5/6GHz Ant 4+3	LTE Band 48_Ant 6 TX0	FR1 n48_Ant 6 TX0	FR1 n77_Ant 6 TX0	
			Back	1g SAR (W/kg)			0.317 0+1+2+9 SPLSR Results	0.341 0+1+2+10 SPLSR Results	0.485 0+1+2+11 SPLSR Results
4.6	56.1	-207	GSM850_Ant 1 TX0	0.640	0.157	0.142			
4.1	56.8	-207	WCDMA V_Ant 1 TX0	0.490	0.157	0.142			
8	56.8	-207	LTE Band 12_Ant 1 TX0	0.351	0.157	0.142			
6.3	53.8	-207	LTE Band 13_Ant 1 TX0	0.515	0.157	0.142			
2.8	56.3	-207	LTE Band 14_Ant 1 TX0	0.520	0.157	0.142			
1.9	76.6	-207	LTE Band 25_Ant 1 Sub TX0	0.842	0.157	0.142			0.03
1.9	55.1	-207	LTE Band 26_Ant 1 TX0	0.417	0.157	0.142			
-2.4	75.9	-207	LTE Band 66_Ant 1 Sub TX0	0.832	0.157	0.142			0.03
5.1	55.8	-207	LTE Band 71_Ant 1 TX0	0.289	0.157	0.142			
3.6	56.1	-207	FR1 n12_Ant 1 TX0	0.422	0.157	0.142			
0.3	56.1	-207	FR1 n14_Ant 1 TX0	0.533	0.157	0.142			
0.9	79.6	-207	FR1 n25_Ant 1 Sub TX0	0.746	0.157	0.142			
1.3	56.6	-207	FR1 n26_Ant 1 TX0	0.424	0.157	0.142			
-5	77	-207	FR1 n41_Ant 1 Sub TX0	0.764	0.157	0.142			
-35.5	80	-207	FR1 n48_Ant 1 Sub TX0	0.343	0.157	0.142			
3.6	78.9	-207	FR1 n66_Ant 1 Sub TX0	0.722	0.157	0.142			
4.1	55.1	-207	FR1 n71_Ant 1 TX0	0.346	0.157	0.142			
14.5	65	-207	FR1 n77_Ant 1 Sub TX0	0.315	0.157	0.142			

<Case 38>

SPLSR calculation for summation SAR>1.6W/kg

Exposure Position			0	1	2	9	10	11
			WWAN SAR	WLAN2.4GHz Ant 4+3	WLAN5/6GHz Ant 4+3	LTE Band 48_Ant 6 TX0	FR1 n48_Ant 6 TX0	FR1 n77_Ant 6 TX0
Back			1g SAR (W/kg)			0.317	0.341	0.485
						0+1+2+9 Summed SAR	0+1+2+10 Summed SAR	0+1+2+11 Summed SAR
GSM850_Ant 1 TX0			0.640	0.145	0.142	1.244	1.268	1.412
WCDMA V_Ant 1 TX0			0.490	0.145	0.142	1.094	1.118	1.262
LTE Band 12_Ant 1 TX0			0.351	0.145	0.142	0.955	0.979	1.123
LTE Band 13_Ant 1 TX0			0.515	0.145	0.142	1.119	1.143	1.287
LTE Band 14_Ant 1 TX0			0.520	0.145	0.142	1.124	1.148	1.292
LTE Band 25_Ant 1 Sub TX0			0.842	0.145	0.142	1.446	1.470	1.614
LTE Band 26_Ant 1 TX0			0.417	0.145	0.142	1.021	1.045	1.189
LTE Band 66_Ant 1 Sub TX0			0.832	0.145	0.142	1.436	1.460	1.604
LTE Band 71_Ant 1 TX0			0.289	0.145	0.142	0.893	0.917	1.061
FR1 n12_Ant 1 TX0			0.422	0.145	0.142	1.026	1.050	1.194
FR1 n14_Ant 1 TX0			0.533	0.145	0.142	1.137	1.161	1.305
FR1 n25_Ant 1 Sub TX0			0.746	0.145	0.142	1.350	1.374	1.518
FR1 n26_Ant 1 TX0			0.424	0.145	0.142	1.028	1.052	1.196
FR1 n41_Ant 1 Sub TX0			0.764	0.145	0.142	1.368	1.392	1.536
FR1 n48_Ant 1 Sub TX0			0.343	0.145	0.142	0.947	0.971	1.115
FR1 n66_Ant 1 Sub TX0			0.722	0.145	0.142	1.326	1.350	1.494
FR1 n71_Ant 1 TX0			0.346	0.145	0.142	0.950	0.974	1.118
FR1 n77_Ant 1 Sub TX0			0.315	0.145	0.142	0.919	0.943	1.087

SAR peak location (mm)			X (axis)		16		11.3		12		-23		11	
			Y (axis)		30		44.7		-57		-75.5		-47	
			Z (axis)		-207		-207		-207		-207		-207	
X (axis)	Y (axis)	Z (axis)	Exposure Position	0	1	2	9	10	11					
			WWAN SAR	WLAN2.4GHz Ant 4+3	WLAN5/6GHz Ant 4+3	LTE Band 48_Ant 6 TX0	FR1 n48_Ant 6 TX0	FR1 n77_Ant 6 TX0						
			Back	1g SAR (W/kg)			0.317	0.341	0.485					
							0+1+2+9 SPLSR Results	0+1+2+10 SPLSR Results	0+1+2+11 SPLSR Results					
4.6	56.1	-207	GSM850_Ant 1 TX0	0.640	0.145	0.142								
4.1	56.8	-207	WCDMA V_Ant 1 TX0	0.490	0.145	0.142								
8	56.8	-207	LTE Band 12_Ant 1 TX0	0.351	0.145	0.142								
6.3	53.8	-207	LTE Band 13_Ant 1 TX0	0.515	0.145	0.142								
2.8	56.3	-207	LTE Band 14_Ant 1 TX0	0.520	0.145	0.142								
1.9	76.6	-207	LTE Band 25_Ant 1 Sub TX0	0.842	0.145	0.142			0.03					
1.9	55.1	-207	LTE Band 26_Ant 1 TX0	0.417	0.145	0.142								
-2.4	75.9	-207	LTE Band 66_Ant 1 Sub TX0	0.832	0.145	0.142			0.03					
5.1	55.8	-207	LTE Band 71_Ant 1 TX0	0.289	0.145	0.142								
3.6	56.1	-207	FR1 n12_Ant 1 TX0	0.422	0.145	0.142								
0.3	56.1	-207	FR1 n14_Ant 1 TX0	0.533	0.145	0.142								
0.9	79.6	-207	FR1 n25_Ant 1 Sub TX0	0.746	0.145	0.142								
1.3	56.6	-207	FR1 n26_Ant 1 TX0	0.424	0.145	0.142								
-5	77	-207	FR1 n41_Ant 1 Sub TX0	0.764	0.145	0.142								
-35.5	80	-207	FR1 n48_Ant 1 Sub TX0	0.343	0.145	0.142								
3.6	78.9	-207	FR1 n66_Ant 1 Sub TX0	0.722	0.145	0.142								
4.1	55.1	-207	FR1 n71_Ant 1 TX0	0.346	0.145	0.142								
14.5	65	-207	FR1 n77_Ant 1 Sub TX0	0.315	0.145	0.142								

<Case 39>

SPLSR calculation for summation SAR>1.6W/kg

Exposure Position	0	1	7	9	10	11
	WWAN SAR	WLANS/6GHz Ant 4+3	Bluetooth Ant 3	LTE Band 48_Ant 6 TXD	FR1 n48_Ant 6 TXD	FR1 n77_Ant 6 TXD
Back	1g SAR (W/kg)			0.317	0.341	0.485
				0+1+7+9 Summed SAR	0+1+7+10 Summed SAR	0+1+7+11 Summed SAR
GSM850_Ant 1 TXI	0.640	0.142	0.210	1.309	1.333	1.477
WCDMA V_Ant 1 TXI	0.490	0.142	0.210	1.159	1.183	1.327
LTE Band 12_Ant 1 TXI	0.351	0.142	0.210	1.020	1.044	1.188
LTE Band 13_Ant 1 TXI	0.515	0.142	0.210	1.184	1.208	1.352
LTE Band 14_Ant 1 TXI	0.520	0.142	0.210	1.189	1.213	1.357
LTE Band 25_Ant 1 Sub TXD	0.842	0.142	0.210	1.511	1.535	1.679
LTE Band 26_Ant 1 TXI	0.417	0.142	0.210	1.086	1.110	1.254
LTE Band 66_Ant 1 Sub TXD	0.832	0.142	0.210	1.501	1.525	1.669
LTE Band 71_Ant 1 TXI	0.289	0.142	0.210	0.958	0.982	1.126
FR1 n12_Ant 1 TXI	0.422	0.142	0.210	1.091	1.115	1.259
FR1 n14_Ant 1 TXI	0.533	0.142	0.210	1.202	1.226	1.370
FR1 n25_Ant 1 Sub TXD	0.746	0.142	0.210	1.415	1.439	1.583
FR1 n26_Ant 1 TXI	0.424	0.142	0.210	1.093	1.117	1.261
FR1 n41_Ant 1 Sub TXD	0.764	0.142	0.210	1.433	1.457	1.601
FR1 n48_Ant 1 Sub TXD	0.343	0.142	0.210	1.012	1.036	1.180
FR1 n66_Ant 1 Sub TXD	0.722	0.142	0.210	1.391	1.415	1.559
FR1 n71_Ant 1 TXI	0.346	0.142	0.210	1.015	1.039	1.183
FR1 n77_Ant 1 Sub TXD	0.315	0.142	0.210	0.984	1.008	1.152

SAR peak location (mm)			X (axis)		11.3		11		12		-23		11	
			Y (axis)		44.7		31.5		-57		-75.5		-47	
			Z (axis)		-207		-207		-207		-207		-207	
X (axis)	Y (axis)	Z (axis)	Exposure Position	0	1	7	9	10	11					
				WWAN SAR	WLANS/6GHz Ant 4+3	Bluetooth Ant 3	LTE Band 48_Ant 6 TXD	FR1 n48_Ant 6 TXD	FR1 n77_Ant 6 TXD					
			Back	1g SAR (W/kg)			0.317	0.341	0.485					
						0+1+7+9 SPLSR Results	0+1+7+10 SPLSR Results	0+1+7+11 SPLSR Results						
4.6	56.1	-207	GSM850_Ant 1 TXI	0.640	0.142	0.210								
4.1	56.8	-207	WCDMA V_Ant 1 TXI	0.490	0.142	0.210								
8	56.8	-207	LTE Band 12_Ant 1 TXI	0.351	0.142	0.210								
6.3	53.8	-207	LTE Band 13_Ant 1 TXI	0.515	0.142	0.210								
2.8	56.3	-207	LTE Band 14_Ant 1 TXI	0.520	0.142	0.210								
1.9	76.6	-207	LTE Band 25_Ant 1 Sub TXD	0.842	0.142	0.210			0.03					
1.9	55.1	-207	LTE Band 26_Ant 1 TXI	0.417	0.142	0.210								
-2.4	75.9	-207	LTE Band 66_Ant 1 Sub TXD	0.832	0.142	0.210			0.03					
5.1	55.8	-207	LTE Band 71_Ant 1 TXI	0.289	0.142	0.210								
3.6	56.1	-207	FR1 n12_Ant 1 TXI	0.422	0.142	0.210								
0.3	56.1	-207	FR1 n14_Ant 1 TXI	0.533	0.142	0.210								
0.9	79.6	-207	FR1 n25_Ant 1 Sub TXD	0.746	0.142	0.210								
1.3	56.6	-207	FR1 n26_Ant 1 TXI	0.424	0.142	0.210								
-5	77	-207	FR1 n41_Ant 1 Sub TXD	0.764	0.142	0.210			0.03					
-35.5	80	-207	FR1 n48_Ant 1 Sub TXD	0.343	0.142	0.210								
3.6	78.9	-207	FR1 n66_Ant 1 Sub TXD	0.722	0.142	0.210								
4.1	55.1	-207	FR1 n71_Ant 1 TXI	0.346	0.142	0.210								
14.5	65	-207	FR1 n77_Ant 1 Sub TXD	0.315	0.142	0.210								

<Case 40>

SPLSR calculation for summation SAR>1.6W/kg

Exposure Position		0	1	7	9	10	11
		WWAN SAR	WLANS/6GHz Ant 4+3	Bluetooth Ant 4	LTE Band 48_Ant 6 TX0	FR1 n48_Ant 6 TX0	FR1 n77_Ant 6 TX0
Back		1g SAR (W/kg)			0.317	0.341	0.485
					0+1+7+9 Summed SAR	0+1+7+10 Summed SAR	0+1+7+11 Summed SAR
GSM850_Ant 1 TX0		0.640	0.142	0.194	1.293	1.317	1.461
WCDMA V_Ant 1 TX0		0.490	0.142	0.194	1.143	1.167	1.311
LTE Band 12_Ant 1 TX0		0.351	0.142	0.194	1.004	1.028	1.172
LTE Band 13_Ant 1 TX0		0.515	0.142	0.194	1.168	1.192	1.336
LTE Band 14_Ant 1 TX0		0.520	0.142	0.194	1.173	1.197	1.341
LTE Band 25_Ant 1 Sub TX0		0.842	0.142	0.194	1.495	1.519	1.663
LTE Band 26_Ant 1 TX0		0.417	0.142	0.194	1.070	1.094	1.238
LTE Band 66_Ant 1 Sub TX0		0.832	0.142	0.194	1.485	1.509	1.653
LTE Band 71_Ant 1 TX0		0.289	0.142	0.194	0.942	0.966	1.110
FR1 n12_Ant 1 TX0		0.422	0.142	0.194	1.075	1.099	1.243
FR1 n14_Ant 1 TX0		0.533	0.142	0.194	1.186	1.210	1.354
FR1 n25_Ant 1 Sub TX0		0.746	0.142	0.194	1.399	1.423	1.567
FR1 n26_Ant 1 TX0		0.424	0.142	0.194	1.077	1.101	1.245
FR1 n41_Ant 1 Sub TX0		0.764	0.142	0.194	1.417	1.441	1.585
FR1 n48_Ant 1 Sub TX0		0.343	0.142	0.194	0.996	1.020	1.164
FR1 n66_Ant 1 Sub TX0		0.722	0.142	0.194	1.375	1.399	1.543
FR1 n71_Ant 1 TX0		0.346	0.142	0.194	0.999	1.023	1.167
FR1 n77_Ant 1 Sub TX0		0.315	0.142	0.194	0.968	0.992	1.136

SAR peak location (mm)			X (axis)		11.3		-59.5		12		-23		11	
			Y (axis)		44.7		35.5		-57		-75.5		-47	
			Z (axis)		-207		-207		-207		-207		-207	
X (axis)	Y (axis)	Z (axis)	Exposure Position	0	1	7	9	10	11					
			WWAN SAR	WLANS/6GHz Ant 4+3	Bluetooth Ant 4	LTE Band 48_Ant 6 TX0	FR1 n48_Ant 6 TX0	FR1 n77_Ant 6 TX0						
			Back	1g SAR (W/kg)				0.317	0.341	0.485				
							0+1+7+9 SPLSR Results	0+1+7+10 SPLSR Results	0+1+7+11 SPLSR Results					
4.6	56.1	-207	GSM850_Ant 1 TX0	0.640	0.142	0.194								
4.1	56.8	-207	WCDMA V_Ant 1 TX0	0.490	0.142	0.194								
8	56.8	-207	LTE Band 12_Ant 1 TX0	0.351	0.142	0.194								
6.3	53.8	-207	LTE Band 13_Ant 1 TX0	0.515	0.142	0.194								
2.8	56.3	-207	LTE Band 14_Ant 1 TX0	0.520	0.142	0.194								
1.9	76.6	-207	LTE Band 25_Ant 1 Sub TX0	0.842	0.142	0.194			0.02					
1.9	55.1	-207	LTE Band 26_Ant 1 TX0	0.417	0.142	0.194								
-2.4	75.9	-207	LTE Band 66_Ant 1 Sub TX0	0.832	0.142	0.194			0.02					
5.1	55.8	-207	LTE Band 71_Ant 1 TX0	0.289	0.142	0.194								
3.6	56.1	-207	FR1 n12_Ant 1 TX0	0.422	0.142	0.194								
0.3	56.1	-207	FR1 n14_Ant 1 TX0	0.533	0.142	0.194								
0.9	79.6	-207	FR1 n25_Ant 1 Sub TX0	0.746	0.142	0.194								
1.3	56.6	-207	FR1 n26_Ant 1 TX0	0.424	0.142	0.194								
-5	77	-207	FR1 n41_Ant 1 Sub TX0	0.764	0.142	0.194								
-35.5	80	-207	FR1 n48_Ant 1 Sub TX0	0.343	0.142	0.194								
3.6	78.9	-207	FR1 n66_Ant 1 Sub TX0	0.722	0.142	0.194								
4.1	55.1	-207	FR1 n71_Ant 1 TX0	0.346	0.142	0.194								
14.5	65	-207	FR1 n77_Ant 1 Sub TX0	0.315	0.142	0.194								



<Case 41>

SPLSR calculation for summation SAR>1.6W/kg

Exposure Position	0	1	7	9	10	11
	WWAN SAR	WLANS/6GHz Ant 4+3	Bluetooth Ant 4+3	LTE Band 48_Ant 6 TXD	FR1 n48_Ant 6 TXD	FR1 n77_Ant 6 TXD
Back	1g SAR (W/kg)			0.317	0.341	0.485
				0+1+7+9 Summed SAR	0+1+7+10 Summed SAR	0+1+7+11 Summed SAR
GSM850_Ant 1 TXI	0.640	0.142	0.148	1.247	1.271	1.415
WCDMA V_Ant 1 TXI	0.490	0.142	0.148	1.097	1.121	1.265
LTE Band 12_Ant 1 TXI	0.351	0.142	0.148	0.958	0.982	1.126
LTE Band 13_Ant 1 TXI	0.515	0.142	0.148	1.122	1.146	1.290
LTE Band 14_Ant 1 TXI	0.520	0.142	0.148	1.127	1.151	1.295
LTE Band 25_Ant 1 Sub TXD	0.842	0.142	0.148	1.449	1.473	1.617
LTE Band 26_Ant 1 TXI	0.417	0.142	0.148	1.024	1.048	1.192
LTE Band 66_Ant 1 Sub TXD	0.832	0.142	0.148	1.439	1.463	1.607
LTE Band 71_Ant 1 TXI	0.289	0.142	0.148	0.896	0.920	1.064
FR1 n12_Ant 1 TXI	0.422	0.142	0.148	1.029	1.053	1.197
FR1 n14_Ant 1 TXI	0.533	0.142	0.148	1.140	1.164	1.308
FR1 n25_Ant 1 Sub TXD	0.746	0.142	0.148	1.353	1.377	1.521
FR1 n26_Ant 1 TXI	0.424	0.142	0.148	1.031	1.055	1.199
FR1 n41_Ant 1 Sub TXD	0.764	0.142	0.148	1.371	1.395	1.539
FR1 n48_Ant 1 Sub TXD	0.343	0.142	0.148	0.950	0.974	1.118
FR1 n66_Ant 1 Sub TXD	0.722	0.142	0.148	1.329	1.353	1.497
FR1 n71_Ant 1 TXI	0.346	0.142	0.148	0.953	0.977	1.121
FR1 n77_Ant 1 Sub TXD	0.315	0.142	0.148	0.922	0.946	1.090

SAR peak location (mm)			X (axis)		11.3	12	12	-23	11			
			Y (axis)		44.7	37.5	-57	-75.5	-47			
			Z (axis)		-207	-207	-207	-207	-207			
X (axis)	Y (axis)	Z (axis)	Exposure Position	0	1	7	9	10	11			
				WWAN SAR	WLANS/6GHz Ant 4+3	Bluetooth Ant 4+3	LTE Band 48_Ant 6 TXD	FR1 n48_Ant 6 TXD	FR1 n77_Ant 6 TXD			
			Back	1g SAR (W/kg)						0.317	0.341	0.485
										0+1+7+9 SPLSR_Results	0+1+7+10 SPLSR_Results	0+1+7+11 SPLSR_Results
4.6	56.1	-207	GSM850_Ant 1 TXI	0.640	0.142	0.148						
4.1	56.8	-207	WCDMA V_Ant 1 TXI	0.490	0.142	0.148						
8	56.8	-207	LTE Band 12_Ant 1 TXI	0.351	0.142	0.148						
6.3	53.8	-207	LTE Band 13_Ant 1 TXI	0.515	0.142	0.148						
2.8	56.3	-207	LTE Band 14_Ant 1 TXI	0.520	0.142	0.148						
1.9	76.6	-207	LTE Band 25_Ant 1 Sub TXD	0.842	0.142	0.148			0.02			
1.9	55.1	-207	LTE Band 26_Ant 1 TXI	0.417	0.142	0.148						
-2.4	75.9	-207	LTE Band 66_Ant 1 Sub TXD	0.832	0.142	0.148			0.02			
5.1	55.8	-207	LTE Band 71_Ant 1 TXI	0.289	0.142	0.148						
3.6	56.1	-207	FR1 n12_Ant 1 TXI	0.422	0.142	0.148						
0.3	56.1	-207	FR1 n14_Ant 1 TXI	0.533	0.142	0.148						
0.9	79.6	-207	FR1 n25_Ant 1 Sub TXD	0.746	0.142	0.148						
1.3	56.6	-207	FR1 n26_Ant 1 TXI	0.424	0.142	0.148						
-5	77	-207	FR1 n41_Ant 1 Sub TXD	0.764	0.142	0.148						
-35.5	80	-207	FR1 n48_Ant 1 Sub TXD	0.343	0.142	0.148						
3.6	78.9	-207	FR1 n66_Ant 1 Sub TXD	0.722	0.142	0.148						
4.1	55.1	-207	FR1 n71_Ant 1 TXI	0.346	0.142	0.148						
14.5	65	-207	FR1 n77_Ant 1 Sub TXD	0.315	0.142	0.148						



<Case 42>

SPLSR calculation for summation SAR>1.6W/kg

Exposure Position	0	1	7	9	10	11
	WWAN SAR	WLANS/6GHz Ant 4+3	Thread Ant 3	LTE Band 48_Ant 6 TXD	FR1 n48_Ant 6 TXD	FR1 n77_Ant 6 TXD
Back	1g SAR (W/kg)			0.317	0.341	0.485
				0+1+7+9 Summed SAR	0+1+7+10 Summed SAR	0+1+7+11 Summed SAR
GSM850_Ant 1 TXI	0.640	0.142	0.187	1.286	1.310	1.454
WCDMA V_Ant 1 TXI	0.490	0.142	0.187	1.136	1.160	1.304
LTE Band 12_Ant 1 TXI	0.351	0.142	0.187	0.997	1.021	1.165
LTE Band 13_Ant 1 TXI	0.515	0.142	0.187	1.161	1.185	1.329
LTE Band 14_Ant 1 TXI	0.520	0.142	0.187	1.166	1.190	1.334
LTE Band 25_Ant 1 Sub TXD	0.842	0.142	0.187	1.488	1.512	1.656
LTE Band 26_Ant 1 TXI	0.417	0.142	0.187	1.063	1.087	1.231
LTE Band 66_Ant 1 Sub TXD	0.832	0.142	0.187	1.478	1.502	1.646
LTE Band 71_Ant 1 TXI	0.289	0.142	0.187	0.935	0.959	1.103
FR1 n12_Ant 1 TXI	0.422	0.142	0.187	1.068	1.092	1.236
FR1 n14_Ant 1 TXI	0.533	0.142	0.187	1.179	1.203	1.347
FR1 n25_Ant 1 Sub TXD	0.746	0.142	0.187	1.392	1.416	1.560
FR1 n26_Ant 1 TXI	0.424	0.142	0.187	1.070	1.094	1.238
FR1 n41_Ant 1 Sub TXD	0.764	0.142	0.187	1.410	1.434	1.578
FR1 n48_Ant 1 Sub TXD	0.343	0.142	0.187	0.989	1.013	1.157
FR1 n66_Ant 1 Sub TXD	0.722	0.142	0.187	1.368	1.392	1.536
FR1 n71_Ant 1 TXI	0.346	0.142	0.187	0.992	1.016	1.160
FR1 n77_Ant 1 Sub TXD	0.315	0.142	0.187	0.961	0.985	1.129

SAR peak location (mm)			X (axis)		11.3	17	12	-23	11
			Y (axis)		44.7	33	-57	-75.5	-47
			Z (axis)		-207	-207	-207	-207	-207
X (axis)	Y (axis)	Z (axis)	Exposure Position	0	1	7	9	10	11
			Back	WWAN SAR	WLANS/6GHz Ant 4+3	Thread Ant 3	LTE Band 48_Ant 6 TXD	FR1 n48_Ant 6 TXD	FR1 n77_Ant 6 TXD
			1g SAR (W/kg)				0.317	0.341	0.485
							0+1+7+9 SPLSR Results	0+1+7+10 SPLSR Results	0+1+7+11 SPLSR Results
4.6	56.1	-207	GSM850_Ant 1 TXI	0.640	0.142	0.187			
4.1	56.8	-207	WCDMA V_Ant 1 TXI	0.490	0.142	0.187			
8	56.8	-207	LTE Band 12_Ant 1 TXI	0.351	0.142	0.187			
6.3	53.8	-207	LTE Band 13_Ant 1 TXI	0.515	0.142	0.187			
2.8	56.3	-207	LTE Band 14_Ant 1 TXI	0.520	0.142	0.187			
1.9	76.6	-207	LTE Band 25_Ant 1 Sub TXD	0.842	0.142	0.187			0.03
1.9	55.1	-207	LTE Band 26_Ant 1 TXI	0.417	0.142	0.187			
-2.4	75.9	-207	LTE Band 66_Ant 1 Sub TXD	0.832	0.142	0.187			0.03
5.1	55.8	-207	LTE Band 71_Ant 1 TXI	0.289	0.142	0.187			
3.6	56.1	-207	FR1 n12_Ant 1 TXI	0.422	0.142	0.187			
0.3	56.1	-207	FR1 n14_Ant 1 TXI	0.533	0.142	0.187			
0.9	79.6	-207	FR1 n25_Ant 1 Sub TXD	0.746	0.142	0.187			
1.3	56.6	-207	FR1 n26_Ant 1 TXI	0.424	0.142	0.187			
-5	77	-207	FR1 n41_Ant 1 Sub TXD	0.764	0.142	0.187			
-35.5	80	-207	FR1 n48_Ant 1 Sub TXD	0.343	0.142	0.187			
3.6	78.9	-207	FR1 n66_Ant 1 Sub TXD	0.722	0.142	0.187			
4.1	55.1	-207	FR1 n71_Ant 1 TXI	0.346	0.142	0.187			
14.5	65	-207	FR1 n77_Ant 1 Sub TXD	0.315	0.142	0.187			

<Case 43>

SPLSR calculation for summation SAR>1.6W/kg

Exposure Position	0	1	2	9	10	11
	WWAN SAR	WLAN2.4GHz Ant 3	WLAN5/6GHz Ant 4+3	LTE Band 48_Ant 6 TXD	FR1 n48_Ant 6 TXD	FR1 n77_Ant 6 TXD
Left Edge	1g SAR (W/kg)			0.421	0.452	0.694
				0+1+2+9 Summed SAR	0+1+2+10 Summed SAR	0+1+2+11 Summed SAR
GSM850_Ant 1 TXI	0.353	0.242	0.260	1.276	1.307	1.549
WCDMA V_Ant 1 TXI	0.217	0.242	0.260	1.140	1.171	1.413
LTE Band 12_Ant 1 TXI	0.214	0.242	0.260	1.137	1.168	1.410
LTE Band 13_Ant 1 TXI	0.318	0.242	0.260	1.241	1.272	1.514
LTE Band 14_Ant 1 TXI	0.392	0.242	0.260	1.315	1.346	1.588
LTE Band 25_Ant 1 Sub TXD	0.278	0.242	0.260	1.201	1.232	1.474
LTE Band 26_Ant 1 TXI	0.121	0.242	0.260	1.044	1.075	1.317
LTE Band 66_Ant 1 Sub TXD	0.187	0.242	0.260	1.110	1.141	1.383
LTE Band 71_Ant 1 TXI	0.221	0.242	0.260	1.144	1.175	1.417
FR1 n12_Ant 1 TXI	0.266	0.242	0.260	1.189	1.220	1.462
FR1 n14_Ant 1 TXI	0.357	0.242	0.260	1.280	1.311	1.553
FR1 n25_Ant 1 Sub TXD	0.262	0.242	0.260	1.185	1.216	1.458
FR1 n26_Ant 1 TXI	0.104	0.242	0.260	1.027	1.058	1.300
FR1 n41_Ant 1 Sub TXD	0.081	0.242	0.260	1.004	1.035	1.277
FR1 n48_Ant 1 Sub TXD	0.483	0.242	0.260	1.406	1.437	1.679
FR1 n66_Ant 1 Sub TXD	0.264	0.242	0.260	1.187	1.218	1.460
FR1 n71_Ant 1 TXI	0.271	0.242	0.260	1.194	1.225	1.467
FR1 n77_Ant 1 Sub TXD	0.489	0.242	0.260	1.412	1.443	1.685

SAR peak location (mm)			X (axis)		-25	-24.4	-25.9	-25.7	-24.1
			Y (axis)		33.5	49.2	-58.5	-58.2	-56
			Z (axis)		-207	-207	-207	-207	-207
X (axis)	Y (axis)	Z (axis)	Exposure Position	0	1	2	9	10	11
			Left Edge	1g SAR (W/kg)			0.421	0.452	0.694
-24	-8.7	-207	GSM850_Ant 1 TXI	0.353	0.242	0.260			
-26.2	-11	-207	WCDMA V_Ant 1 TXI	0.217	0.242	0.260			
-24.9	62.5	-207	LTE Band 12_Ant 1 TXI	0.214	0.242	0.260			
-23	19	-207	LTE Band 13_Ant 1 TXI	0.318	0.242	0.260			
-24.4	10.5	-207	LTE Band 14_Ant 1 TXI	0.392	0.242	0.260			
-21.2	65.9	-207	LTE Band 25_Ant 1 Sub TXD	0.278	0.242	0.260			
-26.5	-20.8	-207	LTE Band 26_Ant 1 TXI	0.121	0.242	0.260			
-21.2	68.4	-207	LTE Band 66_Ant 1 Sub TXD	0.187	0.242	0.260			
-26.1	63	-207	LTE Band 71_Ant 1 TXI	0.221	0.242	0.260			
-25.6	62	-207	FR1 n12_Ant 1 TXI	0.266	0.242	0.260			
-25.6	11.2	-207	FR1 n14_Ant 1 TXI	0.357	0.242	0.260			
-23.1	63.6	-207	FR1 n25_Ant 1 Sub TXD	0.262	0.242	0.260			
-22	-1.2	-207	FR1 n26_Ant 1 TXI	0.104	0.242	0.260			
-23.7	85	-207	FR1 n41_Ant 1 Sub TXD	0.081	0.242	0.260			
-29.5	65	-207	FR1 n48_Ant 1 Sub TXD	0.483	0.242	0.260			0.02
-24	66.6	-207	FR1 n66_Ant 1 Sub TXD	0.264	0.242	0.260			
-24.4	21.5	-207	FR1 n71_Ant 1 TXI	0.271	0.242	0.260			
-21.4	58.5	-207	FR1 n77_Ant 1 Sub TXD	0.489	0.242	0.260			0.02



<Case 44>

SPLSR calculation for summation SAR>1.6W/kg

Exposure Position	0	1	2	9	10	11
	WWAN SAR	WLAN2.4GHz Ant 4+3	WLAN5/6GHz Ant 4+3	LTE Band 48_Ant 6 TXD	FR1 n48_Ant 6 TXD	FR1 n77_Ant 6 TXD
Left Edge	1g SAR (W/kg)			0.421	0.452	0.694
				0+1+2+9 Summed SAR	0+1+2+10 Summed SAR	0+1+2+11 Summed SAR
GSM850_Ant 1 TXI	0.353	0.225	0.260	1.259	1.290	1.532
WCDMA V_Ant 1 TXI	0.217	0.225	0.260	1.123	1.154	1.396
LTE Band 12_Ant 1 TXI	0.214	0.225	0.260	1.120	1.151	1.393
LTE Band 13_Ant 1 TXI	0.318	0.225	0.260	1.224	1.255	1.497
LTE Band 14_Ant 1 TXI	0.392	0.225	0.260	1.298	1.329	1.571
LTE Band 25_Ant 1 Sub TXD	0.278	0.225	0.260	1.184	1.215	1.457
LTE Band 26_Ant 1 TXI	0.121	0.225	0.260	1.027	1.058	1.300
LTE Band 66_Ant 1 Sub TXD	0.187	0.225	0.260	1.093	1.124	1.366
LTE Band 71_Ant 1 TXI	0.221	0.225	0.260	1.127	1.158	1.400
FR1 n12_Ant 1 TXI	0.266	0.225	0.260	1.172	1.203	1.445
FR1 n14_Ant 1 TXI	0.357	0.225	0.260	1.263	1.294	1.536
FR1 n25_Ant 1 Sub TXD	0.262	0.225	0.260	1.168	1.199	1.441
FR1 n26_Ant 1 TXI	0.104	0.225	0.260	1.010	1.041	1.283
FR1 n41_Ant 1 Sub TXD	0.081	0.225	0.260	0.987	1.018	1.260
FR1 n48_Ant 1 Sub TXD	0.483	0.225	0.260	1.389	1.420	1.662
FR1 n66_Ant 1 Sub TXD	0.264	0.225	0.260	1.170	1.201	1.443
FR1 n71_Ant 1 TXI	0.271	0.225	0.260	1.177	1.208	1.450
FR1 n77_Ant 1 Sub TXD	0.489	0.225	0.260	1.395	1.426	1.668

SAR peak location (mm)			X (axis)		-24.5	-24.4	-25.9	-25.7	-24.1
			Y (axis)		36.5	49.2	-58.5	-58.2	-56
			Z (axis)		-207	-207	-207	-207	-207
X (axis)	Y (axis)	Z (axis)	Exposure Position	0	1	2	9	10	11
			Left Edge	1g SAR (W/kg)			0.421	0.452	0.694
-24	-8.7	-207	GSM850_Ant 1 TXI	0.353	0.225	0.260			
-26.2	-11	-207	WCDMA V_Ant 1 TXI	0.217	0.225	0.260			
-24.9	62.5	-207	LTE Band 12_Ant 1 TXI	0.214	0.225	0.260			
-23	19	-207	LTE Band 13_Ant 1 TXI	0.318	0.225	0.260			
-24.4	10.5	-207	LTE Band 14_Ant 1 TXI	0.392	0.225	0.260			
-21.2	65.9	-207	LTE Band 25_Ant 1 Sub TXD	0.278	0.225	0.260			
-26.5	-20.8	-207	LTE Band 26_Ant 1 TXI	0.121	0.225	0.260			
-21.2	68.4	-207	LTE Band 66_Ant 1 Sub TXD	0.187	0.225	0.260			
-26.1	63	-207	LTE Band 71_Ant 1 TXI	0.221	0.225	0.260			
-25.6	62	-207	FR1 n12_Ant 1 TXI	0.266	0.225	0.260			
-25.6	11.2	-207	FR1 n14_Ant 1 TXI	0.357	0.225	0.260			
-23.1	63.6	-207	FR1 n25_Ant 1 Sub TXD	0.262	0.225	0.260			
-22	-1.2	-207	FR1 n26_Ant 1 TXI	0.104	0.225	0.260			
-23.7	85	-207	FR1 n41_Ant 1 Sub TXD	0.081	0.225	0.260			
-29.5	65	-207	FR1 n48_Ant 1 Sub TXD	0.483	0.225	0.260			0.02
-24	66.6	-207	FR1 n66_Ant 1 Sub TXD	0.264	0.225	0.260			
-24.4	21.5	-207	FR1 n71_Ant 1 TXI	0.271	0.225	0.260			
-21.4	58.5	-207	FR1 n77_Ant 1 Sub TXD	0.489	0.225	0.260			0.02



<Case 45>

SPLSR calculation for summation SAR>1.6W/kg

Exposure Position	0	1	7	9	10	11
	WWAN SAR	WLANS/6GHz Ant 4+3	Bluetooth Ant 3	LTE Band 48_Ant 6 TX0	FR1 n48_Ant 6 TX0	FR1 n77_Ant 6 TX0
Left Edge	1g SAR (W/kg)			0.421	0.452	0.694
				0+1+7+9 Summed SAR	0+1+7+10 Summed SAR	0+1+7+11 Summed SAR
GSM850_Ant 1 TX1	0.353	0.260	0.255	1.289	1.320	1.562
WCDMA V_Ant 1 TX1	0.217	0.260	0.255	1.153	1.184	1.426
LTE Band 12_Ant 1 TX1	0.214	0.260	0.255	1.150	1.181	1.423
LTE Band 13_Ant 1 TX1	0.318	0.260	0.255	1.254	1.285	1.527
LTE Band 14_Ant 1 TX1	0.392	0.260	0.255	1.328	1.359	1.601
LTE Band 25_Ant 1 Sub TX0	0.278	0.260	0.255	1.214	1.245	1.487
LTE Band 26_Ant 1 TX1	0.121	0.260	0.255	1.057	1.088	1.330
LTE Band 66_Ant 1 Sub TX0	0.187	0.260	0.255	1.123	1.154	1.396
LTE Band 71_Ant 1 TX1	0.221	0.260	0.255	1.157	1.188	1.430
FR1 n12_Ant 1 TX1	0.266	0.260	0.255	1.202	1.233	1.475
FR1 n14_Ant 1 TX1	0.357	0.260	0.255	1.293	1.324	1.566
FR1 n25_Ant 1 Sub TX0	0.262	0.260	0.255	1.198	1.229	1.471
FR1 n26_Ant 1 TX1	0.104	0.260	0.255	1.040	1.071	1.313
FR1 n41_Ant 1 Sub TX0	0.081	0.260	0.255	1.017	1.048	1.290
FR1 n48_Ant 1 Sub TX0	0.483	0.260	0.255	1.419	1.450	1.692
FR1 n66_Ant 1 Sub TX0	0.264	0.260	0.255	1.200	1.231	1.473
FR1 n71_Ant 1 TX1	0.271	0.260	0.255	1.207	1.238	1.480
FR1 n77_Ant 1 Sub TX0	0.489	0.260	0.255	1.425	1.456	1.698

SAR peak location (mm)			X (axis)		-24.4	-25.9	-25.9	-25.7	-24.1
			Y (axis)		49.2	32	-58.5	-58.2	-56
			Z (axis)		-207	-207	-207	-207	-207
X (axis)	Y (axis)	Z (axis)	Exposure Position	0	1	7	9	10	11
				WWAN SAR	WLAN/5GHz Ant 4+3	Bluetooth Ant 3	LTE Band 48_Ant 6 TX0	FR1 n48_Ant 6 TX0	FR1 n77_Ant 6 TX0
			Left Edge	1g SAR (W/kg)			0.421	0.452	0.694
						0+1+7+9 SPLSR Results	0+1+7+10 SPLSR Results	0+1+7+11 SPLSR Results	
-24	-8.7	-207	GSM850_Ant 1 TX0	0.353	0.260	0.255			
-26.2	-11	-207	WCDMA V_Ant 1 TX0	0.217	0.260	0.255			
-24.9	62.5	-207	LTE Band 12_Ant 1 TX0	0.214	0.260	0.255			
-23	19	-207	LTE Band 13_Ant 1 TX0	0.318	0.260	0.255			
-24.4	10.5	-207	LTE Band 14_Ant 1 TX0	0.392	0.260	0.255			0.03
-21.2	65.9	-207	LTE Band 25_Ant 1 Sub TX0	0.278	0.260	0.255			
-26.5	-20.8	-207	LTE Band 26_Ant 1 TX0	0.121	0.260	0.255			
-21.2	68.4	-207	LTE Band 66_Ant 1 Sub TX0	0.187	0.260	0.255			
-26.1	63	-207	LTE Band 71_Ant 1 TX0	0.221	0.260	0.255			
-25.6	62	-207	FR1 n12_Ant 1 TX0	0.266	0.260	0.255			
-25.6	11.2	-207	FR1 n14_Ant 1 TX0	0.357	0.260	0.255			
-23.1	63.6	-207	FR1 n25_Ant 1 Sub TX0	0.262	0.260	0.255			
-22	-1.2	-207	FR1 n26_Ant 1 TX0	0.104	0.260	0.255			
-23.7	85	-207	FR1 n41_Ant 1 Sub TX0	0.081	0.260	0.255			
-29.5	65	-207	FR1 n48_Ant 1 Sub TX0	0.483	0.260	0.255			0.03
-24	66.6	-207	FR1 n66_Ant 1 Sub TX0	0.264	0.260	0.255			
-24.4	21.5	-207	FR1 n71_Ant 1 TX0	0.271	0.260	0.255			
-21.4	58.5	-207	FR1 n77_Ant 1 Sub TX0	0.489	0.260	0.255			0.03



<Case 46>

SPLSR calculation for summation SAR>1.6W/kg

Exposure Position	0	1	7	9	10	11
	WWAN SAR	WLANS/6GHz Ant 4+3	Bluetooth Ant 4+3	LTE Band 48_Ant 6 TXD	FR1 n48_Ant 6 TXD	FR1 n77_Ant 6 TXD
Left Edge	1g SAR (W/kg)			0.421	0.452	0.694
				0+1+7+9 Summed SAR	0+1+7+10 Summed SAR	0+1+7+11 Summed SAR
GSM850_Ant 1 TXI	0.353	0.260	0.221	1.255	1.286	1.528
WCDMA V_Ant 1 TXI	0.217	0.260	0.221	1.119	1.150	1.392
LTE Band 12_Ant 1 TXI	0.214	0.260	0.221	1.116	1.147	1.389
LTE Band 13_Ant 1 TXI	0.318	0.260	0.221	1.220	1.251	1.493
LTE Band 14_Ant 1 TXI	0.392	0.260	0.221	1.294	1.325	1.567
LTE Band 25_Ant 1 Sub TXD	0.278	0.260	0.221	1.180	1.211	1.453
LTE Band 26_Ant 1 TXI	0.121	0.260	0.221	1.023	1.054	1.296
LTE Band 66_Ant 1 Sub TXD	0.187	0.260	0.221	1.089	1.120	1.362
LTE Band 71_Ant 1 TXI	0.221	0.260	0.221	1.123	1.154	1.396
FR1 n12_Ant 1 TXI	0.266	0.260	0.221	1.168	1.199	1.441
FR1 n14_Ant 1 TXI	0.357	0.260	0.221	1.259	1.290	1.532
FR1 n25_Ant 1 Sub TXD	0.262	0.260	0.221	1.164	1.195	1.437
FR1 n26_Ant 1 TXI	0.104	0.260	0.221	1.006	1.037	1.279
FR1 n41_Ant 1 Sub TXD	0.081	0.260	0.221	0.983	1.014	1.256
FR1 n48_Ant 1 Sub TXD	0.483	0.260	0.221	1.385	1.416	1.658
FR1 n66_Ant 1 Sub TXD	0.264	0.260	0.221	1.166	1.197	1.439
FR1 n71_Ant 1 TXI	0.271	0.260	0.221	1.173	1.204	1.446
FR1 n77_Ant 1 Sub TXD	0.489	0.260	0.221	1.391	1.422	1.664

SAR peak location (mm)			X (axis)		-24.4	-25.5	-25.9	-25.7	-24.1
			Y (axis)		49.2	36.5	-58.5	-58.2	-56
			Z (axis)		-207	-207	-207	-207	-207
X (axis)	Y (axis)	Z (axis)	Exposure Position	0	1	7	9	10	11
			Left Edge	WWAN SAR	WLANS/6GHz Ant 4+3	Bluetooth Ant 4+3	LTE Band 48_Ant 6 TXD	FR1 n48_Ant 6 TXD	FR1 n77_Ant 6 TXD
			Left Edge	1g SAR (W/kg)			0.421	0.452	0.694
						0+1+7+9 SPLSR Results	0+1+7+10 SPLSR Results	0+1+7+11 SPLSR Results	
-24	-8.7	-207	GSM850_Ant 1 TXI	0.353	0.260	0.221			
-26.2	-11	-207	WCDMA V_Ant 1 TXI	0.217	0.260	0.221			
-24.9	62.5	-207	LTE Band 12_Ant 1 TXI	0.214	0.260	0.221			
-23	19	-207	LTE Band 13_Ant 1 TXI	0.318	0.260	0.221			
-24.4	10.5	-207	LTE Band 14_Ant 1 TXI	0.392	0.260	0.221			
-21.2	65.9	-207	LTE Band 25_Ant 1 Sub TXD	0.278	0.260	0.221			
-26.5	-20.8	-207	LTE Band 26_Ant 1 TXI	0.121	0.260	0.221			
-21.2	68.4	-207	LTE Band 66_Ant 1 Sub TXD	0.187	0.260	0.221			
-26.1	63	-207	LTE Band 71_Ant 1 TXI	0.221	0.260	0.221			
-25.6	62	-207	FR1 n12_Ant 1 TXI	0.266	0.260	0.221			
-25.6	11.2	-207	FR1 n14_Ant 1 TXI	0.357	0.260	0.221			
-23.1	63.6	-207	FR1 n25_Ant 1 Sub TXD	0.262	0.260	0.221			
-22	-1.2	-207	FR1 n26_Ant 1 TXI	0.104	0.260	0.221			
-23.7	85	-207	FR1 n41_Ant 1 Sub TXD	0.081	0.260	0.221			
-29.5	65	-207	FR1 n48_Ant 1 Sub TXD	0.483	0.260	0.221			0.02
-24	66.6	-207	FR1 n66_Ant 1 Sub TXD	0.264	0.260	0.221			
-24.4	21.5	-207	FR1 n71_Ant 1 TXI	0.271	0.260	0.221			
-21.4	58.5	-207	FR1 n77_Ant 1 Sub TXD	0.489	0.260	0.221			0.02



<Case 47>

SPLSR calculation for summation SAR>1.6W/kg

Exposure Position	0	1	7	9	10	11
	WWAN SAR	WLANS/6GHz Ant 4+3	Thread Ant 3	LTE Band 48_Ant 6 TX0	FR1 n48_Ant 6 TX0	FR1 n77_Ant 6 TX0
Left Edge	1g SAR (W/kg)			0.421	0.452	0.694
				0+1+7+9 Summed SAR	0+1+7+10 Summed SAR	0+1+7+11 Summed SAR
GSM850_Ant 1 TX1	0.353	0.260	0.242	1.276	1.307	1.549
WCDMA V_Ant 1 TX1	0.217	0.260	0.242	1.140	1.171	1.413
LTE Band 12_Ant 1 TX1	0.214	0.260	0.242	1.137	1.168	1.410
LTE Band 13_Ant 1 TX1	0.318	0.260	0.242	1.241	1.272	1.514
LTE Band 14_Ant 1 TX1	0.392	0.260	0.242	1.315	1.346	1.588
LTE Band 25_Ant 1 Sub TX0	0.278	0.260	0.242	1.201	1.232	1.474
LTE Band 26_Ant 1 TX1	0.121	0.260	0.242	1.044	1.075	1.317
LTE Band 66_Ant 1 Sub TX0	0.187	0.260	0.242	1.110	1.141	1.383
LTE Band 71_Ant 1 TX1	0.221	0.260	0.242	1.144	1.175	1.417
FR1 n12_Ant 1 TX1	0.266	0.260	0.242	1.189	1.220	1.462
FR1 n14_Ant 1 TX1	0.357	0.260	0.242	1.280	1.311	1.553
FR1 n25_Ant 1 Sub TX0	0.262	0.260	0.242	1.185	1.216	1.458
FR1 n26_Ant 1 TX1	0.104	0.260	0.242	1.027	1.058	1.300
FR1 n41_Ant 1 Sub TX0	0.081	0.260	0.242	1.004	1.035	1.277
FR1 n48_Ant 1 Sub TX0	0.483	0.260	0.242	1.406	1.437	1.679
FR1 n66_Ant 1 Sub TX0	0.264	0.260	0.242	1.187	1.218	1.460
FR1 n71_Ant 1 TX1	0.271	0.260	0.242	1.194	1.225	1.467
FR1 n77_Ant 1 Sub TX0	0.489	0.260	0.242	1.412	1.443	1.685

SAR peak location (mm)			X (axis)		-24.4	-20.8	-25.9	-25.7	-24.1
			Y (axis)		49.2	30.5	-58.5	-58.2	-56
			Z (axis)		-207	-207	-207	-207	-207
X (axis)	Y (axis)	Z (axis)	Exposure Position	0	1	7	9	10	11
				WWAN SAR	WLAN/6GHz Ant 4+3	Thread Ant 3	LTE Band 48_Ant 6 TX0	FR1 n48_Ant 6 TX0	FR1 n77_Ant 6 TX0
			Left Edge	1g SAR (W/kg)			0.421 SPLSR Results	0.452 SPLSR Results	0.694 SPLSR Results
-24	-8.7	-207	GSM850_Ant 1 TX1	0.353	0.260	0.242			
-26.2	-11	-207	WCDMA V_Ant 1 TX0	0.217	0.260	0.242			
-24.9	62.5	-207	LTE Band 12_Ant 1 TX1	0.214	0.260	0.242			
-23	19	-207	LTE Band 13_Ant 1 TX1	0.318	0.260	0.242			
-24.4	10.5	-207	LTE Band 14_Ant 1 TX1	0.392	0.260	0.242			
-21.2	65.9	-207	LTE Band 25_Ant 1 Sub TX0	0.278	0.260	0.242			
-26.5	-20.8	-207	LTE Band 26_Ant 1 TX1	0.121	0.260	0.242			
-21.2	68.4	-207	LTE Band 66_Ant 1 Sub TX0	0.187	0.260	0.242			
-26.1	63	-207	LTE Band 71_Ant 1 TX1	0.221	0.260	0.242			
-25.6	62	-207	FR1 n12_Ant 1 TX1	0.266	0.260	0.242			
-25.6	11.2	-207	FR1 n14_Ant 1 TX1	0.357	0.260	0.242			
-23.1	63.6	-207	FR1 n25_Ant 1 Sub TX0	0.262	0.260	0.242			
-22	-1.2	-207	FR1 n26_Ant 1 TX1	0.104	0.260	0.242			
-23.7	85	-207	FR1 n41_Ant 1 Sub TX0	0.081	0.260	0.242			
-29.5	65	-207	FR1 n48_Ant 1 Sub TX0	0.483	0.260	0.242			0.03
-24	66.6	-207	FR1 n66_Ant 1 Sub TX0	0.264	0.260	0.242			
-24.4	21.5	-207	FR1 n71_Ant 1 TX1	0.271	0.260	0.242			
-21.4	58.5	-207	FR1 n77_Ant 1 Sub TX0	0.489	0.260	0.242			0.03

<Case 55>

SPLSR calculation for summation SAR>1.6W/kg

Exposure Position	0	1	2	9	10	11
	WWAN SAR	WLAN2.4GHz Ant 4	WLAN5/6GHz Ant 4+3	LTE Band 48_Ant 7 TX1	FR1 n48_Ant 7 TX1	FR1 n77_Ant 7 TX1
Right Edge	1g SAR (W/kg)			0.460	0.594	0.604
				0+1+2+9 Summed SAR	0+1+2+10 Summed SAR	0+1+2+11 Summed SAR
LTE Band 25_Ant 5 Sub TX1	0.844	0.107	0.081	1.492	1.626	1.636
LTE Band 66_Ant 5 Sub TX1	0.707	0.107	0.081	1.355	1.489	1.499
FR1 n25_Ant 5 Sub TX1	0.689	0.107	0.081	1.337	1.471	1.481
FR1 n66_Ant 5 Sub TX1	0.847	0.107	0.081	1.495	1.629	1.639
FR1 n41_Ant 5 Sub TX1	0.679	0.107	0.081	1.327	1.461	1.471
FR1 n48_Ant 5 Sub TX1	0.666	0.107	0.081	1.314	1.448	1.458
FR1 n77_Ant 5 Sub TX1	0.377	0.107	0.081	1.025	1.159	1.169

Combination	SAR	SAR peak location (mm)			3D distance (mm)	Summed SAR (W/kg)	SPLSR Results	Simultaneous SAR
		X	Y	Z				
Max WWAN Ant 7 + WLAN2.4G Ant 4	0.711	-27.0	-34.6	-207.0	86.7	1.64	0.02	Not required
Max WWAN Ant 5 + WLAN5/6G Ant 4+3	0.928	-23.6	52.0	-207.0				

<Case 56>

SPLSR calculation for summation SAR>1.6W/kg

Exposure Position	0	1	2	9	10	11
	WWAN SAR	WLAN2.4GHz Ant 4+3	WLAN5/6GHz Ant 4+3	LTE Band 48_Ant 7 TX1	FR1 n48_Ant 7 TX1	FR1 n77_Ant 7 TX1
Right Edge	1g SAR (W/kg)			0.460	0.594	0.604
				0+1+2+9 Summed SAR	0+1+2+10 Summed SAR	0+1+2+11 Summed SAR
LTE Band 25_Ant 5 Sub TX1	0.844	0.135	0.081	1.520	1.654	1.664
LTE Band 66_Ant 5 Sub TX1	0.707	0.135	0.081	1.383	1.517	1.527
FR1 n25_Ant 5 Sub TX1	0.689	0.135	0.081	1.365	1.499	1.509
FR1 n66_Ant 5 Sub TX1	0.847	0.135	0.081	1.523	1.657	1.667
FR1 n41_Ant 5 Sub TX1	0.679	0.135	0.081	1.355	1.489	1.499
FR1 n48_Ant 5 Sub TX1	0.666	0.135	0.081	1.342	1.476	1.486
FR1 n77_Ant 5 Sub TX1	0.377	0.135	0.081	1.053	1.187	1.197

SAR peak location (mm)			X (axis)			Y (axis)			Z (axis)		
			0			1			2		
X (axis)	Y (axis)	Z (axis)	Exposure Position			0			1		
			Right Edge			1g SAR (W/kg)			0+1+2+9 Summed SAR		
-24.9	-39.1	-207	LTE Band 25_Ant 5 Sub TX1	0.844	0.135	0.081	1.520	1.654	1.664	0.02	0.02
-22.1	-33.9	-207	LTE Band 66_Ant 5 Sub TX1	0.707	0.135	0.081	1.383	1.517	1.527		
-27	-35.6	-207	FR1 n25_Ant 5 Sub TX1	0.689	0.135	0.081	1.365	1.499	1.509		
-27	-34.6	-207	FR1 n66_Ant 5 Sub TX1	0.847	0.135	0.081	1.523	1.657	1.667	0.02	0.02
-23.6	-40	-207	FR1 n41_Ant 5 Sub TX1	0.679	0.135	0.081	1.355	1.489	1.499		
-26.4	-62	-207	FR1 n48_Ant 5 Sub TX1	0.666	0.135	0.081	1.342	1.476	1.486		
-24.1	-45	-207	FR1 n77_Ant 5 Sub TX1	0.377	0.135	0.081	1.053	1.187	1.197		

<Case 57>

SPLSR calculation for summation SAR>1.6W/kg

Exposure Position	0	1	7	9	10	11
	WWAN SAR	WLANS/6GHz Ant 4+3	Bluetooth Ant 4	LTE Band 48_Ant 7 TX1	FR1 n48_Ant 7 TX1	FR1 n77_Ant 7 TX1
Right Edge	1g SAR (W/kg)			0.460	0.594	0.604
				0+1+7+9 Summed SAR	0+1+7+10 Summed SAR	0+1+7+11 Summed SAR
LTE Band 25_Ant 5 Sub TX1	0.844	0.081	0.294	1.679	1.813	1.823
LTE Band 66_Ant 5 Sub TX1	0.707	0.081	0.294	1.542	1.676	1.686
FR1 n25_Ant 5 Sub TX1	0.689	0.081	0.294	1.524	1.658	1.668
FR1 n66_Ant 5 Sub TX1	0.847	0.081	0.294	1.682	1.816	1.826
FR1 n41_Ant 5 Sub TX1	0.679	0.081	0.294	1.514	1.648	1.658
FR1 n48_Ant 5 Sub TX1	0.666	0.081	0.294	1.501	1.635	1.645
FR1 n77_Ant 5 Sub TX1	0.377	0.081	0.294	1.212	1.346	1.356

SAR peak location (mm)			X (axis)	-21.4	-25.5	-23.2	-23.6	-23.6
			Y (axis)	-48.7	-48	59	55.5	53.5
			Z (axis)	-207	-207	-207	-207	-207
X (axis)	Y (axis)	Z (axis)	Exposure Position	0	1	7	9	10
				WWAN SAR	WLANS/6GHz Ant 4+3	Bluetooth Ant 4	LTE Band 48_Ant 7 TX1	FR1 n48_Ant 7 TX1
			Right Edge	1g SAR (W/kg)			0.46	0.594
							0+1+7+9 SPLSR Results	0+1+7+10 SPLSR Results
-24.9	-39.1	-207	LTE Band 25_Ant 5 Sub TX1	0.844	0.081	0.294	0.02	0.03
-22.1	-33.9	-207	LTE Band 66_Ant 5 Sub TX1	0.707	0.081	0.294		0.02
-27	-35.6	-207	FR1 n25_Ant 5 Sub TX1	0.689	0.081	0.294		0.02
-27	-34.6	-207	FR1 n66_Ant 5 Sub TX1	0.847	0.081	0.294	0.02	0.03
-23.6	-40	-207	FR1 n41_Ant 5 Sub TX1	0.679	0.081	0.294		0.02
-26.4	-62	-207	FR1 n48_Ant 5 Sub TX1	0.666	0.081	0.294		0.02
-24.1	-45	-207	FR1 n77_Ant 5 Sub TX1	0.377	0.081	0.294		

<Case 58>

SPLSR calculation for summation SAR>1.6W/kg

Exposure Position	0	1	7	9	10	11
	WWAN SAR	WLANS/6GHz Ant 4+3	Bluetooth Ant 4+3	LTE Band 48_Ant 7 TX1	FR1 n48_Ant 7 TX1	FR1 n77_Ant 7 TX1
Right Edge	1g SAR (W/kg)			0.460	0.594	0.604
				0+1+7+9 Summed SAR	0+1+7+10 Summed SAR	0+1+7+11 Summed SAR
LTE Band 25_Ant 5 Sub TX1	0.844	0.081	0.128	1.513	1.647	1.657
LTE Band 66_Ant 5 Sub TX1	0.707	0.081	0.128	1.376	1.510	1.520
FR1 n25_Ant 5 Sub TX1	0.689	0.081	0.128	1.358	1.492	1.502
FR1 n66_Ant 5 Sub TX1	0.847	0.081	0.128	1.516	1.650	1.660
FR1 n41_Ant 5 Sub TX1	0.679	0.081	0.128	1.348	1.482	1.492
FR1 n48_Ant 5 Sub TX1	0.666	0.081	0.128	1.335	1.469	1.479
FR1 n77_Ant 5 Sub TX1	0.377	0.081	0.128	1.046	1.180	1.190

SAR peak location (mm)			X (axis)	-21.4	-23.2	-23.2	-23.6	-23.6
			Y (axis)	-48.7	-52.5	59	55.5	53.5
			Z (axis)	-207	-207	-207	-207	-207
X (axis)	Y (axis)	Z (axis)	Exposure Position	0	1	7	9	10
				WWAN SAR	WLANS/6GHz Ant 4+3	Bluetooth Ant 4+3	LTE Band 48_Ant 7 TX1	FR1 n48_Ant 7 TX1
			Right Edge	1g SAR (W/kg)			0.46	0.594
							0+1+7+9 SPLSR Results	0+1+7+10 SPLSR Results
-24.9	-39.1	-207	LTE Band 25_Ant 5 Sub TX1	0.844	0.081	0.128		0.02
-22.1	-33.9	-207	LTE Band 66_Ant 5 Sub TX1	0.707	0.081	0.128		
-27	-35.6	-207	FR1 n25_Ant 5 Sub TX1	0.689	0.081	0.128		
-27	-34.6	-207	FR1 n66_Ant 5 Sub TX1	0.847	0.081	0.128	0.02	0.02
-23.6	-40	-207	FR1 n41_Ant 5 Sub TX1	0.679	0.081	0.128		
-26.4	-62	-207	FR1 n48_Ant 5 Sub TX1	0.666	0.081	0.128		
-24.1	-45	-207	FR1 n77_Ant 5 Sub TX1	0.377	0.081	0.128		



<Case 59>

SPLSR calculation for summation SAR>1.6W/kg

[illegible]

<Case 60>

SPLSR calculation for summation SAR>1.6W/kg

[illegible]

<Case 61>

SPLSR calculation for summation SAR>1.6W/kg

[illegible]



<Case 62>

SPLSR calculation for summation SAR>1.6W/kg

[illegible]

<Case 63>

SPLSR calculation for summation SAR>1.6W/kg

Date	Project Name		Status	Priority	Owner	Team	Start Date	End Date	Duration	Progress (%)	Budget (€)	Actual Cost (€)	Variance (€)	Risk Level	Notes
	Project ID	Project Name													
2023-01-01	001	Project A	Completed	High	John Doe	Team Alpha	2022-12-15	2023-01-05	21 days	100%	100000	98000	2000	Low	Project A completed successfully.
2023-01-02	002	Project B	In Progress	Medium	Jane Smith	Team Beta	2023-01-01	2023-01-15	14 days	75%	150000	120000	30000	Medium	Project B progress update.
2023-01-03	003	Project C	On Hold	Low	Mike Johnson	Team Gamma	2023-01-01	2023-01-31	30 days	10%	200000	20000	180000	High	Project C on hold due to budget constraints.
2023-01-04	004	Project D	Planned	High	Sarah Lee	Team Alpha	2023-01-15	2023-02-15	31 days	0%	180000	0	180000	Medium	Project D planning phase.
2023-01-05	005	Project E	Completed	Medium	David Kim	Team Beta	2022-12-20	2023-01-10	21 days	100%	120000	125000	-5000	Low	Project E completed with slight over budget.
2023-01-06	006	Project F	In Progress	High	Emily White	Team Gamma	2023-01-05	2023-01-25	20 days	60%	160000	96000	64000	Medium	Project F progress update.
2023-01-07	007	Project G	On Hold	Low	Chris Brown	Team Alpha	2023-01-01	2023-02-28	58 days	5%	220000	11000	209000	High	Project G on hold due to resource allocation.
2023-01-08	008	Project H	Planned	Medium	Alex Green	Team Beta	2023-01-20	2023-03-10	50 days	0%	190000	0	190000	Medium	Project H planning phase.
2023-01-09	009	Project I	Completed	High	Mia Black	Team Gamma	2022-12-10	2023-01-01	22 days	100%	110000	112000	-2000	Low	Project I completed successfully.
2023-01-10	010	Project J	In Progress	Medium	Noah Blue	Team Alpha	2023-01-01	2023-01-20	19 days	80%	130000	104000	26000	Medium	Project J progress update.
2023-01-11	011	Project K	On Hold	Low	Olivia Red	Team Beta	2023-01-01	2023-02-28	58 days	15%	210000	31500	178500	High	Project K on hold due to budget constraints.
2023-01-12	012	Project L	Planned	High	Peter Yellow	Team Gamma	2023-01-15	2023-03-15	60 days	0%	200000	0	200000	Medium	Project L planning phase.
2023-01-13	013	Project M	Completed	Medium	Quinn Purple	Team Alpha	2022-12-25	2023-01-15	21 days	100%	140000	145000	-5000	Low	Project M completed with slight over budget.
2023-01-14	014	Project N	In Progress	High	Rachel Pink	Team Beta	2023-01-05	2023-01-25	20 days	70%	170000	119000	51000	Medium	Project N progress update.
2023-01-15	015	Project O	On Hold	Low	Sam Green	Team Gamma	2023-01-01	2023-02-28	58 days	10%	230000	23000	207000	High	Project O on hold due to resource allocation.
2023-01-16	016	Project P	Planned	Medium	Tyler Blue	Team Alpha	2023-01-20	2023-03-20	60 days	0%	195000	0	195000	Medium	Project P planning phase.
2023-01-17	017	Project Q	Completed	High	Uma Red	Team Beta	2022-12-15	2023-01-05	21 days	100%	115000	117000	-2000	Low	Project Q completed successfully.
2023-01-18	018	Project R	In Progress	Medium	Victor Yellow	Team Gamma	2023-01-01	2023-01-20	19 days	85%	135000	114750	20250	Medium	Project R progress update.
2023-01-19	019	Project S	On Hold	Low	Wendy Purple	Team Alpha	2023-01-01	2023-02-28	58 days	5%	240000	12000	228000	High	Project S on hold due to budget constraints.
2023-01-20	020	Project T	Planned	High	Xavier Pink	Team Beta	2023-01-15	2023-03-15	60 days	0%	205000	0	205000	Medium	Project T planning phase.
2023-01-21	021	Project U	Completed	Medium	Yara Green	Team Gamma	2022-12-20	2023-01-10	21 days	100%	125000	128000	-3000	Low	Project U completed with slight over budget.
2023-01-22	022	Project V	In Progress	High	Zoe Blue	Team Alpha	2023-01-05	2023-01-25	20 days	78%	175000	136500	38500	Medium	Project V progress update.
2023-01-23	023	Project W	On Hold	Low	Adam Red	Team Beta	2023-01-01	2023-02-28	58 days						

<Case 64>

SPLSR calculation for summation SAR>1.6W/kg

[illegible]



<Case 65>

SPLSR calculation for summation SAR>1.6W/kg

Project Information				Timeline		Budget		Risk		Performance		Communication		Stakeholder		Documentation		Compliance		Reporting	
Project Name	Project Manager	Project Sponsor	Project Charter	Start Date	End Date	Initial Budget	Current Budget	Risk Level	Risk Score	Performance Index	Performance Score	Communication Index	Communication Score	Stakeholder Index	Stakeholder Score	Documentation Index	Documentation Score	Compliance Index	Compliance Score	Reporting Index	Reporting Score
Project A	John Doe	Jane Smith	Project A Charter	2023-01-01	2023-12-31	\$1,000,000	\$1,000,000	Low	10	85	85	90	90	95	95	90	90	95	95	90	90
Project B	Jane Smith	John Doe	Project B Charter	2023-02-01	2024-01-31	\$2,500,000	\$2,500,000	Medium	20	75	75	80	80	85	85	80	80	85	85	80	80
Project C	John Doe	Jane Smith	Project C Charter	2023-03-01	2024-02-28	\$1,500,000	\$1,500,000	Low	15	90	90	95	95	90	90	95	95	90	90	95	95
Project D	Jane Smith	John Doe	Project D Charter	2023-04-01	2024-03-31	\$3,000,000	\$3,000,000	Medium	25	65	65	70	70	75	75	70	70	75	75	70	70
Project E	John Doe	Jane Smith	Project E Charter	2023-05-01	2024-04-30	\$2,000,000	\$2,000,000	Low	20	80	80	85	85	90	90	85	85	90	90	85	85
Project F	Jane Smith	John Doe	Project F Charter	2023-06-01	2024-05-31	\$1,800,000	\$1,800,000	Medium	18	70	70	75	75	80	80	75	75	80	80	75	75
Project G	John Doe	Jane Smith	Project G Charter	2023-07-01	2024-06-30	\$2,200,000	\$2,200,000	Low	22	85	85	90	90	95	95	90	90	95	95	90	90
Project H	Jane Smith	John Doe	Project H Charter	2023-08-01	2024-07-31	\$2,800,000	\$2,800,000	Medium	28	60	60	65	65	70	70	65	65	70	70	65	65
Project I	John Doe	Jane Smith	Project I Charter	2023-09-01	2024-08-31	\$1,600,000	\$1,600,000	Low	16	90	90	95	95	90	90	95	95	90	90	95	95
Project J	Jane Smith	John Doe	Project J Charter	2023-10-01	2024-09-30	\$2,400,000	\$2,400,000	Medium	24	75	75	80	80	85	85	80	80	85	85	80	80
Project K	John Doe	Jane Smith	Project K Charter	2023-11-01	2024-10-31	\$1,900,000	\$1,900,000	Low	19	80	80	85	85	90	90	85	85	90	90	85	85
Project L	Jane Smith	John Doe	Project L Charter	2023-12-01	2024-11-30	\$2,600,000	\$2,600,000	Medium	26	70	70	75	75	80	80	75	75	80	80	75	75
Project M	John Doe	Jane Smith	Project M Charter	2024-01-01	2024-12-31	\$1,700,000	\$1,700,000	Low	17	85	85	90	90	95	95	90	90	95	95	90	90
Project N	Jane Smith	John Doe	Project N Charter	2024-02-01	2025-01-31	\$2,100,000	\$2,100,000	Medium	21	65	65	70	70	75	75	70	70	75	75	70	70
Project O	John Doe	Jane Smith	Project O Charter	2024-03-01	2025-02-28	\$1,400,000	\$1,400,000	Low	14	90	90	95	95	90	90	95	95	90	90	95	95
Project P	Jane Smith	John Doe	Project P Charter	2024-04-01	2025-03-31	\$2,300,000	\$2,300,000	Medium	23	75	75	80	80	85	85	80	80	85	85	80	80
Project Q	John Doe	Jane Smith	Project Q Charter	2024-05-01	2025-04-30	\$1,800,000	\$1,800,000	Low	18	80	80	85	85	90	90	85	85	90	90	85	85
Project R	Jane Smith	John Doe	Project R Charter	2024-06-01	2025-05-31	\$2,000,000	\$2,000,000	Medium	20	70	70	75	75	80	80	75	75	80	80	75	75

Project Information				Timeline		Budget		Risk		Performance		Communication		Stakeholder		Documentation		Compliance		Reporting	
Project Name	Project Manager	Project Sponsor	Project Charter	Start Date	End Date	Initial Budget	Current Budget	Risk Level	Risk Score	Performance Index	Performance Score	Communication Index	Communication Score	Stakeholder Index	Stakeholder Score	Documentation Index	Documentation Score	Compliance Index	Compliance Score	Reporting Index	Reporting Score
Project A	John Doe	Jane Smith	Project A Charter	2023-01-01	2023-12-31	\$1,000,000	\$1,000,000	Low	10	85	85	90	90	95	95	90	90	95	95	90	90
Project B	Jane Smith	John Doe	Project B Charter	2023-02-01	2024-01-31	\$2,500,000	\$2,500,000	Medium	20	75	75	80	80	85	85	80	80	85	85	80	80
Project C	John Doe	Jane Smith	Project C Charter	2023-03-01	2024-02-28	\$1,500,000	\$1,500,000	Low	15	90	90	95	95	90	90	95	95	90	90	95	95
Project D	Jane Smith	John Doe	Project D Charter	2023-04-01	2024-03-31	\$3,000,000	\$3,000,000	Medium	25	65	65	70	70	75	75	70	70	75	75	70	70
Project E	John Doe	Jane Smith	Project E Charter	2023-05-01	2024-04-30	\$2,000,000	\$2,000,000	Low	20	80	80	85	85	90	90	85	85	90	90	85	85
Project F	Jane Smith	John Doe	Project F Charter	2023-06-01	2024-05-31	\$1,800,000	\$1,800,000	Medium	18	70	70	75	75	80	80	75	75	80	80	75	75
Project G	John Doe	Jane Smith	Project G Charter	2023-07-01	2024-06-30	\$2,200,000	\$2,200,000	Low	22	85	85	90	90	95	95	90	90	95	95	90	90
Project H	Jane Smith	John Doe	Project H Charter	2023-08-01	2024-07-31	\$2,800,000	\$2,800,000	Medium	28	60	60	65	65	70	70	65	65	70	70	65	65
Project I	John Doe	Jane Smith	Project I Charter	2023-09-01	2024-08-31	\$1,600,000	\$1,600,000	Low	16	90	90	95	95	90	90	95	95	90	90	95	95
Project J	Jane Smith	John Doe	Project J Charter	2023-10-01	2024-09-30	\$2,400,000	\$2,400,000	Medium	24	75	75	80	80	85	85	80	80	85	85	80	80
Project K	John Doe	Jane Smith	Project K Charter	2023-11-01	2024-10-31	\$1,900,000	\$1,900,000	Low	19	80	80	85	85	90	90	85	85	90	90	85	85
Project L	Jane Smith	John Doe	Project L Charter	2023-12-01	2024-11-30	\$2,600,000	\$2,600,000	Medium	26	70	70	75	75	80	80	75	75	80	80	75	75
Project M	John Doe	Jane Smith	Project M Charter	2024-01-01	2024-12-31	\$1,700,000	\$1,700,000	Low	17	85	85	90	90	95	95	90	90	95	95	90	90
Project N	Jane Smith	John Doe	Project N Charter	2024-02-01	2025-01-31	\$2,100,000	\$2,100,000	Medium	21	65	65	70	70	75	75	70	70	75	75	70	70
Project O	John Doe	Jane Smith	Project O Charter	2024-03-01	2025-02-28	\$1,400,000	\$1,400,000	Low	14	90	90	95	95	90	90	95	95	90	90	95	95
Project P	Jane Smith	John Doe	Project P Charter	2024-04-01	2025-03-31	\$2,300,000	\$2,300,000	Medium	23	75	75	80	80	85	85	80	80	85	85	80	80
Project Q	John Doe	Jane Smith	Project Q Charter	2024-05-01	2025-04-30	\$1,800,000	\$1,800,000	Low	18	80	80	85	85	90	90	85	85	90	90	85	85
Project R	Jane Smith	John Doe	Project R Charter	2024-06-01	2025-05-31	\$2,000,000	\$2,000,000	Medium	20	70	70	75	75	80	80	75	75	80	80	75	75

<Case 66>

SPLSR calculation for summation SAR>1.6W/kg

[illegible]

<Case 67>

SPLSR calculation for summation SAR>1.6W/kg

Project Overview				Timeline		Budget		Resources		Risk		Status		Notes	
Project Name	Start Date	End Date	Duration	Start Date	End Date	Budget	Actual	Resources	Availability	Risk Level	Impact	Current Status	Next Steps	Comments	Owner
Project A	2023-01-01	2023-03-31	90 Days	2023-01-01	2023-03-31	\$100,000	\$95,000	5 FTE	100%	Low	Minor	On Track	Review Progress	Project A is on track and within budget.	John Doe
Project B	2023-04-01	2023-06-30	90 Days	2023-04-01	2023-06-30	\$150,000	\$160,000	8 FTE	100%	Medium	Minor	Delayed	Investigate Delay	Project B is delayed and over budget.	Jane Smith
Project C	2023-07-01	2023-09-30	90 Days	2023-07-01	2023-09-30	\$200,000	\$190,000	10 FTE	100%	High	Major	At Risk	Monitor Closely	Project C is at risk of failure.	Mike Johnson
Project D	2023-10-01	2023-12-31	90 Days	2023-10-01	2023-12-31	\$120,000	\$115,000	6 FTE	100%	Low	Minor	On Track	Review Progress	Project D is on track and within budget.	Sarah Lee
Project E	2024-01-01	2024-03-31	90 Days	2024-01-01	2024-03-31	\$80,000	\$78,000	4 FTE	100%	Low	Minor	On Track	Review Progress	Project E is on track and within budget.	David Kim
Project F	2024-04-01	2024-06-30	90 Days	2024-04-01	2024-06-30	\$110,000	\$112,000	7 FTE	100%	Medium	Minor	On Track	Review Progress	Project F is on track and within budget.	Emily White
Project G	2024-07-01	2024-09-30	90 Days	2024-07-01	2024-09-30	\$130,000	\$125,000	9 FTE	100%	Medium	Minor	On Track	Review Progress	Project G is on track and within budget.	Chris Brown
Project H	2024-10-01	2024-12-31	90 Days	2024-10-01	2024-12-31	\$90,000	\$88,000	5 FTE	100%	Low	Minor	On Track	Review Progress	Project H is on track and within budget.	Alex Green
Project I	2025-01-01	2025-03-31	90 Days	2025-01-01	2025-03-31	\$140,000	\$135,000	8 FTE	100%	Medium	Minor	On Track	Review Progress	Project I is on track and within budget.	Olivia Black
Project J	2025-04-01	2025-06-30	90 Days	2025-04-01	2025-06-30	\$160,000	\$158,000	10 FTE	100%	High	Major	At Risk	Monitor Closely	Project J is at risk of failure.	Noah Gray
Project K	2025-07-01	2025-09-30	90 Days	2025-07-01	2025-09-30	\$180,000	\$175,000	12 FTE	100%	High	Major	At Risk	Monitor Closely	Project K is at risk of failure.	Isabella Blue
Project L	2025-10-01	2025-12-31	90 Days	2025-10-01	2025-12-31	\$100,000	\$98,000	6 FTE	100%	Low	Minor	On Track	Review Progress	Project L is on track and within budget.	Liam Red
Project M	2026-01-01	2026-03-31	90 Days	2026-01-01	2026-03-31	\$120,000	\$118,000	7 FTE	100%	Medium	Minor	On Track	Review Progress	Project M is on track and within budget.	Mia Purple
Project N	2026-04-01	2026-06-30	90 Days	2026-04-01	2026-06-30	\$140,000	\$138,000	9 FTE	100%	Medium	Minor	On Track	Review Progress	Project N is on track and within budget.	Benjamin Yellow
Project O	2026-07-01	2026-09-30	90 Days	2026-07-01	2026-09-30	\$160,000	\$158,000	11 FTE	100%	High	Major	At Risk	Monitor Closely	Project O is at risk of failure.	Charlotte Pink
Project P	2026-10-01	2026-12-31	90 Days	2026-10-01	2026-12-31	\$180,000	\$175,000	13 FTE	100%	High	Major	At Risk	Monitor Closely	Project P is at risk of failure.	Ethan Orange
Project Q	2027-01-01	2027-03-31	90 Days	2027-01-01	2027-03-31	\$100,000	\$98,000	6 FTE	100%	Low	Minor	On Track	Review Progress	Project Q is on track and within budget.	Ava Green
Project R	2027-04-01	2027-06-30	90 Days	2027-04-01	2027-06-30	\$120,000	\$118,000	7 FTE	100%	Medium	Minor	On Track	Review Progress	Project R is on track and within budget.	Lucas Blue
Project S	2027-07-01	2027-09-30	90 Days	2027-07-01	2027-09-30	\$140,000	\$138,000	9 FTE	100%	Medium	Minor	On Track	Review Progress	Project S is on track and within budget.	Sophia Yellow
Project T	2027-10-01	2027-12-31	90 Days	2027-10-01	2027-12-31	\$160,000	\$158,000	11 FTE	100%	High	Major	At Risk	Monitor Closely	Project T is at risk of failure.	Oliver Pink
Project U	2028-01-01	2028-03-31	90 Days	2028-01-01	2028-03-31	\$180,000	\$175,000	13 FTE	100%	High	Major	At Risk	Monitor Closely	Project U is at risk of failure.	Emma Orange
Project V	2028-04-01	2028-06-30	90 Days	2028-04-01	2028-06-30	\$100,000	\$98,000	6 FTE	100%	Low	Minor	On Track	Review Progress	Project V is on track and within budget.	William Green
Project W	2028-07-01	2028-09-30	90 Days	2028-07-01	2028-09-30	\$120,000	\$118,000	7 FTE	100%	Medium	Minor	On Track	Review Progress	Project W is on track and within budget.	Aria Blue
Project X	2028-10-01	2028-12-31	90 Days	2028-10-01	2028-12-31	\$140,000	\$138,000	9 FTE	100%						



<Case 68>

SPLSR calculation for summation SAR>1.6W/kg

Case	Frequency	Power	Antenna	Position	Distance	Summation SAR	3D distance	Summed SAR	SPLSR Results	Simultaneous SAR
68	900MHz	1.5W	WLAN5	Ant 2	1.381	1.54	99.8	1.54	0.02	Not required
68	900MHz	1.5W	WLAN5	Ant 3	0.157	1.54	123.8	1.66	0.02	Not required
68	900MHz	1.5W	WLAN5	Ant 4	0.276	1.54	121.5	1.58	0.02	Not required
68	900MHz	1.5W	WLAN5	Ant 5	0.194	1.54	62.4	0.35	0.00	Not required
68	900MHz	1.5W	WLAN5	Ant 6	0.157	1.54	39.0	0.43	0.01	Not required
68	900MHz	1.5W	WLAN5	Ant 7	0.276	1.54	30.6	0.47	0.01	Not required

Case	Frequency	Power	Antenna	Position	Distance	Summation SAR	3D distance	Summed SAR	SPLSR Results	Simultaneous SAR
68	900MHz	1.5W	WLAN5	Ant 2	1.381	1.54	99.8	1.54	0.02	Not required
68	900MHz	1.5W	WLAN5	Ant 3	0.157	1.54	123.8	1.66	0.02	Not required
68	900MHz	1.5W	WLAN5	Ant 4	0.276	1.54	121.5	1.58	0.02	Not required
68	900MHz	1.5W	WLAN5	Ant 5	0.194	1.54	62.4	0.35	0.00	Not required
68	900MHz	1.5W	WLAN5	Ant 6	0.157	1.54	39.0	0.43	0.01	Not required
68	900MHz	1.5W	WLAN5	Ant 7	0.276	1.54	30.6	0.47	0.01	Not required

<Case 69>

SPLSR calculation for summation SAR>1.6W/kg

Case	Frequency	Power	Antenna	Position	Distance	Summation SAR	3D distance	Summed SAR	SPLSR Results	Simultaneous SAR
69	900MHz	1.5W	WLAN5	Ant 2	1.381	1.54	99.8	1.54	0.02	Not required
69	900MHz	1.5W	WLAN5	Ant 3	0.157	1.54	123.8	1.66	0.02	Not required
69	900MHz	1.5W	WLAN5	Ant 4	0.276	1.54	121.5	1.58	0.02	Not required
69	900MHz	1.5W	WLAN5	Ant 5	0.194	1.54	62.4	0.35	0.00	Not required
69	900MHz	1.5W	WLAN5	Ant 6	0.157	1.54	39.0	0.43	0.01	Not required
69	900MHz	1.5W	WLAN5	Ant 7	0.276	1.54	30.6	0.47	0.01	Not required

Case	Frequency	Power	Antenna	Position	Distance	Summation SAR	3D distance	Summed SAR	SPLSR Results	Simultaneous SAR
69	900MHz	1.5W	WLAN5	Ant 2	1.381	1.54	99.8	1.54	0.02	Not required
69	900MHz	1.5W	WLAN5	Ant 3	0.157	1.54	123.8	1.66	0.02	Not required
69	900MHz	1.5W	WLAN5	Ant 4	0.276	1.54	121.5	1.58	0.02	Not required
69	900MHz	1.5W	WLAN5	Ant 5	0.194	1.54	62.4	0.35	0.00	Not required
69	900MHz	1.5W	WLAN5	Ant 6	0.157	1.54	39.0	0.43	0.01	Not required
69	900MHz	1.5W	WLAN5	Ant 7	0.276	1.54	30.6	0.47	0.01	Not required

<Case 70>

SPLSR calculation for summation SAR>1.6W/kg

Case	Frequency	Power	Antenna	Position	Distance	Summation SAR	3D distance	Summed SAR	SPLSR Results	Simultaneous SAR
70	900MHz	1.5W	WLAN5	Ant 2	1.381	1.54	99.8	1.54	0.02	Not required
70	900MHz	1.5W	WLAN5	Ant 3	0.157	1.54	123.8	1.66	0.02	Not required
70	900MHz	1.5W	WLAN5	Ant 4	0.276	1.54	121.5	1.58	0.02	Not required
70	900MHz	1.5W	WLAN5	Ant 5	0.194	1.54	62.4	0.35	0.00	Not required
70	900MHz	1.5W	WLAN5	Ant 6	0.157	1.54	39.0	0.43	0.01	Not required
70	900MHz	1.5W	WLAN5	Ant 7	0.276	1.54	30.6	0.47	0.01	Not required

Combination	SAR	X	Y	Z	3D distance (mm)	Summed SAR (W/kg)	SPLSR Results	Simultaneous SAR
Max WWAN Ant 2 + Max WWAN Ant 0	1.381	-5.4	-67.4	-207.0	99.8	1.54	0.02	Not required
WLAN2.4G Ant 3	0.157	14.0	30.5	-207.0				
Max WWAN Ant 2 + Max WWAN Ant 0	1.381	-56.5	-43.0	-207.0	123.8	1.66	0.02	Not required
WLAN5/6G Ant 4+3(3)	0.276	0.3	67.0	-207.0				
Max WWAN Ant 2 + Max WWAN Ant 0	1.381	-59.0	-42.0	-207.0	121.5	1.58	0.02	Not required
WLAN5/6G Ant 4+3(4)	0.194	-29.0	75.7	-207.0				
WLAN2.4G Ant 3	0.157	14.0	30.5	-207.0	62.4	0.35	0.00	Not required
WLAN5/6G Ant 4+3(4)	0.194	-29.0	75.7	-207.0				
WLAN2.4G Ant 3	0.157	14.0	30.5	-207.0	39.0	0.43	0.01	Not required
WLAN5/6G Ant 4+3(3)	0.276	0.3	67.0	-207.0				
WLAN5/6G Ant 4+3(3)	0.276	0.3	67.0	-207.0	30.6	0.47	0.01	Not required
WLAN5/6G Ant 4+3(4)	0.194	-29.0	75.7	-207.0				



SPLSR calculation for summation SAR>1.6W/kg

[illegible]

SPLSR calculation for summation SAR>1.6W/kg

[illegible]

SPLSR calculation for summation SAR>1.6W/kg

[illegible]

SPLSR calculation for summation SAR>1.6W/kg

Project Information				Project Overview		Project Phases										Project Milestones										Project Deliverables										Project Risks									
				Project Name	Project ID	Project Status		Project Start/End		Project Budget		Project Resources		Project Risks		Project Milestones		Project Deliverables		Project Risks		Project Deliverables		Project Risks		Project Deliverables																			
						Phase 1	Phase 2	Phase 3	Phase 4	Phase 5	Phase 6	Phase 7	Phase 8	Phase 9	Phase 10	Phase 11	Phase 12	Phase 13	Phase 14	Phase 15	Phase 16	Phase 17	Phase 18	Phase 19	Phase 20	Phase 21	Phase 22	Phase 23	Phase 24																
Project Name	Project ID	Project Status	Project Start/End	Project Budget	Project Resources	Project Risks	Project Milestones	Project Deliverables	Project Risks	Project Deliverables	Project Risks	Project Deliverables	Project Risks	Project Deliverables	Project Risks	Project Deliverables	Project Risks	Project Deliverables	Project Risks	Project Deliverables	Project Risks	Project Deliverables	Project Risks	Project Deliverables	Project Risks	Project Deliverables																			
Project A	101	Active	2023-01-01	2023-12-31	\$1,000,000	10 FTE	Low	2023-03-01	2023-06-30	2023-07-01	2023-09-30	2023-10-01	2023-12-31	2024-01-01	2024-03-31	2024-04-01	2024-06-30	2024-07-01	2024-09-30	2024-10-01	2024-12-31	2025-01-01	2025-03-31	2025-04-01	2025-06-30	2025-07-01																			
Project B	102	On Hold	2023-02-01	2023-11-30	\$500,000	5 FTE	Medium	2023-04-01	2023-08-31	2023-09-01	2023-11-30	2024-01-01	2024-03-31	2024-04-01	2024-06-30	2024-07-01	2024-09-30	2024-10-01	2024-12-31	2025-01-01	2025-03-31	2025-04-01	2025-06-30	2025-07-01	2025-09-30	2025-10-01																			
Project C	103	Completed	2023-03-01	2023-10-31	\$750,000	8 FTE	Low	2023-05-01	2023-09-30	2023-10-01	2023-12-31	2024-01-01	2024-03-31	2024-04-01	2024-06-30	2024-07-01	2024-09-30	2024-10-01	2024-12-31	2025-01-01	2025-03-31	2025-04-01	2025-06-30	2025-07-01	2025-09-30	2025-10-01																			
Project D	104	Active	2023-04-01	2024-03-31	\$1,200,000	12 FTE	High	2023-06-01	2023-12-31	2024-01-01	2024-03-31	2024-04-01	2024-06-30	2024-07-01	2024-09-30	2024-10-01	2024-12-31	2025-01-01	2025-03-31	2025-04-01	2025-06-30	2025-07-01	2025-09-30	2025-10-01	2025-12-31	2026-01-01																			
Project E	105	On Hold	2023-05-01	2024-02-28	\$600,000	6 FTE	Medium	2023-07-01	2024-01-31	2024-02-01	2024-03-31	2024-04-01	2024-06-30	2024-07-01	2024-09-30	2024-10-01	2024-12-31	2025-01-01	2025-03-31	2025-04-01	2025-06-30	2025-07-01	2025-09-30	2025-10-01	2025-12-31	2026-01-01																			
Project F	106	Completed	2023-06-01	2023-11-30	\$800,000	9 FTE	Low	2023-08-01	2023-11-30	2023-12-01	2024-01-31	2024-02-01	2024-03-31	2024-04-01	2024-06-30	2024-07-01	2024-09-30	2024-10-01	2024-12-31	2025-01-01	2025-03-31	2025-04-01	2025-06-30	2025-07-01	2025-09-30	2025-10-01																			
Project G	107	Active	2023-07-01	2024-06-30	\$900,000	11 FTE	Medium	2023-09-01	2024-06-30	2024-07-01	2024-09-30	2024-10-01	2024-12-31	2025-01-01	2025-03-31	2025-04-01	2025-06-30	2025-07-01	2025-09-30	2025-10-01	2025-12-31	2026-01-01	2026-03-31	2026-04-01	2026-06-30	2026-07-01																			
Project H	108	On Hold	2023-08-01	2024-05-31	\$700,000	7 FTE	Medium	2023-10-01	2024-05-31	2024-06-01	2024-08-31	2024-09-01	2024-11-30	2024-12-01	2025-01-31	2025-02-01	2025-03-31	2025-04-01	2025-06-30	2025-07-01	2025-09-30	2025-10-01	2025-12-31	2026-01-01	2026-03-31	2026-04-01																			
Project I	109	Completed	2023-09-01	2023-12-31	\$400,000	4 FTE	Low	2023-11-01	2023-12-31	2024-01-01	2024-01-31	2024-02-01	2024-02-28	2024-03-01	2024-03-31	2024-04-01	2024-04-30	2024-05-01	2024-05-31	2024-06-01	2024-06-30	2024-07-01	2024-07-31	2024-08-01	2024-08-31	2024-09-01																			
Project J	110	Active	2023-10-01	2024-09-30	\$1,100,000	10 FTE	Medium	2023-12-01	2024-09-30	2024-10-01	2024-12-31																																		

SPLSR calculation for summation SAR>1.6W/kg

[illegible]



SPLSR calculation for summation SAR>1.6W/kg

[illegible]

SPLSR calculation for summation SAR>1.6W/kg

Topic		Subtopic		Concept		Definition		Example		Application		Impact		Conclusion		Summary		Key Points		Notes	
				Concept	Definition	Example	Application	Impact	Conclusion	Summary	Key Points	Notes	Concept	Definition	Example	Application	Impact	Conclusion	Summary	Key Points	Notes
Topic 1	Subtopic 1.1	Concept 1.1.1	Definition 1.1.1	Example 1.1.1	Application 1.1.1	Impact 1.1.1	Conclusion 1.1.1	Summary 1.1.1	Key Points 1.1.1	Notes 1.1.1	Concept 1.1.2	Definition 1.1.2	Example 1.1.2	Application 1.1.2	Impact 1.1.2	Conclusion 1.1.2	Summary 1.1.2	Key Points 1.1.2	Notes 1.1.2		
	Subtopic 1.2	Concept 1.2.1	Definition 1.2.1	Example 1.2.1	Application 1.2.1	Impact 1.2.1	Conclusion 1.2.1	Summary 1.2.1	Key Points 1.2.1	Notes 1.2.1	Concept 1.2.2	Definition 1.2.2	Example 1.2.2	Application 1.2.2	Impact 1.2.2	Conclusion 1.2.2	Summary 1.2.2	Key Points 1.2.2	Notes 1.2.2		
	Subtopic 1.3	Concept 1.3.1	Definition 1.3.1	Example 1.3.1	Application 1.3.1	Impact 1.3.1	Conclusion 1.3.1	Summary 1.3.1	Key Points 1.3.1	Notes 1.3.1	Concept 1.3.2	Definition 1.3.2	Example 1.3.2	Application 1.3.2	Impact 1.3.2	Conclusion 1.3.2	Summary 1.3.2	Key Points 1.3.2	Notes 1.3.2		
	Subtopic 1.4	Concept 1.4.1	Definition 1.4.1	Example 1.4.1	Application 1.4.1	Impact 1.4.1	Conclusion 1.4.1	Summary 1.4.1	Key Points 1.4.1	Notes 1.4.1	Concept 1.4.2	Definition 1.4.2	Example 1.4.2	Application 1.4.2	Impact 1.4.2	Conclusion 1.4.2	Summary 1.4.2	Key Points 1.4.2	Notes 1.4.2		
Topic 2	Subtopic 2.1	Concept 2.1.1	Definition 2.1.1	Example 2.1.1	Application 2.1.1	Impact 2.1.1	Conclusion 2.1.1	Summary 2.1.1	Key Points 2.1.1	Notes 2.1.1	Concept 2.1.2	Definition 2.1.2	Example 2.1.2	Application 2.1.2	Impact 2.1.2	Conclusion 2.1.2	Summary 2.1.2	Key Points 2.1.2	Notes 2.1.2		
	Subtopic 2.2	Concept 2.2.1	Definition 2.2.1	Example 2.2.1	Application 2.2.1	Impact 2.2.1	Conclusion 2.2.1	Summary 2.2.1	Key Points 2.2.1	Notes 2.2.1	Concept 2.2.2	Definition 2.2.2	Example 2.2.2	Application 2.2.2	Impact 2.2.2	Conclusion 2.2.2	Summary 2.2.2	Key Points 2.2.2	Notes 2.2.2		
	Subtopic 2.3	Concept 2.3.1	Definition 2.3.1	Example 2.3.1	Application 2.3.1	Impact 2.3.1	Conclusion 2.3.1	Summary 2.3.1	Key Points 2.3.1	Notes 2.3.1	Concept 2.3.2	Definition 2.3.2	Example 2.3.2	Application 2.3.2	Impact 2.3.2	Conclusion 2.3.2	Summary 2.3.2	Key Points 2.3.2	Notes 2.3.2		
	Subtopic 2.4	Concept 2.4.1	Definition 2.4.1	Example 2.4.1	Application 2.4.1	Impact 2.4.1	Conclusion 2.4.1	Summary 2.4.1	Key Points 2.4.1	Notes 2.4.1	Concept 2.4.2	Definition 2.4.2	Example 2.4.2	Application 2.4.2	Impact 2.4.2	Conclusion 2.4.2	Summary 2.4.2	Key Points 2.4.2	Notes 2.4.2		
Topic 3	Subtopic 3.1	Concept 3.1.1	Definition 3.1.1	Example 3.1.1	Application 3.1.1	Impact 3.1.1	Conclusion 3.1.1	Summary 3.1.1	Key Points 3.1.1	Notes 3.1.1	Concept 3.1.2	Definition 3.1.2	Example 3.1.2	Application 3.1.2	Impact 3.1.2	Conclusion 3.1.2	Summary 3.1.2	Key Points 3.1.2	Notes 3.1.2		
	Subtopic 3.2	Concept 3.2.1	Definition 3.2.1	Example 3.2.1	Application 3.2.1	Impact 3.2.1	Conclusion 3.2.1	Summary 3.2.1	Key Points 3.2.1	Notes 3.2.1	Concept 3.2.2	Definition 3.2.2	Example 3.2.2	Application 3.2.2	Impact 3.2.2	Conclusion 3.2.2	Summary 3.2.2	Key Points 3.2.2	Notes 3.2.2		
	Subtopic 3.3	Concept 3.3.1	Definition 3.3.1	Example 3.3.1	Application 3.3.1	Impact 3.3.1	Conclusion 3.3.1	Summary 3.3.1	Key Points 3.3.1	Notes 3.3.1	Concept 3.3.2	Definition 3.3.2	Example 3.3.2	Application 3.3.2	Impact 3.3.2	Conclusion 3.3.2	Summary 3.3.2	Key Points 3.3.2	Notes 3.3.2		
	Subtopic 3.4	Concept 3.4.1	Definition 3.4.1	Example 3.4.1	Application 3.4.1	Impact 3.4.1	Conclusion 3.4.1	Summary 3.4.1	Key Points 3.4.1	Notes 3.4.1	Concept 3.4.2	Definition 3.4.2	Example 3.4.2	Application 3.4.2	Impact 3.4.2	Conclusion 3.4.2	Summary 3.4.2	Key Points 3.4.2	Notes 3.4.2		
Topic 4	Subtopic 4.1	Concept 4.1.1	Definition 4.1.1	Example 4.1.1	Application 4.1.1	Impact 4.1.1	Conclusion 4.1.1	Summary 4.1.1	Key Points 4.1.1	Notes 4.1.1	Concept 4.1.2	Definition 4.1.2	Example 4.1.2	Application 4.1.2	Impact 4.1.2	Conclusion 4.1.2	Summary 4.1.2	Key Points 4.1.2	Notes 4.1.2		
	Subtopic 4.2	Concept 4.2.1	Definition 4.2.1	Example 4.2.1	Application 4.2.1	Impact 4.2.1	Conclusion 4.2.1	Summary 4.2.1	Key Points 4.2.1	Notes 4.2.1	Concept 4.2.2	Definition 4.2.2	Example 4.2.2	Application 4.2.2	Impact 4.2.2	Conclusion 4.2.2	Summary 4.2.2	Key Points 4.2.2	Notes 4.2.2		
	Subtopic 4.3	Concept 4.3.1	Definition 4.3.1	Example 4.3.1	Application 4.3.1	Impact 4.3.1	Conclusion 4.3.1	Summary 4.3.1	Key Points 4.3.1	Notes 4.3.1	Concept 4.3.2	Definition 4.3.2	Example 4.3.2	Application 4.3.2	Impact 4.3.2	Conclusion 4.3.2	Summary 4.3.2	Key Points 4.3.2	Notes 4.3.2		
	Subtopic 4.4	Concept 4.4.1	Definition 4.4.1	Example 4.4.1	Application 4.4.1	Impact 4.4.1	Conclusion 4.4.1	Summary 4.4.1	Key Points 4.4.1	Notes 4.4.1	Concept 4.4.2	Definition 4.4.2	Example 4.4.2	Application 4.4.2	Impact 4.4.2	Conclusion 4.4.2	Summary 4.4.2	Key Points 4.4.2	Notes 4.4.2		
Topic 5	Subtopic 5.1	Concept 5.1.1	Definition 5.1.1	Example 5.1.1	Application 5.1.1	Impact 5.1.1	Conclusion 5.1.1	Summary 5.1.1	Key Points 5.1.1	Notes 5.1.1	Concept 5.1.2	Definition 5.1.2	Example 5.1.2	Application 5.1.2	Impact 5.1.2	Conclusion 5.1.2	Summary 5.1.2	Key Points 5.1.2	Notes 5.1.2		
	Subtopic 5.2	Concept 5.2.1	Definition 5.2.1	Example 5.2.1	Application 5.2.1	Impact 5.2.1	Conclusion 5.2.1	Summary 5.2.1	Key Points 5.2.1	Notes 5.2.1	Concept 5.2.2	Definition 5.2.2	Example 5.2.2	Application 5.2.2	Impact 5.2.2	Conclusion 5.2.2	Summary 5.2.2	Key Points 5.2.2	Notes 5.2.2		
	Subtopic 5.3	Concept 5.3.1	Definition 5.3.1	Example 5.3.1	Application 5.3.1	Impact 5.3.1	Conclusion 5.3.1	Summary 5.3.1	Key Points 5.3.1	Notes 5.3.1	Concept 5.3.2	Definition 5.3.2	Example 5.3.2	Application 5.3.2	Impact 5.3.2	Conclusion 5.3.2	Summary 5.3.2	Key Points 5.3.2	Notes 5.3.2		
	Subtopic 5.4	Concept 5.4.1	Definition 5.4.1	Example 5.4.1	Application 5.4.1	Impact 5.4.1	Conclusion 5.4.1	Summary 5.4.1	Key Points 5.4.1	Notes 5.4.1	Concept 5.4.2	Definition 5.4.2	Example 5.4.2	Application 5.4.2	Impact 5.4.2	Conclusion 5.4.2	Summary 5.4.2	Key Points 5.4.2	Notes 5.4.2		

SPLSR calculation for summation SAR>1.6W/kg

[illegible]

SPLSR calculation for summation SAR>1.6W/kg

Year	Country	Domestic Supply (kg)	Domestic Demand (kg)	Year 1										Year 2										Year 3										Year 4										Year 5										Year 6										Year 7										Year 8										Year 9										Year 10												Year 11												Year 12												Year 13												Year 14												Year 15												Year 16												Year 17												Year 18												Year 19												Year 20												Year 21												Year 22												Year 23												Year 24												Year 25												Year 26												Year 27												Year 28												Year 29												Year 30														Year 31														Year 32														Year 33														Year 34														Year 35														Year 36														Year 37														Year 38			
------	---------	----------------------	----------------------	--------	--	--	--	--	--	--	--	--	--	--------	--	--	--	--	--	--	--	--	--	--------	--	--	--	--	--	--	--	--	--	--------	--	--	--	--	--	--	--	--	--	--------	--	--	--	--	--	--	--	--	--	--------	--	--	--	--	--	--	--	--	--	--------	--	--	--	--	--	--	--	--	--	--------	--	--	--	--	--	--	--	--	--	--------	--	--	--	--	--	--	--	--	--	---------	--	--	--	--	--	--	--	--	--	--	--	---------	--	--	--	--	--	--	--	--	--	--	--	---------	--	--	--	--	--	--	--	--	--	--	--	---------	--	--	--	--	--	--	--	--	--	--	--	---------	--	--	--	--	--	--	--	--	--	--	--	---------	--	--	--	--	--	--	--	--	--	--	--	---------	--	--	--	--	--	--	--	--	--	--	--	---------	--	--	--	--	--	--	--	--	--	--	--	---------	--	--	--	--	--	--	--	--	--	--	--	---------	--	--	--	--	--	--	--	--	--	--	--	---------	--	--	--	--	--	--	--	--	--	--	--	---------	--	--	--	--	--	--	--	--	--	--	--	---------	--	--	--	--	--	--	--	--	--	--	--	---------	--	--	--	--	--	--	--	--	--	--	--	---------	--	--	--	--	--	--	--	--	--	--	--	---------	--	--	--	--	--	--	--	--	--	--	--	---------	--	--	--	--	--	--	--	--	--	--	--	---------	--	--	--	--	--	--	--	--	--	--	--	---------	--	--	--	--	--	--	--	--	--	--	--	---------	--	--	--	--	--	--	--	--	--	--	--	---------	--	--	--	--	--	--	--	--	--	--	--	--	--	---------	--	--	--	--	--	--	--	--	--	--	--	--	--	---------	--	--	--	--	--	--	--	--	--	--	--	--	--	---------	--	--	--	--	--	--	--	--	--	--	--	--	--	---------	--	--	--	--	--	--	--	--	--	--	--	--	--	---------	--	--	--	--	--	--	--	--	--	--	--	--	--	---------	--	--	--	--	--	--	--	--	--	--	--	--	--	---------	--	--	--	--	--	--	--	--	--	--	--	--	--	---------	--	--	--

SPLSR calculation for summation SAR>1.6W/kg

Region	Population (2023)		GDP (2023)		Unemployment Rate (%)		Inflation Rate (%)		Poverty Share (%)		Healthcare Expenditure (\$Bn)		Education Expenditure (\$Bn)		Renewable Energy Share (%)		Digital Literacy Rate (%)		Gender Equality Index	
	Urban	Rural	Urban	Rural	Urban	Rural	Urban	Rural	Urban	Rural	Urban	Rural	Urban	Rural	Urban	Rural	Urban	Rural	Urban	Rural
North America	120M	80M	\$25T	\$15T	4.5%	3.8%	3.2%	2.5%	8.5%	7.2%	\$120B	\$80B	\$45B	\$30B	15%	12%	65%	55%	78%	72%
	115M	75M	\$24T	\$14T	4.8%	4.1%	3.5%	2.8%	9.0%	7.8%	\$115B	\$75B	\$43B	\$28B	14%	11%	63%	53%	76%	70%
	110M	70M	\$23T	\$13T	5.1%	4.4%	3.8%	3.1%	9.5%	8.3%	\$110B	\$70B	\$41B	\$26B	13%	10%	61%	51%	74%	68%
Europe	75M	50M	\$18T	\$10T	3.5%	2.8%	2.5%	1.8%	6.5%	5.2%	\$90B	\$60B	\$35B	\$22B	12%	9%	60%	50%	75%	69%
	70M	45M	\$17T	\$9T	3.8%	3.1%	2.8%	2.1%	7.0%	5.8%	\$85B	\$55B	\$33B	\$20B	11%	8%	58%	48%	73%	67%
	65M	40M	\$16T	\$8T	4.1%	3.4%	3.1%	2.4%	7.5%	6.3%	\$80B	\$50B	\$31B	\$18B	10%	7%	56%	46%	71%	65%
Asia	150M	100M	\$30T	\$18T	5.5%	4.8%	4.2%	3.5%	10.5%	9.2%	\$150B	\$100B	\$60B	\$40B	18%	15%	70%	60%	80%	74%
	145M	95M	\$29T	\$17T	5.8%	5.1%	4.5%	3.8%	11.0%	9.8%	\$145B	\$95B	\$58B	\$38B	17%	14%	68%	58%	78%	72%
	140M	90M	\$28T	\$16T	6.1%	5.4%	4.8%	4.1%	11.5%	10.3%	\$140B	\$90B	\$56B	\$36B	16%	13%	66%	56%	76%	70%
South America	45M	30M	\$8T	\$5T	6.5%	5.8%	5.2%	4.5%	12.5%	11.2%	\$40B	\$25B	\$15B	\$10B	8%	6%	55%	45%	65%	59%
	40M	25M	\$7T	\$4T	6.8%	6.1%	5.5%	4.8%	13.0%	11.8%	\$38B	\$23B	\$14B	\$9B	7%	5%	53%	43%	63%	57%
	35M	20M	\$6T	\$3T	7.1%	6.4%	5.8%	5.1%	13.5%	12.3%	\$35B	\$20B	\$13B	\$8B	6%	4%	51%	41%	61%	55%
Africa	25M	15M	\$3T	\$1.5T	8.5%	7.8%	7.2%	6.5%	15.5%	14.2%	\$15B	\$8B	\$5B	\$3B	3%	2%	40%	30%	50%	44%
	20M	10M	\$2T	\$1T	8.8%	8.1%	7.5%	6.8%	16.0%	14.8%	\$14B	\$7B	\$4B	\$2B	2%	1%	38%	28%	48%	42%
	15M	5M	\$1T	\$0.5T	9.1%	8.4%	7.8%	7.1%	16.5%	15.3%	\$13B	\$6B	\$3B	\$1B	1%	0%	36%	26%	46%	40%
Oceania	20M	10M	\$4T	\$2T	4.0%	3.2%	2.8%	2.0%	7.0%	5.8%	\$20B	\$10B	\$8B	\$5B	5%	3%	60%	50%	70%	64%
	18M	9M	\$3.5T	\$1.8T	4.3%	3.5%	3.1%	2.3%	7.3%	6.1%	\$19B	\$9B	\$7B	\$4B	4%	2%	58%	48%	68%	62%
	16M	8M	\$3T	\$1.6T	4.6%	3.8%	3.4%	2.6%	7.6%	6.4%	\$18B	\$8B	\$6B	\$3B	3%	1%	56%	46%	66%	60%



SPLSR calculation for summation SAR>1.6W/kg

[illegible]

SPLSR calculation for summation SAR>1.6W/kg

[illegible]

SPLSR calculation for summation SAR>1.6W/kg

[illegible]

SPLSR calculation for summation SAR>1.6W/kg

[illegible][illegible]

<Case 94>

SPLSR calculation for summation SAR>1.6W/kg

[illegible][illegible]

<Case 95>

SPLSR calculation for summation SAR>1.6W/kg

[illegible]

SAP (part number, description)		1.2.20		1.2.21		1.2.22		1.2.23		1.2.24		1.2.25		1.2.26		1.2.27		1.2.28		1.2.29		1.2.30		1.2.31		1.2.32		1.2.33		1.2.34		1.2.35		1.2.36		1.2.37		1.2.38		1.2.39		1.2.40		1.2.41		1.2.42		1.2.43		1.2.44		1.2.45		1.2.46		1.2.47		1.2.48		1.2.49		1.2.50		1.2.51		1.2.52		1.2.53		1.2.54		1.2.55		1.2.56		1.2.57		1.2.58		1.2.59		1.2.60		1.2.61		1.2.62		1.2.63		1.2.64		1.2.65		1.2.66		1.2.67		1.2.68		1.2.69		1.2.70		1.2.71		1.2.72		1.2.73		1.2.74		1.2.75		1.2.76		1.2.77		1.2.78		1.2.79		1.2.80		1.2.81		1.2.82		1.2.83		1.2.84		1.2.85		1.2.86		1.2.87		1.2.88		1.2.89		1.2.90		1.2.91		1.2.92		1.2.93		1.2.94		1.2.95		1.2.96		1.2.97		1.2.98		1.2.99		1.3.00		1.3.01		1.3.02		1.3.03		1.3.04		1.3.05		1.3.06		1.3.07		1.3.08		1.3.09		1.3.10		1.3.11		1.3.12		1.3.13		1.3.14		1.3.15		1.3.16		1.3.17		1.3.18		1.3.19		1.3.20		1.3.21		1.3.22		1.3.23		1.3.24		1.3.25		1.3.26		1.3.27		1.3.28		1.3.29		1.3.30		1.3.31		1.3.32		1.3.33		1.3.34		1.3.35		1.3.36		1.3.37		1.3.38		1.3.39		1.3.40		1.3.41		1.3.42		1.3.43		1.3.44		1.3.45		1.3.46		1.3.47		1.3.48		1.3.49		1.3.50		1.3.51		1.3.52		1.3.53		1.3.54		1.3.55		1.3.56		1.3.57		1.3.58		1.3.59		1.3.60		1.3.61		1.3.62		1.3.63		1.3.64		1.3.65		1.3.66		1.3.67		1.3.68		1.3.69		1.3.70		1.3.71		1.3.72		1.3.73		1.3.74		1.3.75		1.3.76		1.3.77		1.3.78		1.3.79		1.3.80		1.3.81		1.3.82		1.3.83		1.3.84		1.3.85		1.3.86		1.3.87		1.3.88		1.3.89		1.3.90		1.3.91		1.3.92		1.3.93		1.3.94		1.3.95		1.3.96		1.3.97		1.3.98		1.3.99		1.4.00		1.4.01		1.4.02		1.4.03		1.4.04		1.4.05		1.4.06		1.4.07		1.4.08		1.4.09		1.4.10		1.4.11		1.4.12		1.4.13		1.4.14		1.4.15		1.4.16		1.4.17		1.4.18		1.4.19		1.4.20		1.4.21		1.4.22		1.4.23		1.4.24		1.4.25		1.4.26		1.4.27		1.4.28		1.4.29		1.4.30		1.4.31		1.4.32		1.4.33		1.4.34		1.4.35		1.4.36		1.4.37		1.4.38		1.4.39		1.4.40		1.4.41		1.4.42		1.4.43		1.4.44		1.4.45		1.4.46		1.4.47		1.4.48		1.4.49		1.4.50		1.4.51		1.4.52		1.4.53		1.4.54		1.4.55		1.4.56		1.4.57		1.4.58		1.4.59		1.4.60		1.4.61		1.4.62		1.4.63		1.4.64		1.4.65		1.4.66		1.4.67		1.4.68		1.4.69		1.4.70		1.4.71		1.4.72		1.4.73		1.4.74		1.4.75		1.4.76		1.4.77		1.4.78		1.4.79		1.4.80		1.4.81		1.4.82		1.4.83		1.4.84		1.4.85		1.4.86		1.4.87		1.4.88		1.4.89		1.4.90	
--------------------------------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--	--------	--



<Case 98>

SPLSR calculation for summation SAR>1.6W/kg

Exposure Position	0	1	2	9	10	11
	WWAN SAR	WLAN2.4GHz Ant 3	WLAN5/6GHz Ant 4+3	LTE Band 48_Ant 6 TX0	FR1 n48_Ant 6 TX0	FR1 n77_Ant 6 TX0
Back	1g SAR (W/kg)			0.317	0.341	0.523
				0+1+2+9 Summed SAR	0+1+2+10 Summed SAR	0+1+2+11 Summed SAR
GSM850_Ant 1 TX1	0.640	0.157	0.276	1.390	1.414	1.596
WCDMA V_Ant 1 TX1	0.490	0.157	0.276	1.240	1.264	1.446
LTE Band 12_Ant 1 TX1	0.351	0.157	0.276	1.101	1.125	1.307
LTE Band 13_Ant 1 TX1	0.515	0.157	0.276	1.265	1.289	1.471
LTE Band 14_Ant 1 TX1	0.520	0.157	0.276	1.270	1.294	1.476
LTE Band 25_Ant 1 Sub TX0	0.842	0.157	0.276	1.592	1.616	1.798
LTE Band 26_Ant 1 TX1	0.417	0.157	0.276	1.167	1.191	1.373
LTE Band 66_Ant 1 Sub TX0	0.832	0.157	0.276	1.582	1.606	1.788
LTE Band 71_Ant 1 TX1	0.289	0.157	0.276	1.039	1.063	1.245
FR1 n12_Ant 1 TX1	0.422	0.157	0.276	1.172	1.196	1.378
FR1 n14_Ant 1 TX1	0.533	0.157	0.276	1.283	1.307	1.489
FR1 n25_Ant 1 Sub TX0	0.746	0.157	0.276	1.496	1.520	1.702
FR1 n26_Ant 1 TX1	0.424	0.157	0.276	1.174	1.198	1.380
FR1 n41_Ant 1 Sub TX0	0.819	0.157	0.276	1.569	1.593	1.775
FR1 n48_Ant 1 Sub TX0	0.343	0.157	0.276	1.093	1.117	1.299
FR1 n66_Ant 1 Sub TX0	0.722	0.157	0.276	1.472	1.496	1.678
FR1 n71_Ant 1 TX1	0.346	0.157	0.276	1.096	1.120	1.302
FR1 n77_Ant 1 Sub TX0	0.384	0.157	0.276	1.134	1.158	1.340

SAR peak location (mm)			X (axis)		14	0.3	12	-23	12.5
			Y (axis)		30.5	67	-57	-75.5	-96
			Z (axis)		-207	-207	-207	-207	-207
X (axis)	Y (axis)	Z (axis)	Exposure Position	0	1	2	9	10	11
				WWAN SAR	WLAN2.4GHz Ant 3	WLAN5/6GHz Ant 4+3	LTE Band 48_Ant 6 TX0	FR1 n48_Ant 6 TX0	FR1 n77_Ant 6 TX0
			Back	1g SAR (W/kg)			0.317	0.341	0.523
							0+1+2+9 SPLSR Results	0+1+2+10 SPLSR Results	0+1+2+11 SPLSR Results
4.6	56.1	-207	GSM850_Ant 1 TX1	0.640	0.157	0.276			0.02
4.1	56.8	-207	WCDMA V_Ant 1 TX1	0.490	0.157	0.276			
8	56.8	-207	LTE Band 12_Ant 1 TX1	0.351	0.157	0.276			
6.3	53.8	-207	LTE Band 13_Ant 1 TX1	0.515	0.157	0.276			
2.8	56.3	-207	LTE Band 14_Ant 1 TX1	0.520	0.157	0.276			
1.9	76.6	-207	LTE Band 25_Ant 1 Sub TX0	0.842	0.157	0.276		0.02	0.03
1.9	55.1	-207	LTE Band 26_Ant 1 TX1	0.417	0.157	0.276			
-2.4	75.9	-207	LTE Band 66_Ant 1 Sub TX0	0.832	0.157	0.276		0.02	0.03
5.1	55.8	-207	LTE Band 71_Ant 1 TX1	0.289	0.157	0.276			
3.6	56.1	-207	FR1 n12_Ant 1 TX1	0.422	0.157	0.276			
0.3	56.1	-207	FR1 n14_Ant 1 TX1	0.533	0.157	0.276			
0.9	79.6	-207	FR1 n25_Ant 1 Sub TX0	0.746	0.157	0.276			0.03
1.3	56.6	-207	FR1 n26_Ant 1 TX1	0.424	0.157	0.276			
-5	77	-207	FR1 n41_Ant 1 Sub TX0	0.819	0.157	0.276			0.03
-35.5	80	-207	FR1 n48_Ant 1 Sub TX0	0.343	0.157	0.276			
3.6	78.9	-207	FR1 n66_Ant 1 Sub TX0	0.722	0.157	0.276			0.03
4.1	55.1	-207	FR1 n71_Ant 1 TX1	0.346	0.157	0.276			
14.5	65	-207	FR1 n77_Ant 1 Sub TX0	0.384	0.157	0.276			

<Case 99>

SPLSR calculation for summation SAR>1.6W/kg

Exposure Position	0	1	2	9	10	11
	WWAN SAR	WLAN2.4GHz Ant 4	WLAN5/6GHz Ant 4+3	LTE Band 48_Ant 6 TX0	FR1 n48_Ant 6 TX0	FR1 n77_Ant 6 TX0
Back	1g SAR (W/kg)			0.317	0.341	0.523
				0+1+2+9 Summed SAR	0+1+2+10 Summed SAR	0+1+2+11 Summed SAR
GSM850_Ant 1 TX1	0.640	0.062	0.276	1.295	1.319	1.501
WCDMA V_Ant 1 TX1	0.490	0.062	0.276	1.145	1.169	1.351
LTE Band 12_Ant 1 TX1	0.351	0.062	0.276	1.006	1.030	1.212
LTE Band 13_Ant 1 TX1	0.515	0.062	0.276	1.170	1.194	1.376
LTE Band 14_Ant 1 TX1	0.520	0.062	0.276	1.175	1.199	1.381
LTE Band 25_Ant 1 Sub TX0	0.842	0.062	0.276	1.497	1.521	1.703
LTE Band 26_Ant 1 TX1	0.417	0.062	0.276	1.072	1.096	1.278
LTE Band 66_Ant 1 Sub TX0	0.832	0.062	0.276	1.487	1.511	1.693
LTE Band 71_Ant 1 TX1	0.289	0.062	0.276	0.944	0.968	1.150
FR1 n12_Ant 1 TX1	0.422	0.062	0.276	1.077	1.101	1.283
FR1 n14_Ant 1 TX1	0.533	0.062	0.276	1.188	1.212	1.394
FR1 n25_Ant 1 Sub TX0	0.746	0.062	0.276	1.401	1.425	1.607
FR1 n26_Ant 1 TX1	0.424	0.062	0.276	1.079	1.103	1.285
FR1 n41_Ant 1 Sub TX0	0.819	0.062	0.276	1.474	1.498	1.680
FR1 n48_Ant 1 Sub TX0	0.343	0.062	0.276	0.998	1.022	1.204
FR1 n66_Ant 1 Sub TX0	0.722	0.062	0.276	1.377	1.401	1.583
FR1 n71_Ant 1 TX1	0.346	0.062	0.276	1.001	1.025	1.207
FR1 n77_Ant 1 Sub TX0	0.384	0.062	0.276	1.039	1.063	1.245

SAR peak location (mm)			X (axis)		-59	0.3	12	-23	12.5
			Y (axis)		36	67	-57	-75.5	-56
			Z (axis)		-207	-207	-207	-207	-207
X (axis)	Y (axis)	Z (axis)	Exposure Position	0	1	2	9	10	11
				WWAN SAR	WLAN2.4GHz Ant 4	WLAN5/6GHz Ant 4+3	LTE Band 48_Ant 6 TX0	FR1 n48_Ant 6 TX0	FR1 n77_Ant 6 TX0
			Back	1g SAR (W/kg)			0.317	0.341	0.523
							0+1+2+9 SPLSR Results	0+1+2+10 SPLSR Results	0+1+2+11 SPLSR Results
4.6	56.1	-207	GSM850_Ant 1 TX0	0.640	0.062	0.276			
4.1	56.8	-207	WCDMA V_Ant 1 TX0	0.490	0.062	0.276			
8	56.8	-207	LTE Band 12_Ant 1 TX0	0.351	0.062	0.276			
6.3	53.8	-207	LTE Band 13_Ant 1 TX0	0.515	0.062	0.276			
2.8	56.3	-207	LTE Band 14_Ant 1 TX0	0.520	0.062	0.276			
1.9	76.6	-207	LTE Band 25_Ant 1 Sub TX0	0.842	0.062	0.276			0.02
1.9	55.1	-207	LTE Band 26_Ant 1 TX0	0.417	0.062	0.276			
-2.4	75.9	-207	LTE Band 66_Ant 1 Sub TX0	0.832	0.062	0.276			0.02
5.1	55.8	-207	LTE Band 71_Ant 1 TX0	0.289	0.062	0.276			
3.6	56.1	-207	FR1 n12_Ant 1 TX0	0.422	0.062	0.276			
0.3	56.1	-207	FR1 n14_Ant 1 TX0	0.533	0.062	0.276			
0.9	79.6	-207	FR1 n25_Ant 1 Sub TX0	0.746	0.062	0.276			0.02
1.3	56.6	-207	FR1 n26_Ant 1 TX0	0.424	0.062	0.276			
-5	77	-207	FR1 n41_Ant 1 Sub TX0	0.819	0.062	0.276			0.02
-35.5	80	-207	FR1 n48_Ant 1 Sub TX0	0.343	0.062	0.276			
3.6	78.9	-207	FR1 n66_Ant 1 Sub TX0	0.722	0.062	0.276			
4.1	55.1	-207	FR1 n71_Ant 1 TX0	0.346	0.062	0.276			
14.5	65	-207	FR1 n77_Ant 1 Sub TX0	0.384	0.062	0.276			



<Case 100>

SPLSR calculation for summation SAR>1.6W/kg

Exposure Position	0	1	2	9	10	11
	WWAN SAR	WLAN2.4GHz Ant 4+3	WLAN5/6GHz Ant 4+3	LTE Band 48_Ant 6 TXD	FR1 n48_Ant 6 TXD	FR1 n77_Ant 6 TXD
Back	1g SAR (W/kg)			0.317	0.341	0.523
				0+1+2+9 Summed SAR	0+1+2+10 Summed SAR	0+1+2+11 Summed SAR
GSM850_Ant 1 TXI	0.640	0.145	0.276	1.378	1.402	1.584
WCDMA V_Ant 1 TXI	0.490	0.145	0.276	1.228	1.252	1.434
LTE Band 12_Ant 1 TXI	0.351	0.145	0.276	1.089	1.113	1.295
LTE Band 13_Ant 1 TXI	0.515	0.145	0.276	1.253	1.277	1.459
LTE Band 14_Ant 1 TXI	0.520	0.145	0.276	1.258	1.282	1.464
LTE Band 25_Ant 1 Sub TXD	0.842	0.145	0.276	1.580	1.604	1.786
LTE Band 26_Ant 1 TXI	0.417	0.145	0.276	1.155	1.179	1.361
LTE Band 66_Ant 1 Sub TXD	0.832	0.145	0.276	1.570	1.594	1.776
LTE Band 71_Ant 1 TXI	0.289	0.145	0.276	1.027	1.051	1.233
FR1 n12_Ant 1 TXI	0.422	0.145	0.276	1.160	1.184	1.366
FR1 n14_Ant 1 TXI	0.533	0.145	0.276	1.271	1.295	1.477
FR1 n25_Ant 1 Sub TXD	0.746	0.145	0.276	1.484	1.508	1.690
FR1 n26_Ant 1 TXI	0.424	0.145	0.276	1.162	1.186	1.368
FR1 n41_Ant 1 Sub TXD	0.819	0.145	0.276	1.557	1.581	1.763
FR1 n48_Ant 1 Sub TXD	0.343	0.145	0.276	1.081	1.105	1.287
FR1 n66_Ant 1 Sub TXD	0.722	0.145	0.276	1.460	1.484	1.666
FR1 n71_Ant 1 TXI	0.346	0.145	0.276	1.084	1.108	1.290
FR1 n77_Ant 1 Sub TXD	0.384	0.145	0.276	1.122	1.146	1.328

SAR peak location (mm)			X (axis)		16	0.3	12	-23	12.5
			Y (axis)		30	67	-57	-75.5	-56
			Z (axis)		-207	-207	-207	-207	-207
X (axis)	Y (axis)	Z (axis)	Exposure Position	0	1	2	9	10	11
			Back	WWAN SAR	WLAN2.4GHz Ant 4+3	WLAN5/6GHz Ant 4+3	LTE Band 48_Ant 6 TXD	FR1 n48_Ant 6 TXD	FR1 n77_Ant 6 TXD
			1g SAR (W/kg)			0.317			
						0+1+2+9 SPLSR Results			
4.6	56.1	-207	GSM850_Ant 1 TXI	0.640	0.145	0.276			
4.1	56.8	-207	WCDMA V_Ant 1 TXI	0.490	0.145	0.276			
8	56.8	-207	LTE Band 12_Ant 1 TXI	0.351	0.145	0.276			
6.3	53.8	-207	LTE Band 13_Ant 1 TXI	0.515	0.145	0.276			
2.8	56.3	-207	LTE Band 14_Ant 1 TXI	0.520	0.145	0.276			
1.9	76.6	-207	LTE Band 25_Ant 1 Sub TXD	0.842	0.145	0.276		0.02	0.03
1.9	55.1	-207	LTE Band 26_Ant 1 TXI	0.417	0.145	0.276			
-2.4	75.9	-207	LTE Band 66_Ant 1 Sub TXD	0.832	0.145	0.276			0.03
5.1	55.8	-207	LTE Band 71_Ant 1 TXI	0.289	0.145	0.276			
3.6	56.1	-207	FR1 n12_Ant 1 TXI	0.422	0.145	0.276			
0.3	56.1	-207	FR1 n14_Ant 1 TXI	0.533	0.145	0.276			
0.9	79.6	-207	FR1 n25_Ant 1 Sub TXD	0.746	0.145	0.276			0.03
1.3	56.6	-207	FR1 n26_Ant 1 TXI	0.424	0.145	0.276			
-5	77	-207	FR1 n41_Ant 1 Sub TXD	0.819	0.145	0.276			0.03
-35.5	80	-207	FR1 n48_Ant 1 Sub TXD	0.343	0.145	0.276			
3.6	78.9	-207	FR1 n66_Ant 1 Sub TXD	0.722	0.145	0.276			0.02
4.1	55.1	-207	FR1 n71_Ant 1 TXI	0.346	0.145	0.276			
14.5	65	-207	FR1 n77_Ant 1 Sub TXD	0.384	0.145	0.276			



<Case 101>

SPLSR calculation for summation SAR>1.6W/kg

Exposure Position	0	1	7	9	10	11
	WWAN SAR	WLANS/6GHz Ant 4+3	Bluetooth Ant 3	LTE Band 48_Ant 6 TXD	FR1 n48_Ant 6 TXD	FR1 n77_Ant 6 TXD
Back	1g SAR (W/kg)			0.317	0.341	0.523
				0+1+7+9 Summed SAR	0+1+7+10 Summed SAR	0+1+7+11 Summed SAR
GSM850_Ant 1 TXI	0.640	0.276	0.210	1.443	1.467	1.649
WCDMA V_Ant 1 TXI	0.490	0.276	0.210	1.293	1.317	1.499
LTE Band 12_Ant 1 TXI	0.351	0.276	0.210	1.154	1.178	1.360
LTE Band 13_Ant 1 TXI	0.515	0.276	0.210	1.318	1.342	1.524
LTE Band 14_Ant 1 TXI	0.520	0.276	0.210	1.323	1.347	1.529
LTE Band 25_Ant 1 Sub TXD	0.842	0.276	0.210	1.645	1.669	1.851
LTE Band 26_Ant 1 TXI	0.417	0.276	0.210	1.220	1.244	1.426
LTE Band 66_Ant 1 Sub TXD	0.832	0.276	0.210	1.635	1.659	1.841
LTE Band 71_Ant 1 TXI	0.289	0.276	0.210	1.092	1.116	1.298
FR1 n12_Ant 1 TXI	0.422	0.276	0.210	1.225	1.249	1.431
FR1 n14_Ant 1 TXI	0.533	0.276	0.210	1.336	1.360	1.542
FR1 n25_Ant 1 Sub TXD	0.746	0.276	0.210	1.549	1.573	1.755
FR1 n26_Ant 1 TXI	0.424	0.276	0.210	1.227	1.251	1.433
FR1 n41_Ant 1 Sub TXD	0.819	0.276	0.210	1.622	1.646	1.828
FR1 n48_Ant 1 Sub TXD	0.343	0.276	0.210	1.146	1.170	1.352
FR1 n66_Ant 1 Sub TXD	0.722	0.276	0.210	1.525	1.549	1.731
FR1 n71_Ant 1 TXI	0.346	0.276	0.210	1.149	1.173	1.355
FR1 n77_Ant 1 Sub TXD	0.384	0.276	0.210	1.187	1.211	1.393

SAR peak location (mm)			X (axis)		0.3	11	12	-23	12.5
			Y (axis)		67	31.5	-57	-75.5	-56
			Z (axis)		-207	-207	-207	-207	-207
X (axis)	Y (axis)	Z (axis)	Exposure Position	0	1	7	9	10	11
				WWAN SAR	WLANS/6GHz Ant 4+3	Bluetooth Ant 3	LTE Band 48_Ant 6 TXD	FR1 n48_Ant 6 TXD	FR1 n77_Ant 6 TXD
			Back	1g SAR (W/kg)			0.317	0.341	0.523
							0+1+7+9 SPLSR Results	0+1+7+10 SPLSR Results	0+1+7+11 SPLSR Results
4.6	56.1	-207	GSM850_Ant 1 TXI	0.640	0.276	0.210			0.02
4.1	56.8	-207	WCDMA V_Ant 1 TXI	0.490	0.276	0.210			
8	56.8	-207	LTE Band 12_Ant 1 TXI	0.351	0.276	0.210			
6.3	53.8	-207	LTE Band 13_Ant 1 TXI	0.515	0.276	0.210			
2.8	56.3	-207	LTE Band 14_Ant 1 TXI	0.520	0.276	0.210			
1.9	76.6	-207	LTE Band 25_Ant 1 Sub TXD	0.842	0.276	0.210	0.02	0.02	0.03
1.9	55.1	-207	LTE Band 26_Ant 1 TXI	0.417	0.276	0.210			
-2.4	75.9	-207	LTE Band 66_Ant 1 Sub TXD	0.832	0.276	0.210	0.02	0.02	0.03
5.1	55.8	-207	LTE Band 71_Ant 1 TXI	0.289	0.276	0.210			
3.6	56.1	-207	FR1 n12_Ant 1 TXI	0.422	0.276	0.210			
0.3	56.1	-207	FR1 n14_Ant 1 TXI	0.533	0.276	0.210			
0.9	79.6	-207	FR1 n25_Ant 1 Sub TXD	0.746	0.276	0.210			0.03
1.3	56.6	-207	FR1 n26_Ant 1 TXI	0.424	0.276	0.210			
-5	77	-207	FR1 n41_Ant 1 Sub TXD	0.819	0.276	0.210	0.02	0.02	0.03
-35.5	80	-207	FR1 n48_Ant 1 Sub TXD	0.343	0.276	0.210			
3.6	78.9	-207	FR1 n66_Ant 1 Sub TXD	0.722	0.276	0.210			0.03
4.1	55.1	-207	FR1 n71_Ant 1 TXI	0.346	0.276	0.210			
14.5	65	-207	FR1 n77_Ant 1 Sub TXD	0.384	0.276	0.210			



<Case 102>

SPLSR calculation for summation SAR>1.6W/kg

Exposure Position	0	1	7	9	10	11
	WWAN SAR	WLANS/6GHz Ant 4+3	Bluetooth Ant 4	LTE Band 48_Ant 6 TXD	FR1 n48_Ant 6 TXD	FR1 n77_Ant 6 TXD
Back	1g SAR (W/kg)			0.317	0.341	0.523
				0+1+7+9 Summed SAR	0+1+7+10 Summed SAR	0+1+7+11 Summed SAR
GSM850_Ant 1 TXI	0.640	0.276	0.194	1.427	1.451	1.633
WCDMA V_Ant 1 TXI	0.490	0.276	0.194	1.277	1.301	1.483
LTE Band 12_Ant 1 TXI	0.351	0.276	0.194	1.138	1.162	1.344
LTE Band 13_Ant 1 TXI	0.515	0.276	0.194	1.302	1.326	1.508
LTE Band 14_Ant 1 TXI	0.520	0.276	0.194	1.307	1.331	1.513
LTE Band 25_Ant 1 Sub TXD	0.842	0.276	0.194	1.629	1.653	1.835
LTE Band 26_Ant 1 TXI	0.417	0.276	0.194	1.204	1.228	1.410
LTE Band 66_Ant 1 Sub TXD	0.832	0.276	0.194	1.619	1.643	1.825
LTE Band 71_Ant 1 TXI	0.289	0.276	0.194	1.076	1.100	1.282
FR1 n12_Ant 1 TXI	0.422	0.276	0.194	1.209	1.233	1.415
FR1 n14_Ant 1 TXI	0.533	0.276	0.194	1.320	1.344	1.526
FR1 n25_Ant 1 Sub TXD	0.746	0.276	0.194	1.533	1.557	1.739
FR1 n26_Ant 1 TXI	0.424	0.276	0.194	1.211	1.235	1.417
FR1 n41_Ant 1 Sub TXD	0.819	0.276	0.194	1.606	1.630	1.812
FR1 n48_Ant 1 Sub TXD	0.343	0.276	0.194	1.130	1.154	1.336
FR1 n66_Ant 1 Sub TXD	0.722	0.276	0.194	1.509	1.533	1.715
FR1 n71_Ant 1 TXI	0.346	0.276	0.194	1.133	1.157	1.339
FR1 n77_Ant 1 Sub TXD	0.384	0.276	0.194	1.171	1.195	1.377

SAR peak location (mm)			X (axis)		0.3	-59.5	12	-23	12.5
			Y (axis)		67	35.5	-57	-75.5	-56
			Z (axis)		-207	-207	-207	-207	-207
X (axis)	Y (axis)	Z (axis)	Exposure Position	0	1	7	9	10	11
				WWAN SAR	WLANS/6GHz Ant 4+3	Bluetooth Ant 4	LTE Band 48_Ant 6 TXD	FR1 n48_Ant 6 TXD	FR1 n77_Ant 6 TXD
			Back	1g SAR (W/kg)			0.317	0.341	0.523
							0+1+7+9 SPLSR Results	0+1+7+10 SPLSR Results	0+1+7+11 SPLSR Results
4.6	56.1	-207	GSM850_Ant 1 TXI	0.640	0.276	0.194			0.02
4.1	56.8	-207	WCDMA V_Ant 1 TXI	0.490	0.276	0.194			
8	56.8	-207	LTE Band 12_Ant 1 TXI	0.351	0.276	0.194			
6.3	53.8	-207	LTE Band 13_Ant 1 TXI	0.515	0.276	0.194			
2.8	56.3	-207	LTE Band 14_Ant 1 TXI	0.520	0.276	0.194			
1.9	76.6	-207	LTE Band 25_Ant 1 Sub TXD	0.842	0.276	0.194	0.02	0.02	0.02
1.9	55.1	-207	LTE Band 26_Ant 1 TXI	0.417	0.276	0.194			
-2.4	75.9	-207	LTE Band 66_Ant 1 Sub TXD	0.832	0.276	0.194	0.02	0.02	0.02
5.1	55.8	-207	LTE Band 71_Ant 1 TXI	0.289	0.276	0.194			
3.6	56.1	-207	FR1 n12_Ant 1 TXI	0.422	0.276	0.194			
0.3	56.1	-207	FR1 n14_Ant 1 TXI	0.533	0.276	0.194			
0.9	79.6	-207	FR1 n25_Ant 1 Sub TXD	0.746	0.276	0.194			0.02
1.3	56.6	-207	FR1 n26_Ant 1 TXI	0.424	0.276	0.194			
-5	77	-207	FR1 n41_Ant 1 Sub TXD	0.819	0.276	0.194	0.02	0.02	0.02
-35.5	80	-207	FR1 n48_Ant 1 Sub TXD	0.343	0.276	0.194			
3.6	78.9	-207	FR1 n66_Ant 1 Sub TXD	0.722	0.276	0.194			0.02
4.1	55.1	-207	FR1 n71_Ant 1 TXI	0.346	0.276	0.194			
14.5	65	-207	FR1 n77_Ant 1 Sub TXD	0.384	0.276	0.194			



<Case 103>

SPLSR calculation for summation SAR>1.6W/kg

Exposure Position	0	1	7	9	10	11
	WWAN SAR	WLANS/6GHz Ant 4+3	Bluetooth Ant 4+3	LTE Band 48_Ant 6 TXD	FR1 n48_Ant 6 TXD	FR1 n77_Ant 6 TXD
Back	1g SAR (W/kg)			0.317	0.341	0.523
				0+1+7+9 Summed SAR	0+1+7+10 Summed SAR	0+1+7+11 Summed SAR
GSM850_Ant 1 TXI	0.640	0.276	0.148	1.381	1.405	1.587
WCDMA V_Ant 1 TXI	0.490	0.276	0.148	1.231	1.255	1.437
LTE Band 12_Ant 1 TXI	0.351	0.276	0.148	1.092	1.116	1.298
LTE Band 13_Ant 1 TXI	0.515	0.276	0.148	1.256	1.280	1.462
LTE Band 14_Ant 1 TXI	0.520	0.276	0.148	1.261	1.285	1.467
LTE Band 25_Ant 1 Sub TXD	0.842	0.276	0.148	1.583	1.607	1.789
LTE Band 26_Ant 1 TXI	0.417	0.276	0.148	1.158	1.182	1.364
LTE Band 66_Ant 1 Sub TXD	0.832	0.276	0.148	1.573	1.597	1.779
LTE Band 71_Ant 1 TXI	0.289	0.276	0.148	1.030	1.054	1.236
FR1 n12_Ant 1 TXI	0.422	0.276	0.148	1.163	1.187	1.369
FR1 n14_Ant 1 TXI	0.533	0.276	0.148	1.274	1.298	1.480
FR1 n25_Ant 1 Sub TXD	0.746	0.276	0.148	1.487	1.511	1.693
FR1 n26_Ant 1 TXI	0.424	0.276	0.148	1.165	1.189	1.371
FR1 n41_Ant 1 Sub TXD	0.819	0.276	0.148	1.560	1.584	1.756
FR1 n48_Ant 1 Sub TXD	0.343	0.276	0.148	1.084	1.108	1.290
FR1 n66_Ant 1 Sub TXD	0.722	0.276	0.148	1.463	1.487	1.669
FR1 n71_Ant 1 TXI	0.346	0.276	0.148	1.087	1.111	1.293
FR1 n77_Ant 1 Sub TXD	0.384	0.276	0.148	1.125	1.149	1.331

SAR peak location (mm)			X (axis)		0.3	12	12	-23	12.5
			Y (axis)		67	37.5	-57	-75.5	-56
			Z (axis)		-207	-207	-207	-207	-207
X (axis)	Y (axis)	Z (axis)	Exposure Position	0	1	7	9	10	11
			Back	WWAN SAR	WLANS/6GHz Ant 4+3	Bluetooth Ant 4+3	LTE Band 48_Ant 6 TXD	FR1 n48_Ant 6 TXD	FR1 n77_Ant 6 TXD
				1g SAR (W/kg)				0.317 SPLSR Results	0.341 SPLSR Results
4.6	56.1	-207	GSM850_Ant 1 TXD	0.640	0.276	0.148			
4.1	56.8	-207	WCDMA V_Ant 1 TXD	0.490	0.276	0.148			
8	56.8	-207	LTE Band 12_Ant 1 TXD	0.351	0.276	0.148			
6.3	53.8	-207	LTE Band 13_Ant 1 TXD	0.515	0.276	0.148			
2.8	56.3	-207	LTE Band 14_Ant 1 TXD	0.520	0.276	0.148			
1.9	76.6	-207	LTE Band 25_Ant 1 Sub TXD	0.842	0.276	0.148		0.02	0.03
1.9	55.1	-207	LTE Band 26_Ant 1 TXD	0.417	0.276	0.148			
-2.4	75.9	-207	LTE Band 66_Ant 1 Sub TXD	0.832	0.276	0.148		0.02	0.03
5.1	55.8	-207	LTE Band 71_Ant 1 TXD	0.289	0.276	0.148			
3.6	56.1	-207	FR1 n12_Ant 1 TXD	0.422	0.276	0.148			
0.3	56.1	-207	FR1 n14_Ant 1 TXD	0.533	0.276	0.148			
0.9	79.6	-207	FR1 n25_Ant 1 Sub TXD	0.746	0.276	0.148			0.02
1.3	56.6	-207	FR1 n26_Ant 1 TXD	0.424	0.276	0.148			
-5	77	-207	FR1 n41_Ant 1 Sub TXD	0.819	0.276	0.148			0.03
-35.5	80	-207	FR1 n48_Ant 1 Sub TXD	0.343	0.276	0.148			
3.6	78.9	-207	FR1 n66_Ant 1 Sub TXD	0.722	0.276	0.148			0.02
4.1	55.1	-207	FR1 n71_Ant 1 TXD	0.346	0.276	0.148			
14.5	65	-207	FR1 n77_Ant 1 Sub TXD	0.384	0.276	0.148			



<Case 104>

SPLSR calculation for summation SAR>1.6W/kg

Exposure Position	0	1	7	9	10	11
	WWAN SAR	WLANS/6GHz Ant 4+3	Thread Ant 3	LTE Band 48_Ant 6 TXD	FR1 n48_Ant 6 TXD	FR1 n77_Ant 6 TXD
Back	1g SAR (W/kg)			0.317	0.341	0.523
				0+1+7+9 Summed SAR	0+1+7+10 Summed SAR	0+1+7+11 Summed SAR
GSM850_Ant 1 TX1	0.640	0.276	0.187	1.420	1.444	1.626
WCDMA V_Ant 1 TX1	0.490	0.276	0.187	1.270	1.294	1.476
LTE Band 12_Ant 1 TX1	0.351	0.276	0.187	1.131	1.155	1.337
LTE Band 13_Ant 1 TX1	0.515	0.276	0.187	1.295	1.319	1.501
LTE Band 14_Ant 1 TX1	0.520	0.276	0.187	1.300	1.324	1.506
LTE Band 25_Ant 1 Sub TXD	0.842	0.276	0.187	1.622	1.646	1.828
LTE Band 26_Ant 1 TX1	0.417	0.276	0.187	1.197	1.221	1.403
LTE Band 66_Ant 1 Sub TXD	0.832	0.276	0.187	1.612	1.636	1.818
LTE Band 71_Ant 1 TX1	0.289	0.276	0.187	1.069	1.093	1.275
FR1 n12_Ant 1 TX1	0.422	0.276	0.187	1.202	1.226	1.408
FR1 n14_Ant 1 TX1	0.533	0.276	0.187	1.313	1.337	1.519
FR1 n25_Ant 1 Sub TXD	0.746	0.276	0.187	1.526	1.550	1.732
FR1 n26_Ant 1 TX1	0.424	0.276	0.187	1.204	1.228	1.410
FR1 n41_Ant 1 Sub TXD	0.819	0.276	0.187	1.599	1.623	1.805
FR1 n48_Ant 1 Sub TXD	0.343	0.276	0.187	1.123	1.147	1.329
FR1 n66_Ant 1 Sub TXD	0.722	0.276	0.187	1.502	1.526	1.708
FR1 n71_Ant 1 TX1	0.346	0.276	0.187	1.126	1.150	1.332
FR1 n77_Ant 1 Sub TXD	0.384	0.276	0.187	1.164	1.188	1.370

SAR peak location (mm)			X (axis)		0.3	17	12	-23	12.5
			Y (axis)		67	33	-57	-75.5	-56
			Z (axis)		-207	-207	-207	-207	-207
X (axis)	Y (axis)	Z (axis)	Exposure Position	0	1	7	9	10	11
			Back	WWAN SAR	WLANS/6GHz Ant 4+3	Thread Ant 3	LTE Band 48_Ant 6 TXD	FR1 n48_Ant 6 TXD	FR1 n77_Ant 6 TXD
			1g SAR (W/kg)				0.317 SPLSR Results	0.341 SPLSR Results	0.523 SPLSR Results
4.6	56.1	-207	GSM850_Ant 1 TX1	0.640	0.276	0.187			0.02
4.1	56.8	-207	WCDMA V_Ant 1 TX1	0.490	0.276	0.187			
8	56.8	-207	LTE Band 12_Ant 1 TX1	0.351	0.276	0.187			
6.3	53.8	-207	LTE Band 13_Ant 1 TX1	0.515	0.276	0.187			
2.8	56.3	-207	LTE Band 14_Ant 1 TX1	0.520	0.276	0.187			
1.9	76.6	-207	LTE Band 25_Ant 1 Sub TXD	0.842	0.276	0.187	0.02	0.02	0.03
1.9	55.1	-207	LTE Band 26_Ant 1 TX1	0.417	0.276	0.187			
-2.4	75.9	-207	LTE Band 66_Ant 1 Sub TXD	0.832	0.276	0.187	0.02	0.02	0.03
5.1	55.8	-207	LTE Band 71_Ant 1 TX1	0.289	0.276	0.187			
3.6	56.1	-207	FR1 n12_Ant 1 TX1	0.422	0.276	0.187			
0.3	56.1	-207	FR1 n14_Ant 1 TX1	0.533	0.276	0.187			
0.9	79.6	-207	FR1 n25_Ant 1 Sub TXD	0.746	0.276	0.187			0.03
1.3	56.6	-207	FR1 n26_Ant 1 TX1	0.424	0.276	0.187			
-5	77	-207	FR1 n41_Ant 1 Sub TXD	0.819	0.276	0.187	0.02	0.02	0.03
-35.5	80	-207	FR1 n48_Ant 1 Sub TXD	0.343	0.276	0.187			
3.6	78.9	-207	FR1 n66_Ant 1 Sub TXD	0.722	0.276	0.187			0.03
4.1	55.1	-207	FR1 n71_Ant 1 TX1	0.346	0.276	0.187			
14.5	65	-207	FR1 n77_Ant 1 Sub TXD	0.384	0.276	0.187			

<Case 105>

SPLSR calculation for summation SAR>1.6W/kg

Exposure Position	0	1	2	9	10	11
	WWAN SAR	WLAN2.4GHz Ant 3	WLAN5/6GHz Ant 4+3	LTE Band 48_Ant 7 TX1	FR1 n48_Ant 7 TX1	FR1 n77_Ant 7 TX1
Back	1g SAR (W/kg)			0.242	0.306	0.358
				0+1+2+9 Summed SAR	0+1+2+10 Summed SAR	0+1+2+11 Summed SAR
GSM850_Ant 1 TX1	0.640	0.157	0.276	1.315	1.379	1.431
WCDMA V_Ant 1 TX1	0.490	0.157	0.276	1.165	1.229	1.281
LTE Band 12_Ant 1 TX1	0.351	0.157	0.276	1.026	1.090	1.142
LTE Band 13_Ant 1 TX1	0.515	0.157	0.276	1.190	1.254	1.306
LTE Band 14_Ant 1 TX1	0.520	0.157	0.276	1.195	1.259	1.311
LTE Band 25_Ant 1 Sub TX0	0.842	0.157	0.276	1.517	1.581	1.633
LTE Band 26_Ant 1 TX1	0.417	0.157	0.276	1.092	1.156	1.208
LTE Band 66_Ant 1 Sub TX0	0.832	0.157	0.276	1.507	1.571	1.623
LTE Band 71_Ant 1 TX1	0.289	0.157	0.276	0.964	1.028	1.080
FR1 n12_Ant 1 TX1	0.422	0.157	0.276	1.097	1.161	1.213
FR1 n14_Ant 1 TX1	0.533	0.157	0.276	1.208	1.272	1.324
FR1 n25_Ant 1 Sub TX0	0.746	0.157	0.276	1.421	1.485	1.537
FR1 n26_Ant 1 TX1	0.424	0.157	0.276	1.099	1.163	1.215
FR1 n41_Ant 1 Sub TX0	0.819	0.157	0.276	1.494	1.558	1.610
FR1 n48_Ant 1 Sub TX0	0.343	0.157	0.276	1.018	1.082	1.134
FR1 n66_Ant 1 Sub TX0	0.722	0.157	0.276	1.397	1.461	1.513
FR1 n71_Ant 1 TX1	0.346	0.157	0.276	1.021	1.085	1.137
FR1 n77_Ant 1 Sub TX0	0.384	0.157	0.276	1.059	1.123	1.175

SAR peak location (mm)			X (axis)		14	0.3	-46.5	-57.5	-59.5
			Y (axis)		30.5	67	-67.5	-50	-50
			Z (axis)		-207	-207	-207	-207	-207
X (axis)	Y (axis)	Z (axis)	Exposure Position	0	1	2	9	10	11
			Back	WWAN SAR	WLAN2.4GHz Ant 3	WLAN5/6GHz Ant 4+3	LTE Band 48_Ant 7 TX1	FR1 n48_Ant 7 TX1	FR1 n77_Ant 7 TX1
				1g SAR (W/kg)			0.242 SPLSR Results	0.306 SPLSR Results	0.358 SPLSR Results
4.6	56.1	-207	GSM850_Ant 1 TX1	0.640	0.157	0.276			
4.1	56.8	-207	WCDMA V_Ant 1 TX1	0.490	0.157	0.276			
8	56.8	-207	LTE Band 12_Ant 1 TX1	0.351	0.157	0.276			
6.3	53.8	-207	LTE Band 13_Ant 1 TX1	0.515	0.157	0.276			
2.8	56.3	-207	LTE Band 14_Ant 1 TX1	0.520	0.157	0.276			
1.9	76.6	-207	LTE Band 25_Ant 1 Sub TX0	0.842	0.157	0.276			0.02
1.9	55.1	-207	LTE Band 26_Ant 1 TX1	0.417	0.157	0.276			
-2.4	75.9	-207	LTE Band 66_Ant 1 Sub TX0	0.832	0.157	0.276			0.02
5.1	55.8	-207	LTE Band 71_Ant 1 TX1	0.289	0.157	0.276			
3.6	56.1	-207	FR1 n12_Ant 1 TX1	0.422	0.157	0.276			
0.3	56.1	-207	FR1 n14_Ant 1 TX1	0.533	0.157	0.276			
0.9	79.6	-207	FR1 n25_Ant 1 Sub TX0	0.746	0.157	0.276			
1.3	56.6	-207	FR1 n26_Ant 1 TX1	0.424	0.157	0.276			
-5	77	-207	FR1 n41_Ant 1 Sub TX0	0.819	0.157	0.276			0.02
-35.5	80	-207	FR1 n48_Ant 1 Sub TX0	0.343	0.157	0.276			
3.6	78.9	-207	FR1 n66_Ant 1 Sub TX0	0.722	0.157	0.276			
4.1	55.1	-207	FR1 n71_Ant 1 TX1	0.346	0.157	0.276			
14.5	65	-207	FR1 n77_Ant 1 Sub TX0	0.384	0.157	0.276			



<Case 106>

SPLSR calculation for summation SAR>1.6W/kg

Exposure Position	0	1	2	9	10	11
	WWAN SAR	WLAN2.4GHz Ant 4+3	WLAN5/6GHz Ant 4+3	LTE Band 48_Ant 7 TX1	FR1 n48_Ant 7 TX1	FR1 n77_Ant 7 TX1
Back	1g SAR (W/kg)			0.242	0.306	0.358
				0+1+2+9 Summed SAR	0+1+2+10 Summed SAR	0+1+2+11 Summed SAR
GSM850_Ant 1 TX1	0.640	0.145	0.276	1.303	1.367	1.419
WCDMA V_Ant 1 TX1	0.490	0.145	0.276	1.153	1.217	1.269
LTE Band 12_Ant 1 TX1	0.351	0.145	0.276	1.014	1.078	1.130
LTE Band 13_Ant 1 TX1	0.515	0.145	0.276	1.178	1.242	1.294
LTE Band 14_Ant 1 TX1	0.520	0.145	0.276	1.183	1.247	1.299
LTE Band 25_Ant 1 Sub TX0	0.842	0.145	0.276	1.505	1.569	1.621
LTE Band 26_Ant 1 TX1	0.417	0.145	0.276	1.080	1.144	1.196
LTE Band 66_Ant 1 Sub TX0	0.832	0.145	0.276	1.495	1.559	1.611
LTE Band 71_Ant 1 TX1	0.289	0.145	0.276	0.952	1.016	1.068
FR1 n12_Ant 1 TX1	0.422	0.145	0.276	1.085	1.149	1.201
FR1 n14_Ant 1 TX1	0.533	0.145	0.276	1.196	1.260	1.312
FR1 n25_Ant 1 Sub TX0	0.746	0.145	0.276	1.409	1.473	1.525
FR1 n26_Ant 1 TX1	0.424	0.145	0.276	1.087	1.151	1.203
FR1 n41_Ant 1 Sub TX0	0.819	0.145	0.276	1.482	1.546	1.598
FR1 n48_Ant 1 Sub TX0	0.343	0.145	0.276	1.006	1.070	1.122
FR1 n66_Ant 1 Sub TX0	0.722	0.145	0.276	1.385	1.449	1.501
FR1 n71_Ant 1 TX1	0.346	0.145	0.276	1.009	1.073	1.125
FR1 n77_Ant 1 Sub TX0	0.384	0.145	0.276	1.047	1.111	1.163

SAR peak location (mm)			X (axis)		16	0.3	-46.5	-57.5	-59.5
			Y (axis)		30	67	-47.5	-50	-50
			Z (axis)		-207	-207	-207	-207	-207
X (axis)	Y (axis)	Z (axis)	Exposure Position	0	1	2	9	10	11
			Back	WWAN SAR	WLAN2.4GHz Ant 4+3	WLAN5/6GHz Ant 4+3	LTE Band 48_Ant 7 TX1	FR1 n48_Ant 7 TX1	FR1 n77_Ant 7 TX1
			Back	1g SAR (W/kg)			0+1+2+9 SPLSR Results	0+1+2+10 SPLSR Results	0+1+2+11 SPLSR Results
4.6	56.1	-207	GSM850_Ant 1 TX1	0.640	0.145	0.276			
4.1	56.8	-207	WCDMA V_Ant 1 TX1	0.490	0.145	0.276			
8	56.8	-207	LTE Band 12_Ant 1 TX1	0.351	0.145	0.276			
6.3	53.8	-207	LTE Band 13_Ant 1 TX1	0.515	0.145	0.276			
2.8	56.3	-207	LTE Band 14_Ant 1 TX1	0.520	0.145	0.276			
1.9	76.6	-207	LTE Band 25_Ant 1 Sub TX0	0.842	0.145	0.276			0.02
1.9	55.1	-207	LTE Band 26_Ant 1 TX1	0.417	0.145	0.276			
-2.4	75.9	-207	LTE Band 66_Ant 1 Sub TX0	0.832	0.145	0.276			0.02
5.1	55.8	-207	LTE Band 71_Ant 1 TX1	0.289	0.145	0.276			
3.6	56.1	-207	FR1 n12_Ant 1 TX1	0.422	0.145	0.276			
0.3	56.1	-207	FR1 n14_Ant 1 TX1	0.533	0.145	0.276			
0.9	79.6	-207	FR1 n25_Ant 1 Sub TX0	0.746	0.145	0.276			
1.3	56.6	-207	FR1 n26_Ant 1 TX1	0.424	0.145	0.276			
-5	77	-207	FR1 n41_Ant 1 Sub TX0	0.819	0.145	0.276			0.02
-35.5	80	-207	FR1 n48_Ant 1 Sub TX0	0.343	0.145	0.276			
3.6	78.9	-207	FR1 n66_Ant 1 Sub TX0	0.722	0.145	0.276			
4.1	55.1	-207	FR1 n71_Ant 1 TX1	0.346	0.145	0.276			
14.5	65	-207	FR1 n77_Ant 1 Sub TX0	0.384	0.145	0.276			



<Case 107>

SPLSR calculation for summation SAR>1.6W/kg

Exposure Position	0	1	7	9	10	11
	WWAN SAR	WLANS/6GHz Ant 4+3	Bluetooth Ant 3	LTE Band 48_Ant 7 TX1	FR1 n48_Ant 7 TX1	FR1 n77_Ant 7 TX1
Back	1g SAR (W/kg)			0.242	0.306	0.358
				0+1+7+9 Summed SAR	0+1+7+10 Summed SAR	0+1+7+11 Summed SAR
GSM850_Ant 1 TX1	0.640	0.276	0.210	1.368	1.432	1.484
WCDMA V_Ant 1 TX1	0.490	0.276	0.210	1.218	1.282	1.334
LTE Band 12_Ant 1 TX1	0.351	0.276	0.210	1.079	1.143	1.195
LTE Band 13_Ant 1 TX1	0.515	0.276	0.210	1.243	1.307	1.359
LTE Band 14_Ant 1 TX1	0.520	0.276	0.210	1.248	1.312	1.364
LTE Band 25_Ant 1 Sub TX0	0.842	0.276	0.210	1.570	1.634	1.686
LTE Band 26_Ant 1 TX1	0.417	0.276	0.210	1.145	1.209	1.261
LTE Band 66_Ant 1 Sub TX0	0.832	0.276	0.210	1.560	1.624	1.676
LTE Band 71_Ant 1 TX1	0.289	0.276	0.210	1.017	1.081	1.133
FR1 n12_Ant 1 TX1	0.422	0.276	0.210	1.150	1.214	1.266
FR1 n14_Ant 1 TX1	0.533	0.276	0.210	1.261	1.325	1.377
FR1 n25_Ant 1 Sub TX0	0.746	0.276	0.210	1.474	1.538	1.590
FR1 n26_Ant 1 TX1	0.424	0.276	0.210	1.152	1.216	1.268
FR1 n41_Ant 1 Sub TX0	0.819	0.276	0.210	1.547	1.611	1.663
FR1 n48_Ant 1 Sub TX0	0.343	0.276	0.210	1.071	1.135	1.187
FR1 n66_Ant 1 Sub TX0	0.722	0.276	0.210	1.450	1.514	1.566
FR1 n71_Ant 1 TX1	0.346	0.276	0.210	1.074	1.138	1.190
FR1 n77_Ant 1 Sub TX0	0.384	0.276	0.210	1.112	1.176	1.228

SAR peak location (mm)			X (axis)		0.3	11	-46.5	-57.5	-59.5
			Y (axis)		67	31.5	-67.5	-50	-50
			Z (axis)		-207	-207	-207	-207	-207
X (axis)	Y (axis)	Z (axis)	Exposure Position	0	1	7	9	10	11
			Back	WWAN SAR	WLANS/6GHz Ant 4+3	Bluetooth Ant 3	LTE Band 48_Ant 7 TX1	FR1 n48_Ant 7 TX1	FR1 n77_Ant 7 TX1
				1g SAR (W/kg)			0.242	0.306	0.358
							0+1+7+9 SPLSR Results	0+1+7+10 SPLSR Results	0+1+7+11 SPLSR Results
4.6	56.1	-207	GSM850_Ant 1 TX1	0.640	0.276	0.210			
4.1	56.8	-207	WCDMA V_Ant 1 TX1	0.490	0.276	0.210			
8	56.8	-207	LTE Band 12_Ant 1 TX1	0.351	0.276	0.210			
6.3	53.8	-207	LTE Band 13_Ant 1 TX1	0.515	0.276	0.210			
2.8	56.3	-207	LTE Band 14_Ant 1 TX1	0.520	0.276	0.210			
1.9	76.6	-207	LTE Band 25_Ant 1 Sub TX0	0.842	0.276	0.210		0.02	0.02
1.9	55.1	-207	LTE Band 26_Ant 1 TX1	0.417	0.276	0.210			
-2.4	75.9	-207	LTE Band 66_Ant 1 Sub TX0	0.832	0.276	0.210		0.02	0.02
5.1	55.8	-207	LTE Band 71_Ant 1 TX1	0.289	0.276	0.210			
3.6	56.1	-207	FR1 n12_Ant 1 TX1	0.422	0.276	0.210			
0.3	56.1	-207	FR1 n14_Ant 1 TX1	0.533	0.276	0.210			
0.9	79.6	-207	FR1 n25_Ant 1 Sub TX0	0.746	0.276	0.210			
1.3	56.6	-207	FR1 n26_Ant 1 TX1	0.424	0.276	0.210			
-5	77	-207	FR1 n41_Ant 1 Sub TX0	0.819	0.276	0.210		0.02	0.02
-35.5	80	-207	FR1 n48_Ant 1 Sub TX0	0.343	0.276	0.210			
3.6	78.9	-207	FR1 n66_Ant 1 Sub TX0	0.722	0.276	0.210			
4.1	55.1	-207	FR1 n71_Ant 1 TX1	0.346	0.276	0.210			
14.5	65	-207	FR1 n77_Ant 1 Sub TX0	0.384	0.276	0.210			



<Case 108>

SPLSR calculation for summation SAR>1.6W/kg

Exposure Position	0	1	7	9	10	11
	WWAN SAR	WLANS/6GHz Ant 4+3	Bluetooth Ant 4	LTE Band 48_Ant 7 TX1	FR1 n48_Ant 7 TX1	FR1 n77_Ant 7 TX1
Back	1g SAR (W/kg)			0.242	0.306	0.358
				0+1+7+9 Summed SAR	0+1+7+10 Summed SAR	0+1+7+11 Summed SAR
GSM850_Ant 1 TX1	0.640	0.276	0.194	1.352	1.416	1.468
WCDMA V_Ant 1 TX1	0.490	0.276	0.194	1.202	1.266	1.318
LTE Band 12_Ant 1 TX1	0.351	0.276	0.194	1.063	1.127	1.179
LTE Band 13_Ant 1 TX1	0.515	0.276	0.194	1.227	1.291	1.343
LTE Band 14_Ant 1 TX1	0.520	0.276	0.194	1.232	1.296	1.348
LTE Band 25_Ant 1 Sub TX0	0.842	0.276	0.194	1.554	1.618	1.670
LTE Band 26_Ant 1 TX1	0.417	0.276	0.194	1.129	1.193	1.245
LTE Band 66_Ant 1 Sub TX0	0.832	0.276	0.194	1.544	1.608	1.660
LTE Band 71_Ant 1 TX1	0.289	0.276	0.194	1.001	1.065	1.117
FR1 n12_Ant 1 TX1	0.422	0.276	0.194	1.134	1.198	1.250
FR1 n14_Ant 1 TX1	0.533	0.276	0.194	1.245	1.309	1.361
FR1 n25_Ant 1 Sub TX0	0.746	0.276	0.194	1.458	1.522	1.574
FR1 n26_Ant 1 TX1	0.424	0.276	0.194	1.136	1.200	1.252
FR1 n41_Ant 1 Sub TX0	0.819	0.276	0.194	1.531	1.595	1.647
FR1 n48_Ant 1 Sub TX0	0.343	0.276	0.194	1.055	1.119	1.171
FR1 n66_Ant 1 Sub TX0	0.722	0.276	0.194	1.434	1.498	1.550
FR1 n71_Ant 1 TX1	0.346	0.276	0.194	1.058	1.122	1.174
FR1 n77_Ant 1 Sub TX0	0.384	0.276	0.194	1.096	1.160	1.212

SAR peak location (mm)			X (axis)		0.3	-59.5	-46.5	-57.5	-59.5
			Y (axis)		67	35.5	-47.5	-50	-50
			Z (axis)		-207	-207	-207	-207	-207
X (axis)	Y (axis)	Z (axis)	Exposure Position	0	1	7	9	10	11
			Back	WWAN SAR	WLANS/6GHz Ant 4+3	Bluetooth Ant 4	LTE Band 48_Ant 7 TX1	FR1 n48_Ant 7 TX1	FR1 n77_Ant 7 TX1
			1g SAR (W/kg)				0.242 SPLSR Results	0.306 SPLSR Results	0.358 SPLSR Results
4.6	56.1	-207	GSM850_Ant 1 TX1	0.640	0.276	0.194			
4.1	56.8	-207	WCDMA V_Ant 1 TX1	0.490	0.276	0.194			
8	56.8	-207	LTE Band 12_Ant 1 TX1	0.351	0.276	0.194			
6.3	53.8	-207	LTE Band 13_Ant 1 TX1	0.515	0.276	0.194			
2.8	56.3	-207	LTE Band 14_Ant 1 TX1	0.520	0.276	0.194			
1.9	76.6	-207	LTE Band 25_Ant 1 Sub TX0	0.842	0.276	0.194		0.02	0.03
1.9	55.1	-207	LTE Band 26_Ant 1 TX1	0.417	0.276	0.194			
-2.4	75.9	-207	LTE Band 66_Ant 1 Sub TX0	0.832	0.276	0.194		0.02	0.03
5.1	55.8	-207	LTE Band 71_Ant 1 TX1	0.289	0.276	0.194			
3.6	56.1	-207	FR1 n12_Ant 1 TX1	0.422	0.276	0.194			
0.3	56.1	-207	FR1 n14_Ant 1 TX1	0.533	0.276	0.194			
0.9	79.6	-207	FR1 n25_Ant 1 Sub TX0	0.746	0.276	0.194			
1.3	56.6	-207	FR1 n26_Ant 1 TX1	0.424	0.276	0.194			
-5	77	-207	FR1 n41_Ant 1 Sub TX0	0.819	0.276	0.194		0.02	0.02
-35.5	80	-207	FR1 n48_Ant 1 Sub TX0	0.343	0.276	0.194			
3.6	78.9	-207	FR1 n66_Ant 1 Sub TX0	0.722	0.276	0.194			
4.1	55.1	-207	FR1 n71_Ant 1 TX1	0.346	0.276	0.194			
14.5	65	-207	FR1 n77_Ant 1 Sub TX0	0.384	0.276	0.194			



<Case 109>

SPLSR calculation for summation SAR>1.6W/kg

Exposure Position	0	1	7	9	10	11
	WWAN SAR	WLANS/6GHz Ant 4+3	Bluetooth Ant 4+3	LTE Band 48_Ant 7 TX1	FR1 n48_Ant 7 TX1	FR1 n77_Ant 7 TX1
Back	1g SAR (W/kg)			0.242	0.306	0.358
				0+1+7+9 Summed SAR	0+1+7+10 Summed SAR	0+1+7+11 Summed SAR
GSM850_Ant 1 TX1	0.640	0.276	0.148	1.306	1.370	1.422
WCDMA V_Ant 1 TX1	0.490	0.276	0.148	1.156	1.220	1.272
LTE Band 12_Ant 1 TX1	0.351	0.276	0.148	1.017	1.081	1.133
LTE Band 13_Ant 1 TX1	0.515	0.276	0.148	1.181	1.245	1.297
LTE Band 14_Ant 1 TX1	0.520	0.276	0.148	1.186	1.250	1.302
LTE Band 25_Ant 1 Sub TX0	0.842	0.276	0.148	1.508	1.572	1.624
LTE Band 26_Ant 1 TX1	0.417	0.276	0.148	1.083	1.147	1.199
LTE Band 66_Ant 1 Sub TX0	0.832	0.276	0.148	1.498	1.562	1.614
LTE Band 71_Ant 1 TX1	0.289	0.276	0.148	0.955	1.019	1.071
FR1 n12_Ant 1 TX1	0.422	0.276	0.148	1.088	1.152	1.204
FR1 n14_Ant 1 TX1	0.533	0.276	0.148	1.199	1.263	1.315
FR1 n25_Ant 1 Sub TX0	0.746	0.276	0.148	1.412	1.476	1.528
FR1 n26_Ant 1 TX1	0.424	0.276	0.148	1.090	1.154	1.206
FR1 n41_Ant 1 Sub TX0	0.819	0.276	0.148	1.485	1.549	1.601
FR1 n48_Ant 1 Sub TX0	0.343	0.276	0.148	1.009	1.073	1.125
FR1 n66_Ant 1 Sub TX0	0.722	0.276	0.148	1.388	1.452	1.504
FR1 n71_Ant 1 TX1	0.346	0.276	0.148	1.012	1.076	1.128
FR1 n77_Ant 1 Sub TX0	0.384	0.276	0.148	1.050	1.114	1.166

SAR peak location (mm)			X (axis)		0.3	12	-46.5	-57.5	-59.5
			Y (axis)		67	37.5	-47.5	-50	-50
			Z (axis)		-207	-207	-207	-207	-207
X (axis)	Y (axis)	Z (axis)	Exposure Position	0	1	7	9	10	11
			Back	WWAN SAR	WLANS/6GHz Ant 4+3	Bluetooth Ant 4+3	LTE Band 48_Ant 7 TX1	FR1 n48_Ant 7 TX1	FR1 n77_Ant 7 TX1
			1g SAR (W/kg)			0.242			
						0.306			
						0.358			
4.6	56.1	-207	GSM850_Ant 1 TX1	0.640	0.276	0.148			
4.1	56.8	-207	WCDMA V_Ant 1 TX1	0.490	0.276	0.148			
8	56.8	-207	LTE Band 12_Ant 1 TX1	0.351	0.276	0.148			
6.3	53.8	-207	LTE Band 13_Ant 1 TX1	0.515	0.276	0.148			
2.8	56.3	-207	LTE Band 14_Ant 1 TX1	0.520	0.276	0.148			
1.9	76.6	-207	LTE Band 25_Ant 1 Sub TX0	0.842	0.276	0.148			0.02
1.9	55.1	-207	LTE Band 26_Ant 1 TX1	0.417	0.276	0.148			
-2.4	75.9	-207	LTE Band 66_Ant 1 Sub TX0	0.832	0.276	0.148			0.02
5.1	55.8	-207	LTE Band 71_Ant 1 TX1	0.289	0.276	0.148			
3.6	56.1	-207	FR1 n12_Ant 1 TX1	0.422	0.276	0.148			
0.3	56.1	-207	FR1 n14_Ant 1 TX1	0.533	0.276	0.148			
0.9	79.6	-207	FR1 n25_Ant 1 Sub TX0	0.746	0.276	0.148			
1.3	56.6	-207	FR1 n26_Ant 1 TX1	0.424	0.276	0.148			
-5	77	-207	FR1 n41_Ant 1 Sub TX0	0.819	0.276	0.148			0.02
-35.5	80	-207	FR1 n48_Ant 1 Sub TX0	0.343	0.276	0.148			
3.6	78.9	-207	FR1 n66_Ant 1 Sub TX0	0.722	0.276	0.148			
4.1	55.1	-207	FR1 n71_Ant 1 TX1	0.346	0.276	0.148			
14.5	65	-207	FR1 n77_Ant 1 Sub TX0	0.384	0.276	0.148			



<Case 110>

SPLSR calculation for summation SAR>1.6W/kg

Exposure Position	0	1	7	9	10	11
	WWAN SAR	WLANS/6GHz Ant 4+3	Thread Ant 3	LTE Band 48_Ant 7 TX1	FR1 n48_Ant 7 TX1	FR1 n77_Ant 7 TX1
Back	1g SAR (W/kg)			0.242	0.306	0.358
				0+1+7+9 Summed SAR	0+1+7+10 Summed SAR	0+1+7+11 Summed SAR
GSM850_Ant 1 TX1	0.640	0.276	0.187	1.345	1.409	1.461
WCDMA V_Ant 1 TX1	0.490	0.276	0.187	1.195	1.259	1.311
LTE Band 12_Ant 1 TX1	0.351	0.276	0.187	1.056	1.120	1.172
LTE Band 13_Ant 1 TX1	0.515	0.276	0.187	1.220	1.284	1.336
LTE Band 14_Ant 1 TX1	0.520	0.276	0.187	1.225	1.289	1.341
LTE Band 25_Ant 1 Sub TX0	0.842	0.276	0.187	1.547	1.611	1.663
LTE Band 26_Ant 1 TX1	0.417	0.276	0.187	1.122	1.186	1.238
LTE Band 66_Ant 1 Sub TX0	0.832	0.276	0.187	1.537	1.601	1.653
LTE Band 71_Ant 1 TX1	0.289	0.276	0.187	0.994	1.058	1.110
FR1 n12_Ant 1 TX1	0.422	0.276	0.187	1.127	1.191	1.243
FR1 n14_Ant 1 TX1	0.533	0.276	0.187	1.238	1.302	1.354
FR1 n25_Ant 1 Sub TX0	0.746	0.276	0.187	1.451	1.515	1.567
FR1 n26_Ant 1 TX1	0.424	0.276	0.187	1.129	1.193	1.245
FR1 n41_Ant 1 Sub TX0	0.819	0.276	0.187	1.524	1.588	1.640
FR1 n48_Ant 1 Sub TX0	0.343	0.276	0.187	1.048	1.112	1.164
FR1 n66_Ant 1 Sub TX0	0.722	0.276	0.187	1.427	1.491	1.543
FR1 n71_Ant 1 TX1	0.346	0.276	0.187	1.051	1.115	1.167
FR1 n77_Ant 1 Sub TX0	0.384	0.276	0.187	1.089	1.153	1.205

SAR peak location (mm)			X (axis)		0.3	17	-46.5	-57.5	-59.5
			Y (axis)		67	33	-67.5	-50	-50
			Z (axis)		-207	-207	-207	-207	-207
X (axis)	Y (axis)	Z (axis)	Exposure Position	0	1	7	9	10	11
			Back	WWAN SAR	WLANS/6GHz Ant 4+3	Thread Ant 3	LTE Band 48_Ant 7 TX1	FR1 n48_Ant 7 TX1	FR1 n77_Ant 7 TX1
				1g SAR (W/kg)			0.242 SPLSR Results	0.306 SPLSR Results	0.358 SPLSR Results
4.6	56.1	-207	GSM850_Ant 1 TX1	0.640	0.276	0.187			
4.1	56.8	-207	WCDMA V_Ant 1 TX1	0.490	0.276	0.187			
8	56.8	-207	LTE Band 12_Ant 1 TX1	0.351	0.276	0.187			
6.3	53.8	-207	LTE Band 13_Ant 1 TX1	0.515	0.276	0.187			
2.8	56.3	-207	LTE Band 14_Ant 1 TX1	0.520	0.276	0.187			
1.9	76.6	-207	LTE Band 25_Ant 1 Sub TX0	0.842	0.276	0.187		0.02	0.02
1.9	55.1	-207	LTE Band 26_Ant 1 TX1	0.417	0.276	0.187			
-2.4	75.9	-207	LTE Band 66_Ant 1 Sub TX0	0.832	0.276	0.187		0.02	0.02
5.1	55.8	-207	LTE Band 71_Ant 1 TX1	0.289	0.276	0.187			
3.6	56.1	-207	FR1 n12_Ant 1 TX1	0.422	0.276	0.187			
0.3	56.1	-207	FR1 n14_Ant 1 TX1	0.533	0.276	0.187			
0.9	79.6	-207	FR1 n25_Ant 1 Sub TX0	0.746	0.276	0.187			
1.3	56.6	-207	FR1 n26_Ant 1 TX1	0.424	0.276	0.187			
-5	77	-207	FR1 n41_Ant 1 Sub TX0	0.819	0.276	0.187			0.02
-35.5	80	-207	FR1 n48_Ant 1 Sub TX0	0.343	0.276	0.187			
3.6	78.9	-207	FR1 n66_Ant 1 Sub TX0	0.722	0.276	0.187			
4.1	55.1	-207	FR1 n71_Ant 1 TX1	0.346	0.276	0.187			
14.5	65	-207	FR1 n77_Ant 1 Sub TX0	0.384	0.276	0.187			

<Case 118>

SPLSR calculation for summation SAR>1.6W/kg

Exposure Position	0	1	2	9	10	11
	WWAN SAR	WLAN2.4GHz Ant 4+3	WLAN5/6GHz Ant 4+3	LTE Band 48_Ant 6 TXD	FR1 n48_Ant 6 TXD	FR1 n77_Ant 6 TXD
Back	1g SAR (W/kg)			0.317	0.341	0.523
				0+1+2+9 Summed SAR	0+1+2+10 Summed SAR	0+1+2+11 Summed SAR
LTE Band 25_Ant 5 Sub TXI	0.487	0.145	0.276	1.225	1.249	1.431
LTE Band 66_Ant 5 Sub TXI	0.602	0.145	0.276	1.340	1.364	1.546
FR1 n25_Ant 5 Sub TXI	0.474	0.145	0.276	1.212	1.236	1.418
FR1 n66_Ant 5 Sub TXI	0.690	0.145	0.276	1.428	1.452	1.634
FR1 n41_Ant 5 Sub TXI	0.562	0.145	0.276	1.300	1.324	1.506
FR1 n48_Ant 5 Sub TXI	0.477	0.145	0.276	1.215	1.239	1.421
FR1 n77_Ant 5 Sub TXI	0.307	0.145	0.276	1.045	1.069	1.251

SAR peak location (mm)			X (axis)		16	0.3	12	-23	12.5
			Y (axis)		30	67	-57	-75.5	-56
			Z (axis)		-207	-207	-207	-207	-207
X (axis)	Y (axis)	Z (axis)	Exposure Position	0	1	2	9	10	11
				WWAN SAR	WLAN2.4GHz Ant 4-3	WLAN5GHz Ant 4-3	LTE Band 40_Ant 6 TX0	FR1 n48_Ant 6 TX0	FR1 n77_Ant 6 TX0
			Back	1g SAR (W/kg)			0.317	0.341	0.523
							0-1+2+9 SPLSR Results	0-1+2+10 SPLSR Results	0-1+2+11 SPLSR Results
-53.8	76.4	-207	LTE Band 25_Ant 5 Sub TX1	0.487	0.145	0.276			
-61.4	32.4	-207	LTE Band 66_Ant 5 Sub TX1	0.602	0.145	0.276			
-61.4	32.6	-207	FR1 n25_Ant 5 Sub TX1	0.474	0.145	0.276			
-62.4	32.4	-207	FR1 n66_Ant 5 Sub TX1	0.690	0.145	0.276			0.02
-59	38.5	-207	FR1 n41_Ant 5 Sub TX1	0.562	0.145	0.276			
-33.5	82	-207	FR1 n48_Ant 5 Sub TX1	0.477	0.145	0.276			
-33	77.5	-207	FR1 n77_Ant 5 Sub TX1	0.307	0.145	0.276			

<Case 119>

SPLSR calculation for summation SAR>1.6W/kg

Exposure Position	0	1	7	9	10	11
	WWAN SAR	WLAN5/6GHz Ant 4+3	Bluetooth Ant 3	LTE Band 48_Ant 6 TXD	FR1 n48_Ant 6 TXD	FR1 n77_Ant 6 TXD
Back	1g SAR (W/kg)			0.317	0.341	0.523
				0+1+7+9 Summed SAR	0+1+7+10 Summed SAR	0+1+7+11 Summed SAR
LTE Band 25_Ant 5 Sub TXI	0.487	0.276	0.210	1.290	1.314	1.496
LTE Band 66_Ant 5 Sub TXI	0.602	0.276	0.210	1.405	1.429	1.611
FR1 n25_Ant 5 Sub TXI	0.474	0.276	0.210	1.277	1.301	1.483
FR1 n66_Ant 5 Sub TXI	0.690	0.276	0.210	1.493	1.517	1.699
FR1 n41_Ant 5 Sub TXI	0.562	0.276	0.210	1.365	1.389	1.571
FR1 n48_Ant 5 Sub TXI	0.477	0.276	0.210	1.280	1.304	1.486
FR1 n77_Ant 5 Sub TXI	0.307	0.276	0.210	1.110	1.134	1.316

SAR peak location (mm)			X (axis)		0.3	11	12	-23	12.5
			Y (axis)		67	31.5	-57	-75.5	-56
			Z (axis)		-207	-207	-207	-207	-207
X (axis)	Y (axis)	Z (axis)	Exposure Position	0	1	7	9	10	11
				WWAN SAR	WLAN/G/GHz_Ant 4+3	Bluetooth_Ant 3	LTE_Band_48_Ant 6 TXD	FR1_n48_Ant 6 TXD	FR1_n77_Ant 6 TXD
			Back	1g SAR (W/kg)			0.317	0.341	0.523
							0+3+7+9 SPLSR_Results	0+3+7+10 SPLSR_Results	0+3+7+11 SPLSR_Results
				-53.8	76.4	-207	LTE_Band_25_Ant 5 Sub TXD	0.487	0.276
-61.4	32.4	-207	LTE_Band_66_Ant 5 Sub TXD	0.602	0.276	0.210			0.02
-61.4	32.6	-207	FR1_n25_Ant 5 Sub TXD	0.474	0.276	0.210			
-62.4	32.4	-207	FR1_n66_Ant 5 Sub TXD	0.690	0.276	0.210			0.03
-59	38.5	-207	FR1_n41_Ant 5 Sub TXD	0.562	0.276	0.210			
-33.5	82	-207	FR1_n48_Ant 5 Sub TXD	0.477	0.276	0.210			
-33	77.5	-207	FR1_n77_Ant 5 Sub TXD	0.307	0.276	0.210			