

Matsushita Kotobuki
Electronics Industries, Ltd.

Visual Products Business Unit
Address: 247 Fukutake, Saijo, Ehime 793 - 8510 Japan
Tel: 0897 - 56 - 1216 / Fax: 0897 - 56 - 6720

Date: Dec. 6, 2002

REPORT OF MEASUREMENTS-(Part I)
REQUIRED IN (X) SUBPART B (TV INTERFACE DEVICE)

EXHIBIT # : 3
FCC ID : ACJ927147AHV
OUR REF. : MKES02-F017
MODEL NO. : PV-D4763
Sheet 1 of 30 Sheets

Name of Manufacturer : Matsushita Kotobuki Electronics Industries, Ltd.

Address of Manufacturer : 247 Fukutake, Saijo, Ehime, Japan

Device Under Measurement

FCC ID : ACJ927147AHV
Model No. : PV-D4763
Trade Name : Panasonic
Applicant : Matsushita Electric Ind. Co., Ltd.

Data Also Applied To

FCC ID Model No.(Trade Name)

Device Description

Name of Device : (X) Video Cassette Recorder, () Tuner Adapter
Frequency : VHF 3 or 4 ch.
Video Line Terminals : (X) Provided, () Not Provided
RF Out Cable (0.9 m), Video/Audio out Cable (1.5 m)
Component out Cable (1.5 m), S-Video out Cable (1.5 m)
Audio out Cable (1.5 m) × 4

Certification

On the basis of the measurement data contained in Part II, all devices bearing the aforementioned FCC ID (model No., chassis No., and trade names) are stated by the undersigned to be capable of complying with the applicable sections of Part 15 of the FCC rules governing restricted radiation devices at the time of manufacture and may be expected to continue to comply under normal conditions and with usual maintenance.

The undersigned also states that the device measured was an engineering prototype, pre production, or production unit. If changes are applied to future units and such changes adversely alter spurious radiation, an amended report of measurements will be supplied to the FCC.



K. Ishikawa
Coordinator

Matsushita Kotobuki Electronics Industries, Ltd.

Visual Products Business Unit
Address: 247 Fukutake, Saijo, Ehime 793 - 8510 Japan
Tel: 0897 - 56 - 1216 / Fax: 0897 - 56 - 6720

EXHIBIT # : 3
FCC ID : ACJ927147AHV
OUR REF. : MKES02-F017
MODEL NO. : PV-D4763
Sheet 2 of 30 Sheets

Tuner: ENG56D01G1
Part 15 Subpart B, (TV Interface Device)- Part

1) 15.107 Power Line Conducted Voltage

Freq. (MHz)	Limits (dBuV)	Interference (dBuV)	
		1- end & Grounded	The other- End & Gro.
0.45	48.0	37.2	35.5
0.55	48.0	38.9	37.4
0.65	48.0	39.6	38.2
0.78	48.0	39.7	38.9
0.85	48.0	32.4	33.5
4.12	48.0	33.6	32.4

(Refer to Sheet 5, 24, 27 of 30 Sheets)

2) 15.109 Radiated Emission(Including Tuner)

Freq. (MHz)	Limits (dBuV/m)	Emission (dBuV/m)	
		Horiz.	Vert.
108.00	43.5	28.4	33.7
162.00	43.5	34.8	34.7
212.75	43.5	34.5	35.5
216.00	43.5	38.3	38.1
243.03	46.0	38.1	39.2
486.04	46.0	37.2	38.7

(Refer to Sheet 6, 25, 26, 28, 29, 30 of 30 Sheets)

Note: Without Laurel Antenna
With accessories

3) 15.111(a) Antenna Power Conducted Voltage

Freq. (MHz)	Limits (dBuV)	Conducted Voltage (dBuV)
1454.0	51.8	37.4
1462.0	51.8	37.7
1466.0	51.8	38.1
1474.0	51.8	37.8
1478.0	51.8	37.4
1486.0	51.8	37.1

(Refer to Sheet 7 of 30 Sheets)

4) 15.115(b)(1) Output Signal Level

Ch	Limits (dBuV)		Level (dBuV)	
	Visual	Aural	Visual	Aural
3	69.5	56.5	67.5	52.1
4	69.5	56.5	67.1	52.3

(Refer to Sheet 8 of 30 Sheets)

5) 15.115(b)(2) Output Terminal
Conducted Interference

Ch	Freq. (MHz)	Limits (dBuV)	Interference (dBuV)
3	36.20	39.5	24.3
	43.34	39.5	31.4
	50.50	39.5	38.0
	72.00	39.5	35.1
	122.50	39.5	31.4
	183.75	39.5	31.6
4	42.17	39.5	24.8
	49.39	39.5	30.4
	56.50	39.5	36.8
	78.00	39.5	35.1
	134.50	39.5	31.2
	201.75	39.5	27.7

(Refer to Sheet 9, 10 of 30 Sheets)

6) 15.115(c) Transfer SW Isolation

Ch	Limits (dBuV)	Level (dBuV)
3	9.5	<3.9
4	9.5	<3.9

(Refer to Sheet 11 of 30 Sheets)

MEASUREMENT SITE : MKS Site
MEASUREMENT PROCEDURE : ANSI C63.4-1992

Note:(1) Detailed report: Refer to attached sheets.

I HEREBY STATE THAT: The measurements shown in Part II of this form were made in accordance with the procedures indicated and the energy emitted by this equipment was found to be within the limits applicable. I assume full responsibility for the accuracy and completeness of these measurements and vouch for the qualifications of all persons taking them.

I FURTHER STATE THAT: On the basis of the measurements made, the device tested is capable of operation in compliance with the requirements of Part 15 of the FCC Rules under normal use and maintenance.



T. Watanabe
Engineer

Matsushita Kotobuki Electronics Industries, Ltd.

Visual Products Business Unit
Address: 247 Fukutake, Saijo, Ehime 793 - 8510 Japan
Tel: 0897 - 56 - 1216 / Fax: 0897 - 56 - 6720

EXHIBIT # : 3
FCC ID : ACJ927147AHV
OUR REF. : MKES02-F017
MODEL NO. : PV-D4763
Sheet 3 of 30 Sheets

Tuner: TMZH2-005
Part 15 Subpart B, (TV Interface Device)- Part

2) 15.109 Radiated Emission(Including Tuner)

Freq. (MHz)	Limits (dBuV/m)	Emission (dBuV/m)	
		Horiz.	Vert.
108.00	43.5	27.8	32.7
162.00	43.5	35.1	35.1
212.75	43.5	35.0	35.7
216.00	43.5	38.0	37.4
243.03	46.0	37.5	38.4
486.04	46.0	37.2	38.2

(Refer to Sheet 12, 25, 26, 28, 29, 30 of 30 Sheets)

Note: Without Laurel Antenna
With accessories

3) 15.111 Antenna Power Conducted Voltage

Freq. (MHz)	Limits (dBuV)	Conducted Voltage (dBuV)
1006.0	51.8	42.1
1018.0	51.8	42.3
1030.0	51.8	42.5
1042.0	51.8	42.8
1046.0	51.8	42.6
1054.0	51.8	42.2

(Refer to Sheet 13 of 27 Sheets)

4) 15.115(b)(1) Output Signal Level

Ch	Limits (dBuV)		Level (dBuV)	
	Visual	Aural	Visual	Aural
3	69.5	56.5	67.0	51.1
4	69.5	56.5	66.5	50.7

(Refer to Sheet 14 of 30 Sheets)

5) 15.115(b)(2) Output Terminal
Conducted Interference

Ch	Freq. (MHz)	Limits (dBuV)	Interference (dBuV)
3	36.20	39.5	22.2
	43.40	39.5	27.6
	50.50	39.5	35.0
	72.00	39.5	34.1
	79.13	39.5	27.1
	122.50	39.5	27.5
4	42.17	39.5	21.9
	49.39	39.5	26.9
	56.50	39.5	25.0
	78.00	39.5	33.1
	85.14	39.5	25.8
	134.50	39.5	25.5

(Refer to Sheet 15, 16 of 30 Sheets)

6) 15.115© Transfer SW Isolation

Ch	Limits (dBuV)	Level (dBuV)
3	9.5	<3.9
4	9.5	<3.9

(Refer to Sheet 17 of 30 Sheets)

MEASUERMENT SITE : MKS Site
MEASUERMENT PROCEDURE : ANSI C63.4-1992

Note:(1) Detailed report: Refer to attached sheets.

I HEREBY STATE THAT: The measurements shown in Part II of this form were made in accordance with the procedures indicated and the energy emitted by this equipment was found to be within the limits applicable. I assume full responsibility for the accuracy and completeness of these measurements and vouch for the qualifications of all persons taking them.

I FURTHER STATE THAT: On the basis of the measurements made, the device tested is capable of operation in compliance with the requirements of Part 15 of the FCC Rules under normal use and maintenance.



T. Watanabe
Engineer

Matsushita Kotobuki Electronics Industries, Ltd.

Visual Products Business Unit
Address: 247 Fukutake, Saijo, Ehime 793 - 8510 Japan
Tel: 0897 - 56 - 1216 / Fax: 0897 - 56 - 6720

EXHIBIT # : 3
FCC ID : ACJ927147AHV
OUR REF. : MKES02-F017
MODEL NO. : PV-D4763
Sheet 4 of 30 Sheets

Tuner: 115-V-H015AK
Part 15 Subpart B, (TV Interface Device)- Part

2) 15.109 Radiated Emission(Including Tuner)

Freq. (MHz)	Limits (dBuV/m)	Emission (dBuV/m)	
		Horiz.	Vert.
108.00	43.5	28.1	32.9
162.00	43.5	35.1	35.1
212.75	43.5	35.3	36.1
216.00	43.5	37.9	37.4
243.03	46.0	38.8	38.1
486.04	46.0	38.2	39.0

(Refer to Sheet 18, 25, 26, 28, 29, 30 of 30 Sheets)

Note: Without Laurel Antenna
With accessories

3) 15.111 Antenna Power Conducted Voltage

Freq. (MHz)	Limits (dBuV)	Conducted Voltage (dBuV)
1522.0	51.8	38.8
1526.0	51.8	39.1
1534.0	51.8	39.8
1538.0	51.8	39.4
1546.0	51.8	39.1
1550.0	51.8	38.7

(Refer to Sheet 19 of 30 Sheets)

4) 15.115(b)(1) Output Signal Level

Ch	Limits (dBuV)		Level (dBuV)	
	Visual	Aural	Visual	Aural
3	69.5	56.5	66.8	50.7
4	69.5	56.5	66.4	50.0

(Refer to Sheet 20 of 30 Sheets)

5) 15.115(b)(2) Output Terminal Conducted Interference

Ch	Freq. (MHz)	Limits (dBuV)	Interference (dBuV)
3	36.20	39.5	22.7
	43.34	39.5	30.1
	50.50	39.5	36.4
	72.00	39.5	34.1
	79.13	39.5	27.4
	610.00	39.5	28.8
	4	42.17	39.5
49.40		39.5	29.5
56.50		39.5	36.0
78.00		39.5	33.4
85.14		39.5	25.1
608.60		39.5	28.7

(Refer to Sheet 21, 22 of 30 Sheets)

6) 15.115© Transfer SW Isolation

Ch	Limits (dBuV)	Level (dBuV)
3	9.5	<3.9
4	9.5	<3.9

(Refer to Sheet 23 of 30 Sheets)

MEASUERMENT SITE : MKS Site
MEASUERMENT PROCEDURE : ANSI C63.4-1992

Note:(1) Detailed report: Refer to attached sheets.

I HEREBY STATE THAT: The measurements shown in Part II of this form were made in accordance with the procedures indicated and the energy emitted by this equipment was found to be within the limits applicable. I assume full responsibility for the accuracy and completeness of these measurements and vouch for the qualifications of all persons taking them.

I FURTHER STATE THAT: On the basis of the measurements made, the device tested is capable of operation in compliance with the requirements of Part 15 of the FCC Rules under normal use and maintenance.



T. Watanabe
Engineer

Part 15 Subpart B, (TV Interface Device)

1) 15.107 Power Line Conducted Voltage

Video Signal	Freq. (MHz)	Meter Read. (dBuV)		LISN Factor (dB)	Interference (dBuV)	
		1-end & Gro.	The other-End&Gro.		1-end & Gro.	The other-End &Gro.
Multi Burst 1 V p-p	0.45	36.3	34.8	0.1	36.4	34.9
	0.55	37.7	37.0	0.1	37.8	37.1
	0.65	38.7	37.9	0.1	38.8	38.0
	0.78	38.7	38.4	0.1	38.8	38.5
	0.85	31.6	32.6	0.1	31.7	32.7
	4.12	32.7	32.0	0.3	33.0	32.3
Multi Burst 5 V p-p	0.45	36.7	35.1	0.1	36.8	35.2
	0.55	37.9	37.4	0.1	38.0	37.5
	0.65	37.8	37.4	0.1	37.9	37.5
	0.78	38.1	37.5	0.1	38.2	37.6
	0.85	31.8	33.1	0.1	31.9	33.2
	4.12	34.2	34.4	0.3	34.5	34.7
RF/CATV Signal Input	0.45	35.8	34.9	0.1	35.9	35.0
	0.55	37.4	37.1	0.1	37.5	37.2
	0.65	38.1	37.4	0.1	38.2	37.5
	0.78	38.0	37.5	0.1	38.1	37.6
	0.85	32.3	33.4	0.1	32.4	33.5
	4.12	32.2	32.6	0.3	32.5	32.9
Internal Signal (DVD Playback)	0.45	37.1	35.4	0.1	37.2	35.5
	0.55	38.8	37.3	0.1	38.9	37.4
	0.65	39.5	38.1	0.1	39.6	38.2
	0.78	39.6	38.8	0.1	39.7	38.9
	0.85	32.3	33.4	0.1	32.4	33.5
	4.12	33.3	32.1	0.3	33.6	32.4
Internal Signal (SD Card slide show)	0.45	36.6	36.0	0.1	36.7	36.1
	0.55	38.6	37.2	0.1	38.7	37.3
	0.65	39.1	38.1	0.1	39.2	38.2
	0.78	39.5	38.4	0.1	39.6	38.5
	0.85	33.1	32.8	0.1	33.2	32.9
	4.12	33.3	33.4	0.3	33.6	33.7

Note:

- Sample calculation at
M.B., 1 V p-p, 1-end & Gro. 0.45 MHz ; 36.3 + 0.1 = 36.4 (dBuV)
- Measuring Instruments:
 - Field strength meter - Kyoritsu Electric Work Co., Ltd.
 Model : KNM-2403
 (1) Detector function : CISPR Q-Peak
 (2) IF band width : 9 kHz
 (3) Input impedance : 50 ohms
 - Line impedance stabilized network (LISN)
 - Kyoritsu Electric Work Co., Ltd.
 Model : KNW-406
 50 ohms / 50 uH network
 - Test Signal Generator - Shibasoku Co., Ltd.
 (Multi Burst) Model : 205
- The spectrum was checked from 0.45 MHz to 30 MHz and the six highest emissions relative to the appropriate limit were measured and reported.

Part 15 Subpart B, (TV Interface Device)

2) 15.109 Radiated Emission (Including Tuner)

Video Signal	Frequency (MHz)	Meter Reading Open Volt. (dBuV)		Correction Factor (dB) Open Vol.	Emission & 3 meters(dBuV)	
		Horiz.	Vert.		Horiz.	Vert.
Multi Burst 1 V p-p	108.00	14.3	19.0	13.5	27.8	32.5
	162.00	16.3	14.9	18.2	34.5	33.1
	212.75	14.7	14.9	19.9	34.6	34.8
	216.00	16.5	13.0	20.4	36.9	33.4
	243.03	17.0	17.4	20.8	37.8	38.2
	486.04	15.2	15.6	21.8	37.0	37.4
Multi Burst 5 V p-p	108.00	14.3	18.9	13.5	27.8	32.4
	162.00	16.4	14.8	18.2	34.6	33.0
	212.75	14.6	14.6	19.9	34.5	34.5
	216.00	16.6	12.8	20.4	37.0	33.2
	243.03	16.9	17.4	20.8	37.7	38.2
	486.04	15.1	15.7	21.8	36.9	37.5
RF/CATV Signal Input	108.00	14.1	18.8	13.5	27.6	32.3
	162.00	15.5	11.7	18.2	33.7	29.9
	212.75	13.7	11.2	19.9	33.6	31.1
	216.00	16.8	15.2	20.4	37.2	35.6
	243.03	15.7	16.5	20.8	36.5	37.3
	486.04	13.1	14.0	21.8	34.9	35.8
Internal Signal (DVD Playback)	108.00	14.9	20.2	13.5	28.4	33.7
	162.00	16.6	16.5	18.2	34.8	34.7
	212.75	14.6	15.6	19.9	34.5	35.5
	216.00	17.9	17.7	20.4	38.3	38.1
	243.03	17.3	18.4	20.8	38.1	39.2
	486.04	15.4	16.9	21.8	37.2	38.7
Internal Signal (SD Card slide show)	108.00	14.0	17.2	13.5	27.5	30.7
	162.00	17.0	16.0	18.2	35.2	34.2
	212.75	14.3	15.1	19.9	34.2	35.0
	216.00	16.6	17.6	20.4	37.0	38.0
	243.03	15.1	18.2	20.8	35.9	39.0
	486.04	13.9	16.7	21.8	35.7	38.5

Note: 1. Sample calculation at

M.B., 1 V p-p, Horiz. 108.00 MHz ; 14.3 + 13.5 = 27.8 (dBuV/m)

2. Measuring Instruments:

a) Field strength meter

- Hewlett Packard company

Model: HP 8546A

(1) Frequency range : 9 kHz to 6.5 GHz

(2) RF Input : 50 ohm

(3) IF band width : 200 Hz/ 9 kHz/ 120 kHz/ 1MHz

(4) Detector function : Average/CISPR Q-Peak/Peak

b) Test Signal Generator
(Multi Burst)

- Shibasoku Co., Ltd.

Model: TG-5, 2U2

c) Receiving antenna

- Schwarzbeck

Model: VHA9103

30 - 300 MHz

Model: UHALP9108A

300 - 1000 MHz

- The Electro-Mechanics Company

Model: 3115

1 - 18 GHz

3. The spectrum was checked from 30 MHz to 1694 MHz and the six highest emissions relative to the appropriate limit were measured and reported.

Tuner: ENG56D01G1

EXHIBIT # : 3
FCC ID : ACJ927147AHV
OUR REF. : MKES02-F017
MODEL NO. : PV-D4763
Sheet 7 of 30 Sheets

Part 15 Subpart B. (TV Interface Device)

3) 15.111 (a) Antenna Power Conducted Voltage

Frequency (MHz)	Meter Reading (dBuV)	Matc. Pad Loss (dB)	Interference (dBuV)
1454.0	28.6	8.8	37.4
1462.0	28.9	8.8	37.7
1466.0	29.3	8.8	38.1
1474.0	29.0	8.8	37.8
1478.0	28.6	8.8	37.4
1486.0	28.3	8.8	37.1

Antenna Input Impedance: 75 ohms (Unbalanced)

Note:

1. Sample calculation at 1454.0 MHz ; 28.6 + 8.8 = 37.4 (dBuV)

2. Measuring Instrument:

a) Spectrum Analyzer

- ADVANTEST Co., Ltd.

Model : R3261A

(1) Detector function : Peak

(2) Band width : 100 kHz

b) Matching Pad

- Anritsu Electric Co., Ltd.

Model : MB-009

(1) Frequency range : DC – 2 GHz

3. The spectrum was checked from 30 MHz to 1694 MHz and the six highest emissions relative to the appropriate limit were measured and reported.

4) 15.115 (b) (1) Output Signal Level

Video Signal	Ch	Measured Frequency(MHz)		Meter Reading (dBuV)		Pad Loss (dB)	Output Signal Level (dBuV)	
		Visual	Aural	Visual	Aural		Visual	Aural
Multi Burst 1 V p-p	3	61.25	65.75	65.2	49.8	2.3	67.5	52.1
	4	67.25	71.75	64.8	50.0	2.3	67.1	52.3
Multi Burst 5 V p-p	3	61.25	65.75	65.2	49.8	2.3	67.5	52.1
	4	67.25	71.75	64.8	50.0	2.3	67.1	52.3
RF/CATV Signal	3	61.25	65.75	65.2	49.8	2.3	67.5	52.1
	4	67.25	71.75	64.8	50.0	2.3	67.1	52.3
Internal Signal (DVD Playback)	3	61.25	65.75	65.2	49.8	2.3	67.5	52.1
	4	67.25	71.75	64.8	50.0	2.3	67.1	52.3
Internal Signal (SD Card slide show)	3	61.25	65.75	65.2	49.8	2.3	67.5	52.1
	4	67.25	71.75	64.8	50.0	2.3	67.1	52.3

RF Output Impedance: 75 ohms (Unbalanced)

Note:

1. Sample calculation at

M.B., 1 V p-p, Visual, 3 Ch ; 65.2 + 2.3 = 67.5 (dBuV)

2. Measuring Instrument:

a) Spectrum Analyzer

- Anritsu Electric Co., Ltd.

Model : MS62B

(1) Detector function : Peak

(2) Band width : 100 kHz

b) Matching Pad

- Anritsu Electric Co., Ltd.

Model : MP614A

(1) Frequency range : 10 - 1200 MHz

c) Test Signal Generator
(Multi Burst)

- Shibasoku Co., Ltd.

Model : 205

Part 15 Subpart B, (TV Interface Device)

5) 15.115 (b) (2) Output Terminal Conducted Interference

Video Signal	Ch	Freq. (MHz)	Meter Read. (dBuV)	Matc. Pad Loss (dB)	Att. Pad Loss(dB)	Gain of Amp.(dB)	Interference (dBuV)	
Multi Burst 1 V p-p	3	36.20	46.3	2.3	N/A	24.3	24.3	
		43.34	53.4	2.3	N/A	24.3	31.4	
		50.50	60.0	2.3	N/A	24.3	38.0	
		72.00	57.2	2.3	N/A	24.4	35.1	
		122.50	53.4	2.3	N/A	24.3	31.4	
		183.75	53.6	2.3	N/A	24.3	31.6	
	4	42.17	46.8	2.3	N/A	24.3	24.8	
		49.39	52.4	2.3	N/A	24.3	30.4	
		56.50	58.8	2.3	N/A	24.3	36.8	
		78.00	57.2	2.3	N/A	24.4	35.1	
		134.50	53.2	2.3	N/A	24.3	31.2	
		201.75	49.7	2.3	N/A	24.3	27.7	
	Multi Burst 5 V p-p	3	36.20	46.3	2.3	N/A	24.3	24.3
			43.34	53.4	2.3	N/A	24.3	31.4
50.50			60.0	2.3	N/A	24.3	38.0	
72.00			57.2	2.3	N/A	24.4	35.1	
122.50			53.4	2.3	N/A	24.3	31.4	
183.75			53.6	2.3	N/A	24.3	31.6	
4		42.17	46.8	2.3	N/A	24.3	24.8	
		49.39	52.4	2.3	N/A	24.3	30.4	
		56.50	58.8	2.3	N/A	24.3	36.8	
		78.00	57.2	2.3	N/A	24.4	35.1	
		134.50	53.2	2.3	N/A	24.3	31.2	
		201.75	49.7	2.3	N/A	24.3	27.7	
RF/CATV Signal Input		3	36.20	46.3	2.3	N/A	24.3	24.3
			43.34	53.4	2.3	N/A	24.3	31.4
	50.50		60.0	2.3	N/A	24.3	38.0	
	72.00		57.2	2.3	N/A	24.4	35.1	
	122.50		53.4	2.3	N/A	24.3	31.4	
	183.75		53.6	2.3	N/A	24.3	31.6	
	4	42.17	46.8	2.3	N/A	24.3	24.8	
		49.39	52.4	2.3	N/A	24.3	30.4	
		56.50	58.8	2.3	N/A	24.3	36.8	
		78.00	57.2	2.3	N/A	24.4	35.1	
		134.50	53.2	2.3	N/A	24.3	31.2	
		201.75	49.7	2.3	N/A	24.3	27.7	

Part 15 Subpart B, (TV Interface Device)

5) 15.115 (b) (2) Output Terminal Conducted Interference

Video Signal	Ch	Freq. (MHz)	Meter Read. (dBuV)	Matc. Pad Loss (dB)	Att. Pad Loss(dB)	Gain of Amp.(dB)	Interference (dBuV)	
Internal Signal (DVD Playback)	3	36.20	46.3	2.3	N/A	24.3	24.3	
		43.34	53.4	2.3	N/A	24.3	31.4	
		50.50	60.0	2.3	N/A	24.3	38.0	
		72.00	57.2	2.3	N/A	24.4	35.1	
		122.50	53.4	2.3	N/A	24.3	31.4	
		183.75	53.6	2.3	N/A	24.3	31.6	
	4	42.17	46.8	2.3	N/A	24.3	24.8	
		49.39	52.4	2.3	N/A	24.3	30.4	
		56.50	58.8	2.3	N/A	24.3	36.8	
		78.00	57.2	2.3	N/A	24.4	35.1	
		134.50	53.2	2.3	N/A	24.3	31.2	
		201.75	49.7	2.3	N/A	24.3	27.7	
	Internal Signal (SD Card slide show)	3	36.20	46.3	2.3	N/A	24.3	24.3
			43.34	53.4	2.3	N/A	24.3	31.4
50.50			60.0	2.3	N/A	24.3	38.0	
72.00			57.2	2.3	N/A	24.4	35.1	
122.50			53.4	2.3	N/A	24.3	31.4	
183.75			53.6	2.3	N/A	24.3	31.6	
4		42.17	46.8	2.3	N/A	24.3	24.8	
		49.39	52.4	2.3	N/A	24.3	30.4	
		56.50	58.8	2.3	N/A	24.3	36.8	
		78.00	57.2	2.3	N/A	24.4	35.1	
		134.50	53.2	2.3	N/A	24.3	31.2	
		201.75	49.7	2.3	N/A	24.3	27.7	

RF Output Impedance: 75 ohms (Unbalanced)

Note:

1. Sample calculation at

M.B., 1 V p-p, 3 Ch., 36.20 MHz ; $46.3 + 2.3 - 24.3 = 24.3$ (dBuV)

2. Measuring Instrument:

a) Spectrum Analyzer

- Anritsu Electric Co., Ltd.

Model : MS62B

(1) Detector function : Peak

(2) Band width : 100 kHz

b) Matching Pad

- Anritsu Electric Co., Ltd.

Model : MP614A

(1) Frequency range : 10 - 1200 MHz

c) Test Signal Generator
(Multi Burst)

- Shibasoku Co., Ltd.

Model : 205

d) Amplifier

- Hewlett Packard

Model : 8447F

3. The spectrum was checked from 30 MHz to 1000 MHz and the six highest emissions relative to the appropriate limit were measured and reported.

Part 15 Subpart B. (TV Interface Device)

6) 15.115 (c) Transfer Switch Isolation

Video Signal	Ch	Meter Read.(dBuV)	Matching Pad Loss(dB)	Gain of Amp.(dB)	Pad Loss (dB)	Level (dBuV)
Multi Burst 1 V p-p	3	<26.0	2.3	24.4	N/A	<3.9
	4	<26.0	2.3	24.4	N/A	<3.9
Multi Burst 5 V p-p	3	<26.0	2.3	24.4	N/A	<3.9
	4	<26.0	2.3	24.4	N/A	<3.9
Internal Signal (DVD Playback)	3	<26.0	2.3	24.4	N/A	<3.9
	4	<26.0	2.3	24.4	N/A	<3.9
Internal Signal (SD Card slide show)	3	<26.0	2.3	24.4	N/A	<3.9
	4	<26.0	2.3	24.4	N/A	<3.9

RF Output Impedance: 75 ohms (Unbalanced)

Note:

1. Sample calculation at

M.B., 1 V p-p, Visual, 3 Ch ; $<26.0 + 2.3 - 24.4 = <3.9$ (dBuV)

2. Measuring Instrument:

a) Spectrum Analyzer

- Anritsu Electric Co., Ltd.

Model : MS62B

(1) Detector function : Peak

(2) Band width : 100 kHz

b) Matching Pad

- Anritsu Electric Co., Ltd.

Model : MP614A

(1) Frequency range : 10 - 1200 MHz

c) Test Signal Generator
(Multi Burst)

- Shibasoku Co., Ltd.

Model : 205

d) Amplifier

- Hewlett Packard

Model : 8447F

Tuner: TMZH2-005

EXHIBIT # : 3
 FCC ID : ACJ927147AHV
 OUR REF. : MKES02-F017
 MODEL NO. : PV-D4763

Part 15 Subpart B, (TV Interface Device)

2) 15.109 Radiated Emission (Including Tuner)

Sheet 12 of 30 Sheets

Video Signal	Frequency (MHz)	Meter Reading Open Volt. (dBuV)		Correction Factor (dB) Open Vol.	Emission & 3 meters(dBuV)	
		Horiz.	Vert.		Horiz.	Vert.
Multi Burst 1 V p-p	108.00	14.0	17.7	13.5	27.5	31.2
	162.00	16.0	14.2	18.2	34.2	32.4
	212.75	14.8	15.3	19.9	34.7	35.2
	216.00	16.7	12.5	20.4	37.1	32.9
	243.03	17.3	16.7	20.8	38.1	37.5
	486.04	14.6	15.7	21.8	36.4	37.5
Multi Burst 5 V p-p	108.00	15.0	18.0	13.5	28.5	31.5
	162.00	15.8	13.8	18.2	34.0	32.0
	212.75	14.4	15.4	19.9	34.3	35.3
	216.00	17.1	12.8	20.4	37.5	33.2
	243.03	17.3	17.2	20.8	38.1	38.0
	486.04	14.5	16.2	21.8	36.3	38.0
RF/CATV Signal Input	108.00	14.7	17.5	13.5	28.2	31.0
	162.00	15.2	13.7	18.2	33.4	31.9
	212.75	13.8	14.9	19.9	33.7	34.8
	216.00	16.9	13.2	20.4	37.3	33.6
	243.03	16.9	17.0	20.8	37.7	37.8
	486.04	13.4	14.9	21.8	35.2	36.7
Internal Signal (DVD Playback)	108.00	14.3	19.2	13.5	27.8	32.7
	162.00	16.9	16.9	18.2	35.1	35.1
	212.75	15.1	15.8	19.9	35.0	35.7
	216.00	17.6	17.0	20.4	38.0	37.4
	243.03	16.7	17.6	20.8	37.5	38.4
	486.04	15.4	16.4	21.8	37.2	38.2
Internal Signal (SD Card slide show)	108.00	13.3	17.6	13.5	26.8	31.1
	162.00	16.7	15.4	18.2	34.9	33.6
	212.75	15.4	14.8	19.9	35.3	34.7
	216.00	16.8	16.9	20.4	37.2	37.3
	243.03	15.3	17.7	20.8	36.1	38.5
	486.04	14.6	17.1	21.8	36.4	38.9

Note: 1. Sample calculation at

M.B., 1 V p-p, Horiz. 108.00 MHz ; $14.0 + 13.5 = 27.5$ (dBuV/m)

2. Measuring Instruments:

a) Field strength meter

- Hewlett Packard company

Model: HP 8546A

(1) Frequency range : 9 kHz to 6.5 GHz

(2) RF Input : 50 ohm

(3) IF band width : 200 Hz/ 9 kHz/ 120 kHz/ 1MHz

(4) Detector function : Average/CISPR Q-Peak/Peak

b) Test Signal Generator
(Multi Burst)

- Shibasoku Co., Ltd.

Model: TG-5, 2U2

c) Receiving antenna

- Schwarzbeck

Model: VHA9103

30 - 300 MHz

Model: UHALP9108A

300 - 1000 MHz

- The Electro-Mechanics Company

Model: 3115

1 - 18 GHz

3. The spectrum was checked from 30 MHz to 1694 MHz and the six highest emissions relative to the appropriate limit were measured and reported.

Tuner: TMZH2-005

EXHIBIT # : 3
FCC ID : ACJ927147AHV
OUR REF. : MKES02-F017
MODEL NO. : PV-D4763
Sheet 13 of 30 Sheets

Part 15 Subpart B. (TV Interface Device)

3) 15.111 (a) Antenna Power Conducted Voltage

Frequency (MHz)	Meter Reading (dBuV)	Matc. Pad Loss (dB)	Interference (dBuV)
1006.0	33.3	8.8	42.1
1018.0	33.5	8.8	42.3
1030.0	33.7	8.8	42.5
1042.0	34.0	8.8	42.8
1046.0	33.8	8.8	42.6
1054.0	33.4	8.8	42.2

Antenna Input Impedance: 75 ohms (Unbalanced)

Note:

1. Sample calculation at 1006.0 MHz ; $33.3 + 8.8 = 42.1$ (dBuV)

2. Measuring Instrument:

a) Spectrum Analyzer

- ADVANTEST Co., Ltd.

Model : R3261A

(1) Detector function : Peak

(2) Band width : 100 kHz

b) Matching Pad

- Anritsu Electric Co., Ltd.

Model : MB-009

(1) Frequency range : DC – 2 GHz

3. The spectrum was checked from 30 MHz to 1694 MHz and the six highest emissions relative to the appropriate limit were measured and reported.

4) 15.115 (b) (1) Output Signal Level

Video Signal	Ch	Measured Frequency(MHz)		Meter Reading (dBuV)		Pad Loss (dB)	Output Signal Level (dBuV)	
		Visual	Aural	Visual	Aural		Visual	Aural
Multi Burst 1 V p-p	3	61.25	65.75	64.7	48.8	2.3	67.0	51.1
	4	67.25	71.75	64.2	48.4	2.3	66.5	50.7
Multi Burst 5 V p-p	3	61.25	65.75	64.7	48.8	2.3	67.0	51.1
	4	67.25	71.75	64.2	48.4	2.3	66.5	50.7
RF/CATV Signal	3	61.25	65.75	64.7	48.8	2.3	67.0	51.1
	4	67.25	71.75	64.2	48.4	2.3	66.5	50.7
Internal Signal (DVD Playback)	3	61.25	65.75	64.7	48.8	2.3	67.0	51.1
	4	67.25	71.75	64.2	48.4	2.3	66.5	50.7
Internal Signal (SD Card slide show)	3	61.25	65.75	64.7	48.8	2.3	67.0	51.1
	4	67.25	71.75	64.2	48.4	2.3	66.5	50.7

RF Output Impedance: 75 ohms (Unbalanced)

Note:

1. Sample calculation at

M.B., 1 V p-p, Visual, 3 Ch ; 64.7 + 2.3 = 67.0 (dBuV)

2. Measuring Instrument:

a) Spectrum Analyzer

- Anritsu Electric Co., Ltd.

Model : MS62B

(1) Detector function : Peak

(2) Band width : 100 kHz

b) Matching Pad

- Anritsu Electric Co., Ltd.

Model : MP614A

(1) Frequency range : 10 - 1200 MHz

c) Test Signal Generator
(Multi Burst)

- Shibasoku Co., Ltd.

Model : 205

Part 15 Subpart B, (TV Interface Device)

5) 15.115 (b) (2) Output Terminal Conducted Interference

Video Signal	Ch	Freq. (MHz)	Meter Read. (dBuV)	Matc. Pad Loss (dB)	Att. Pad Loss(dB)	Gain of Amp.(dB)	Interference (dBuV)		
Multi Burst 1 V p-p	3	36.20	44.2	2.3	N/A	24.3	22.2		
		43.40	49.6	2.3	N/A	24.3	27.6		
		50.50	57.0	2.3	N/A	24.3	35.0		
		72.00	56.2	2.3	N/A	24.4	34.1		
		79.13	49.2	2.3	N/A	24.4	27.1		
		122.50	49.5	2.3	N/A	24.3	27.5		
		42.17	43.9	2.3	N/A	24.3	21.9		
	4	49.39	48.9	2.3	N/A	24.3	26.9		
		56.50	47.0	2.3	N/A	24.3	25.0		
		78.00	55.2	2.3	N/A	24.4	33.1		
		85.14	47.9	2.3	N/A	24.4	25.8		
		134.50	47.5	2.3	N/A	24.3	25.5		
		Multi Burst 5 V p-p	3	36.20	44.2	2.3	N/A	24.3	22.2
				43.40	49.6	2.3	N/A	24.3	27.6
50.50	57.0			2.3	N/A	24.3	35.0		
72.00	56.2			2.3	N/A	24.4	34.1		
79.13	49.2			2.3	N/A	24.4	27.1		
122.50	49.5			2.3	N/A	24.3	27.5		
42.17	43.9			2.3	N/A	24.3	21.9		
4	49.39		48.9	2.3	N/A	24.3	26.9		
	56.50		47.0	2.3	N/A	24.3	25.0		
	78.00		55.2	2.3	N/A	24.4	33.1		
	85.14		47.9	2.3	N/A	24.4	25.8		
	134.50		47.5	2.3	N/A	24.3	25.5		
	RF/CATV Signal Input		3	36.20	44.2	2.3	N/A	24.3	22.2
				43.40	49.6	2.3	N/A	24.3	27.6
50.50		57.0		2.3	N/A	24.3	35.0		
72.00		56.2		2.3	N/A	24.4	34.1		
79.13		49.2		2.3	N/A	24.4	27.1		
122.50		49.5		2.3	N/A	24.3	27.5		
42.17		43.9		2.3	N/A	24.3	21.9		
4		49.39	48.9	2.3	N/A	24.3	26.9		
		56.50	47.0	2.3	N/A	24.3	25.0		
		78.00	55.2	2.3	N/A	24.4	33.1		
		85.14	47.9	2.3	N/A	24.4	25.8		
		134.50	47.5	2.3	N/A	24.3	25.5		

Part 15 Subpart B, (TV Interface Device)

5) 15.115 (b) (2) Output Terminal Conducted Interference

Video Signal	Ch	Freq. (MHz)	Meter Read. (dBuV)	Matc. Pad Loss (dB)	Att. Pad Loss(dB)	Gain of Amp.(dB)	Interference (dBuV)	
Internal Signal (DVD Playback)	3	36.20	44.2	2.3	N/A	24.3	22.2	
		43.40	49.6	2.3	N/A	24.3	27.6	
		50.50	57.0	2.3	N/A	24.3	35.0	
		72.00	56.2	2.3	N/A	24.4	34.1	
		79.13	49.2	2.3	N/A	24.4	27.1	
		122.50	49.5	2.3	N/A	24.3	27.5	
	4	42.17	43.9	2.3	N/A	24.3	21.9	
		49.39	48.9	2.3	N/A	24.3	26.9	
		56.50	47.0	2.3	N/A	24.3	25.0	
		78.00	55.2	2.3	N/A	24.4	33.1	
		85.14	47.9	2.3	N/A	24.4	25.8	
		134.50	47.5	2.3	N/A	24.3	25.5	
	Internal Signal (SD Card slide show)	3	36.20	44.2	2.3	N/A	24.3	22.2
			43.40	49.6	2.3	N/A	24.3	27.6
50.50			57.0	2.3	N/A	24.3	35.0	
72.00			56.2	2.3	N/A	24.4	34.1	
79.13			49.2	2.3	N/A	24.4	27.1	
122.50			49.5	2.3	N/A	24.3	27.5	
4		42.17	43.9	2.3	N/A	24.3	21.9	
		49.39	48.9	2.3	N/A	24.3	26.9	
		56.50	47.0	2.3	N/A	24.3	25.0	
		78.00	55.2	2.3	N/A	24.4	33.1	
		85.14	47.9	2.3	N/A	24.4	25.8	
		134.50	47.5	2.3	N/A	24.3	25.5	

RF Output Impedance: 75 ohms (Unbalanced)

Note:

1. Sample calculation at

M.B., 1 V p-p, 3 Ch., 36.20 MHz ; $44.2 + 2.3 - 24.3 = 22.2$ (dBuV)

2. Measuring Instrument:

a) Spectrum Analyzer

- Anritsu Electric Co., Ltd.

Model : MS62B

(1) Detector function : Peak

(2) Band width : 100 kHz

b) Matching Pad

- Anritsu Electric Co., Ltd.

Model : MP614A

(1) Frequency range : 10 - 1200 MHz

c) Test Signal Generator
(Multi Burst)

- Shibasoku Co., Ltd.

Model : 205

d) Amplifier

- Hewlett Packard

Model : 8447F

3. The spectrum was checked from 30 MHz to 1000 MHz and the six highest emissions relative to the appropriate limit were measured and reported.

Part 15 Subpart B. (TV Interface Device)

6) 15.115 (c) Transfer Switch Isolation

Video Signal	Ch	Meter Read.(dBuV)	Matching Pad Loss(dB)	Gain of Amp.(dB)	Pad Loss (dB)	Level (dBuV)
Multi Burst 1 V p-p	3	<26.0	2.3	24.4	N/A	<3.9
	4	<26.0	2.3	24.4	N/A	<3.9
Multi Burst 5 V p-p	3	<26.0	2.3	24.4	N/A	<3.9
	4	<26.0	2.3	24.4	N/A	<3.9
Internal Signal (DVD Playback)	3	<26.0	2.3	24.4	N/A	<3.9
	4	<26.0	2.3	24.4	N/A	<3.9
Internal Signal (SD Card slide show)	3	<26.0	2.3	24.4	N/A	<3.9
	4	<26.0	2.3	24.4	N/A	<3.9

RF Output Impedance: 75 ohms (Unbalanced)

Note:

1. Sample calculation at

M.B., 1 V p-p, Visual, 3 Ch ; $<26.0 + 2.3 - 24.4 = <3.9$ (dBuV)

2. Measuring Instrument:

a) Spectrum Analyzer

- Anritsu Electric Co., Ltd.

Model : MS62B

(1) Detector function : Peak

(2) Band width : 100 kHz

b) Matching Pad

- Anritsu Electric Co., Ltd.

Model : MP614A

(1) Frequency range : 10 - 1200 MHz

c) Test Signal Generator
(Multi Burst)

- Shibasoku Co., Ltd.

Model : 205

d) Amplifier

- Hewlett Packard

Model : 8447F

Tuner: 115-V-H015AK

EXHIBIT # : 3
 FCC ID : ACJ927147AHV
 OUR REF. : MKES02-F017
 MODEL NO. : PV-D4763

Part 15 Subpart B, (TV Interface Device)

2) 15.109 Radiated Emission (Including Tuner)

Sheet 18 of 30 Sheets

Video Signal	Frequency (MHz)	Meter Reading Open Volt. (dBuV)		Correction Factor (dB) Open Vol.	Emission & 3 meters(dBuV)	
		Horiz.	Vert.		Horiz.	Vert.
Multi Burst 1 V p-p	108.00	14.2	19.6	13.5	27.7	33.1
	162.00	16.3	15.0	18.2	34.5	33.2
	212.75	14.6	14.3	19.9	34.5	34.2
	216.00	16.5	13.1	20.4	36.9	33.5
	243.03	16.2	16.8	20.8	37.0	37.6
	486.04	14.7	15.4	21.8	36.5	37.2
Multi Burst 5 V p-p	108.00	14.3	19.7	13.5	27.8	33.2
	162.00	16.6	15.0	18.2	34.8	33.2
	212.75	14.6	14.6	19.9	34.5	34.5
	216.00	16.8	12.3	20.4	37.2	32.7
	243.03	16.1	16.4	20.8	36.9	37.2
	486.04	15.0	15.7	21.8	36.8	37.5
RF/CATV Signal Input	108.00	13.3	17.9	13.5	26.8	31.4
	162.00	14.6	9.6	18.2	32.8	27.8
	212.75	13.9	11.5	19.9	33.8	31.4
	216.00	16.9	11.0	20.4	37.3	31.4
	243.03	14.6	15.9	20.8	35.4	36.7
	486.04	13.4	14.7	21.8	35.2	36.5
Internal Signal (DVD Playback)	108.00	14.6	19.4	13.5	28.1	32.9
	162.00	16.9	16.9	18.2	35.1	35.1
	212.75	15.4	16.2	19.9	35.3	36.1
	216.00	17.5	17.0	20.4	37.9	37.4
	243.03	18.0	17.3	20.8	38.8	38.1
	486.04	16.4	17.2	21.8	38.2	39.0
Internal Signal (SD Card slide show)	108.00	12.9	15.9	13.5	26.4	29.4
	162.00	16.6	16.9	18.2	34.8	35.1
	212.75	13.8	15.6	19.9	33.7	35.5
	216.00	16.0	16.1	20.4	36.4	36.5
	243.03	15.3	17.9	20.8	36.1	38.7
	486.04	12.8	15.6	21.8	34.6	37.4

Note: 1. Sample calculation at M.B., 1 V p-p, Horiz. 108.00 MHz ; 14.2 + 13.5 = 27.7 (dBuV/m)

2. Measuring Instruments:

- a) Field strength meter
 - Hewlett Packard company
 - Model: HP 8546A
 - (1) Frequency range : 9 kHz to 6.5 GHz
 - (2) RF Input : 50 ohm
 - (3) IF band width : 200 Hz/ 9 kHz/ 120 kHz/ 1MHz
 - (4) Detector function : Average/CISPR Q-Peak/Peak
- b) Test Signal Generator (Multi Burst)
 - Shibasoku Co., Ltd.
 - Model: TG-5, 2U2
- c) Receiving antenna
 - Schwarzbeck
 - Model: VHA9103 30 - 300 MHz
 - Model: UHALP9108A 300 - 1000 MHz
 - The Electro-Mechanics Company
 - Model: 3115 1 - 18 GHz

3. The spectrum was checked from 30 MHz to 1694 MHz and the six highest emissions relative to the appropriate limit were measured and reported.

Tuner: 115-V-H015AK

EXHIBIT # : 3
FCC ID : ACJ927147AHV
OUR REF. : MKES02-F017
MODEL NO. : PV-D4763
Sheet 19 of 30 Sheets

Part 15 Subpart B. (TV Interface Device)

3) 15.111 (a) Antenna Power Conducted Voltage

Frequency (MHz)	Meter Reading (dBuV)	Matc. Pad Loss (dB)	Interference (dBuV)
1522.0	30.0	8.8	38.8
1526.0	30.3	8.8	39.1
1534.0	31.0	8.8	39.8
1538.0	30.6	8.8	39.4
1546.0	30.3	8.8	39.1
1550.0	29.9	8.8	38.7

Antenna Input Impedance: 75 ohms (Unbalanced)

Note:

1. Sample calculation at 1522.0 MHz ; 30.0 + 8.8 = 38.8 (dBuV)

2. Measuring Instrument:

a) Spectrum Analyzer

- ADVANTEST Co., Ltd.

Model : R3261A

(1) Detector function : Peak

(2) Band width : 100 kHz

b) Matching Pad

- Anritsu Electric Co., Ltd.

Model : MB-009

(1) Frequency range : DC – 2 GHz

3. The spectrum was checked from 30 MHz to 1694 MHz and the six highest emissions relative to the appropriate limit were measured and reported.

4) 15.115 (b) (1) Output Signal Level

Video Signal	Ch	Measured Frequency(MHz)		Meter Reading (dBuV)		Pad Loss (dB)	Output Signal Level (dBuV)	
		Visual	Aural	Visual	Aural		Visual	Aural
Multi Burst 1 V p-p	3	61.25	65.75	64.5	48.4	2.3	66.8	50.7
	4	67.25	71.75	64.1	47.7	2.3	66.4	50.0
Multi Burst 5 V p-p	3	61.25	65.75	64.5	48.4	2.3	66.8	50.7
	4	67.25	71.75	64.1	47.7	2.3	66.4	50.0
RF/CATV Signal	3	61.25	65.75	64.5	48.4	2.3	66.8	50.7
	4	67.25	71.75	64.1	47.7	2.3	66.4	50.0
Internal Signal (DVD Playback)	3	61.25	65.75	64.5	48.4	2.3	66.8	50.7
	4	67.25	71.75	64.1	47.7	2.3	66.4	50.0
Internal Signal (SD Card slide show)	3	61.25	65.75	64.5	48.4	2.3	66.8	50.7
	4	67.25	71.75	64.1	47.7	2.3	66.4	50.0

RF Output Impedance: 75 ohms (Unbalanced)

Note:

1. Sample calculation at

M.B., 1 V p-p, Visual, 3 Ch ; 64.5 + 2.3 = 66.8 (dBuV)

2. Measuring Instrument:

a) Spectrum Analyzer

- Anritsu Electric Co., Ltd.

Model : MS62B

(1) Detector function : Peak

(2) Band width : 100 kHz

b) Matching Pad

- Anritsu Electric Co., Ltd.

Model : MP614A

(1) Frequency range : 10 - 1200 MHz

c) Test Signal Generator
(Multi Burst)

- Shibasoku Co., Ltd.

Model : 205

Part 15 Subpart B, (TV Interface Device)

5) 15.115 (b) (2) Output Terminal Conducted Interference

Video Signal	Ch	Freq. (MHz)	Meter Read. (dBuV)	Matc. Pad Loss (dB)	Att. Pad Loss(dB)	Gain of Amp.(dB)	Interference (dBuV)		
Multi Burst 1 V p-p	3	36.20	44.7	2.3	N/A	24.3	22.7		
		43.34	52.1	2.3	N/A	24.3	30.1		
		50.50	58.4	2.3	N/A	24.3	36.4		
		72.00	56.2	2.3	N/A	24.4	34.1		
		79.13	49.5	2.3	N/A	24.4	27.4		
		610.00	49.4	2.3	N/A	22.9	28.8		
		42.17	44.7	2.3	N/A	24.3	22.7		
	4	49.40	51.5	2.3	N/A	24.3	29.5		
		56.50	58.0	2.3	N/A	24.3	36.0		
		78.00	55.5	2.3	N/A	24.4	33.4		
		85.14	47.2	2.3	N/A	24.4	25.1		
		608.60	49.3	2.3	N/A	22.9	28.7		
		Multi Burst 5 V p-p	3	36.20	44.7	2.3	N/A	24.3	22.7
				43.34	52.1	2.3	N/A	24.3	30.1
50.50	58.4			2.3	N/A	24.3	36.4		
72.00	56.2			2.3	N/A	24.4	34.1		
79.13	49.5			2.3	N/A	24.4	27.4		
610.00	49.4			2.3	N/A	22.9	28.8		
42.17	44.7			2.3	N/A	24.3	22.7		
4	49.40		51.5	2.3	N/A	24.3	29.5		
	56.50		58.0	2.3	N/A	24.3	36.0		
	78.00		55.5	2.3	N/A	24.4	33.4		
	85.14		47.2	2.3	N/A	24.4	25.1		
	608.60		49.3	2.3	N/A	22.9	28.7		
	RF/CATV Signal Input		3	36.20	44.7	2.3	N/A	24.3	22.7
				43.34	52.1	2.3	N/A	24.3	30.1
50.50		58.4		2.3	N/A	24.3	36.4		
72.00		56.2		2.3	N/A	24.4	34.1		
79.13		49.5		2.3	N/A	24.4	27.4		
610.00		49.4		2.3	N/A	22.9	28.8		
42.17		44.7		2.3	N/A	24.3	22.7		
4		49.40	51.5	2.3	N/A	24.3	29.5		
		56.50	58.0	2.3	N/A	24.3	36.0		
		78.00	55.5	2.3	N/A	24.4	33.4		
		85.14	47.2	2.3	N/A	24.4	25.1		
		608.60	49.3	2.3	N/A	22.9	28.7		

Part 15 Subpart B, (TV Interface Device)

5) 15.115 (b) (2) Output Terminal Conducted Interference

Video Signal	Ch	Freq. (MHz)	Meter Read. (dBuV)	Matc. Pad Loss (dB)	Att. Pad Loss(dB)	Gain of Amp.(dB)	Interference (dBuV)	
Internal Signal (DVD Playback)	3	36.20	44.7	2.3	N/A	24.3	22.7	
		43.34	52.1	2.3	N/A	24.3	30.1	
		50.50	58.4	2.3	N/A	24.3	36.4	
		72.00	56.2	2.3	N/A	24.4	34.1	
		79.13	49.5	2.3	N/A	24.4	27.4	
		610.00	49.4	2.3	N/A	22.9	28.8	
	4	42.17	44.7	2.3	N/A	24.3	22.7	
		49.40	51.5	2.3	N/A	24.3	29.5	
		56.50	58.0	2.3	N/A	24.3	36.0	
		78.00	55.5	2.3	N/A	24.4	33.4	
		85.14	47.2	2.3	N/A	24.4	25.1	
		608.60	49.3	2.3	N/A	22.9	28.7	
	Internal Signal (SD Card slide show)	3	36.20	44.7	2.3	N/A	24.3	22.7
			43.34	52.1	2.3	N/A	24.3	30.1
50.50			58.4	2.3	N/A	24.3	36.4	
72.00			56.2	2.3	N/A	24.4	34.1	
79.13			49.5	2.3	N/A	24.4	27.4	
610.00			49.4	2.3	N/A	22.9	28.8	
4		42.17	44.7	2.3	N/A	24.3	22.7	
		49.40	51.5	2.3	N/A	24.3	29.5	
		56.50	58.0	2.3	N/A	24.3	36.0	
		78.00	55.5	2.3	N/A	24.4	33.4	
		85.14	47.2	2.3	N/A	24.4	25.1	
		608.60	49.3	2.3	N/A	22.9	28.7	

RF Output Impedance: 75 ohms (Unbalanced)

Note:

1. Sample calculation at

M.B., 1 V p-p, 3 Ch., 36.20 MHz ; $44.7 + 2.3 - 24.3 = 22.7$ (dBuV)

2. Measuring Instrument:

a) Spectrum Analyzer

- Anritsu Electric Co., Ltd.

Model : MS62B

(1) Detector function : Peak

(2) Band width : 100 kHz

b) Matching Pad

- Anritsu Electric Co., Ltd.

Model : MP614A

(1) Frequency range : 10 - 1200 MHz

c) Test Signal Generator
(Multi Burst)

- Shibasoku Co., Ltd.

Model : 205

d) Amplifier

- Hewlett Packard

Model : 8447F

3. The spectrum was checked from 30 MHz to 1000 MHz and the six highest emissions relative to the appropriate limit were measured and reported.

Tuner: 115-V-H015AK

EXHIBIT # : 3
FCC ID : ACJ927147AHV
OUR REF. : MKES02-F017
MODEL NO. : PV-D4763
Sheet 23 of 30 Sheets

Part 15 Subpart B. (TV Interface Device)

6) 15.115 (c) Transfer Switch Isolation

Video Signal	Ch	Meter Read.(dBuV)	Matching Pad Loss(dB)	Gain of Amp.(dB)	Pad Loss (dB)	Level (dBuV)
Multi Burst 1 V p-p	3	<26.0	2.3	24.4	N/A	<3.9
	4	<26.0	2.3	24.4	N/A	<3.9
Multi Burst 5 V p-p	3	<26.0	2.3	24.4	N/A	<3.9
	4	<26.0	2.3	24.4	N/A	<3.9
Internal Signal (DVD Playback)	3	<26.0	2.3	24.4	N/A	<3.9
	4	<26.0	2.3	24.4	N/A	<3.9
Internal Signal (SD Card slide show)	3	<26.0	2.3	24.4	N/A	<3.9
	4	<26.0	2.3	24.4	N/A	<3.9

RF Output Impedance: 75 ohms (Unbalanced)

Note:

1. Sample calculation at

M.B., 1 V p-p, Visual, 3 Ch ; $<26.0 + 2.3 - 24.4 = <3.9$ (dBuV)

2. Measuring Instrument:

a) Spectrum Analyzer

- Anritsu Electric Co., Ltd.

Model : MS62B

(1) Detector function : Peak

(2) Band width : 100 kHz

b) Matching Pad

- Anritsu Electric Co., Ltd.

Model : MP614A

(1) Frequency range : 10 - 1200 MHz

c) Test Signal Generator
(Multi Burst)

- Shibasoku Co., Ltd.

Model : 205

d) Amplifier

- Hewlett Packard

Model : 8447F

Part 15 Subpart B. (TV Interface Device)

15.107 POWER LINE CONDUCTED VOLTAGE

- CONFIGURATION OF THE EQUIPMENT UNDER TEST -

(Arrangement of interface cable on the test table)




Part 15 Subpart B. (TV Interface Device)

15.109 RADIATED EMISSION

- CONFIGURATION OF THE EQUIPMENT UNDER TEST -

(Arrangement of interface cable on the test table)




Part 15 Subpart B. (TV Interface Device)


15.109 RADIATED EMISSION

- CONFIGURATION OF THE EQUIPMENT UNDER TEST -


(Arrangement of interface cable on the test table)



JIS A4 190 × 250mm



CORRECTION FACTOR OF UHALP9108A



$E = V + K$

E : Field Strength

V : Correction Factor (dB)

———— : Correction Factor

----- : Antenna Factor

..... : Cable Loss

