

RF Exposure Report

Report No.: SA160701E08 R2

FCC ID: ACQ-MT76125G

Test Model: MT7612 5G

Received Date: July 05, 2016

Test Date: July 15, 2016

Issued Date: Aug. 11, 2016

Applicant: ARRIS Group, Inc.

Address: 6450 Sequence Drive, San Diego, CA USA, 92121

Issued By: Bureau Veritas Consumer Products Services (H.K.) Ltd., Taoyuan Branch
Hsin Chu Laboratory

Lab Address: E-2, No.1, Li Hsin 1st Road, Hsinchu Science Park, Hsinchu City 300,
Taiwan R.O.C.

This report is for your exclusive use. Any copying or replication of this report to or for any other person or entity, or use of our name or trademark, is permitted only with our prior written permission. This report sets forth our findings solely with respect to the test samples identified herein. The results set forth in this report are not indicative or representative of the quality or characteristics of the lot from which a test sample was taken or any similar or identical product unless specifically and expressly noted. Our report includes all of the tests requested by you and the results thereof based upon the information that you provided to us. You have 60 days from date of issuance of this report to notify us of any material error or omission caused by our negligence, provided, however, that such notice shall be in writing and shall specifically address the issue you wish to raise. A failure to raise such issue within the prescribed time shall constitute your unqualified acceptance of the completeness of this report, the tests conducted and the correctness of the report contents. Unless specific mention, the uncertainty of measurement has been explicitly taken into account to declare the compliance or non-compliance to the specification. The report must not be used by the client to claim product certification, approval, or endorsement by any government agencies.

Table of Contents

Release Control Record	3
1 Certificate of Conformity.....	4
2 RF Exposure.....	5
2.1 Limits For Maximum Permissible Exposure (MPE).....	5
2.2 MPE Calculation Formula	5
2.3 Classification	5
2.4 Antenna Gain	6
2.5 Calculation Result Of Maximum Conducted Power	7

Release Control Record

Issue No.	Description	Date Issued
SA160701E08	Original release.	July 28, 2016
SA160701E08 R1	Revised section 2.5	Aug. 11, 2016
SA160701E08 R2	Revised address of applicant	Aug. 11, 2016

1 Certificate of Conformity

Product: WiFi Wireless Module

Brand: ARRIS

Test Model: MT7612 5G

Sample Status: ENGINEERING SAMPLE

Applicant: ARRIS Group, Inc.

Test Date: July 15, 2016

Standards: FCC Part 2 (Section 2.1091)

KDB 447498 D01 General RF Exposure Guidance v06

IEEE C95.1-1992

The above equipment has been tested by **Bureau Veritas Consumer Products Services (H.K.) Ltd., Taoyuan Branch**, and found compliance with the requirement of the above standards. The test record, data evaluation & Equipment Under Test (EUT) configurations represented herein are true and accurate accounts of the measurements of the sample's EMC characteristics under the conditions specified in this report.

Prepared by : Midoli Peng, **Date:** Aug. 11, 2016

Midoli Peng / Specialist

Approved by : May Chen, **Date:** Aug. 11, 2016

May Chen / Manager

2 RF Exposure

2.1 Limits for Maximum Permissible Exposure (MPE)

Frequency Range (MHz)	Electric Field Strength (V/m)	Magnetic Field Strength (A/m)	Power Density (mW/cm ²)	Average Time (minutes)
Limits For General Population / Uncontrolled Exposure				
300-1500	F/1500	30
1500-100,000	1.0	30

F = Frequency in MHz

2.2 MPE Calculation Formula

$$Pd = (Pout * G) / (4 * \pi * r^2)$$

where

Pd = power density in mW/cm²

Pout = output power to antenna in mW

G = gain of antenna in linear scale

Pi = 3.1416

R = distance between observation point and center of the radiator in cm

2.3 Classification

The antenna of this product, under normal use condition, is at least 20cm away from the body of the user.

So, this device is classified as **Mobile Device**.

2.4 Antenna Gain

The antenna provided to the EUT, please refer to the following table:

Set 1							
Transmitter Circuit	Brand	Model	Gain (dBi) (Include cable loss)	Antenna Type	Connector Type	Frequency range (GHz to GHz)	Cable Length (mm)
Chain (0)	Amphenol	N5X20SC-G112U	3.57	PCB	i-pex(MHF)	5.15~5.25	112
			3.41			5.25~5.35	
			3.01			5.47~5.725	
			3.48			5.725~5.85	
Chain (1)	Amphenol	N5X20SC-G162U	3.57	PCB	i-pex(MHF)	5.15~5.25	162
			3.41			5.25~5.35	
			3.01			5.47~5.725	
			3.48			5.725~5.85	
Set 2							
Transmitter Circuit	Brand	Model	Gain (dBi) (Include cable loss)	Antenna Type	Connector Type	Frequency range (GHz to GHz)	Cable Length (mm)
Chain (0)	Airgain	AMSTD-112-00	2	PCB	i-pex(MHF)	5.15~5.25	112
			2			5.25~5.35	
			2			5.47~5.725	
			2			5.725~5.85	
Chain (1)	Airgain	AMSTD-162-00	2	PCB	i-pex(MHF)	5.15~5.25	162
			2			5.25~5.35	
			2			5.47~5.725	
			2			5.725~5.85	

2.5 Calculation Result of Maximum Conducted Power

Frequency Band (MHz)	Max Power (mW)	Antenna Gain (dBi)	Distance (cm)	Power Density (mW/cm ²)	Limit (mW/cm ²)
5180-5240	76.831	6.58	20	0.06954	1
5260-5320	76.039	6.42	20	0.06634	1
5500-5720	77.274	6.02	20	0.06148	1
5745-5825	77.193	6.49	20	0.06844	1

NOTE:

1. **For U-NII-1:** Directional gain = $3.57\text{dBi} + 10\log(2) = 6.58\text{dBi}$
2. **For U-NII-2A:** Directional gain = $3.41\text{dBi} + 10\log(2) = 6.42\text{dBi}$
3. **For U-NII-2C:** Directional gain = $3.01\text{dBi} + 10\log(2) = 6.02\text{dBi}$
4. **For U-NII-3:** Directional gain = $3.48\text{dBi} + 10\log(2) = 6.49\text{dBi}$

BT-EDR (IP SET TOP BOX, FCC ID: ACQ-VIP4402W)

Frequency Band (MHz)	Max Power (mW)	Antenna Gain (dBi)	Distance (cm)	Power Density (mW/cm ²)	Limit (mW/cm ²)
2402-2480	3.304	4.38	20	0.00180	1

BT-LE (IP SET TOP BOX, FCC ID: ACQ-VIP4402W)

Frequency Band (MHz)	Max Power (mW)	Antenna Gain (dBi)	Distance (cm)	Power Density (mW/cm ²)	Limit (mW/cm ²)
2402-2480	4.55	4.38	20	0.00248	1

Conclusion:

The formula of calculated the MPE is:

CPD1 / LPD1 + CPD2 / LPD2 +etc. < 1

CPD = Calculation power density

LPD = Limit of power density

Bluetooth + WLAN 5GHz = $0.06954 / 1 + 0.00248 / 1 = 0.07202$

Therefore the maximum calculations of above situations are less than the “1” limit.

--- END ---