

## RF Exposure Report

**Report No.:** SA160910C09A

**FCC ID:** ACQ-WVB2R0-34

**Test Model:** WVB2

**Received Date:** Dec. 09, 2016

**Test Date:** Dec. 09, 2016 ~ Mar. 15, 2017

**Issued Date:** Mar. 16, 2017

**Applicant:** ARRIS Group, Inc.

**Address:** 101 Tournament Drive, Horsham, Pennsylvania, United States, 19044

**Issued By:** Bureau Veritas Consumer Products Services (H.K.) Ltd., Taoyuan Branch

**Lab Address:** No. 47-2, 14th Ling, Chia Pau Vil., Lin Kou Dist., New Taipei City, Taiwan, R.O.C.

**Test Location:** No. 19, Hwa Ya 2nd Rd., Wen Hwa Vil., Kwei Shan Dist., Taoyuan City 33383, TAIWAN (R.O.C.)



This report is for your exclusive use. Any copying or replication of this report to or for any other person or entity, or use of our name or trademark, is permitted only with our prior written permission. This report sets forth our findings solely with respect to the test samples identified herein. The results set forth in this report are not indicative or representative of the quality or characteristics of the lot from which a test sample was taken or any similar or identical product unless specifically and expressly noted. Our report includes all of the tests requested by you and the results thereof based upon the information that you provided to us. You have 60 days from date of issuance of this report to notify us of any material error or omission caused by our negligence, provided, however, that such notice shall be in writing and shall specifically address the issue you wish to raise. A failure to raise such issue within the prescribed time shall constitute your unqualified acceptance of the completeness of this report, the tests conducted and the correctness of the report contents. Unless specific mention, the uncertainty of measurement has been explicitly taken into account to declare the compliance or non-compliance to the specification. The report must not be used by the client to claim product certification, approval, or endorsement by TAF or any government agencies.



BUREAU  
VERITAS

## Table of Contents

<b>Release Control Record</b> .....	<b>3</b>
<b>1      Certificate of Conformity</b> .....	<b>4</b>
<b>2      RF Exposure</b> .....	<b>5</b>
2.1    Limits for Maximum Permissible Exposure (MPE).....	5
2.2    MPE Calculation Formula .....	5
2.3    Classification .....	5
<b>3      Calculation Result of Maximum Conducted Power</b> .....	<b>6</b>



BUREAU  
VERITAS

### Release Control Record

Issue No.	Description	Date Issued
SA160910C09A	Original release.	Mar. 16, 2017

## 1 Certificate of Conformity

**Product:** Wireless Gateway

**Brand:** Arris

**Test Model:** WVB2

**Sample Status:** Engineering sample

**Applicant:** ARRIS Group, Inc.

**Test Date:** Dec. 09, 2016 ~ Mar. 15, 2017

**Standards:** FCC Part 2 (Section 2.1091)

KDB 447498 D01 General RF Exposure Guidance v06

IEEE C95.1-1992

The above equipment has been tested by **Bureau Veritas Consumer Products Services (H.K.) Ltd., Taoyuan Branch**, and found compliance with the requirement of the above standards. The test record, data evaluation & Equipment Under Test (EUT) configurations represented herein are true and accurate accounts of the measurements of the sample's EMC characteristics under the conditions specified in this report.

**Prepared by :**  , **Date:** Mar. 16, 2017

Polly Chien / Specialist

**Approved by :**  , **Date:** Mar. 16, 2017

Ken Liu / Senior Manager

## 2 RF Exposure

### 2.1 Limits for Maximum Permissible Exposure (MPE)

Frequency Range (MHz)	Electric Field Strength (V/m)	Magnetic Field Strength (A/m)	Power Density (mW/cm <sup>2</sup> )	Average Time (minutes)
Limits For General Population / Uncontrolled Exposure				
300-1500	...	...	F/1500	30
1500-100,000	...	...	1.0	30

F = Frequency in MHz

### 2.2 MPE Calculation Formula

$$Pd = (Pout * G) / (4 * \pi * r^2)$$

where

Pd = power density in mW/cm<sup>2</sup>

Pout = output power to antenna in mW

G = gain of antenna in linear scale

Pi = 3.1416

R = distance between observation point and center of the radiator in cm

### 2.3 Classification

The antenna of this product, under normal use condition, is at least 20cm away from the body of the user. So, this device is classified as **Mobile Device**.

### 3 Calculation Result of Maximum Conducted Power

Frequency Band (MHz)	Max Power (dBm)	Antenna Gain (dBi)	Distance (cm)	Power Density (mW/cm <sup>2</sup> )	Limit (mW/cm <sup>2</sup> )
CDD mode: Mode F (4T2S)					
5180-5240	27.78	1.5	20	0.169	1
5260-5320	23.91	1.1	20	0.063	1
5500-5720	23.74	2.2	20	0.078	1
5745-5825	27.58	2.8	20	0.217	1
CDD mode: Mode G (4T3S)					
5180-5240	28.27	1.5	20	0.189	1
5260-5320	23.98	1.1	20	0.064	1
5500-5720	23.96	2.2	20	0.082	1
5745-5825	27.51	2.8	20	0.214	1
Beamforming mode: Mode F (4T2S)					
5180-5240	27.75	4.5	20	0.334	1
5260-5320	23.91	4.1	20	0.126	1
5500-5720	23.92	5.2	20	0.162	1
5745-5825	27.54	5.8	20	0.429	1
Beamforming mode: Mode G (4T3S)					
5180-5240	28.27	2.7	20	0.249	1
5260-5320	23.98	2.3	20	0.084	1
5500-5720	23.96	3.4	20	0.108	1
5745-5825	27.49	4	20	0.280	1

Note:

CDD mode: Mode F (4T2S) and Mode G (4T3S)

5180-5320MHz: Directional gain = 1.5dBi

5260-5320MHz: Directional gain = 1.1dBi

5500~5720MHz: Directional gain = 2.2dBi

5745~5825MHz: Directional gain = 2.8dBi

Beamforming mode: Mode F (4T2S)

5180-5324MHz: Directional gain = 4.5dBi

5260-5320MHz: Directional gain = 4.1dBi

5500~5720MHz: Directional gain = 5.2dBi

5745~5825MHz: Directional gain = 5.8dBi

Beamforming mode: Mode G (4T3S)

5180-5320MHz: Directional gain = 2.7dBi

5260-5320MHz: Directional gain = 2.3dBi

5500~5720MHz: Directional gain = 3.4dBi

5745~5825MHz: Directional gain = 4dBi

---END---