

Setting Call Forwarding Service

Call Forwarding Service is a free option (no monthly fees) that requires subscription.

- 1 In the Normal menu, [TEL function] ▶ [Other network service] ▶ [Call forwarding]
- 2 [Activate] ▶ [Yes] ▶ [Yes] ▶ enter a phone number ▶  ▶ [Yes] ▶ enter the ringing time ▶ [OK]

Bluetooth function

- The Bluetooth word mark and logos are owned by the Bluetooth SIG, INC. and any use of such marks by NTT DOCOMO, INC. is under license. Other trademarks and trade names are those of their respective owners.

Registering Bluetooth devices on FOMA terminal

- Switch the other party's Bluetooth device to the registration stand-by status in advance.
- 1 In the Normal menu, [Tool] ▶ [Bluetooth] ▶ [List/cnct/discnct]
 - The device list screen appears when registered device exists. Press  and proceed to step 3.
 - 2 [Yes]
 - 3 Point the cursor to the Bluetooth device to register ▶  ▶ [Register Devices]
 - 4 Enter the Bluetooth passkey

Connecting with Bluetooth devices

- 1 In the Normal menu, [Tool] ▶ [Bluetooth] ▶ [List/cnct/discnct]
- 2 Select a Bluetooth device to connect to

General Notes

Options and related devices

- Battery Pack SH34
- FOMA AC Adapter 01 for Global use
- FOMA AC Adapter 01/02
- Wireless Charger SH01

Main specifications

Size	110 (H) × 50 (W) × 17.3 (D) mm (18.1 mm at thickest point) (when folded)*	
Weight	132 g (with battery pack attached)*	
Continuous talk time	FOMA/3G	Voice call: 270 min*
		Videophone: 130 min*
Continuous stand-by time	FOMA/3G	At rest : 770 hr*
Charge time	FOMA AC Adapter 01/02	●● min*
	FOMA DC Adapter 01/02	●● min*
	Wireless Charger SH01	220 min*

* Approximate value