

Measurement Procedure & Test Equipment Used

Except where otherwise stated, all measurements are made following the Electronic Industries Association (EIA) Minimum Standard for Portable/Personal Land Mobile Communications FM or PM Equipment 25-1000 MHz-(EIA/TIA-603-C).

This exhibit presents a brief summary of how the measurements were made, the required limits, and the test equipment used.

The following procedures are presented with this application.

1.	Test Equipment List	<u> X </u>
2.	RF Power Output Data	<u> X </u>
3.	Audio Frequency Response	<u> X </u>
4.	Audio Low Pass Filter Response	<u> X </u>
5.	Modulation Limiting	<u> X </u>
6.	Occupied Bandwidth	<u> X </u>
7.	Radiated Spurious Emissions	<u> X </u>
8.	Conducted Spurious Emissions	<u> X </u>
9.	Frequency Stability (Volt/Temp)	<u> X </u>
10.	Transient Frequency Behavior	<u> X </u>

Test Equipment List

Pursuant To FCC Rules 2.947 (d)

No	Equipment	Calibration Date (next due)
1	HP 6033A Power Supply	23-Apr-14
2	HP 8903B Audio Analyzer.	6-May-14
3	HP 34401A Digital Multimeter	14-Apr-14
4	HP 8901B Modulation Analyzer	30-Mar-14
5	Weinschel Model WA53 30 dB attenuator (DC - 1.5 GHz)	*Calibration not required*
6	Agilent E4416A Power Meter with E9301B Power Sensor	26-May-14
7	Agilent Technologies MXA Signal Analyzer N9020A (20 Hz – 3.6 GHz)	19-Oct-12
8	Agilent E4440A PSA Spectrum Analyzer (3 Hz – 26.5 GHz)	11-Jun-14
9	Mini-Circuits, VHF High Pass Filter, NHP 300	*Calibration not required*
10	Agilent infinium 54831D Oscilloscope	9-Jan-14
11	Weinschel Model1440-4 RF Terminating Load	*Calibration not required*
12	Agilent 778D, Bi directional coupler	*Calibration not required*
13	Chase CBL6111 Antenna	7-Jan-13
14	EMCO 3108 Antenna	30-Nov-13
15	EMCO 3146 Antenna	30-Nov-13
16	EMCO 3115 Antenna	2-Mar-13
17	HP 8447D Amplifiers	18-Jan-14
18	ACS Boca Chamber EMI cable set	2-Jan-13
19	ACS Boca Substitution cable set	12-Jan-13
20	Agilent 8573A Spectrum Analyzers	12-Dec-13
21	HP 8673D Signal Generator	22-Feb-13
22	Agilent 83017A Amplifier	23-Sep-12
23	ESPEC Temperature Chamber	13-Aug-13

RF Power Output

Pursuant to FCC Rules 2.1046 (a)

Method of Measurement

The RF power output is measured with the transmitter adjusted in accordance with the tune-up procedure outlined in Exhibit 10 to give the value of voltage and current as specified in Exhibit 12 as required by 2.1033(c) (8). A 50-ohm RF attenuator of proper power rating was used as a load for making these measurements.

The power measurements are made using an Agilent series E4416A RF power meter and 30 dB attenuator.

Audio Frequency Response

Pursuant FCC Rules 2.1047 (a)

Method of Measurement

Operate the transmitter under standard test conditions and monitor the output with a frequency deviation meter or calibrated test receiver. With 1000 Hz sine wave audio input applied through a dummy microphone circuit, adjust the audio input to give 20% of full rated system deviation. Maintaining a constant input voltage, vary the input frequency from 300 to 3000 Hz, and observe the deviation.

Minimum Standard

The audio frequency response shall not vary more than +1 or -3 dB from 300 to 3000 Hz from a true 6 dB per octave pre-emphasis characteristic as referenced to 1000 Hz level, with the exception of a permissible 6 dB/octave roll off below 500 Hz. Equivalent to EIA/TIA 603-C Section 3.1.10.2.1 mask.

Audio Low Pass Filter Response

Pursuant FCC Rules 2.1047 (a)

Method of Measurement

A Dynamic Signal Analyzer is used to sweep the response from 1kHz to 25kHz. The source of the analyzer is connected to the AUDIO IN port of the radio interface box. The audio input level is adjusted to produce a standard test modulation. The transmitter is operated under standard test conditions and the output of the Switch Cap Filter is monitored, with the post limiter low pass filter within the lineup. The output is connected to channel 2 of the analyzer and referenced to its input signal. A sinusoidal sweep from 1K to 25kHz will produce the frequency response of the low pass filter during TX mode.

FCC Limits -- Per applicable rule parts.

450 to 869 MHz & VHF Marine.

Frequencies between 3 kHz and 20 kHz shall be attenuated greater than the attenuation at 1 kHz by $60 \log_{10} (f/3)$ dB.

Frequencies above 20 kHz shall be attenuated at least 50 dB.

Modulation Limiting

Pursuant FCC Rules 2.1047 (b)

Method of Measurement

The transmitter shall be adjusted for full rated system deviation. Adjust the audio input for 60% of rated system deviation at 1000 Hz. Using this level as a reference (0 dB) vary the audio input level from the reference to a level 20 dB above it for modulation frequencies between 300 and 3000 Hz in 100Hz steps. Record the system deviation obtained as a function of the input level.

FCC Limits

Minimum Standard - The transmitter modulation must not exceed rated system deviation at any audio frequency input or reasonable change in input level. In the exhibit, 100% corresponds to the maximum rated system deviation for the given channel bandwidth.

Occupied Bandwidth

Pursuant to FCC Rules 2.1049

Method of Measurement

Data on occupied bandwidth is presented in the form of a spectrum analyzer photograph, which illustrates the transmitter sidebands. For analog signals, the reference line for the data plot is taken of the unmodulated carrier, to which is superimposed the sideband display generated by modulating the carrier with a 2500 Hz tone at a level 16 dB greater than that required to produce 50 percent modulation. For digital voice and data, the reference line for the data plot is that of the peak value of the modulated carrier. For digital voice, the carrier with a 2500 Hz tone at a level 16 dB greater than that required to produce 50 percent modulation. For digital data, the carrier is modulated with a Standard Transmitter Test Pattern, which is a continuously repeating 511 bit pseudo-random bit sequence based on ITU-T 0.153. If tone or digital coded squelch is indicated, photographs using both the 2500 Hz tone and the indicated squelch signal are used to modulate the transmitter. During these measurements, the instantaneous Deviation Control is set for a maximum of +5 kHz.

FCC Limits - Per 90.210 (b), (d).

Emission Mask B. For transmitters that are equipped with an audio low-pass filter pursuant to Sec. 90.211(a), the power of any emission must be below the unmodulated carrier power (P) as follows:

- (1) On any frequency removed from the assigned frequency by more than 50 percent, but not more than 100 percent of the authorized bandwidth: At least 25 dB.
- (2) On any frequency removed from the assigned frequency by more than 100 percent, but not more than 250 percent of the authorized bandwidth: At least 35 dB.
- (3) On any frequency removed from the assigned frequency by more than 250 percent of the authorized bandwidth: At least $43 + 10 \log (P)$ dB, where P is the mean output power in watts.

Emission Mask D. 12.5 kHz channel bandwidth equipment. For transmitters designed to operate with a 12.5 kHz channel bandwidth, any emission must be attenuated below the power (P) of the highest emission contained within the authorized bandwidth as follows:

- (1) On any frequency from the center of the authorized bandwidth f_0 to 5.625 kHz removed from f_0 : Zero dB.
- (2) On any frequency removed from the center of the authorized bandwidth by a displacement frequency (f_d in kHz) of more than 5.625 kHz but no more than 12.5 kHz: At least $7.27(f_d - 2.88\text{kHz})$ dB.

(3) On any frequency removed from the center of the authorized bandwidth by a displacement frequency (f_d in kHz) of more than 12.5 kHz: At least $50 + 10 \log (P)$ dB or 70 dB, whichever is the lesser attenuation.

(4) The reference level for showing compliance with the emission mask shall be established using a resolution bandwidth sufficiently wide (We used 30 kHz, which is more than two times the channel bandwidth) to capture the true peak emission of the equipment under test. In order to show compliance with the emissions mask up to and including 50 kHz removed from the edge of the authorized bandwidth, adjust the resolution bandwidth to 100 Hz with the measuring instrument in a peak hold mode. A sufficient number of sweeps must be measured to insure that the emission profile is developed. If video filtering is used, its bandwidth must not be less than the instrument resolution bandwidth. For emissions beyond 50 kHz from the edge of the authorized bandwidth, see paragraph (m) of this section. If it can be shown that use of the above instrumentation settings do not accurately represent the true interference potential of the equipment under test, then an alternate procedure may be used provided prior Commission approval is obtained. (m) Instrumentation. The reference level for showing compliance with the emission mask shall be established, except as indicated in Secs. 90.210 (d), (e), and (k), using standard engineering practices for the modulation characteristic used by the equipment under test. When measuring emissions in the 150-174 MHz and 421-512 MHz the following procedures will apply. A sufficient number of sweeps must be measured to insure that the emission profile is developed. If video filtering is used, its bandwidth must not be less than the instrument resolution bandwidth. For frequencies more than 50 kHz removed from the edge of the authorized bandwidth a resolution of at least 10 kHz must be used for frequencies below 1000 MHz. Above 1000 MHz the resolution bandwidth of the instrumentation must be at least 1 MHz. If it can be shown that use of the above instrumentation settings do not accurately represent the true interference potential of the equipment under test, then an alternate procedure may be used provided prior Commission approval is obtained.

Radiated Spurious Emissions

Pursuant to FCC Rules 2.1053

Test Site:

The site, located at Plantation, Florida, is in a region which is reasonably free from RF interference and has been approved by the Commission for Spurious Measurements.

The equipment is placed on the turntable, connected to a dummy RF load and then placed in normal operation using the intended power source. A broadband receiving antenna, located 3 meters from the transmitter-under-test (TUT), picks up any signals radiated from the transmitter and its operation accessories. The antenna is adjustable in height and can be horizontally and vertically polarized. A spectrum analyzer covering the necessary frequency range is used to detect and measure any radiation picked up by the above mentioned receiving antenna.

Method of Measurement

The equipment is adjusted to obtain peak reading of received signals wherever they occur in the spectrum by:

1. Rotating the transmitter under test.
2. Adjusting the antenna height.

The testing procedure is repeated for both horizontal and vertical polarization of the receiving antenna. Relative signal strength is indicated on the spectrum analyzer connected to the receiving antenna. To obtain actual radiated signal strength for each spurious and harmonic frequency observed, a standard signal generator with calibrated output is connected to a dipole antenna adjusted to that particular frequency. This dipole antenna is substituted for the transmitter under test. The signal generator is

adjusted in output level until a reading identical to that obtained with the actual transmitter is observed on the spectrum analyzer. Signal strength is then read directly from the generator. Actual measurements are recorded on the attached graphs.

FCC Limits -- Per Applicable Rule Parts.

Radiated spurious emissions shall be attenuated below the maximum level of emission of the carrier frequency in accordance with the following formula:

Spurious attenuation in dB = $43 + 10 \log_{10}(\text{Power output in watts})$

Conducted Spurious Emissions

Pursuant to FCC Rule 2.1051

Method of Measurement

The transmitter is terminated into a 50 ohm load and interfaced with a spectrum analyzer which allows the spurious emission level relative to the carrier level to be measured directly. Modulate the transmitter with a 2500 Hz sine wave at an input level 16 dB greater than that required to produce 50% of rated system deviation at 1000 Hz. Measurements shall be made from the lowest radio frequency generated in the equipment to the tenth harmonic of the carrier or as high as the state of the art permits except for that region close to the carrier equal to $\pm 250\%$ of the authorized bandwidth.

FCC Limits - Per Applicable Rule Parts.

Conducted spurious emissions shall be attenuated below the maximum level of emission of the carrier frequency in accordance with the following formula:

Spurious attenuation in dB = $43 + 10 \log_{10}(\text{Power output in watts})$ for 25 kHz Channelization.

Spurious attenuation in dB = $50 + 10 \log_{10}(\text{Power output in watts})$ for 12.5 kHz Channelization.

Frequency Stability

Pursuant to FCC Rule 2.1055

Method of Measurement

A. Temperature (Non-heated type crystal oscillators):

Frequency measurements are made at the extremes of the temperature range -30 to +60 degrees centigrade and at intervals of not more than 10 degrees centigrade throughout the range. Sufficient time is allowed prior to each measurement for the circuit components to stabilize.

B. Power Supply Voltage:

The primary voltage was varied from 85% to 115% of the nominal supply voltage. Voltage is measured at the input to the cable normally provided with the equipment, or at the power supply terminals if cables are not normally provided.

FCC Limits -- Per FCC Rule 90.213

Temperature - Frequency Stability of ± 2.0 ppm from -30 to +60 degrees centigrade.

Power Supply Voltage - Frequency Stability of ± 2.0 ppm from 85% to 115% of nominal voltage.

Transient Frequency Behavior

Pursuant to FCC Rule 90.214

Transient frequency behavior is a measure of the difference, as a function in time, of the actual transmitter frequency to the assigned transmitter frequency when the transmitted RF output power is switched on or off.

Setup -- Per TIA/EIA 603-C, Section 2.2.19

Connect the output port of the transmitter under test (TUT) to an attenuator and this to a directional coupler. Connect an RF peak detector to the coupled output of the directional coupler, and connect the output of the RF peak detector to the external trigger on a storage oscilloscope. The output of the directional coupler is mixed, via an RF combining network, with the output of a signal generator. Verify that the TUT signal level present at the combining network output is approximately 40 dB below the maximum input level of the test receiver as per step (f). Set the signal generator at the same frequency as the TUT, modulated with a 1 kHz tone, with an FM deviation equal to the assigned channel spacing (+25 kHz).

Following step (h), adjust the signal generator to provide 20 dB less power at the combiner output than the level set in step (f). Connect the output of the RF combiner to a test receiver, and the test receiver's output port to a vertical input channel of the storage scope. Adjust the horizontal sweep rate on the oscilloscope to 10msec/div, and the vertical amplitude to display the 1 kHz tone over +/- 4 divisions centered on the display. Reduce the transmit attenuation by 30 dB as per step (l) so that the difference in the power between the reference signal and the TUT signal at the combiner is 50 dB when the TUT is turned on. Following step (k), adjust the oscilloscope to trigger on an increasing signal from the RF detector at one division from the left side of the display when the TUT is turned on. Switch on the TUT and record the display (for RF Output Power ON). Following step (q), adjust the oscilloscope trigger controls to trigger on a decreasing signal from the RF peak detector, at 1 division from the right side of the display when the TUT is turned off. Switch off the transmitter and record the display (for RF Output Power OFF).

* Steps (f), (h), (k), (l), and (q) - section 2.2.19 of the TIA/EIA 603-C were followed.

Method of Measurement -- Per TIA/EIA-603-C, Section 2.2 19.

For RF Output Power ON: Turn the transmitter ON. Once the demodulator output has been captured by the transmitter power, the 1 kHz test signal will be completely suppressed. This point in time is named T-on. The display will then show the frequency difference from the assigned frequency to the actual transmitter frequency versus time. Two time intervals will be measured following T-on: T-1 and T-2. So, the RF ON time intervals are as follows: T-on -----> T-1 -----> T-2

For RF Output Power OFF: Turn the transmitter OFF. The display will show the transmitter frequency difference versus time, and when the 1 kHz test signal starts to rise, it indicates total absence of the transmitter output at the specified frequency. This point is named T-off. Time interval T-3 precedes T-off. So, the RF OFF time intervals are as follows: T-3 -----> T-off.

FCC Limits -- Per 90.214.

Time Interval	Frequency Range (MHz)		
	30 to 300	300 to 500	500 to 1000
T-1	5.0 ms	10.0 ms	20.0 ms
T-2	20.0 ms	25.0 ms	50.0 ms
T-3	5.0 ms	10.0 ms	10.0 ms

*Per Applicable Rule Parts.