

<b>Tuned Frequency MHz</b>	<b>Emission Frequency MHz</b>	<b>Meter Reading dBuV</b>	<b>Ant. Polarity</b>	<b>Coax Loss dB</b>	<b>Correction Factor dB</b>	<b>Field Strength dBuV/m</b>	<b>Margin dB</b>
2,405.0	2,405.00	49.2	V	3.18	32.33	84.71	0.00
2,405.0	2,405.00	53.7	H	3.18	32.33	89.21	0.00
2,405.0	4,810.00	18.6	V	4.91	34.35	57.86	0.00
2,405.0	4,810.00	20.0	H	4.91	34.35	59.26	0.00
2,405.0	7,215.00	18.8	V	5.73	36.16	60.69	0.00
2,405.0	7,215.00	27.4	H	5.73	36.16	69.29	0.00
2,445.0	2,445.00	52.5	V	3.21	32.45	88.16	0.00
2,445.0	2,445.00	56.1	H	3.21	32.45	91.76	0.00
2,445.0	4,890.00	17.7	V	4.95	34.41	57.06	0.00
2,445.0	4,890.00	19.6	H	4.95	34.41	58.96	0.00
2,445.0	7,335.00	24.3	V	5.80	36.30	66.40	0.00
2,445.0	7,335.00	25.3	H	5.80	36.30	67.40	0.00
2,480.0	2,480.00	54.6	V	3.24	32.54	90.38	0.00
2,480.0	2,480.00	60.2	H	3.24	32.54	95.98	0.00
2,480.0	4,960.00	14.1	H	4.98	34.47	53.55	0.00
2,480.0	4,960.00	14.4	V	4.98	34.47	53.85	0.00
2,480.0	7,440.00	26.2	V	5.86	36.43	68.49	0.00
2,480.0	7,440.00	34.4	H	5.86	36.43	76.69	0.00